Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$



Using the electronic shutter

Using the electronic shutter lets you perform shooting without sounds, blackout-free shooting, etc.



Continuous shooting

Refer to this topic for the continuous shooting speed and the number of images recordable with continuous shooting.



Custom key setting

You can assign frequently used functions to the desired buttons and dials.



Recordable movie times

Refer to this topic for the shooting duration of movies recordable on the memory card.



ILCE-1 support information

This website provides basic information about the camera and information regarding compatible lenses and accessories. (Another window will open.)

How to use the "Help Guide"

Before Use

Checking the camera and the supplied items

Memory cards that can be used

Notes on using your camera

Precautions

Notes on the battery pack and charging the battery

Notes on memory card

- Cleaning the image sensor (Sensor Cleaning)

On cleaning

Names of parts/Basic operations Names of parts Front side Rear side - Top side - Sides Bottom **Basic operations** Touch operations on the monitor Using the control wheel Using the multi-selector Using the mode dial Using the focus mode dial Using the drive mode dial Using the MENU button Using the C (custom) buttons Using the Fn (Function) button Using the DISP (Display Setting) button Using the Delete button Using the AEL button Using the AF-ON button Using the front dial and rear dial Using the keyboard Basic icons In-Camera Guide Preparing the camera/Basic shooting operations Charging the battery pack Charging the battery pack using a charger Inserting/removing the battery pack

- Charging the battery pack while it is inserted into the camera
Using the battery charger abroad
Supplying power from a wall outlet (wall socket)
Inserting/removing a memory card
Attaching/removing a lens
Setting language, date and time
Basic shooting operations
- Confirmation before shooting
- <u>Shooting still images (Intelligent Auto)</u>
Shooting movies
Finding functions from MENU
Using the shooting functions
Contents of this chapter
Selecting a shooting mode
- <u>Intelligent Auto</u>
- <u>Program Auto</u>
- Aperture Priority
- <u>Shutter Priority</u>
- <u>Manual Exposure</u>
- Bulb shooting
- Exposure Ctrl Type
- Auto/Manual Swt. Set.
- Movie: Exposure Mode
- S&Q Motion: Exposure Mode
Auto Slow Shutter
Focusing
Selecting the focus method (Focus Mode)
_ <u>Selecting the focus area (Focus Area)</u>
Tracking subject (Tracking function)

Face/Eye AF
- Focusing on human eyes
- <u>Face/Eye Prior. in AF (still image/movie)</u>
- <u>Face/Eye Subject (still image/movie)</u>
- <u>Subject Sel. Setting (still image/movie)</u>
- Right/Left Eye Select (still image/movie)
- <u>Face/Eye Frame Disp. (still image/movie)</u>
- <u>Face Memory</u>
Regist. Faces Priority (still image/movie)
Using the AF functions
- <u>Focus Standard</u>
Adjusting the focus area settings to the camera's orientation (horizontal/vertical) (Switch V/H AF Area)
Registering the current focus area (AF Area Registration)
- Deleting a registered AF Area (Del. Regist. AF Area)
- Focus Area Limit (still image/movie)
- <u>Circ. of Focus Point (still image/movie)</u>
- AF Frame Move Amt (still image/movie)
- Focus Area Color (still image/movie)
– AF Area Auto Clear
- Area Disp. dur Tracking
- AF-C Area Display
– <u>Phase Detect. Area</u>
- AF Tracking Sensitivity
- AF Transition Speed
_ AF Subj. Shift Sensitivity
_ AF/MF Selector
- AF w/ Shutter
- AF On
- Focus Hold
- Pre-AF

Priority Set in AF-S Priority Set in AF-C AF in Focus Mag. AF illuminator Aperture Drive in AF Sing the MF functions Manual Focus Direct manual focus (DMF) Auto Magnifier in MF Focus Magnifier Focus Magni	- <u>Prior</u>	
AF in Focus Mag. AE Illuminator Aparture Drive in AE sing the MF functions Manual Focus Direct manual focus (DMF) Auto Magnifier in ME Focus Magnifier		rity Set in AF-S
- AF Illuminator - Asiture Drive in AF sing the MF functions - Manual Eccus - Direct manual focus (DME) - Auto Magnifier in ME - Eccus Magnifier in ME - Eccus Magnifier - Ecc	- <u>Prior</u>	rity Set in AF-C
- Aparture Drive in AF sing the MF functions - Manual Focus - Direct manual focus (DMF) - Auto Magnifier in MF - Focus Magnifier - Focus Magnifier Time (still Image/movie) - Initial Focus Mag, (still image) - Initial Focus Mag, (still image) - Initial Focus Mag, (still image) - Peaking Display djusting the exposure/metering modes - Exposure Comp, (still image/movie) - Histogram display - Reset EV Comp, (still image/movie) - Exposure Std, Adjust (still image/movie) - Dal Ex Comp - D-Range Optimizer (still image/movie) - Metering, Mode (still image/movie) - Face Priority in Multi Metering (still image/movie) - Sact Metering, Point (still image/movie) - Sact Metering, Point (still image/movie) - AE lock - AE Lock - AEL, w/ Shutter - Zebra Display,	- <u>AF ir</u>	n Focus Mag.
sing the MF functions - Manual Focus - Direct manual focus (DME) - Auto Magnifier in ME - Focus Magnifier - Mittal Focus Magnifier - Focus Ma	- <u>AF I</u>	<u>luminator</u>
- Manual Focus - Direct manual focus (DME) - Auto Magnifier in ME - Focus Magnifier - Focus Magnifi. Time (still image/movie) - Initial Focus Mag_(still image) - Peaking Display - Quisting the exposure/metering modes - Exposure Comp_(still image/movie) - Histogram display - Reset EV Comp_(still image/movie) - Exposure step_(still image/movie) - Exposure step_(still image/movie) - Exposure Std. Adjust (still image/movie) - Dial Ev Comp - D-Range Optimizer (still image/movie) - Metering Mode (still image/movie) - Face Priority in Multi Metering (still image/movie) - Spot Metering Point (still image/movie) - AE Lock - AEL w/ Shutter - Zebra Display	- <u>Aper</u>	ture Drive in AF
Direct manual focus (DME) Auto Magnifier in ME Focus Magnifier Focus Magnifier Focus Magnifier (still image/movie) Initial Focus Mag_(still image) Initial Focus Mag_(still image) Initial Focus Mag_(movie) Peaking_Display djusting the exposure/metering modes Exposure Comp_(still image/movie) Histogram display Reset EV Comp_(still image/movie) Exposure step (still image/movie) Exposure step (still image/movie) Dial Ev Comp D-Range Optimizer (still image/movie) Metering Mode (still image/movie) Face Priority in Multi Metering (still image/movie) Spot Metering Point (still image/movie) AE lock AEL_w/ Shutter Zebra Display	sing t	he MF functions
Auto Magnifier in MF Focus Magnifi Time (still image/movie) Initial Focus Mag. (still image) Initial Focus Mag. (still image) Initial Focus Mag. (movie) Peaking Display djusting the exposure/metering modes Exposure Comp. (still image/movie) Histogram display. Reset EV Comp. (still image/movie) Exposure stel (still image/movie) Exposure Std. Adjust (still image/movie) Dial Ev Comp D-Range Optimizer (still image/movie) Metering Mode (still image/movie) Face Priority in Multi Metering (still image/movie) Spot Metering Point (still image/movie) AE Lock AEL, w/ Shutter Zebra Display.	- <u>Man</u>	ual Focus
Focus Magnifier Focus Magnifi. Time (still image/movie) Initial Focus Mag. (still image) Initial Focus Mag. (movie) Peaking Display dijusting the exposure/metering modes Exposure Comp. (still image/movie) Histogram display Reset EV Comp. (still image/movie) Exposure step (still image/movie) Exposure Std. Adjust (still image/movie) Dal Ev Comp. D. Range Optimizer (still image/movie) Metering Mode (still image/movie) Face Priority in Multi Metering (still image/movie) Soot Metering Point (still image/movie) AE Lock AEL w/ Shutter Zebra Display	- <u>Dire</u>	ct manual focus (DMF)
Focus Magnif. Time (still image/movie) Initial Focus Mag_(still image) Initial Focus Mag_(movie) Peaking Display, djusting the exposure/metering modes Exposure Comp_(still image/movie) Histogram display Reset EV Comp_(still image/movie) Exposure step (still image/movie) Exposure Step (still image/movie) Dial Ev Comp D-Range Optimizer (still image/movie) Metering Mode (still image/movie) Face Priority in Multi Metering (still image/movie) Spot Metering-Point (still image/movie) AE Lock AEL w/ Shutter Zebra Display.	- <u>Auto</u>	Magnifier in MF
Initial Focus Mag. (still image) Initial Focus Mag. (movie) Peaking Display djusting the exposure/metering modes Exposure Comp. (still image/movie) Histogram display. Reset EV Comp. (still image/movie) Exposure step (still image/movie) Exposure Std. Adjust (still image/movie) Dial Ev Comp D-Range Optimizer (still image/movie) Metering Mode (still image/movie) Face Priority in Multi Metering (still image/movie) Spot Metering Point (still image/movie) AE Lock AEL w/ Shutter Zebra Display.	- Foci	<u>us Magnifier</u>
Initial Focus Mag_(movie) Peaking Display djusting the exposure/metering modes Exposure Comp_(still image/movie) Histogram display Reset EV Comp_(still image/movie) Exposure step_(still image/movie) Exposure Std. Adjust (still image/movie) Dial Ev Comp D-Range Optimizer (still image/movie) Metering Mode (still image/movie) Face Priority in Multi Metering (still image/movie) Spot Metering Point (still image/movie) AE Lock AEL w/ Shutter Zebra Display	- Focu	us Magnif. Time (still image/movie)
djusting the exposure/metering modes Exposure Comp_(still image/movie) Histogram display Reset EV Comp_(still image/movie) Exposure step_(still image/movie) Exposure Std_Adjust (still image/movie) Dial EV Comp DeRange_Optimizer (still image/movie) Metering_Mode_(still image/movie) Face Priority in Multi Metering_(still image/movie) Spot Metering Point (still image/movie) AE Lock AEL w/ Shutter Zebra Display,	- <u>Initia</u>	ıl Focus Mag. (still image)
djusting the exposure/metering modes - Exposure Comp. (still image/movie) Histogram display Reset EV Comp. (still image/movie) - Exposure step (still image/movie) Exposure Std. Adjust (still image/movie) - Dial Ev Comp - D-Range Optimizer (still image/movie) - Metering Mode (still image/movie) - Face Priority in Multi Metering (still image/movie) - Spot Metering Point (still image/movie) - AE Lock - AEL w/ Shutter - Zebra Display,	- <u>Initia</u>	ıl Focus Mag. (movie)
Exposure Comp. (still image/movie) Histogram display Reset EV Comp. (still image/movie) Exposure step (still image/movie) Exposure Std. Adjust (still image/movie) Dial Ev Comp D-Range Optimizer (still image/movie) Metering Mode (still image/movie) Face Priority in Multi Metering (still image/movie) Spot Metering Point (still image/movie) AE Lock AEL w/ Shutter Zebra Display	- <u>Peal</u>	<u>king Display</u>
Histogram display. Reset EV Comp_ (still image/movie). Exposure step (still image/movie). Exposure Std. Adjust (still image/movie). Dial Ev Comp D-Range Optimizer (still image/movie). Metering Mode (still image/movie). Face Priority in Multi Metering (still image/movie). Spot Metering Point (still image/movie). AE lock AEL w/ Shutter Zebra Display.		
Reset EV Comp. (still image/movie) Exposure step (still image/movie) Exposure Std. Adjust (still image/movie) Dial Ev Comp D-Range Optimizer (still image/movie) Metering Mode (still image/movie) Face Priority in Multi Metering (still image/movie) Spot Metering Point (still image/movie) AE lock AEL w/ Shutter Zebra Display	djusti	ng the exposure/metering modes
Exposure Std. Adjust (still image/movie) Exposure Std. Adjust (still image/movie) Dial Ev Comp D-Range Optimizer (still image/movie) Metering Mode (still image/movie) Face Priority in Multi Metering (still image/movie) Spot Metering Point (still image/movie) AE lock AEL w/ Shutter Zebra Display.		
Exposure Std. Adjust (still image/movie). Dial Ev Comp D-Range Optimizer (still image/movie). Metering Mode (still image/movie). Face Priority in Multi Metering (still image/movie). Spot Metering Point (still image/movie). AE lock AEL w/ Shutter Zebra Display.	Expo	osure Comp. (still image/movie)
Dial Ev Comp D-Range Optimizer (still image/movie) Metering Mode (still image/movie) Face Priority in Multi Metering (still image/movie) Spot Metering Point (still image/movie) AE lock AEL w/ Shutter Zebra Display	Histo	osure Comp. (still image/movie) ogram display
D-Range Optimizer (still image/movie) Metering Mode (still image/movie) Face Priority in Multi Metering (still image/movie) Spot Metering Point (still image/movie) AE lock AEL w/ Shutter Zebra Display	Histor Rese	et EV Comp. (still image/movie)
- Metering Mode (still image/movie) - Face Priority in Multi Metering (still image/movie) - Spot Metering Point (still image/movie) - AE lock - AEL w/ Shutter - Zebra Display	- <u>Histo</u>	psure Comp. (still image/movie) pgram display et EV Comp. (still image/movie) psure step (still image/movie)
- Face Priority in Multi Metering (still image/movie) Spot Metering Point (still image/movie) AE lock - AEL w/ Shutter - Zebra Display.	- Expo	posure Comp. (still image/movie) pogram display et EV Comp. (still image/movie) posure step (still image/movie) posure Std. Adjust (still image/movie)
- Spot Metering Point (still image/movie) - AE lock - AEL w/ Shutter - Zebra Display	- Rese - Expo	posure Comp. (still image/movie) pogram display et EV Comp. (still image/movie) posure step (still image/movie) posure Std. Adjust (still image/movie) Ev Comp
- AE lock - AEL w/ Shutter - Zebra Display	- Reserved Expo	posure Comp. (still image/movie) posure Std. Adjust (still image/movie) Ev Comp ange Optimizer (still image/movie).
- AEL w/ Shutter - Zebra Display	- Expo - Expo - Expo - Dial - D-Ra	posure Comp. (still image/movie) pogram display et EV Comp. (still image/movie) posure step (still image/movie) posure Std. Adjust (still image/movie) Ev Comp ange Optimizer (still image/movie) ering Mode (still image/movie)
- Zebra Display	- Expo	posure Comp. (still image/movie) posure Step (still image/movie) posure Step (still image/movie) posure Std. Adjust (still image/movie) Ev Comp ange Optimizer (still image/movie) pring Mode (still image/movie) priority in Multi Metering (still image/movie)
	- Expo - Expo - Expo - Dial - D-Ra - Mete - Spot	posure Comp. (still image/movie) posure step (still image/movie) posure step (still image/movie) posure Std. Adjust (still image/movie) Ev Comp ange Optimizer (still image/movie) pring Mode (still image/movie)
electing the ISO sensitivity	- Expo - Expo - Expo - Dial - D-Ra - Mete - Face - Spot	posure Comp. (still image/movie) posure Std. Adjust (still image/movie) Ev Comp. ange Optimizer (still image/movie) ering Mode (still image/movie) ering Mode (still image/movie) Ev Priority in Multi Metering (still image/movie) the Metering Point (still image/movie) cock
	- Expo - Expo - Expo - Dial - D-Ra - Mete - Spot - AE Id	pagram display. pet EV Comp_(still image/movie) pagram display. pet EV Comp_(still image/movie) pagram step_(still image/movie) pagram step_(still image/movie) pagram step_(still image/movie) Ev Comp ange Optimizer (still image/movie) pering_Mode (still image/movie) pering_Mode (still image/movie) pering_Point (still image/movie) pering_Point (still image/movie) peck w/ Shutter

-	SO Range Limit (still image/movie)
L.	ISO AUTO Min. SS
Νh	ite balance
-	White Balance (still image/movie)
-	Capturing a standard white color to set the white balance (custom white balance)
-	Priority Set in AWB (still image/movie)
-	Shutter AWB Lock
L.	Shockless WB
٩d٥	ling effects to images
-	Creative Look (still image/movie)
L	Picture Profile (still image/movie)
Sho	ooting with drive modes (continuous shooting/self-timer)
-	<u>Drive Mode</u>
-	Cont. Shooting
 -	Cont. Shooting Speed
-	Self-timer Type: Self-timer(Single)
·	Self-timer Type: Self-timer(Cont)
- -	Bracket Settings: Cont. Bracket
- -	Bracket Settings: Single Bracket
·	Indicator during bracket shooting
-	Bracket Settings: WB bracket
 -	Bracket Settings: DRO Bracket
-	Bracket Settings: Selftimer during Bracket
L-	Bracket Settings: Bracket order
nte	erval Shoot Func.
Sho	poting still images with a higher resolution (Pixel Shift Multi Shoot.)
Set	ting the image quality and recording format
-	JPEG/HEIF Switch
-	Image Quality Settings: File Format (still image)
-	Image Quality Settings: RAW File Type

L	Image Quality Settings: JPEG Quality/HEIF Quality
-	Image Quality Settings: JPEG Image Size/HEIF Image Size
-	Aspect Ratio
-	HLG Still Image
-	Color Space
-	File Format (movie)
-	Movie Settings (movie)
-	S&Q Settings
-	Proxy Settings
L	APS-C S35 (Super 35mm) Shooting (still image/movie)
L	Angle of view
Js	ing touch functions
-	Touch Operation
-	Touch Sensitivity
-	Touch Panel/Pad
L	Touch Pad Settings
-	Touch Func. in Shooting
-	Focusing using touch operations (Touch Focus)
L	Starting tracking with touch operations (Touch Tracking)
Sh	utter settings
-	Silent Mode Settings (still image/movie)
ŀ	Shutter Type
ŀ	<u>Using the electronic shutter</u>
-	Shoot. Start Display (still image)
_	Shoot. Timing Display (still image)
L	Release w/o Lens (still image/movie)
-	Release w/o Card
	Anti-flicker Set.

Js	ing the zoom
-	The zoom features available with this product
ŀ	Clear Image Zoom/Digital Zoom (Zoom)
ŀ	Zoom Range (still image/movie)
ŀ	Zoom Speed (still image/movie)
ŀ	Zoom Speed (Remote commander) (still image/movie)
ŀ	About zoom scale
L	Zoom Ring Rotate
Js	ing the flash
-	<u>Using flash (sold separately)</u>
-	Flash Mode
L	Flash Comp.
-	<u>Exp.comp.set</u>
ŀ	<u>Wireless Flash</u>
F	Flash Sync Spd. Prty.
-	Red Eye Reduction
F	FEL lock
L	External Flash Set.
-	Using a flash with a sync terminal cord
L	<u>Video Light Mode</u>
Re	ducing blur
-	SteadyShot (still image)
L	SteadyShot (movie)
ŀ	SteadyShot Adjust. (still image/movie)
L	SteadyShot focal length (still image/movie)
e	ns Compensation (still image/movie)
No	ise reduction
L	Long Exposure NR
	<u>High ISO NR</u>

0.00.00.00.00.00.00.00.00.00.00.00.00.0	also di Sanaha del
Setting the monitor dis	play during shooting
- Auto Review (still imag	<u>je)</u>
- Remain Shoot Display	(still image)
- Grid Line Display (still	<u>image/movie)</u>
- Grid Line Type (still im	<u>age/movie)</u>
- Live View Display Set.	
- <u>Aperture Preview</u>	
- <u>Shot. Result Preview</u>	
- Bright Monitoring	
- Emphasized REC Disp	<u>olay</u>
- <u>Marker Display</u>	
- Gamma Display Assist	<u>t</u>
Gamma Disp. Assist T	<u>ур.</u>
Recording movie audio	0
- <u>Audio Recording</u>	
- Audio Rec Level	
- Audio Out Timing	
- Wind Noise Reduct.	
- Shoe Audio Set.	
Audio Level Display	
TC/UB settings	
- TC/UB	
TC/UB Disp. Setting	
Customizing the cam	nera
Contents of this chapte	<u>er</u>
Customization feature	s of the camera
Assigning frequently u	sed functions to buttons (Custom Key Setting)
Changing the function	of the dial temporarily (My Dial Settings)
Registering and recalli	ing camera settings

- <u>C</u>	amera Set. Memory
- <u>R</u>	tecall Camera Setting
- <u>M</u>	lemory/Recall Media
L _R	tegistering shooting settings to a custom key (Reg. Custom Shoot Set)
Regi	istering frequently used functions to the function menu
L _E	n Menu Settings
Regi	istering frequently used functions to My Menu
- <u>A</u>	<u>dd Item</u>
- <u>s</u>	ort Item
- <u>D</u>	elete Item
- <u>D</u>	delete Page
- <u>D</u>	elete All
	<u>visplay From My Menu</u>
Sepa	arately adjusting the camera settings for still images and movies
L _D	ifferent Set for Still/Mv
Cust	tomizing the functions of the ring/dial
- <u>A</u>	v/Tv Assign in M
- <u>A</u>	v/Tv Rotate
- <u>E</u>	unction Ring(Lens)
	ock Operation Parts
Reco	ording movies by pressing the shutter button
L _R	EC w/ Shutter (movie)
Mon	itor/viewfinder settings
- <u>S</u>	elect Finder/Monitor
L _D	USP (Screen Disp) Set (Monitor/Finder)
View	ving
Cont	tents of this chapter
View	ving images
- <u>s</u>	electing which memory card to play back (Select Playback Media)
- <u>P</u>	laying back still images

ı	
r	Enlarging an image being played back (Enlarge Image)
-	Enlarge Initial Mag.
-	Enlarge Initial Position
ŀ	Rotating recorded images automatically (Display Rotation)
ŀ	Playing back movies
ŀ	<u>Volume Settings</u>
ŀ	4ch Audio Monitoring (movie)
ŀ	Playing back images using slideshow (Slide Show)
ŀ	Cont. Play for Interval
L	Play Speed for Interval
Cł	nanging how images are displayed
ŀ	Playing back images on the image index screen (Image Index)
L	Switching between still images and movies (View Mode)
ŀ	<u>Display as Group</u>
L	Focus Frame Display (playback)
Se	etting how to jump between images
L	Select Image Jump Dial
L	Image Jump Method
⊃r	otecting recorded still images (Protect)
4 c	Iding information to images
L	<u>Rating</u>
l	Rating Set(Custom Key)
F	
- -	Attaching audio files to images (Voice Memo)
-	Attaching audio files to images (Voice Memo) Voice Memo Play Vol.
-	
- - - -	Voice Memo Play Vol.
	Voice Memo Play Vol. Rotating an image (Rotate)
	Voice Memo Play Vol. Rotating an image (Rotate)

<u>Cop</u>	<u>ying images from one memory card to another (Copy)</u>
Dele	eting images
- <u>D</u>	eleting multiple selected images (Delete)
- - <u>D</u>	elete pressing twice
	elete confirm.
View	ving images on a TV
L	iewing images on a TV using an HDMI cable
Cha	nging the camera settings
Men	nory card settings
- E	<u>ormat</u>
- <u>R</u>	dec. Media Settings (still image/movie): Recording Media (still image)
- <u>R</u>	dec. Media Settings (still image/movie): Recording Media (movie)
- <u>R</u>	dec. Media Settings (still image/movie): Auto Switch Media
- <u>s</u>	elect REC Folder
- <u>C</u>	reate New Folder
- <u>R</u>	decover Image DB (still image/movie)
	risplay Media Info. (still image/movie)
File	settings
- <u>E</u>	ile/Folder Settings
- - <u>E</u>	<u>ile Settings</u>
- <u>I</u> E	PTC Information
- <u>C</u>	<u>copyright Info</u>
_ <u>v</u>	√rite Serial Number
Netv	vork settings
- <u>s</u>	martphone Connection
- <u>C</u>	Connection (smartphone connection information)
- <u>A</u>	lways Connected (smartphone)
- <u>В</u>	luetooth Rmt Ctrl
_ <u>v</u>	VPS Push
_ A	ccess Point Set.

_	Wi-Fi Frequency Band (models supporting 5 GHz)
	<u>Display Wi-Fi Info.</u>
	SSID/PW Reset
_	Bluetooth Settings
-	Wired LAN
_	Airplane Mode
_	Edit Device Name
	Importing root certification to the camera (Import Root Certificate)
_	Security(IPsec)
-	Reset Network Set.
-	FTP Transfer Func.
ΪE	ewfinder/monitor settings
-	Monitor Brightness
-	Viewfinder Bright.
-	Finder Color Temp.
-	Viewfinder Magnifi.
-	Finder Frame Rate (still image)
-	Auto Monitor OFF (still image)
0	wer settings
	Power Save Start Time
-	Auto Power OFF Temp.
	<u>Display Quality</u>
S	B settings
-	USB Connection
-	USB LUN Setting
_	USB Power Supply
X	ternal output settings
_	HDMI Resolution
	HDMI Output Settings (movie)
L	HDMI Info. Display

_ <u>c</u>	TRL FOR HDMI
Gen	eral settings
- <u>La</u>	anguage_
- <u>A</u>	rea/Date/Time Setting
- <u>N</u>	TSC/PAL Selector
- <u>A</u>	udio signals
- <u>IE</u>	R Remote Ctrl
- <u>A</u>	nti-dust Function
- <u>A</u>	uto Pixel Mapping
- <u>P</u>	ixel Mapping
- <u>v</u>	ersion_
- <u>s</u>	ave/Load Settings
S	etting Reset
Coni	necting the camera and a smartphone
_ <u>c</u>	onnecting the camera and a smartphone using the QR Code
- <u>C</u>	onnecting the camera and a smartphone using the SSID and password
_ 0	ne-touch connection with NFC
Usin	g a smartphone as a remote commander
- <u>u</u>	sing a smartphone as a remote commander
L <u>R</u>	emote Shoot Setting (smartphone)
Tran	sferring images to a Smartphone
L _S	elect on Cam & Send (transferring to a smartphone)
Coni	necting while the camera is turned OFF
L _C	nct. during Power OFF
Read	ding location information from a smartphone
L Lo	ocation Information
Jsin	ng a computer
	

Recomn	mended computer environment			
Connecting/disconnecting the camera and a computer				
- Conne	ecting the camera to a computer			
Disco	nnecting the camera from the computer			
Managing and editing images on a computer				
- Introd	luction to computer software (Imaging Edge Desktop/Catalyst)			
<u>Impor</u>	ting images to the computer			
Operating the camera from a computer (PC Remote Function)				
Remote shooting with a wired LAN (Remote Camera Tool)				
Append	dix			
Audio a	ccessories compatible with the Multi Interface Shoe			
<u>Vertical</u>	<u>grip</u>			
Mount A	Adaptor			
- <u>Moun</u>	t Adaptor			
- <u>LA-E</u>	43/LA-EA5 Mount Adaptor			
LA-EA	A4 Mount Adaptor			
<u>Multi Ba</u>	ittery Adaptor Kit			
Battery I	life and number of recordable images			
Number	of recordable images			
Recorda	able movie times			
List of ic	cons on the monitor			
List of d	efault setting values			
<u>Specific</u>	<u>ations</u>			
Tradema	<u>arks</u>			
<u>License</u>				
lf you h	ave problems			
Troubles	<u>shooting</u>			
<u>Warning</u>	<u>g messages</u>			

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

How to use the "Help Guide"

The "Help Guide" is a "Web Instruction Manual" that has been designed to describe the functions and operating methods of this camera. Use the "Help Guide" to search for any information that you require in order to make full use of the camera.

(The "Help Guide" screens shown on this page are for reference only. They may differ from the actual on-screen display of your model.)

Hint

The "Operating Instructions" supplied with the camera describes basic operating methods and precautions for use. Please refer to the "Operating Instructions" in combination with this "Help Guide."

Finding your desired information

Method A: Searching by keyword

Enter a search keyword ("white balance," "focus area," etc.), and use the search results to display the description page that you want to view. If you enter two or more keywords by separating them with spaces (blanks), you can search for pages that contain all of those keywords.


Method B: Viewing the table of contents

Select a heading from the table of contents to display the description page.

Screen displayed on a computer




Screen displayed on a smartphone




Method C: Finding functions from MENU

If you want to search for information while checking it against the MENU screen of the camera, use the "Finding functions from MENU" page. Select a MENU item from the list to go directly to the description page.



Viewing information about related features

"Related Topic" at the bottom of each page lists sections that contain information related to the description page currently being displayed. For a deeper understanding of the currently displayed page, refer to the listed sections as well.



Printing all the pages of the "Help Guide"

To print all the pages, select the [T] Printable PDF] button in the upper right corner of the top page. When the PDF file appears, use the printing menu of the browser to print it out.

This function is not available for certain languages.



Printing only the currently displayed page (only on a computer)

To print only the page currently being displayed, select the [Print] button at the top of the page. When the printing screen appears, specify your printer.



Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Checking the camera and the supplied items

The number in parentheses indicates the number of pieces.

- Camera (1)
- Battery Charger (1)



Power cord (mains lead) (1)*




* Multiple power cords may be supplied with your camera. Use the appropriate one that matches your country/region.


NP-FZ100 Rechargeable Battery Pack (1)



USB Type-C cable (1)




Shoulder Strap (1)



Body Cap (1) (Attached to the camera)



Cable Protector (1)



Shoe Cap (1) (Attached to the camera)



Eyepiece Cup (1) (Attached to the camera)



- Operating Instructions (1)
- Reference Guide (1)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Memory cards that can be used

This camera supports CFexpress Type A memory cards and SD memory cards (UHS-I, UHS-II compatible). When using microSD memory cards with this camera, be sure to use the appropriate adaptor.

For still-image shooting

The following memory cards can be used.

- CFexpress Type A memory cards
- SD/SDHC/SDXC memory cards

For movie recording

Movie recording formats and compatible memory cards are as follows.

File Format	Maximum recordable bit rate	Supported memory card
XAVC HS 8K	520Mbps *1	 CFexpress Type A memory card (VPG200 or higher) SDXC V90 or higher *2
XAVC HS 4K	280Mbps	CFexpress Type A memory card (VPG200 or higher)SDXC V60 or higher
XAVC S 4K	280Mbps	CFexpress Type A memory card (VPG200 or higher)SDXC V60 or higher
XAVC S HD	100Mbps	CFexpress Type A memory cardSDHC/SDXC card (U3 or higher)
XAVC S-I 4K	600Mbps	CFexpress Type A memory card (VPG200 or higher)SDXC V90 or higher
XAVC S-I HD	222Mbps	CFexpress Type A memory card (VPG200 or higher)SDXC V90 or higher

^{*1 400} Mbps if the camera's system software (firmware) version is earlier than Ver.1.30

For S&Q Motion shooting

File formats and compatible memory cards are as follows.

In slow-motion recording, the recording bit rate is higher than usual. You may need a memory card that can be written at a higher speed.

Slow-motion and quick-motion movie shooting are not available with [XAVC HS 8K].

^{*2} V60 or higher if the camera's system software (firmware) version is earlier than Ver.1.30

File Format	Maximum recordable bit rate	Supported memory card
XAVC HS 4K	500Mbps	 CFexpress Type A memory card (VPG200 or higher) SDXC V60 or higher*1
XAVC S 4K	560Mbps	 CFexpress Type A memory card (VPG200 or higher) SDXC V60 or higher*1
XAVC S HD	500Mbps	 CFexpress Type A memory card (VPG200 or higher) SDXC V60 or higher*2
XAVC S-I 4K	1200Mbps	 CFexpress Type A memory card (VPG200 or higher) SDXC V90 or higher*3
XAVC S-I HD	890Mbps	 CFexpress Type A memory card (VPG200 or higher) SDXC V90 or higher*4

^{*1} When [SaQ Frame Rate] is set to [120fps]/[100fps], you may need an SDXC V90 memory card.

Hint

When the recording bit-rate is 200 Mbps, you can also record using an SDXC card (U3/V30).

Note

- When shooting a proxy movie, a higher-speed memory card may be required.
- CFexpress Type B memory cards cannot be used.
- When an SDHC memory card is used to record an XAVC S movie over extended periods of time, the recorded movies will be divided into files 4 GB in size.
- When recording a movie on memory cards in both the Slot 1 and the Slot 2 with following camera settings, insert two memory cards with the same file system. Movies cannot be recorded simultaneously when using a combination of the exFAT file system and FAT32 file system.

Memory card	File system
CFexpress Type A memory card, SDXC memory card	exFAT
SDHC memory card	FAT32

Charge the battery pack sufficiently before attempting to recover the database files on the memory card.

Related Topic

- Notes on memory card
- Number of recordable images
- Recordable movie times
- S&Q Settings

^{*2} When [St0 Frame Rate] is set to [240fps]/[200fps], you may need an SDXC V90 memory card.

^{*3} For slow-motion recording, a CFexpress Type A memory card (VPG200 or higher) is required.

^{*4} When [Sto Frame Rate] is set to [240fps]/[200fps], a CFexpress Type A memory card (VPG200 or higher) is required.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Precautions

Refer also to "Notes on using your camera" in the Operating Instructions (supplied) for this product.

On the data specifications described in this manual

- The data on performance and specifications in this manual are based on an ordinary ambient temperature of 25°C (77°F), except where otherwise indicated.
- For the battery pack, the data are based on a battery pack that was fully charged until the charge lamp turned off.

On operating temperatures

- Shooting in extremely cold or hot environments that exceed the operating temperature range is not recommended.
- Under high ambient temperatures, the temperature of the camera rises quickly.
- When the temperature of the camera rises, the image quality may deteriorate. It is recommended that you wait until the temperature of the camera drops before continuing to shoot.
- Depending on the camera and battery temperature, the camera may become unable to record movies or the power may turn off automatically to protect the camera. A message will be displayed on the screen before the power turns off or you can no longer record movies. In this case, leave the power off and wait until the camera and battery temperature goes down. If you turn on the power without letting the camera and battery cool sufficiently, the power may turn off again, or you may still be unable to record movies.

Notes on recording for long periods of time or recording 4K/8K movies

Especially during 4K/8K shooting, the recording time may be shorter under low temperature conditions. Warm up the battery pack or replace it with a new battery.

Notes on playing movies on other devices

XAVC HS and XAVC S movies can only be played back on compatible devices.

Notes on recording/playback

- Before you start recording, make a trial recording to make sure that the camera is working correctly.
- Playback of images recorded with your product on other equipment and playback of images recorded or edited with other equipment on your product are not guaranteed.
- Sony can provide no guarantees in the event of failure to record, or loss of or damage to recorded images or audio data, due to a malfunction of the camera or recording media, etc. We recommend backing up important data.
- Once you format the memory card, all the data recorded on the memory card will be deleted and cannot be restored.
 Before formatting, copy the data to a computer or other device.

Backing up memory cards

Data may be corrupted in the following cases. Be sure to back up the data for protection.

- When the memory card is removed, the USB cable is disconnected, or the product is turned off in the middle of a read or write operation.
- When the memory card is used in locations subject to static electricity or electrical noise.

Database file error

- If you insert a memory card that does not contain an image database file into the product and turn on the power, the product automatically creates an image database file using some of the memory card's capacity. The process may take a long time and you cannot operate the product until the process is completed.
- If a database file error occurs, export all images to your computer, and then format the memory card using this
 product.

Do not use/store the product in the following places

- In an extremely hot, cold or humid place
 In places such as in a car parked in the sun, the camera body may become deformed and this may cause a malfunction.
- Storing under direct sunlight or near a heater
 The camera body may become discolored or deformed, and this may cause a malfunction.
- In a location subject to rocking vibration
 It may cause malfunctions and an inability to record data. In addition, the recording media may become unusable, and recorded data may be corrupted.
- Near strong magnetic place
- In sandy or dusty places
 - Be careful not to let sand or dust get into the product. This may cause the product to malfunction, and in some cases this malfunction cannot be repaired.
- In places with high humidity
 This may cause the lens to mold.
- In areas where strong radio waves or radiation are being emitted Recording and playback may not function correctly.

On moisture condensation

- If the product is brought directly from a cold to a warm location, moisture may condense inside or outside the product. This moisture condensation may cause a malfunction of the product.
- To prevent moisture condensation when you bring the product directly from a cold to a warm location, first put it in a plastic bag and seal it to prevent air from entering. Wait for about an hour until the temperature of the product has reached the ambient temperature.
- If moisture condensation occurs, turn off the product and wait about an hour for the moisture to evaporate. Note that if you attempt to shoot with moisture remaining inside the lens, you will be unable to record clear images.

Precaution on carrying

- Do not hold, hit, or apply excessive force to the following parts, if your camera is equipped with them:
 - The lens part
 - The movable monitor part
 - The movable flash part
 - The movable viewfinder part
- Do not carry the camera with the tripod attached. This may cause the tripod socket hole to break.
- Do not sit down in a chair or other place with the camera in the back pocket of your trousers or skirt, as this may cause malfunction or damage the camera.

Notes on handling the product

- Before you connect the cable to the terminal, be sure to check the orientation of the terminal. Then, insert the cable straight. Do not insert or remove the cable forcefully. This may cause the terminal part to break.
- The camera uses magnetic parts including magnets. Do not bring objects affected by magnetism, including credit cards and floppy disks, close to the camera.
- The recorded image may be different from the image you monitored before recording.

On storing

- For lens-integrated cameras
 Always attach the lens cap when you are not using the camera. (Only for models supplied with a lens cap)
- For interchangeable-lens cameras
 Always attach the lens front cap or body cap when you are not using the camera. To prevent dust or debris from getting inside the camera, remove dust from the body cap before attaching it to the camera.
- If the camera is dirty after use, clean it. Water, sand, dust, salt, etc. left in the camera may cause a malfunction.

Notes on using lenses

- When using the power zoom lens, be careful not to get your fingers or any other objects caught in the lens. (Only for models with a power zoom feature or interchangeable lens cameras)
- If you must place the camera under a light source such as sunlight, attach the lens cap to the camera. (Only for models supplied with a lens cap or interchangeable lens cameras)
- If sunlight or a strong light source enters the camera through the lens, it may focus inside the camera and cause smoke or fire. Attach the lens cap to the lens when storing the camera. When you shoot with backlighting, keep the sun sufficiently far away from the angle of view. Note that smoke or fire may occur even if the light source is slightly away from the angle of view.
- Do not directly expose the lens to beams such as laser beams. That may damage the image sensor and cause the camera to malfunction.
- If the subject is too close, the image may show any dust or fingerprints on the lens. Wipe the lens with a soft cloth, etc.

Notes on the flash (Only for models with a flash)

- Keep your fingers away from the flash. The light-emitting part may get hot.
- Remove any dirt from the surface of the flash. Dirt on the surface of the flash may emit smoke or burn due to heat generated by the emission of light. If there is dirt/dust, clean it off with a soft cloth.
- Restore the flash to its original position after using it. Make sure that the flash portion is not sticking up. (Only for models with a movable flash)

Notes on the Multi Interface Shoe (Only for models with a Multi Interface Shoe)

- When attaching or detaching accessories such as an external flash to the Multi Interface Shoe, first turn the power to OFF. When attaching the accessory, confirm that it is firmly fastened to the camera.
- Do not use the Multi Interface Shoe with a commercially available flash that applies voltages of 250 V or more or has
 the opposite polarity of the camera. It may cause a malfunction.

Notes on the viewfinder and flash (Only for models with a viewfinder or a flash)

- Take care that your finger is not in the way when pushing the viewfinder or flash down. (Only for models with a movable viewfinder or a movable flash)
- If water, dust or sand adheres to the viewfinder or flash unit, it may cause a malfunction. (Only for models with a movable viewfinder or a movable flash)

Notes on the viewfinder (Only for models with a viewfinder)

- When shooting with the viewfinder, you may experience symptoms such as eyestrain, fatigue, travel sickness, or nausea. We recommend that you take a break at regular intervals when you are shooting with the viewfinder.
 In case you may feel uncomfortable, refrain from using the viewfinder until your condition recovers, and consult your doctor if necessary.
- Do not forcibly push down the viewfinder when the eyepiece is pulled out. It may cause a malfunction. (Only for models with a movable viewfinder and an eyepiece that can be pulled out)
- If you pan the camera while looking into the viewfinder or move your eyes around, the image in the viewfinder may be distorted or the color of the image may change. This is a characteristic of the lens or display device and is not a malfunction. When you shoot an image, we recommend that you look at the center area of the viewfinder.
- The image may be slightly distorted near the corners of the viewfinder. This is not a malfunction. When you want to see the full composition with all its details, you can also use the monitor.
- If you use the camera in a cold location, the image may have a trailing appearance. This is not a malfunction.

Notes on the monitor

- Do not press against the monitor. The monitor may be discolored and that may cause a malfunction.
- If the monitor has drops of water or other liquids on it, wipe it with a soft cloth. If the monitor stays wet, the surface of the monitor may change or deteriorate. This may cause a malfunction.
- If you use the camera in a cold location, the image may have a trailing appearance. This is not a malfunction.
- When you connect cables to the terminals on the camera, the rotating range of the monitor may become limited.

Notes on the image sensor

If you point the camera at an extremely strong light source while shooting images with a low ISO sensitivity, highlighted areas in the images may be recorded as black areas.

On image data compatibility

This product conforms with DCF (Design rule for Camera File system) universal standard established by JEITA (Japan Electronics and Information Technology Industries Association).

Services and software provided by other companies

Network services, content, and the [operating system and] software of this Product may be subject to individual terms and conditions and changed, interrupted or discontinued at any time and may require fees, registration and credit card information.

Notes on connecting to the internet

To connect the camera to a network, connect it through a router or a LAN port with the same function. Failure to connect in this manner may result in security issues.

Notes on security

- SONY WILL NOT BE HELD LIABLE FOR DAMAGES OF ANY KIND RESULTING FROM FAILURE TO IMPLEMENT PROPER SECURITY MEASURES ON TRANSMISSION DEVICES, UNAVOIDABLE DATA LEAKS CAUSED BY TRANSMISSION SPECIFICATIONS, OR OTHER SECURITY PROBLEMS.
- Depending on the usage environment, unauthorized third parties on the network may be able to access the product.
 When connecting the camera to a network, be sure to confirm that the network is protected securely.
- The content of communications may be unknowingly intercepted by unauthorized third parties in the vicinity of the signals. When using wireless LAN communication, implement proper security measures to protect the content of communications.

Notes on the FTP function

Since content, usernames, and passwords are not encrypted using normal FTP, use FTPS if it is available.

Optional accessories

- It is recommended that you use genuine Sony accessories.
- Some Sony accessories are only available in certain countries and regions.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Notes on the battery pack and charging the battery

Notes on using the battery pack


- Be sure to use only genuine Sony brand battery packs.
- The correct remaining battery indicator may not be displayed under some operating or environmental conditions.
- Do not expose the battery pack to water. The battery pack is not water-resistant.
- Do not leave the battery pack in extremely hot places, such as in a car or under direct sunlight.

Notes on charging the battery pack

- Charge the battery pack (supplied) before using the product for the first time.
- The charged battery pack will discharge little by little even if you do not use it. Charge the battery pack each time before you use the product so that you do not miss any opportunities to shoot images.
- Do not charge battery packs except battery packs specified for this product. Doing so can result in leaks, overheating, explosions, electric shocks, burns, or injuries.
- When you use a completely new battery pack or a battery pack that has not been used for a long time, the charge lamp (CHARGE) may flash quickly when the battery is charged. If this happens, remove the battery pack and then re-insert it to recharge.
- We recommend charging the battery pack in an ambient temperature of between 10 °C and 30 °C (50 °F and 86 °F).
 The battery pack may not be correctly charged in temperatures outside this range.
- Operation cannot be guaranteed with all external power supplies.
- After charging is finished, disconnect the charger from the wall outlet (wall socket) if charging with a charger, or disconnect the USB cable from the camera if charging the battery pack while it is inserted into the camera. Not doing so may result in a shorter battery life.
- Do not continuously or repeatedly charge the battery pack without using it if it is already fully charged or close to fully charged. Doing so may cause a deterioration in battery performance.
- If the product's charge lamp flashes while charging, remove the battery pack being charged, and then insert the same battery pack firmly back into the product. If the charge lamp flashes again, this may indicate a faulty battery or that a battery pack other than the specified type has been inserted. Check that the battery pack is the specified type. If the battery pack is the specified type, remove the battery pack, replace it with a new or different one and check that the newly inserted battery is charging correctly. If the newly inserted battery is charging correctly, the previously inserted battery may be faulty.

Remaining battery indicator

The remaining battery indicator appears on the screen.



B: Battery exhausted

- It takes about one minute for the correct remaining battery indicator to appear.
- The correct remaining battery indicator may not be displayed under some operating or environmental conditions.
- If the remaining battery indicator does not appear on the screen, press the DISP (Display Setting) button to display it.

Effective use of the battery pack

- Battery performance decreases in low temperature environments. So in cold places, the operational time of the battery pack is shorter. To ensure longer battery pack use, we recommend putting the battery pack in your pocket close to your body to warm it up, and insert it in the product immediately before you start shooting. If there are any metal objects such as keys in your pocket, be careful of causing a short-circuit.
- The battery pack will run down quickly if you use the flash or continuous shooting function frequently, turn the power on/off frequently, or set the monitor very bright.
- We recommend preparing spare battery packs and taking trial shots before taking the actual shots.
- If the battery terminal is dirty, you may not be able to turn on the product or the battery pack may not be properly charged. In that case, clean the battery by lightly wiping off any dust using a soft cloth or a cotton swab.

How to store the battery pack

To maintain the battery pack's function, charge the battery pack and then fully discharge it in the camera at least once a year before storing it. Store the battery in a cool, dry place after removing it from the camera.

On battery life

- The battery life is limited. If you use the same battery repeatedly, or use the same battery for a long period, the battery capacity decreases gradually. If the available time of the battery is shortened significantly, it is probably time to replace the battery pack with a new one.
- The battery life varies according to how the battery pack is stored and the operating conditions and environment in which each battery pack is used.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Notes on memory card

- If [1] (overheating warning icon) is displayed on the monitor, do not remove the memory card from the camera right away. Instead, wait for a while after turning off the camera, and then remove the memory card. If you touch the memory card while it is hot, you may drop it and the memory card may be damaged. Be careful when removing the memory card.
- If you repeatedly shoot and delete images for a long time, fragmentation of data in a file in the memory card may occur, and movie recording may be interrupted in the middle of shooting. If this happens, save your images to a computer or other storage location, then execute [Format] using this camera.
- Do not remove the battery pack or the memory card, disconnect the USB cable, or turn the camera off while the
 access lamp is lit up. This may cause the data on the memory card to become damaged.
- Be sure to back up the data for protection.
- Not all memory cards are guaranteed to operate correctly.
- Images recorded on an SDXC/CFexpress Type A memory card cannot be imported to or played on computers or AV devices not compatible with exFAT when connected using a USB cable. Make sure that the device is compatible with exFAT before connecting it to the camera. If you connect your camera to an incompatible device, you may be prompted to format the card. Never format the card in response to this prompt, as doing so will erase all data on the card.

(exFAT is the file system used on SDXC memory cards or CFexpress Type A memory cards.)

- Do not expose the memory card to water.
- Do not strike, bend or drop the memory card.
- Do not use or store the memory card under the following conditions:
 - High temperature locations such as in a car parked under the sun
 - Locations exposed to direct sunlight
 - Humid locations or locations with corrosive substances present
- If the memory card is used near areas with strong magnetization, or used in locations subject to static electricity or electrical noise, the data on the memory card may become damaged.
- Do not touch the terminal section of the memory card with your hand or a metal object.
- Do not leave the memory card within the reach of small children. They might accidentally swallow it.
- Do not disassemble or modify the memory card.
- The memory card may be hot just after it has been used for a long time. Be careful when you handle it.
- Memory card formatted with a computer is not guaranteed to operate with the product. Be sure to format the memory card using this product.
- Data read/write speeds differ depending on the combination of the memory card and the equipment used.
- Do not press down hard when writing in the memo space on the memory card.
- Do not attach a label on the memory card itself nor on a memory card adaptor. You may not be able to remove the memory card.
- If the write-protect switch or delete-protect switch of an SD memory card is set to the LOCK position, you cannot record or delete images. In this case, set the switch to the record position.
- To use a microSD memory card with this product:
 - Be sure to insert the memory card into a dedicated adaptor. If you insert a memory card into the product without a memory card adaptor, you might not be able to remove it from the product.
 - When inserting a memory card into a memory card adaptor, be sure that the memory card is inserted in the correct direction and then insert it as far as it will go. If the card is not inserted properly, it may result in a malfunction.

Help Guide


Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Cleaning the image sensor (Sensor Cleaning)

If dust or debris gets inside the camera and adheres to the surface of the image sensor (the part that converts the light to an electric signal), it may appear as dark spots on the image, depending on the shooting environment. If this happens, clean the image sensor quickly by following the steps below.

- 1 Confirm that the battery has been charged sufficiently.
- MENU → (Setup) → [Setup Option] → [Anti-dust Function] → [Sensor Cleaning] → [Enter].

 The image sensor vibrates a little to shake off the dust.
- 3 Detach the lens.
- Use a commercially available blower to clean the image sensor surface and the surrounding area.
 - Hold the camera slightly face downward so that the dust falls out.



- Turn off the camera.
- 6 Attach the lens.

Hint

For how to check the amount of dust on the image sensor, and for further details on cleaning methods, please refer to the following URL.

https://support.d-imaging.sony.co.jp/www/support/ilc/sensor/index.php

Note

- When executing the cleaning mode, attach or remove the lens with the camera turned on.
- Do not turn off the camera during cleaning.
- Make sure that the remaining battery level is (3 remaining battery icons) or more, before performing the cleaning.
- Do not use a spray type blower as it may scatter water droplets inside the camera body.
- Do not put the tip of a blower into the cavity beyond the lens mount area, so that the tip of the blower does not touch the image sensor.

- When cleaning the image sensor with a blower, do not blow too hard. If you blow the sensor too hard, the inside of the product may be damaged.
- If the dust remains even after you cleaned the product as described, consult the service facility.
- During cleaning, the image sensor emits a vibrating noise. This is not a malfunction.
- Cleaning may be performed automatically when the power is turned off.

Related Topic

- Attaching/removing a lens
- Anti-dust Function

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

On cleaning

Cleaning the lens

- Do not use a cleaning solution containing organic solvents, such as thinner, or benzine.
- When cleaning the lens surface, remove dust with a commercially available blower. In case of dust that sticks to the surface, wipe it off with a soft cloth or tissue paper slightly moistened with lens cleaning solution. Wipe in a spiral pattern from the center to the outside. Do not spray lens cleaning solution directly onto the lens surface.

Cleaning the camera body

Do not touch the parts of the product inside the lens mount, such as a lens signal contact. To clean inside the lens mount, use a commercially available blower* to blow any dust off.

* Do not use a spray-type blower as doing so may cause a malfunction.

Cleaning the product surface

Clean the product surface with a soft cloth slightly moistened with water, then wipe the surface with a dry cloth. To prevent damage to the finish or casing:

- Do not expose the product to chemical products such as thinner, benzine, alcohol, disposable cloths, insect repellent, sunscreen or insecticide.
- Do not touch the product with any of the above on your hand.
- Do not leave the product in contact with rubber or vinyl for a long time.


Cleaning the monitor


- If you wipe the monitor firmly using tissue paper, etc., the monitor may be scratched.
- If the monitor becomes dirty with fingerprints or dust, gently remove the dust from the surface, and then clean the monitor using soft cloth, etc.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Front side





- 1. ON/OFF (Power) switch/Shutter button
- 2. Front dial

You can quickly adjust the settings for each shooting mode.

- 3. Infrared remote sensor
- 4. Lens release button
- 5. Microphone

Do not cover this part during movie recording. Doing so may cause noise or lower the volume.

- **6.** AF illuminator/Self-timer lamp/Visible light and IR sensor Do not cover this part during shooting.
- **7.** Mounting index
- 8. Image sensor*
- 9. Mount
- 10. Lens contacts*
- * Do not directly touch these parts.

Related Topic


- Rear side
- Top side

- Sides
- Bottom

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1


Rear side



- 1. Viewfinder
- 2. Eyepiece Cup

To remove the eyepiece cup

Push the grips at the bottom of the eyepiece cup to the left and right and lift up the cup.



- 3. For shooting: C3 button (Custom button 3)
 - For viewing: On (Protect) button
- 4. MENU button
- **5.** Monitor (For touch operation: Touch panel/Touch pad)
 You can adjust the monitor to an easily viewable angle and shoot from any position.



- 6. Eye sensor
- 7. Diopter-adjustment dial

Adjust the diopter-adjustment dial according to your eyesight until the display appears clearly in the viewfinder. If it is hard to operate the diopter-adjustment dial, remove the eyepiece cup before operating the dial.



- 8. MOVIE (Movie) button
- For shooting: AF-ON (AF On) button For viewing:
 (Enlarge) button
- **10.** For shooting: AEL button

[AEL hold] is assigned to the AEL button in the default settings.

For viewing: [Image index] button

- 11. Multi-selector
- 12. For shooting: Fn (Function) button

For viewing: <a>Tor viewing: (Send to Smartphone) button

You can display the screen for transferring images to a smartphone by pressing this button.

- 13. Control wheel
- 14. Access lamp
- **15.** For shooting: C4 button (Custom button 4)

For viewing: (Delete) button

16. ► (Playback) button


Related Topic

- Front side
- Top side
- Sides
- Bottom

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Top side



1. Mode dial

The mode dial is unlocked while you hold down the unlock button at the center.

2. Rear dial


You can quickly adjust the settings for each shooting mode.

3. Exposure compensation dial

Pressing the lock button at the center switches the exposure compensation dial between the locked and unlocked status. The dial is unlocked when the lock button is popped up and the white line is visible.

4. Image sensor position mark

• The image sensor is the sensor that converts light into an electric signal. The position of the image sensor is indicated by (Image sensor position mark). When you measure the exact distance between the camera and the subject, refer to the position of the horizontal line.



- If the subject is closer than the minimum shooting distance of the lens, the focus cannot be confirmed. Make sure you put enough distance between the subject and the camera.
- 5. C1 button (Custom button 1)
- 6. C2 button (Custom button 2)
- 7. Multi Interface Shoe*

Some accessories may not go in all the way and protrude backward from the Multi interface shoe. However, when the accessory reaches the front end of the shoe, the connection is completed.

8. Upper: Drive mode dial

The drive mode dial is unlocked while the unlock button at the center is being pressed.

Lower: Focus mode dial

The focus mode dial is unlocked while the unlock button on the back is being pressed.

* For details on compatible accessories for the Multi Interface Shoe, visit the Sony website, or consult your Sony dealer or local authorized Sony service facility.

Accessories for the Accessory Shoe can also be used. Operations with other manufacturers' accessories are not guaranteed.






Related Topic

- Front side
- Rear side
- Sides
- Bottom

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Sides



- 1. LAN terminal
- 2. **4** (Flash sync) terminal
- 3. Speaker
- 4. Multi/Micro USB Terminal*


This terminal supports Micro USB-compatible devices.

5. (Microphone) jack

When an external microphone is connected, the built-in microphone turns off automatically. When the external microphone is a plugin-power type, the power of the microphone is supplied by the camera.


- 6. (Headphones) jack
- 7. HDMI type A jack
- 8. Charge lamp
- 9. USB Type-C terminal
- 10. Hooks for shoulder strap

Attach both ends of the strap onto the camera.



11. N (N-Mark)

• This mark indicates the touch point for connecting the camera and an NFC-enabled Smartphone.



- NFC (Near Field Communication) is an international standard of short-range wireless communication technology.
- 12. SLOT 1 (Memory card slot 1)
- 13. SLOT 2 (Memory card slot 2)
- * For details on compatible accessories for the Multi/Micro USB Terminal, visit the Sony website, or consult your Sony dealer or local authorized Sony service facility.

Notes on USB terminals

You can use either the USB Type-C terminal or the Multi/Micro USB Terminal for USB communications. However, you cannot conduct USB communications with both terminals simultaneously. Use the USB Type-C terminal to supply power and charge the battery pack. This camera cannot be powered via the Multi/Micro USB terminal.

You can use accessories for the Multi/Micro USB Terminal, such as a remote commander (sold separately), while supplying power or performing PC Remote shooting using the USB Type-C terminal.

Notes on the terminal cover


Ensure that the terminal cover is closed before use.

Notes on the cable protector


Use the cable protector to prevent a cable from being disconnected when shooting images with the cable connected.

To attach the cable protector


1. Open the headphone terminal cover, HDMI terminal cover, and Multi/Micro USB terminal cover.



- 2. Fit the hook (A) of the cable protector into the notch (B) below the USB Type-C terminal, and attach it so that it covers the terminal surface of the camera while pressing down to keep it from coming off.
- 3. Push the attachment screw (C) in and turn it to secure the cable protector.



- 4. Insert the cable into one of the jacks.
- 5. Insert the cable into the holding part and then secure the cable with the fixing dial (D).



To remove the cable protector

Loosen the attachment screw, and then remove the cable protector.


Related Topic

- Front side
- Rear side
- Top side
- Bottom

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Bottom




- 1. Lock lever
- 2. Battery insertion slot
- 3. Battery cover

When attaching an accessory such as a vertical grip (sold separately), remove the battery cover.


To remove the battery cover

Pull the battery cover release lever (A) in the direction of the arrow, and then remove the battery cover.



To attach the battery cover

Insert the shaft on one side of the battery cover into the attachment site, and then push in the battery cover by attaching the shaft on the opposite side.



4. Tripod socket hole

Supports 1/4-20 UNC screws

Use a tripod with a screw less than 5.5 mm (7/32 inches) long. Otherwise, you cannot firmly secure the camera, and damage to the camera may occur.

Related Topic

- Front side
- Rear side
- Top side
- Sides


Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Touch operations on the monitor

By touching the monitor, you can intuitively perform operations such as focusing on the shooting screen and operating the playback screen.


Touch operations (on the shooting screen)




Touch the monitor to specify where to focus (Touch Focus).

Touch a subject on the monitor to use the touch tracking function (Touch Tracking).

Touch operations (on the playback screen)



During single-image playback, swipe the screen to the left or right to move to the previous or next image.



During single-image playback, you can enlarge or reduce the displayed image by moving apart or bringing together two fingers on the screen (pinch-out/pinch-in).

- You can also double-tap the monitor to enlarge a still image or exit the enlarged image.
- During movie playback, you can start or pause playback using touch operations.

Related Topic


- Touch Operation
- Touch Sensitivity
- Touch Panel/Pad
- Focusing using touch operations (Touch Focus)
- Starting tracking with touch operations (Touch Tracking)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Using the control wheel

On the menu screen or the screen displayed by pressing the Fn button, you can move the selection frame by turning the control wheel or by pressing the top/bottom/left/right side of the control wheel. Your selection is confirmed when you press the center of the control wheel.



- The DISP (Display Setting) and ISO (ISO) functions are assigned to the top/right side of the control wheel. In addition, you can assign selected functions to the left/right/bottom side and the center of the control wheel, and to the rotation of the control wheel.
- During playback, you can display the next/previous image by pressing the right/left side of the control wheel or by turning the control wheel.

Related Topic


- Assigning frequently used functions to buttons (Custom Key Setting)
- Changing the function of the dial temporarily (My Dial Settings)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Using the multi-selector

You can move the focus area by pushing the multi-selector up/down/left/right. You can also assign a function to be activated when you press the center of the multi-selector.



- Put your finger right on top of the multi-selector to manipulate it more precisely.
- You can move the focus area when [Focus Area] is set to the following parameters:
 - [Zone]
 - [Spot: S] / [Spot: M] / [Spot: L]
 - [Expand Spot]
 - [Tracking: Zone]
 - [Tracking: Spot S] / [Tracking: Spot M] / [Tracking: Spot L]
 - [Tracking: Expand Spot]
- The [Focus Standard] function is assigned to the center of the multi-selector in the default settings.

Related Topic


- Selecting the focus area (Focus Area)
- Focus Standard

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Using the mode dial


Use the mode dial to select a shooting mode according to the subject and purpose of shooting.



• Turn the mode dial while pressing the mode dial lock release button in the center of the mode dial.

Shooting mode details

The modes on the mode dial are divided into still image shooting modes, movie recording modes, and registration recall modes.



- (A) Still image shooting modes
- (B) Movie recording modes
- (C) Registration recall modes

Hint

The menu items displayed vary depending on the mode dial setting.

(A) Still image shooting modes

The shooting mode you select determines how to adjust the aperture (F value) and shutter speed.

Mode dial	Shooting mode	Description
AUTO (Auto)	Intelligent Auto	The camera shoots with automatic scene recognition.

Mode dial	Shooting mode	Description
Р	Program Auto	Allows you to shoot with the exposure adjusted automatically (both the shutter speed and the aperture value). You can set shooting functions such as [ISO].
A	Aperture Priority	The aperture value is given priority and the shutter speed is adjusted automatically. Select this when you want to blur the background or focus on the entire screen.
s	Shutter Priority	The shutter speed is given priority and the aperture value is adjusted automatically. Select this when you want to shoot a fast-moving subject without blurring, or when you want to shoot a water or light trail.
М	Manual Exposure	Manually adjust both the aperture value and shutter speed. You can shoot with your favorite exposure.

(B) Movie recording modes

Mode dial	Shooting mode	Description
(Movie)	Movie	You can set the exposure mode for movie shooting.
S&Q	S&Q Motion	You can set the exposure mode for S&Q Motion shooting.

The method for setting the exposure in the movie recording modes depends on the MENU \rightarrow \bigcirc (Shooting) \rightarrow [Shooting Mode] \rightarrow [Exposure Ctrl Type] setting.

When [Exposure Ctrl Type] is set to [P/A/S/M Mode]:

 $MENU \rightarrow \bigcirc$ (Shooting) \rightarrow [Shooting Mode] \rightarrow [Exposure Mode] or [SkQ Exposure Mode] \rightarrow Select the desired exposure mode from among P/A/S/M.

When [Exposure Ctrl Type] is set to [Flexible Exp. Mode]:

The aperture value, shutter speed, and ISO sensitivity can be switched between the automatic setting and manual setting by using the following functions assigned to custom keys.

- Aperture value
 [Auto/Manual Swt. Set.] → [Av Auto/Manual Switch]
- Shutter speed [Auto/Manual Swt. Set.] → [Tv Auto/Manual Switch]
- ISO sensitivity
 [Auto/Manual Swt. Set.] → [ISO Auto/Manual Set]

If you select the manual setting, turn the front/rear dial or the control wheel and set the desired value.

(C) Registration recall modes

Mode dial	Shooting mode	Description
1/2/	MR Recall Camera Setting	You can call up frequently used modes and numerical value settings that have been registered* in advance then shoot the images. * In [MR Camera Set. Memory], you can register various shooting settings, such as the exposure mode (P / A / S / M), aperture (F value), and shutter speed.

Related Topic

- Intelligent Auto
- Program Auto


- Aperture Priority
- Shutter Priority
- Manual Exposure
- Exposure Ctrl Type
- Movie: Exposure Mode
- S&Q Motion: Exposure Mode
- Recall Camera Setting
- Camera Set. Memory
- Using the MENU button

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Using the focus mode dial

Use the focus mode dial to select a focus mode according to the subject and the shooting scenario.



Turn the focus mode dial **(B)** while holding down the focus mode dial lock release button **(A)** to select the desired mode.

Related Topic


Selecting the focus method (Focus Mode)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Using the drive mode dial

Use the drive mode dial to select a drive mode according to the subject and the shooting scenario.



Turn the drive mode dial while holding down the drive mode dial lock release button in the center to select the desired mode.

Hint

• When using the electronic shutter, you can select the desired continuous shooting speed from MENU \rightarrow [Orive Mode] \rightarrow [Cont. Shooting Speed].

Related Topic


- Drive Mode
- Cont. Shooting Speed

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Using the MENU button

The menu screen is displayed by pressing the MENU button. You can change settings related to all of the camera operations including shooting and playback, or you can execute a function from the menu screen.



(A) Menu tab

Menu tabs are categorized by usage scenario, such as shooting, playback, network settings, etc.

(B) Menu group

In each tab, menu items are grouped by function.

The number assigned to the group is the serial number in the tab. Refer to the number to determine the location of the group in use.

(C) Menu item


Select the function you want to set or execute.

Hint

- The name of the selected tab or group is displayed at the top of the screen.
- When [Touch Operation] is set to [On], touch operations on the menu screen are possible.

Basic operations on the menu screen

- 1. Press the MENU button to display the menu screen.
- 2. Move within the menu tree and find the desired menu item by pressing the top/bottom/left/right side of the control wheel.
 - The displayed menu items differ between the still image shooting modes and movie recording modes.



- (A) Menu tabs
- (B) Menu groups
- (C) Menu items
- Press the center of the control wheel to select the menu item.The setting screen or execution screen for the selected item will appear on the monitor.
- **4.** Select a parameter or execute the function.
 - If you want to cancel changing the parameter, press the MENU button and go back to the previous screen.
- **5.** Press the MENU button to exit the menu screen. You will return to the shooting screen or playback screen.

Hint


You can display the menu screen by assigning the [MENU] function to a custom key using [Custom Key Setting] or [Custom Key Setting], and then pressing that key.

Relationship between the mode dial and menu screen

The menu groups and menu items displayed in the [Shooting], [Exposure/Color], and [Focus] tabs vary depending on the mode dial setting.

Still image shooting modes (AUTO/P/A/S/M)


Menu items for shooting still images are displayed.*



* Since you can record movies with the MOVIE (Movie) button even in the still image shooting mode, some basic movie menu items are also displayed.

Movie recording modes (| 1 /S&Q)

Menu items for recording movies are displayed.



Icons used in the "Help Guide"

: Menu items displayed in the still image shooting modes (AUTO/P/A/S/M)

☐ / III : Menu items displayed in the movie recording modes (Movie/S&Q)

四/間: Menu items displayed in both the still image shooting modes and movie recording modes

Related Topic

- Add Item
- Display From My Menu
- Assigning frequently used functions to buttons (Custom Key Setting)
- Using the mode dial


Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Using the C (custom) buttons

If you assign frequently used functions to the custom buttons (C1 to C4) in advance, you can quickly call up those functions simply by pressing the button during shooting or playback.

Recommended functions are assigned to the custom buttons by default.



To check/change the functions of the custom buttons

If you want to change the function of the custom button, press the center of the control wheel while the custom button is selected. The functions that can be assigned to that button will appear. Select your desired function.

Related Topic

Assigning frequently used functions to buttons (Custom Key Setting)

Help Guide


Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Using the Fn (Function) button

If you press the Fn (function) button during shooting, a menu (function menu) containing frequently used functions such as the focus area and white balance will appear on the screen, allowing you to quickly access the functions.

Example of function menu

The displayed items differ depending on the camera status.




Hint

- Use MENU → (Setup) → [Operation Customize] →[Fn Menu Settings] to register your favorite functions in the function menu. You can register 12 functions for shooting still images and 12 functions for shooting movies separately.
- When [Touch Operation] is set to [On], touch operations on the menu screen are possible.
- When [Touch Operation] is set to [On], you can also open [Fn Menu Settings] by holding down the icon in the function menu.
- 1 Press the DISP on the control wheel repeatedly to display a screen mode other than [For viewfinder].
- Press the Fn (Function) button.



3 Press the top/bottom/left/right side of the control wheel to select a function to set.






4 Turn the front dial to select the desired setting, and press the center of the control wheel.

• Some functions can be fine-tuned using the rear dial.


Using the Fn button in the [For viewfinder] display

If you press the Fn button while the monitor display is set to [For viewfinder], you can directly operate items you want to change.

In the auto mode




In the P/A/S/M mode



• The displayed contents and their positions shown in the illustrations are just a guideline, and may differ from the actual display.

To adjust settings from the dedicated setting screens

Select the icon for the desired function and then press the center of the control wheel. The dedicated setting screen for the function will appear. Follow the operating guide (A) to adjust settings.



Note

- Items that are grayed out on the [For viewfinder] screen cannot be changed by pressing the Fn button.
- Some settings, such as [Creative Look] and [Picture Profile], cannot be operated on the [For viewfinder] screen unless you enter the dedicated setting screen.

Related Topic


- Fn Menu Settings
- Using the DISP (Display Setting) button

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Using the DISP (Display Setting) button

By pressing the DISP (Display Setting) button, you can change the content displayed on the screen during shooting and playback. The display switches each time the DISP button is pressed. The viewfinder display and the monitor display for shooting can be set separately.




Hint

■ The monitor can be turned off with the DISP button. Add a check mark to [Monitor Off] under MENU \rightarrow [Operation Customize] \rightarrow [DISP (Screen Disp) Set] \rightarrow [Monitor].

During shooting (Monitor)

Display All Info. \rightarrow No Disp. Info. \rightarrow Histogram \rightarrow Level \rightarrow For viewfinder \rightarrow Display All Info.



During shooting (Viewfinder)

 $\mathsf{Level} \to \mathsf{No}\;\mathsf{Disp.}\;\mathsf{Info.} \to \mathsf{Histogram} \to \mathsf{Level}$



To switch the information displayed on the viewfinder, press the DISP button while looking into the viewfinder.

During playback (Monitor/Viewfinder)

Display Info. \rightarrow Histogram \rightarrow No Disp. Info. \rightarrow Display Info.



- If the image has an overexposed or underexposed area, the corresponding section will blink on the histogram display (overexposed/underexposed warning).
- The settings for playback are also applied in [Auto Review].

Note

- The displayed contents and their position shown in the illustration are just a guideline, and may differ from the actual display.
- The following are not displayed in the default settings.
 - Monitor Off
 - Display All Info. (when using the viewfinder)
- In the movie recording modes, [For viewfinder] cannot be displayed. If the monitor display is set to [For viewfinder], the display will switch to all information when movie shooting starts.

Related Topic


DISP (Screen Disp) Set (Monitor/Finder)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Using the Delete button

You can delete an image currently being displayed by pressing the $\hat{\mathbf{m}}$ (Delete) button.



- When a confirmation message appears after you press the (Delete) button, use the control wheel to select [Delete] and press the center.
- You can also delete two or more images at once.
 Select MENU → ► (Playback) → [Delete] → [Delete]. Then, select the images you want to delete.

Hint

- If you set MENU \rightarrow [Delete] \rightarrow [Delete] \rightarrow [$\stackrel{\longleftarrow}{m}$ Delete pressing twice] to [On], you can delete images by pressing the $\stackrel{\longleftarrow}{m}$ (Delete) button twice in a row.
- Other than the single-image playback screen, you can also use the f (Delete) button for the following operations.
 - Custom Key
 - In-Camera Guide

Related Topic


- Deleting multiple selected images (Delete)
- Delete confirm.
- Delete pressing twice
- Using the C (custom) buttons
- In-Camera Guide

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Using the AEL button

If the subject does not reach the proper brightness even when you point the camera toward the subject and press the shutter button halfway down, you can press the AEL button at the desired brightness to perform metering and lock the exposure (AE lock function). Once the exposure is locked, refocus on the subject and shoot the image.



Hint

In the default settings, [AEL hold] is assigned to the AEL button.

Related Topic

AE lock


Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Using the AF-ON button

You can use the AF-ON button to adjust the focus without pressing the shutter button halfway down ([AF On] function) in the following cases:

- When you want to focus at a specific shooting distance predicting the position of the subject.
- When you want to focus and release the shutter separately.



Related Topic

AF On

Help Guide


Interchangeable Lens Digital Camera ILCE-1 α 1

Using the front dial and rear dial

You can use the front dial (A) or rear dial (B) to quickly change the setting values in the following cases:

- When you want to adjust the aperture value or shutter speed.
- When you want to change the camera settings during shooting.

During playback, you can turn the dials to browse images.



You can also use the [My Dial Settings] function to assign your desired functions to the front dial/rear dial, and recall those functions when required.

Related Topic


- Aperture Priority
- Shutter Priority
- Manual Exposure
- Exposure Ctrl Type
- Changing the function of the dial temporarily (My Dial Settings)
- Assigning frequently used functions to buttons (Custom Key Setting)
- Av/Tv Assign in M
- Av/Tv Rotate
- Select Image Jump Dial

Help Guide

Interchangeable Lens Digital Camera ILCE-1 q1

Using the keyboard

When manual character entry is required, a keyboard is displayed on the screen. For examples of functions that use the keyboard, see "Related Topic" at the bottom of this page.



1. Input box

The characters you entered are displayed.

2. Switch character types

Each time you press this key, the character type will switch between alphabet letters, numerals and symbols.

3. Keyboard

Each time you press this key, the characters corresponding to that key will be displayed one-by-one in order. To switch letters from lower to upper case, press \(\bigcap \) (Up arrow).

4. (Left arrow)

Moves the cursor in the input box to the left.

5. (Right arrow)

Moves the cursor in the input box to the right. This key is also used to finalize the input of a character being edited and move to the next character.

6. (Delete)

Deletes the character preceding the cursor.

7. ♠ (Up arrow)

Switches a letter to upper or lower case.

8. **—** (Space)

Enters a space.

9. OK

Press this key after entering characters to finalize the entered characters.

The procedure for entering alphabetic characters is explained below.

Use the control wheel to move the cursor to the desired key.

- Each time you press the center of the control wheel, the characters will change
- To switch the letter to upper or lower case, press (Up arrow).

When the character that you want to enter appears, press 🗭 (Right arrow) to confirm the character.

- Make sure to confirm one character at a time. Unless a character is confirmed, you cannot enter the next character.
- Even if you do not press (Right arrow), the entered character will be automatically confirmed after several seconds.
- After you finish entering all characters, press [OK] to finalize the entered characters.

To cancel input, select [Cancel].

Related Topic

- Copyright Info
- Access Point Set.
- Wired LAN
- Edit Device Name
- Security(IPsec)

Help Guide


Interchangeable Lens Digital Camera ILCE-1 q1

Basic icons

This section describes the screen display when the shooting mode is **P** (Program Auto).


- The examples are of the display when the screen is in the all-information display mode.
- The displayed content and positions are for reference only, and may differ from the actual display. Some icons may not be displayed depending on the camera settings.

During still image shooting



- 1. The mode dial is set to **P** (Program Auto).
- 2. Number of the memory card slot recording the shooting data
- 3. Number of still images that can be recorded on the memory card in the slot indicated by 2
- [JPEG/HEIF Switch] is set to [JPEG]. [Image Quality Settings] → [JPEG Quality] is set to [Fine].
- 5. [Image Quality Settings] → [JPEG Image Size] is set to [M: 21M].
- 6. [SteadyShot] is set to [On].
- 7. [Touch Func. in Shooting] is set to [Touch Tracking].
- 8. Remaining battery level
- [A Metering Mode] is set to [Multi].
- 10. Displayed when [AF Illuminator] is set to [Auto] and the camera detects that the AF Illuminator is required
- 11. NFC is active. [Smartphone Connection] is set to [On].
- 12. [White Balance] is set to [Auto].
- 13. [D-Range Optimizer: Auto] is selected.
- 14. [Creative Look] is set to [ST].
- 15. [Picture Profile] is set to [Off].
- **16.** The drive mode is set to [(Single Shooting).
- **17.** The focus mode is set to AF-S (Single-shot AF).
- 18. [Focus Area] is set to [Wide].
- 19. [Shutter Type] is set to [Auto].
- 20. [Face/Eye Prior. in AF] is set to [On].
- 21. Shutter speed
- 22. Aperture value
- 23. Exposure compensation
- 24. [ISO] is set to [ISO AUTO].
- 25. [Shooting] is set to [On] or [Auto], and the recordable area is the APS-C-equivalent size.

During movie recording



- 1. Recordable movie time for the currently displayed slot
- 2. [File Format] is set to [XAVC S HD].
- 4. Actual movie recording time
- 5. [Audio Level Display] is set to [On].
- 6. [ISO] is set to [ISO AUTO]. (The ISO value automatically set by the camera is displayed.)

Related Topic


List of icons on the monitor


Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

In-Camera Guide

The [In-Camera Guide] displays descriptions of MENU items, Fn (Function) items, and settings.






The descriptions of the item are displayed.

Help Guide


Interchangeable Lens Digital Camera ILCE-1 α 1

Charging the battery pack using a charger

- Insert the battery pack into the battery charger.
 - Place the battery pack on the battery charger aligning the direction of (triangle) mark.
 - Slide the battery pack to the end.



Connect the power cord (supplied) to the battery charger, and connect the battery charger to the wall outlet (wall socket).



- When charging starts, the CHARGE lamp (A) lights up in orange.
- You can check the approximate charging status with the charging status indicator lamp (B) as shown in the following table. (The orange color indicates the lighting of the lamp.)
- When the CHARGE lamp and charging status indicator lamp light up and then immediately turn off, the battery pack is fully charged.

Charging status	CHARGE lamp/Charging status indicator lamp
Immediately after attaching the battery pack - 30%	
30% - 60%	
60% - 90%	
90% - Fully charged	0
Full charging completed	0 000

The charge level shown by the charging status indicator lamp and the percentages in the above table are rough guides.

The actual status may differ depending on the ambient temperature and the condition of the battery pack.

- Charging time (Full charge): The charging time is approximately 150 min.
- The above charging time applies when charging a fully depleted battery pack at a temperature of 25°C (77°F). Charging may take longer depending on conditions of use and circumstances.

Note

- Use a nearby wall outlet (wall socket) when using the AC Adaptor/Battery Charger. If any malfunction occurs, disconnect the plug from the wall outlet (wall socket) immediately to disconnect from the power source.
 If you use the product with a charge lamp, note that the product is not disconnected from the power source even when the lamp turns off.
- Before charging, be sure to also read "Notes on the battery pack and charging the battery."

Related Topic


- Inserting/removing the battery pack
- Notes on the battery pack and charging the battery

Help Guide


Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Inserting/removing the battery pack


1 Slide the switch on the battery cover to open the cover.



Insert the battery pack while pressing the lock lever (A) with the tip of the battery until the battery locks into place.




3 Close the cover and slide the switch to the LOCK side.



To remove the battery pack

Make sure that the access lamp is not lit, and turn off the camera. Then, slide the lock lever (A) and remove the battery pack. Be careful not to drop the battery pack.



Related Topic

- Charging the battery pack using a charger
- Charging the battery pack while it is inserted into the camera
- Notes on the battery pack and charging the battery

Help Guide


Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Charging the battery pack while it is inserted into the camera

You can use a USB cable to charge from an external power source, such as a commercially available USB AC adaptor or mobile battery.

When a device compatible with USB-PD (USB Power Delivery) is connected to the camera, fast charging is possible.

Turn off the camera, and connect an external power source to the USB Type-C terminal on the camera.



Charge lamp on the camera (orange)

Lit; Charging

Off: Charging finished

Flashing: Charging error or charging paused temporarily because the camera is not within the proper temperature range

• The charge lamp turns off when charging is completed.

Note

- USB charging is not possible from the Multi/Micro USB terminal. Use the USB Type-C terminal to charge the battery pack.
- If the product is connected to a laptop computer that is not connected to a power source, the laptop battery level decreases. Do not leave the product connected to a laptop computer for an extended period of time.
- Do not turn on/off or restart the computer, or wake the computer from sleep mode when a USB connection has been established between the computer and the camera. Doing so may cause a malfunction. Before turning on/off or restarting the computer, or waking the computer from sleep mode, disconnect the camera from the computer.
- Charging cannot be guaranteed with a custom-built computer, modified computer, or a computer connected through a USB hub.
- The camera may not operate correctly when other USB devices are used at the same time.
- We recommend using a USB-PD device that is compatible with an output of 9V/3A or 9V/2A.
- Before charging, be sure to also read "Notes on the battery pack and charging the battery."

Related Topic

- Inserting/removing the battery pack
- Notes on the battery pack and charging the battery

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Using the battery charger abroad

You can use the battery charger (supplied) in any country or region where the power supply is within 100 V to 240 V AC and 50 Hz/60 Hz.

Depending on the country/region, a converting plug adaptor may be needed to connect to a wall outlet (wall socket). Consult a travel agency, etc., and prepare one in advance.

Note

Do not use an electronic voltage transformer as doing so may cause a malfunction.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Supplying power from a wall outlet (wall socket)

Use an AC adaptor, etc. to shoot and play back images while power is supplied from a wall outlet (wall socket). This conserves the camera's battery power.

We recommend using a USB-PD (USB Power Delivery) device that is compatible with an output of 9V/3A.

- 1 Insert a sufficiently charged battery pack into the camera.
 - The camera will not activate if there is no remaining battery. Insert a sufficiently charged battery pack into the camera.
- Connect the USB cable to the USB Type-C terminal on the camera.
- 3 Connect to a wall outlet (wall socket) using an AC adaptor, etc.
- 4 Turn on the camera.
 - An icon (☐) indicating that USB power is being supplied will appear on the monitor, and power supply will start.

Note

- USB power cannot be supplied from the Multi/Micro USB Terminal. Use the USB Type-C terminal to supply power.
- As long as the power is on, the battery pack will not be charged even if the camera is connected to the AC Adaptor, etc.
- Under certain conditions, power may be supplied from the battery pack supplementarily even if you are using the AC adaptor, etc.
- Do not remove the battery pack while power is supplied from a wall outlet (wall socket). If you remove the battery pack, the camera will be turned off.
- Only connect the USB cable to the camera or disconnect the USB cable from the camera while the camera is turned off.
- Depending on the camera and battery temperature, the continuous recording time may be shortened while power is supplied from a wall outlet (wall socket).
- When using a mobile charger as a power source, confirm that it is fully charged before use. Also, be careful of the remaining power on the mobile charger during use.
- Operation cannot be guaranteed with all external power supplies.

Related Topic

Inserting/removing the battery pack


Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1


Inserting/removing a memory card

Explains how to insert a memory card (sold separately) to the camera. You can use CFexpress Type A memory cards and SD memory cards with this camera.

Slide the switch on the memory card cover to open the cover.



- 2 Insert the memory card into the slot 1.
 - When using two memory cards, insert the second one into the slot 2.
 - Both Slot 1 and Slot 2 support CFexpress Type A memory cards and SD memory cards.
 - Insert a CFexpress Type A memory card with the label facing the monitor, and an SD memory card with the terminal facing the monitor. Insert the card until it clicks into place.




3 Close the cover.



- When you use a memory card with the camera for the first time, it is recommended that you format the card on the camera for more stable performance of the memory card.
- You can change the memory card slot for recording by selecting MENU → [o] (Shooting) → [Media] → [o] Rec. Media Settings] → [Recording Media] or [Recording Media]. The Slot 1 is used in the default settings.
- To record the same image on two memory cards at the same time or to sort recorded images onto two memory card slots by the image type (still image/movie), select MENU → [O] (Shooting) → [Media] → [P] Rec. Media Settings], and then change the settings of [P] Recording Media] or [P] Recording Media].

To remove the memory card

Open the memory card cover and make sure that the access lamp (A) is not lit, then push in the memory card lightly once to remove it.



Related Topic

- Memory cards that can be used
- Notes on memory card
- Format
- Rec. Media Settings (still image/movie): Recording Media (still image)
- Rec. Media Settings (still image/movie): Recording Media (movie)
- Selecting which memory card to play back (Select Playback Media)


Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$


Attaching/removing a lens

Turn off the camera before attaching or removing the lens.

Remove the body cap (A) from the camera and the rear lens cap (B) from the rear of the lens.



- It is recommended that you attach the front lens cap when you have done shooting.
- 2 Mount the lens by aligning the two white index marks (mounting indexes) on the lens and camera.



- Hold the camera with the lens mount facing down to prevent dust and debris from entering the camera.
- While pushing the lens lightly toward the camera, turn the lens slowly in the direction of the arrow until it clicks into the locked position.




Be sure to hold the lens straight when attaching it.

To remove the lens

Keep pressing the lens release button (A) and turn the lens in the direction of the arrow until it stops.

After removing the lens, attach the body cap to the camera and the lens caps to the front and rear of the lens to prevent dust and debris from entering the camera and lens.



Lens hood

We recommend that you use the lens hood to prevent light outside the shooting frame from affecting the image. Attach the lens hood so that the indexes on the lens and lens hood are aligned.

(There may be no lens hood index on some lenses.)

Note

- When attaching/removing the lens, work quickly in a dust-free location.
- Do not press the lens release button when attaching a lens.
- Do not use force when attaching a lens.
- A Mount Adaptor (sold separately) is required to use an A-mount lens (sold separately). When using the Mount Adaptor, refer to the operating manual supplied with the Mount Adaptor.
- If you want to shoot full-frame images, use a full-frame size compatible lens.
- When you use a lens with a tripod socket, attach a tripod to the tripod socket of the lens to help balance the weight of the lens.
- When carrying the camera with a lens attached, hold both the camera and the lens firmly.
- Do not hold the part of the lens that is extended for zoom or focus adjustment.
- Attach the lens hood properly. Otherwise, the lens hood may not have any effect or may be partially reflected in the image.
- Remove the lens hood when using the flash as the lens hood blocks the flash light and may appear as a shadow on the image.

Related Topic

Mount Adaptor

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Setting language, date and time

The setting screen for language, date and time is displayed automatically when you turn on this product for the first time, initialize this product or when the internal rechargeable backup battery has discharged.

- 1 Set the ON/OFF (Power) switch to "ON" to turn on the camera.
- 2 Select the desired language and then press the center of the control wheel.
- Make sure that [Enter] is selected on the area/date/time confirmation screen, and then press the center of the control wheel.
- Select the desired geographic location, set [Daylight Savings], and then press the center.
 - [Daylight Savings] can be switched on/off using the top/bottom of the control wheel.
- 5 Set the date format (year/month/day), and press the center.
- 6 Set the date and time (hour/minute/second), and press the center.
 - To set the date and time or geographic location again at a later point, select MENU → (Setup) → [Area/Date] → [Area/Date/Time Setting].

On maintaining the date and time

This camera has an internal rechargeable battery for maintaining the date and time and other settings regardless of whether the power is on or off, or whether the battery pack is charged or discharged.

To charge the internal rechargeable backup battery, insert a charged battery pack into the camera, and leave the product for 24 hours or more with the power off.

If the clock resets every time the battery pack is charged, the internal rechargeable backup battery may be worn out. Consult your service facility.

Note

- If the date and time setting is canceled halfway, the setting screen for the date and time appears every time you turn on the camera
- The built-in clock of the camera may exhibit time errors. Adjust the time at regular intervals.

Related Topic

Area/Date/Time Setting

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Confirmation before shooting

This section introduces useful settings and functions that you should know when using the camera. We recommend that you confirm these settings and functions before using the camera.

From each item name listed below, you can jump to the page explaining the respective functions.

Preparing a memory card for use with this camera

- Format
- Recover Image DB (still image/movie)

Selecting a memory card for recording

- Rec. Media Settings (still image/movie): Recording Media (still image)
- Rec. Media Settings (still image/movie): Recording Media (movie)
- Rec. Media Settings (still image/movie): Auto Switch Media

Preventing accidental failure to insert a memory card

Release w/o Card

Selecting a memory card for playback

Selecting which memory card to play back (Select Playback Media)

Setting whether camera operating sounds are generated

Audio signals

Making it easy to check whether the camera is on standby or recording when set to a movie mode

Emphasized REC Display

Resetting shooting settings or resetting all camera settings

Setting Reset

Help Guide


Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Shooting still images (Intelligent Auto)

This section describes how to shoot still images in the [Intelligent Auto] mode. In the [Intelligent Auto] mode, the camera automatically focuses and automatically determines the exposure based on the shooting conditions.


1 Set the mode dial to AUTO (Auto Mode).

The shooting mode will be set to in (Intelligent Auto).



- Turn the mode dial while pressing the mode dial lock release button in the center of the mode dial.
- Adjust the monitor angle, and hold the camera. Or look through the viewfinder and hold the camera.
- When a zoom lens is mounted, enlarge images by rotating the zoom ring.
- 4 Press the shutter button halfway down to focus.

When the image is in focus, a beep sounds and the indicator (____, etc.) lights up.



6 Press the shutter button fully down.

To select the focus mode yourself (focus mode/focus area)

Specifying a focus mode, such as selecting AF-S (Single-shot AF) for landscapes or still subjects and selecting AF-C (Continuous AF) for moving subjects, makes it easier to focus on the desired subject. You can also specify the focus position and range using [Focus Area].

Shooting while focusing on human eyes

The [Face/Eye Prior. in AF] function under [Face/Eye AF] is enabled in the default settings, so you can use the Eye AF function immediately.

To shoot images with the focus locked on the desired subject (Focus-lock)

When you focus on the subject, the focus is locked while the shutter button is pressed halfway down. Switch to the desired composition and press the shutter button all the way down to take the picture.

- You can lock the focus on non-moving subjects. Set the focus mode dial to AF-S (Single-shot AF).
- Setting [Focus Area] to [Center Fix] makes it easier to focus on subjects located in the center of the screen.

Hint

When the product cannot focus automatically, the focus indicator flashes and the beep does not sound. Either recompose the shot or change the focus setting. In [Continuous AF] mode, (focus indicator) lights up and the beep indicating that the focus has been achieved does not sound.

Note

An icon indicating that data is being written is displayed after shooting. Do not remove the memory card while the icon is displayed. Doing so will prevent images from being recorded normally.

Related Topic

- Selecting the focus method (Focus Mode)
- Selecting the focus area (Focus Area)
- Playing back still images
- Auto Review (still image)


Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Shooting movies

You can set the recording format and exposure and record movies by using the dedicated menu items for movies.

Set the mode dial to | (Movie).



- Turn the mode dial while pressing the mode dial lock release button in the center of the mode dial.
- 2 Press the MOVIE (Movie) button to start recording.



3 Press the MOVIE button again to stop recording.

To select the recording format (| File Format)

To select the frame rate or image quality (Movie Settings)

The frame rate determines the smoothness of motion in movies. ([\blacksquare Movie Settings] \rightarrow [Rec Frame Rate]) The image quality changes with the bit rate. ([\blacksquare Movie Settings] \rightarrow [Record Setting])

If the bit rate is high, the amount of information will increase and you can shoot high-quality movies. However, this will result in a larger volume of data.

Select the frame rate and bit rate according to your preference and purpose.

To adjust the exposure (Exposure Ctrl Type/Exposure Mode)

When [Exposure Ctrl Type] is set to [P/A/S/M Mode], select the exposure mode using the shutter speed and aperture value combination in the same way as when shooting a still image.

When [Exposure Ctrl Type] is set to [Flexible Exp. Mode], you can set the shutter speed, aperture value, and ISO sensitivity automatically or manually.

To select the focusing method (focus mode/focus area)

Use the focus mode dial to select AF-C (Continuous AF) or MF (Manual Focus). You can specify the focus area by setting [Focus Area].

Even during shooting with manual focus, you can temporarily switch to auto focus in the following ways.

- Press the custom key to which [AF On] is assigned, or press the shutter button halfway.
- Press the custom key to which [Eye AF] is assigned.
- Touch the subject on the monitor.

To record movie audio in 4 channels

Attach a genuine Sony accessory that supports 4-channel and 24-bit audio recording to the Multi Interface Shoe of the camera.

Hint

- You can also assign the start/stop movie recording function to a preferred key.
- You can focus quickly while shooting movies by pressing the shutter button halfway down. (The sound of auto focus operation
 may be recorded in some cases.)
- You can change the settings for ISO sensitivity, exposure compensation, and focus area while shooting movies.
- The sounds of the camera and lens in operation may be recorded during movie shooting. To prevent sounds from being recorded, set [Audio Recording] to [Off].
- To prevent the operating sound of the zoom ring from being recorded when a power zoom lens is used, we recommend recording movies using the zoom lever. When moving the zoom lever, be careful not to flip the lever.

Note

- An icon indicating that data is being written is displayed after shooting. Do not remove the memory card while the icon is displayed.
- You cannot start recording a movie while writing data. Wait until data writing is completed and "STBY" is displayed before recording a movie.
- If the [(Overheating warning) icon appears, the temperature of the camera has risen. Turn the power off and cool the camera and wait until the camera is ready to shoot again.
- The temperature of the camera tends to rise when shooting movies continuously, and you may feel that the camera is warm. This is not a malfunction. Also, [Internal temp. high. Allow it to cool.] may appear. In such cases, turn the power off and cool the camera and wait until the camera is ready to shoot again.
- For the continuous shooting time of a movie recording, refer to "Recordable movie times." When movie recording is finished, you can record another movie by pressing the MOVIE button again. Recording may stop to protect the product, depending on the temperature of the product or the battery.

Related Topic

- File Format (movie)
- Movie Settings (movie)
- Exposure Ctrl Type
- Movie: Exposure Mode
- Selecting the focus method (Focus Mode)


- Selecting the focus area (Focus Area)
- Shoe Audio Set.
- Assigning frequently used functions to buttons (Custom Key Setting)
- REC w/ Shutter (movie)
- Audio Recording
- Recordable movie times

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Finding functions from MENU

The displayed MENU items vary depending on the position of the mode dial. In the table below, the modes in which each MENU item is displayed are indicated by the still image/movie icons.



The menu item is displayed when the mode dial position is set to the still image shooting modes (A).

The menu item is displayed when the mode dial position is set to the movie recording modes (B).

The menu item is displayed when the mode dial position is set to either the still image shooting modes (A) or the movie recording modes (B).

• When the mode dial is set to 1, 2, or 3 (MR Recall Camera Setting), the displayed menu items are determined by the mode registered to each registration number.

(Shooting) tab

Groups	四/間	Menu items
Image Quality	₽ /⊞	JPEG/HEIF Switch
	四/問	Image Quality Settings: File Format
		Image Quality Settings: RAW File Type
		Image Quality Settings: JPEG Quality
		Image Quality Settings: HEIF Quality
	四/問	Image Quality Settings: JPEG Image Size
	四/問	Image Quality Settings: HEIF Image Size
	四/問	Aspect Ratio
	四/問	File Format
	四/問	Movie Settings
	四/期	S&Q S&Q Settings
	四/問	Px Proxy Settings
	四/問	APS-(S35 Shooting
	四/間	Long Exposure NR

Groups	四/間	Menu items	
	四/問	High ISO NR	
	四/間	HLG Still Image	
	四/間	Color Space	
	四/間	Lens Compensation	
	四/間	Format	
	四/間	Rec. Media Settings: Recording Media	
Media	四/問	Rec. Media Settings: Recording Media	
Media	四/問	Rec. Media Settings: Auto Switch Media	
	四/間	Recover Image DB	
	四/間	Display Media Info.	
	四/問	File/Folder Settings	
	四/問	Select REC Folder	
	四/問	Create New Folder	
File	四/問	IPTC Information	
	P / I I	Copyright Info	
	₽/#	Write Serial Number	
	₽/#	File Settings	
	₽/#	Exposure Mode	
	₽/#	S&Q Exposure Mode	
	₽/#	Exposure Ctrl Type	
Shooting Mode	₽/#	MR Recall Camera Setting	
	四/間	MR Camera Set. Memory	
	四/間	MR Memory/Recall Media	
	四/間	Reg. Custom Shoot Set	
Drive Mode	四/間	Cont. Shooting Speed	
	四/間	Self-timer Type: Self-timer(Single)	
	四/間	Self-timer Type: Self-timer(Cont)	
	四/間	Bracket Settings: Cont. Bracket	
	四/間	Bracket Settings: Single Bracket	
	四/間	Bracket Settings: WB bracket	
	四/問	Bracket Settings: DRO Bracket	
	四/間	Bracket Settings: Selftimer during Bracket	

Groups	四/間	Menu items	
	₽/#	Bracket Settings: Bracket order	
	四/問	Interval Shoot Func.	
	四/問	Pixel Shift Multi Shoot.	
	四/間	Silent Mode Settings	
	四/問	Shutter Type	
Shutter/Silent	₽/#	Release w/o Lens	
	₽/#	Release w/o Card	
	四/間	Anti-flicker Set.	
	₽ /#	Audio Recording	
	₽ /#	Audio Rec Level	
Audio Doording	₽ /#	Audio Out Timing	
Audio Recording	₽/#	Wind Noise Reduct.	
	₽/#	⊓i Shoe Audio Set.	
	₽/#	Audio Level Display	
	□ /#	Time Code Preset	
	□ / #	User Bit Preset	
TC/UB	□ / #	Time Code Format	
10/05		Time Code Run	
	□ / #	Time Code Make	
	四/間	User Bit Time Rec	
	四/間	SteadyShot	
Image Stabilization	四/間	SteadyShot	
image Stabilization	四/間	SteadyShot Adjust.	
	四/間	Focal Length	
	四/間	Zoom	
Zoom	四/間	Zoom Range	
200111	四/間	Zoom Speed	
	四/間	Zoom Speed	
	四/間	Grid Line Display	
Shooting Display	₽/ □	Grid Line Type	
Shooting Biopiay	四/問	Live View Display Set.	
	四月	Emphasized REC Display	

Groups	₽/#	Menu items
	四/間	Marker Display
	□ □	Center Marker
Marker Display	□ □	Aspect Marker
	□ □	Safety Zone
	四/間	Guideframe

(Exposure/Color) tab

Groups	四/間	Menu items
	□ □	Auto Slow Shutter
	☞/#	₽ ISO
Exposure	☞/#	ISO Range Limit
	四/目	ISO AUTO Min. SS
	四/間	Auto/Manual Swt. Set.
	四/間	Exposure Comp.
Exposure Comp.	四/間	Reset EV Comp.
Exposure Comp.	四/間	Exposure step
	四/間	Exposure Std. Adjust
	四/間	Metering Mode
Metering	四/間	Face Priority in Multi Metering
Wictering	四/間	Spot Metering Point
	四/間	AEL w/ Shutter
	四/間	Flash Mode
	四/間	Flash Comp.
	四/間	Exp.comp.set
Flash	四/間	Wireless Flash
	四/間	Flash Sync Spd. Prty.
	四/間	Red Eye Reduction
	四/間	External Flash Set.
	四/間	White Balance
White Balance	四/間	Priority Set in AWB
Willio Balarioc	四/間	Shutter AWB Lock
	四/間	Shockless WB

Groups	四/間	Menu items
	₽ /#	D-Range Optimizer
Color/Tone	四/間	Creative Look
	四/間	Picture Profile
Zahra Dianlay	四/間	Zebra Display
Zebra Display	四/間	Zebra Level

AF_{MF} (Focus) tab

Groups	四/間	Menu items
	四/問	Priority Set in AF-S
	四/問	Priority Set in AF-C
	四/問	AF Tracking Sensitivity
	四/問	AF Illuminator
AF/MF	四/問	Aperture Drive in AF
	四/問	AF w/ Shutter
	四/間	Pre-AF
	四/問	AF Transition Speed
	四/期	AF Subj. Shift Sensitivity
	四/問	Focus Area
	四/問	Focus Area Limit
	四/間	Switch V/H AF Area
	四/間	Focus Area Color
	四/間	AF Area Registration
Fac	四/問	Del. Regist. AF Area
Focus Area	四/問	AF Area Auto Clear
	四/問	Area Disp. dur Tracking
	四/問	AF-C Area Display
	四/問	Phase Detect. Area
	四/間	Circ. of Focus Point
	四/間	AF Frame Move Amt
Face/Eye AF	四/間	Face/Eye Prior. in AF
	四/間	Face/Eye Subject
	四/間	Subject Sel. Setting

Groups	四/間	Menu items
	四/間	Right/Left Eye Select
	四/間	Face/Eye Frame Disp.
	四/間	Face Memory
	四/間	Regist. Faces Priority
	四/間	Auto Magnifier in MF
Focus Assistant	四/間	Focus Magnifier
	四/間	Focus Magnif. Time
1 Ocus Assistant	四/間	Initial Focus Mag.
	四/間	AF in Focus Mag.
	四/間	Initial Focus Mag.
Peaking Display	四/間	Peaking Display
	四/間	Peaking Level
	四/間	Peaking Color

► (Playback) tab

Groups	四/間	Menu items
Dlayback Target	₽/#	Select Playback Media
Playback Target	₽/#	View Mode
	四/間	⊕ Enlarge Image
Magnification	四/間	⊕ Enlarge Initial Mag.
	四/間	⊕ Enlarge Initial Position
	四/間	Protect
	四/間	Rating
Selection/Memo	四/間	Rating Set(Custom Key)
	四/間	Voice Memo
	四/間	Voice Memo Play Vol.
	四/間	Delete
Delete	四/間	Delete pressing twice
	四/間	Delete confirm.
Edit	四/間	Crop
	四/間	Rotate
	四/間	Сору

Groups	四/間	Menu items
	四/間	Photo Capture
	四/間	JPEG/HEIF Switch
	四/間	Cont. Play for 🚺 Interval
Viewing	四/間	Play Speed for 🚺 Interval
	四/間	Slide Show
	四/間	Image Index
	四/間	Display as Group
Playback Option	四/間	Display Rotation
	四/間	Focus Frame Display
	四/間	Select Image Jump Dial
	四/間	Image Jump Method

(Network) tab

Groups	四/間	Menu items
	四/間	Smartphone Connection
	四/間	Connection
Smartphone Connect	四/間	Select on Cam & Send
Smartphone Connect	四/間	Cnct. while Power OFF
	四/間	Remote Shoot Setting
	四/間	Always Connected
	四/間	FTP Transfer Func.
Transfer/Remote	四/間	PC Remote Function
	四/間	Bluetooth Rmt Ctrl
	四/間	Location Info Link
Location Information	四/間	Auto Time Correction
	四/間	Auto Area Adjustment
	四/間	WPS Push
	四/間	Access Point Set.
Wi-Fi	四/間	Wi-Fi Frequency Band
	四/間	Display Wi-Fi Info.
	四/間	SSID/PW Reset
Bluetooth	四/間	Bluetooth Function

Groups	₽/#	Menu items
	四/間	Pairing
	四/間	Disp Device Address
Wired LAN	四/間	LAN IP Address Setting
	四/間	Display Wired LAN Info.
Network Option	₽/#	Airplane Mode
	₽/#	Edit Device Name
	₽/#	Import Root Certificate
	₽/#	Security(IPsec)
	四/間	Reset Network Set.

(Setup) tab

Groups	四/間	Menu items
Area/Date	四/間	A Language
	四/間	Area/Date/Time Setting
	四/間	NTSC/PAL Selector
Reset/Save Settings	四/間	Setting Reset
	四/間	Save/Load Settings
	四/間	Custom Key Setting
	四/間	Custom Key Setting
	四/間	Custom Key Setting
Operation Customize	四/間	Fn Menu Settings
	四/間	Different Set for Still/Mv
	四/間	DISP (Screen Disp) Set
	四/間	REC w/ Shutter
	四/間	Zoom Ring Rotate
Dial Customize	四/間	My Dial Settings
	四/間	Av/Tv Assign in M
	四/間	Av/Tv Rotate
	四/間	Dial Ev Comp
	四/間	Function Ring(Lens)
	四/間	Lock Operation Parts
Touch Operation	四/間	Touch Operation

Groups	四/間	Menu items
	四/間	Touch Sensitivity
	四/間	Touch Panel/Pad
	四/間	Touch Pad Settings
	四/間	Touch Func. in Shooting
	四/間	Select Finder/Monitor
	四/間	Monitor Brightness
	四/間	Viewfinder Bright.
Finder/Monitor	四/間	Finder Color Temp.
	☞/ #	Viewfinder Magnifi.
	☞/ #	Display Quality
	☞/ #	Finder Frame Rate
	₽ /#	TC/UB Disp. Setting
	₽/ □	Gamma Display Assist
	₽/ □	Gamma Disp. Assist Typ.
Display Option	₽/ □	Shoot. Start Display
	₽/#	Shoot. Timing Display
	☑/탭	Remain Shoot Display
	四/間	Auto Review
	四/間	Auto Monitor OFF
Power Setting Option	四/間	Power Save Start Time
	四/間	Auto Power OFF Temp.
	四/間	Volume Settings
Sound Option	四/間	4ch Audio Monitoring
	四/間	Audio signals
	四/間	USB Connection
USB	四/間	USB LUN Setting
	四/間	USB Power Supply
	四/間	HDMI Resolution
Evtornal Output	四/間	HDMI Output Settings
External Output	四/間	HDMI Info. Display
	四/間	CTRL FOR HDMI
Setup Option	四/間	Video Light Mode

Groups	四/間	Menu items
	四/間	IR Remote Ctrl
	₽/#	Anti-dust Function
	四/間	Auto Pixel Mapping
	四/間	Pixel Mapping
	四/間	Version

│ ☆ (My Menu) tab

Groups	四/間	Menu items
My Menu Setting	四/間	Add Item
	四/間	Sort Item
	四/間	Delete Item
	四/間	Delete Page
	四/間	Delete All
	☞/#	Display From My Menu

Note

• The order in which the menu tabs are listed here differs from the actual display.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Contents of this chapter

The following table of contents lists the features described in this chapter ("Using the shooting functions"). From each item name, you can jump to the page describing the respective functions.

Selecting a shooting mode

- Intelligent Auto
- Program Auto
- Aperture Priority
- Shutter Priority
- Manual Exposure
- Bulb shooting
- Exposure Ctrl Type
- Auto/Manual Swt. Set.
- Movie: Exposure Mode
- S&Q Motion: Exposure Mode
- Auto Slow Shutter

Focusing

- Selecting the focus method (Focus Mode)
- Selecting the focus area (Focus Area)
- Tracking subject (Tracking function)

Face/Eye AF

- Focusing on human eyes
- Face/Eye Prior. in AF (still image/movie)
- Face/Eye Subject (still image/movie)
- Subject Sel. Setting (still image/movie)
- Right/Left Eye Select (still image/movie)
- Face/Eye Frame Disp. (still image/movie)
- Face Memory
- Regist. Faces Priority (still image/movie)

Using the AF functions

- Focus Standard
- Adjusting the focus area settings to the camera's orientation (horizontal/vertical) (Switch V/H AF Area)
- Registering the current focus area (AF Area Registration)
- Deleting a registered AF Area (Del. Regist. AF Area)
- Focus Area Limit (still image/movie)
- Circ. of Focus Point (still image/movie)
- AF Frame Move Amt (still image/movie)
- Focus Area Color (still image/movie)
- AF Area Auto Clear
- Area Disp. dur Tracking
- AF-C Area Display
- Phase Detect. Area
- AF Tracking Sensitivity
- AF Transition Speed
- AF Subj. Shift Sensitivity
- AF/MF Selector

- AF w/ Shutter
- AF On
- Focus Hold
- Pre-AF
- Priority Set in AF-S
- Priority Set in AF-C
- AF in Focus Mag.
- AF Illuminator
- Aperture Drive in AF

Using the MF functions

- Manual Focus
- Direct manual focus (DMF)
- Auto Magnifier in MF
- Focus Magnifier
- Focus Magnif. Time (still image/movie)
- Initial Focus Mag. (still image)
- Initial Focus Mag. (movie)
- Peaking Display

Adjusting the exposure/metering modes

- Exposure Comp. (still image/movie)
- Histogram display
- Reset EV Comp. (still image/movie)
- Exposure step (still image/movie)
- Exposure Std. Adjust (still image/movie)
- Dial Ev Comp
- D-Range Optimizer (still image/movie)
- Metering Mode (still image/movie)
- Face Priority in Multi Metering (still image/movie)
- Spot Metering Point (still image/movie)
- AE lock
- AEL w/ Shutter
- Zebra Display

Selecting the ISO sensitivity

- ISO (still image/movie)
- ISO Range Limit (still image/movie)
- ISO AUTO Min. SS

White balance

- White Balance (still image/movie)
- Capturing a standard white color to set the white balance (custom white balance)
- Priority Set in AWB (still image/movie)
- Shutter AWB Lock
- Shockless WB

Adding effects to images

- Creative Look (still image/movie)
- Picture Profile (still image/movie)

Shooting with drive modes (continuous shooting/self-timer)

- Drive Mode
- Cont. Shooting
- Cont. Shooting Speed
- Self-timer Type: Self-timer(Single)

- Self-timer Type: Self-timer(Cont)
- Bracket Settings: Cont. Bracket
- Bracket Settings: Single Bracket
- Indicator during bracket shooting
- Bracket Settings: WB bracket
- Bracket Settings: DRO Bracket
- Bracket Settings: Selftimer during Bracket
- Bracket Settings: Bracket order

Interval Shoot Func.

Shooting still images with a higher resolution (Pixel Shift Multi Shoot.)

Setting the image quality and recording format

- JPEG/HEIF Switch
- Image Quality Settings: File Format (still image)
- Image Quality Settings: RAW File Type
- Image Quality Settings: JPEG Quality/HEIF Quality
- Image Quality Settings: JPEG Image Size/HEIF Image Size
- Aspect Ratio
- HLG Still Image
- Color Space
- File Format (movie)
- Movie Settings (movie)
- S&Q Settings
- Proxy Settings
- APS-C S35 (Super 35mm) Shooting (still image/movie)
- Angle of view

Using touch functions

- Touch Operation
- Touch Sensitivity
- Touch Panel/Pad
- Touch Pad Settings
- Touch Func. in Shooting
- Focusing using touch operations (Touch Focus)
- Starting tracking with touch operations (Touch Tracking)

Shutter settings

- Silent Mode Settings (still image/movie)
- Shutter Type
- Using the electronic shutter
- Shoot. Start Display (still image)
- Shoot. Timing Display (still image)
- Release w/o Lens (still image/movie)
- Release w/o Card
- Anti-flicker Set.
- Differences between the [Anti-flicker Shoot.] and [Variable Shutter] functions

Using the zoom

- The zoom features available with this product
- Clear Image Zoom/Digital Zoom (Zoom)
- Zoom Range (still image/movie)
- Zoom Speed (still image/movie)
- Zoom Speed (Remote commander) (still image/movie)
- About zoom scale

Zoom Ring Rotate

Using the flash

- Using flash (sold separately)
- Flash Mode
- Flash Comp.
- Exp.comp.set
- Wireless Flash
- Flash Sync Spd. Prty.
- Red Eye Reduction
- FEL lock
- External Flash Set.
- Using a flash with a sync terminal cord
- Video Light Mode

Reducing blur

- SteadyShot (still image)
- SteadyShot (movie)
- SteadyShot Adjust. (still image/movie)
- SteadyShot focal length (still image/movie)

Lens Compensation (still image/movie)

Noise reduction

- Long Exposure NR
- High ISO NR

Setting the monitor display during shooting

- Auto Review (still image)
- Remain Shoot Display (still image)
- Grid Line Display (still image/movie)
- Grid Line Type (still image/movie)
- Live View Display Set.
- Aperture Preview
- Shot. Result Preview
- Bright Monitoring
- Emphasized REC Display
- Marker Display
- Gamma Display Assist
- Gamma Disp. Assist Typ.

Recording movie audio

- Audio Recording
- Audio Rec Level
- Audio Out Timing
- Wind Noise Reduct.
- Shoe Audio Set.
- Audio Level Display

TC/UB settings

- TC/UB
- TC/UB Disp. Setting

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Intelligent Auto

The camera shoots with automatic scene recognition.

- Set the mode dial to AUTO (Auto Mode).
 - The shooting mode will be set to in (Intelligent Auto).
- Point the camera at the subject.

When the camera recognized the scene, the icon for the recognized scene appears on the screen.



3 Adjust the focus and shoot the image.

About Scene Recognition

The Scene Recognition function allows the camera to automatically recognize shooting conditions.

When the camera recognizes certain scenes, the following icons and guides are displayed at the top of the screen:

(Portrait), (Infant), (Night Portrait), (Night Scene), (Backlight Portrait), (Backlight), (Landscape), (Macro), (Spotlight), (Low Light), (Night Scene using a tripod)

Note

- The product will not recognize the scene when you shoot images with zoom functions other than optical zoom.
- The product may not properly recognize the scene under certain shooting conditions.
- For [Intelligent Auto] mode, most of the functions are set automatically, and you cannot adjust the settings on your own.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Program Auto

Allows you to shoot with the exposure adjusted automatically (both the shutter speed and the aperture value).

You can set shooting functions such as [ISO].

- 1 Set the mode dial to P (Program Auto).
- Set the shooting functions to your desired settings.
- 3 Adjust the focus and shoot the subject.

Program Shift

When you are not using a flash, you can change the shutter speed and aperture (F-value) combination without changing the appropriate exposure set by the camera.

Turn the front/rear dial to select the aperture value and shutter speed combination.

- "P" on the screen changes to "P*" when you turn the front/rear dial.
- To cancel program shift, set the shooting mode to other than [Program Auto], or turn off the camera.

Note

- According to the brightness of the environment, the program shift may not be used.
- Set the shooting mode to another one than "P" or turn off the power to cancel the setting you made.
- When the brightness changes, the aperture (F-value) and shutter speed also change while maintaining the shift amount.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Aperture Priority

You can shoot by adjusting the aperture and changing the range in focus, or by defocusing the background.

Set the mode dial to A (Aperture Priority).

Select the desired value by turning the front/rear dial.

- Smaller F-value: The subject is in focus, but objects in front of and beyond the subject are blurred.
 Larger F-value: The subject and its foreground and background are all in focus.
- If the aperture value you have set is not suitable for appropriate exposure, the shutter speed on the shooting screen will blink. If this happens, change the aperture value.
- 3 Adjust the focus and shoot the subject.

The shutter speed is automatically adjusted to obtain proper exposure.

Note

• The brightness of the image on the screen may differ from the actual image being shot.

Related Topic

Aperture Preview

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Shutter Priority

You can express the movement of a moving subject in various ways by adjusting the shutter speed, for example, at the instant of the movement with high speed shutter, or as a trailing image with low speed shutter.

- 1 Set the mode dial to S (Shutter Priority).
- Select the desired value by turning the front/rear dial.
 - If proper exposure cannot be obtained after setup, the aperture value on the shooting screen blinks. If this
 happens, change the shutter speed.
- 3 Adjust the focus and shoot the subject.

The aperture is automatically adjusted to obtain proper exposure.

Hint

- Use a tripod to prevent camera-shake when you have selected a slow shutter speed.
- When you shoot indoor sports scenes, set the ISO sensitivity to a higher value.

Note

- The SteadyShot warning indicator does not appear in shutter speed priority mode.
- When [Long Exposure NR] is set to [On] and the shutter speed is 1 second(s) or longer with a [Shutter Type] other than [Electronic Shutter] is set, noise reduction after shooting is performed for the same amount of time that the shutter was open. However, you cannot shoot any more while noise reduction is in progress.
- The brightness of the image on the screen may differ from the actual image being shot.

Related Topic

Long Exposure NR

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Manual Exposure

You can shoot with the desired exposure setting by adjusting both the shutter speed and aperture.

1 Set the mode dial to M (Manual Exposure).

Select the desired aperture value by turning the front dial.
Select the desired shutter speed by turning the rear dial.

- You can change the setting of the front/rear dial using MENU → (Setup) → [Dial Customize] → [Av/Tv Assign in M].
- You can also set [ISO] to [ISO AUTO] in manual exposure mode. The ISO value automatically changes to achieve the appropriate exposure using the aperture value and shutter speed you have set.
- When [ISO] is set to [ISO AUTO], the ISO value indicator will blink if the value you have set is not suitable for appropriate exposure. If this happens, change the shutter speed or aperture value.
- When [ISO] is set to other than [ISO AUTO], use "M.M." (Metered Manual)* to check the exposure value.
 Toward +: Images become brighter.

Toward -: Images become darker.

- **0:** Appropriate exposure analyzed by the camera.
- * Indicates under/over for appropriate exposure. It is displayed using a numerical value on the monitor and with a metering indicator on the viewfinder
- Adjust the focus and shoot the subject.

Hint

You can change the shutter speed and aperture (F-value) combination without changing the set exposure value by rotating the front/rear dial while pressing the AEL button. (Manual shift)

Note

- The Metered Manual indicator does not appear when [☐ ISO] is set to [ISO AUTO].
- When the amount of ambient light exceeds the metering range of the Metered Manual, the Metered Manual indicator flashes.
- The SteadyShot warning indicator does not appear in manual exposure mode.
- The brightness of the image on the screen may differ from the actual image being shot.

Related Topic

- ISO (still image/movie)
- Bulb shooting

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Bulb shooting

You can shoot a trailing image of the movement of a subject with long exposure. Bulb shooting is suitable for shooting trails from stars or fireworks, etc.

- Set the mode dial to M (Manual Exposure).
- 2 Turn the rear dial clockwise until [BULB] is indicated.
- Select the aperture value (F-value) using the front dial.
- 4 Press the shutter button halfway down to focus.
- 5 Press and hold the shutter button for the duration of the shooting.

As long as the shutter button is pressed, the shutter remains open.

Hint

- When shooting fireworks, etc., focus at infinity in manual focus mode. If you use a lens whose infinity point is unclear, adjust the focus on the fireworks in the area you want to focus on in advance.
- In order to perform bulb shooting without causing the image quality to deteriorate, we recommend that you start shooting while the camera is cool.
- During bulb shooting, images tend to blur. It is recommended that you use a tripod, a Bluetooth remote commander (sold separately) or a remote commander equipped with a lock function (sold separately). When using the Bluetooth remote commander, you can start bulb shooting by pressing the shutter button on the remote commander. To stop bulb shooting, press the shutter button on the remote commander again. To use the other remote commander, use the model which can be connected via the Multi/Micro USB terminal.

Note

- The longer the exposure time, the more noise will be visible on the image.
- When [Long Exposure NR] is set to [On], noise reduction is performed after shooting for the same duration that the shutter was open. You cannot shoot while noise reduction is in progress.
- You cannot set the shutter speed to [BULB] in the following situations:
 - When the drive mode is set to the following:
 - [Cont. Shooting]
 - [Self-timer(Cont)]
 - [Cont. Bracket]
 - [Shutter Type] is set to [Electronic Shutter].

If you use the above functions when the shutter speed is set to [BULB], the shutter speed is temporarily set to 30 seconds.

If you set [Drive Mode] to [Cont. Shooting] and [Shutter Type] to [Auto] or [Electronic Shutter] when the shutter speed is set to [BULB], the shutter speed will be temporarily set to 1/2 second.

Related Topic

- Manual Exposure
- Long Exposure NR

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Exposure Ctrl Type



You can select the method for setting the exposure (shutter speed, aperture, and ISO sensitivity) when shooting movies. With [P/A/S/M Mode], you can select from the P/A/S/M modes in the same way as the exposure mode for still images. With [Flexible Exp. Mode], you can individually switch between the automatic and manual settings for aperture value, shutter speed, and ISO sensitivity, like the exposure control system of a professional camera.



 $\textbf{MENU} \rightarrow \textbf{[O]} \ (\textbf{Shooting}) \rightarrow \textbf{[Shooting Mode]} \rightarrow \textbf{[Exposure Ctrl Type]} \rightarrow \textbf{desired setting}.$

Menu item details

P/A/S/M Mode:

Select the desired exposure mode from among [Program Auto], [Aperture Priority], [Shutter Priority], and [Manual Exposure].

Flexible Exp. Mode:

Sets the aperture value, shutter speed, and ISO sensitivity automatically (Auto) or manually (Manual). You can switch between the automatic and manual settings using the assigned custom key, or change the aperture, shutter speed, and ISO sensitivity values by turning the front/rear dials and the control wheel.

Note

Even if [Exposure Ctrl Type] is set to [Flexible Exp. Mode], when shooting a movie by pressing the MOVIE (movie) button in a still image shooting mode, the movie will be shot in the exposure mode for still image shooting.

Related Topic

- Movie: Exposure Mode
- Auto/Manual Swt. Set.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 q1

Auto/Manual Swt. Set.



When shooting movies, you can switch between the automatic and manual settings separately for aperture, shutter speed, and ISO sensitivity as you would with the exposure control system of a professional camera. Set [Exposure Ctrl Type] to [Flexible Exp. Mode] beforehand.



 $MENU \rightarrow$ [Exposure/Color) \rightarrow [Exposure] \rightarrow [Auto/Manual Swt. Set.] \rightarrow desired setting item.

Menu item details

Av Auto/Manual Switch:

Switches the aperture value between [Auto] and [Manual].

Tv Auto/Manual Switch:

Switches the shutter speed between [Auto] and [Manual].

ISO Auto/Manual Set:

Switches the ISO sensitivity between [Auto] and [Manual].

To switch between [Auto] and [Manual] using a custom keys

When [Exposure Ctrl Type] is set to [Flexible Exp. Mode], the following functions are assigned to the custom keys during movie recording.

- [Av Auto/Manual Switch]: C1 (Custom 1) button
- [Tv Auto/Manual Switch]: C4 (Custom 4) button
- [ISO Auto/Manual Set]: C2 (Custom 2) button

Each time you press the respective custom key, the aperture value, shutter speed, or ISO sensitivity switches between [Auto] and [Manual].

When [Auto] is selected, the proper exposure is set automatically, and when [Manual] is selected, the aperture value, shutter speed, and ISO sensitivity can be set with the following dials.

- Aperture value: front dial
- Shutter speed: control wheel
- ISO sensitivity: rear dial

Note

When you set the aperture value with the lens aperture ring, the aperture ring value takes priority over the dial value.

Related Topic

Exposure Ctrl Type

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Movie: Exposure Mode



You can set the exposure mode for movie shooting. The setting you have selected will be applied when [Exposure Ctrl Type] is set to [P/A/S/M Mode].

- 1 Set the mode dial to | (Movie).
- $igotimes_{igotimes$
- Press the MOVIE (movie) button to start recording.
 - Press the MOVIE button again to stop recording.

Menu item details

Program Auto:

Allows you to shoot with the exposure adjusted automatically (both the shutter speed and the aperture value).

□ Aperture Priority:

Allows you to shoot after adjusting the aperture value manually.

Shutter Priority:

Allows you to shoot after adjusting the shutter speed manually.

Manual Exposure:

Allows you to shoot after adjusting the exposure (both the shutter speed and the aperture value) manually.

Related Topic

Exposure Ctrl Type

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

S&Q Motion: Exposure Mode



You can select the exposure mode for slow-motion/quick-motion shooting. The setting you have selected will be applied when [Exposure Ctrl Type] is set to [P/A/S/M Mode].

You can change the setting and playback speed for slow-motion/quick-motion shooting with [S&Q Settings].

- 1 Set the mode dial to \$\&\Q\ (\$\&\Q\ Motion).
- **2** MENU \rightarrow \bigcirc (Shooting) \rightarrow [Shooting Mode] \rightarrow [S&Q Exposure Mode] \rightarrow desired setting.
- 3 Press the MOVIE (movie) button to start recording.
 - Press the MOVIE button again to stop recording.

Menu item details

S&O Program Auto:

Allows you to shoot with the exposure adjusted automatically (both the shutter speed and the aperture value).

Sa0 A Aperture Priority:

Allows you to shoot after adjusting the aperture value manually.

Sko Shutter Priority:

Allows you to shoot after adjusting the shutter speed manually.

S&O_M Manual Exposure:

Allows you to shoot after adjusting the exposure (both the shutter speed and the aperture value) manually.

Related Topic

- S&Q Settings
- Exposure Ctrl Type

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Auto Slow Shutter



Sets whether or not to adjust the shutter speed automatically when recording movies if the subject is dark.



Menu item details

On:

Uses Auto Slow Shutter. The shutter speed automatically slows when recording in dark locations. You can reduce noise in the movie by using a slow shutter speed when recording in dark locations.

Off:

Does not use Auto Slow Shutter. The recorded movie will be darker than when [On] is selected, but you can record movies with smoother motion and less object blur.

Note

- [Auto Slow Shutter] does not function in the following situations:
 - During slow-motion/quick-motion shooting
 - **S** (Shutter Priority)
 - III_M (Manual Exposure)
 - When [☐ ISO] is set to other than [ISO AUTO]
 - When [Exposure Ctrl Type] is set to [Flexible Exp. Mode] and the method for adjusting the shutter speed is set to [Manual]

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α1

Selecting the focus method (Focus Mode)

Selects the focus method to suit the movement of the subject.



Turn the focus mode dial while pressing the focus mode dial lock release button and select the desired mode.

Setting details

AF-S (Single-shot AF):

The product locks the focus once focusing is complete. Use this when the subject is motionless.

AF-C (Continuous AF):

The product continues to focus while the shutter button is pressed and held halfway down. Use this when the subject is in motion. In [Continuous AF] mode, there is no beep when the camera focuses.

DMF (direct manual focus):

You can make fine adjustments manually after performing auto focusing, letting you focus on a subject more quickly than when using [Manual Focus] from the beginning. This is convenient in situations such as macro shooting.

MF (Manual Focus):

Adjusts the focus manually. If you cannot focus on the intended subject using auto focus, use [Manual Focus].

Focus indicator



The subject is in focus and the focus is locked.



The subject is not in focus.



The subject is in focus. The focus will be adjusted continuously according to the movements of the subject.



Focusing is in progress.

Subjects on which it is difficult to focus using auto focus

- Dark and distant subjects
- Subjects with poor contrast
- Subjects seen through glass
- Fast-moving subjects
- Reflective light or shiny surfaces
- Flashing light
- Back-lit subjects
- Continuously repetitive patterns, such as the facades of buildings
- Subjects in the focusing area with different focal distances

Hint

- In [Continuous AF] mode, you can lock the focus by pressing and holding the button that has been assigned the [Focus Hold] function.
- When you set the focus to infinity in [Manual Focus] mode or [DMF] mode, make sure that the focus is on a sufficiently distant subject by checking the monitor or the viewfinder.

Note

- When [Continuous AF] is set, the angle of view may change little by little while focusing. This does not affect the actual recorded images.
- Even if the focus mode dial is set to AF-S or DMF, the focus mode will switch to [Continuous AF] when shooting movies or when the mode dial is set to **\$&Q** (\$&Q Motion).

Related Topic

- Using the focus mode dial
- Direct manual focus (DMF)
- Manual Focus
- Selecting the focus area (Focus Area)
- Assigning frequently used functions to buttons (Custom Key Setting)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Selecting the focus area (Focus Area)



Set the type of focusing frame when shooting with the auto focus. Select the mode according to the subject.



Menu item details

[] Wide:

Focuses on a subject covering the whole range of the screen automatically. When you press the shutter button halfway down in the still image shooting mode, a green frame is displayed around the area that is in focus.

Zone:

Select a zone on the monitor on which to focus, and the product will automatically select a focus area.

Center Fix:

Focuses automatically on a subject in the center of the image. Use together with the focus-lock function to create the composition you want.

Spot: S/Spot: M/Spot: L:

Allows you to move the focusing frame to a desired point on the screen and focus on an extremely small subject in a narrow area.

Expand Spot:

If the product cannot focus on a single selected point, it uses focus points around the [Spot] as a secondary priority area for focusing.

ា្ន ្ធ ្វេ 📆 📆 Tracking:

This setting is available only when the focus mode is set to [Continuous AF]. When the shutter button is pressed and held halfway down, the product tracks the subject within the selected autofocus area. Point the cursor at [Tracking] on the [Fig. Focus Area] setting screen, and then select the desired area to start tracking using the left/right sides of the control wheel. You can also move the tracking start area to the desired point by designating the area as a [Tracking: Zone], [Tracking: Spot S]/[Tracking: Spot M]/[Tracking: Spot L] or [Tracking: Expand Spot].

Hint

In the default settings, [Focus Area] is assigned to the C2 button.

Note


- [☐ Focus Area] is locked to [Wide] in the following situations:
 - [Intelligent Auto]
- The focus area may not light up during continuous shooting or when the shutter button is pressed all the way down at once.

● When the mode dial is set to [(Movie) or **S&Q** (S&Q Motion) or during movie shooting, [Tracking] cannot be selected as the [Focus Area].


Examples of the focusing frame display

The focusing frame differs as follows.

When focusing on a larger area




When focusing on a smaller area



- When [Focus Area] is set to [Wide] or [Zone], the focusing frame may switch between "When focusing on a larger area" and "When focusing on a smaller area" depending on the subject or situation.
- When you attach an A-mount lens with a Mount Adaptor (LA-EA3 or LA-EA5) (sold separately), the focusing frame for "When focusing on a smaller area" may be displayed.

When focus is achieved automatically based on the whole range of the monitor



• When you use a zoom function other than the optical zoom, the [Focus Area] setting is disabled and the focusing frame is shown by the dotted line. The AF operates with priority on and around the center area.

To move the focus area

- You can move the focus area by operating the multi-selector when [Focus Area] is set to the following parameters:
 - [Zone]
 - [Spot: S]/[Spot: M]/[Spot: L]

- [Expand Spot]
- [Tracking: Zone]
- [Tracking: Spot S]/[Tracking: Spot M]/[Tracking: Spot L]
- [Tracking: Expand Spot]

If you assign [Focus Standard] to the center of the multi-selector beforehand, you can move the focusing frame back to the subject being tracked or the center of the monitor by pressing the center of the multi-selector.

Hint

- When [Focus Area] is set to [Spot] or [Expand Spot], you can move the focusing frame over a greater distance at a time with the multi-selector by setting [AF Frame Move Amt] to [Large].
- You can move the focusing frame quickly by touching and dragging it on the monitor. Set [Touch Operation] to [On], and set [Touch Func. in Shooting] to [Touch Focus] beforehand.

To track the subject temporarily (Tracking On)

You can temporarily change the setting for [Focus Area] to [Tracking] while you press and hold down the custom key to which you have assigned [Tracking On] in advance. The [Focus Area] setting before you activated [Tracking On] will switch to the equivalent [Tracking] setting.

For example:

[Focus Area] before you activate [Tracking On]	[Focus Area] while [Tracking On] is active
[Wide]	[Tracking: Wide]
[Spot: S]	[Tracking: Spot S]
[Expand Spot]	[Tracking: Expand Spot]

Phase detection AF

When there are phase detection AF points within the auto focus area, the product uses the combined autofocus of the phase detection AF and contrast AF.

Note

- Phase detection AF is available only when a compatible lens is attached. If you use a lens that does not support phase detection AF, you cannot use the following functions.
 - [AF Tracking Sensitivity]
 - [AF Subj. Shift Sensitivity]
 - [AF Transition Speed]

Also, even if you use a previously purchased applicable lens, the phase detection AF might not function unless you update the lens.

Related Topic

- Selecting the focus method (Focus Mode)
- Touch Operation
- Focusing using touch operations (Touch Focus)
- Adjusting the focus area settings to the camera's orientation (horizontal/vertical) (Switch V/H AF Area)
- Registering the current focus area (AF Area Registration)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Tracking subject (Tracking function)

This camera has the function of tracking which tracks the subject, and keeps marking it with the focusing frame. You can set the start position to track by selecting from focusing areas, or by specifying by touch operation. The required function varies depending on the setting method.

• You can refer to the related functions under "Related Topic" at the bottom of this page.

Setting the start position to track by focusing area ([Tracking] under [Focus Area])

The selected focusing frame is set as the start position to track, and the tracking starts by pressing the shutter button halfway down.

- This function is available in still image shooting mode.
- This function is available when focus mode dial is set to AF-C (Continuous AF).

Setting the start position to track by touch operation ([Touch Tracking] under [Touch Func. in Shooting])

You can set the subject to track by touching it on the monitor.

- This function is available in still image shooting mode and movie shooting mode.
- This function is available when the focus mode dial is set to AF-S (Single-shot AF), AF-C (Continuous AF), or DMF (direct manual focus).

Changing the setting for [Focus Area] to [Tracking] temporarily ([Tracking On] under [Custom Key Setting])

Even [Focus Area] is set to other than [Tracking], you can temporarily change the setting for [Focus Area] to [Tracking] while pressing and holding the key to which you have assigned [Tracking On] function.

- Assign the [Tracking On] function to a desired key using [Custom Key Setting] in advance.
- This function is available in still image shooting mode.
- This function is available when the focus mode dial is set to AF-C (Continuous AF).

Temporarily pausing the tracking function

By pressing the key to which you assigned [Tracking-Off Hold] or [Tracking-Off Toggle] using [Custom Key Setting], you can temporarily pause the tracking function.

Use this function when you are in a shooting situation where it is difficult to keep tracking, or when the tracking frame switches to another subject.

If you press the key to which you assigned [Tracking/Face-Off Hold] or [Tracking/Face-Off Tggle.] using [Custom Key Setting], [Face/Eye Prior. in AF] will temporarily switch to [Off], suspending the tracking function that prioritizes the face/eyes.

Use this function when the tracking frame switches to the face/eyes of another subject.

Related Topic

- Selecting the focus method (Focus Mode)
- Selecting the focus area (Focus Area)
- Starting tracking with touch operations (Touch Tracking)
- Assigning frequently used functions to buttons (Custom Key Setting)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Focusing on human eyes

The camera can automatically detect faces and eyes and focus on the eyes (Eye AF). The following explanation is for cases where the detection target is human. The faces of up to 8 subjects can be detected.

There are two methods for performing [Eye AF], with some differences between their specifications. Select the appropriate method according to your purpose.

Item	[Face/Eye Prior. in AF] function	[Eye AF] via a custom key
Characteristics	The camera will detect faces/eyes with greater priority.	The camera will detect faces/eyes exclusively.
Advance preparation	 Select [☐ Face/Eye Prior. in AF] → [On]. Select [☐ Face/Eye Subject] → [Human]. 	Assign [Eye AF] to the desired key using [Custom Key Setting] or [Custom Key Setting].
How to perform [Eye AF]	Press the shutter button halfway down.	Press the key to which you have assigned the [Eye AF] function*.
Function details	 When the camera detects a face or eye inside or around the designated focus area, it focuses on the face or eye with greater priority. If the camera does not detect any faces or eyes inside or around the designated focus area, it will focus on another detectable subject. 	 The camera focuses exclusively on faces or eyes anywhere on the screen, regardless of the setting for [Focus Area]. The camera will not automatically focus on another subject if no face or eye is detected anywhere on the screen.
Focus mode	Follows the focus mode setting	Follows the focus mode setting
Focus area	Follows the setting designated with [Focus Area]	The focus area temporarily becomes the entire screen, regardless of the setting for [Focus Area].

^{*} Regardless of whether [Face/Eye Prior. in AF] is set to [On] or [Off], you can use [Eye AF] via a custom key while you are pressing the custom key to which you have assigned [Eye AF].

[Eye AF] by custom key

The Eye AF function can be used by assigning [Eye AF] to a custom key. The camera can focus on eyes as long as you are pressing the key. This is useful when you want to temporarily apply the Eye AF function to the entire screen regardless of the setting for [Focus Area].

The camera does not focus automatically if no faces or eyes are detected.

- 2. MENU \rightarrow AF_{MF} (Focus) \rightarrow [Face/Eye AF] \rightarrow [\rightleftharpoons Face/Eye Subject] \rightarrow [Human].
- 3. Point the camera at the face of a human, and press the key to which you have assigned the [Eye AF] function. To shoot a still image, press the shutter button while pressing the key.

To focus on the eyes of an animal or a bird

Set [Face/Eye Subject] to [Animal] or [Bird] before shooting.

If the detection target is an animal or a bird, eyes can be detected only when shooting still images. Faces of animals and birds are not detected.

Note

- The [Eye AF] function may not function very well in the following situations:
 - When the person is wearing sunglasses.
 - When the front hair covers the person's eyes.
 - In low-light or back-lit conditions.
 - When the eyes are closed.
 - When the subject is in the shade.
 - When the subject is out of focus.
 - When the subject is moving too much

There are also other situations in which it may not be possible to focus on the eyes.

- When the camera cannot focus on human eyes, it will detect and focus on the face instead. The camera cannot focus on eyes when no human faces are detected.
- The camera may not detect faces at all or may accidentally detect other objects as faces in some conditions.

Related Topic

- Face/Eye Prior. in AF (still image/movie)
- Face/Eye Subject (still image/movie)
- Subject Sel. Setting (still image/movie)
- Right/Left Eye Select (still image/movie)
- Selecting the focus method (Focus Mode)
- Selecting the focus area (Focus Area)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 q1

Face/Eye Prior. in AF (still image/movie)



Sets whether or not the camera detects faces or eyes inside the focus area while performing autofocus, and then focuses on the eyes automatically (Eye AF).



 $MENU \rightarrow {}^{AF}_{MF}$ (Focus) \rightarrow [Face/Eye AF] \rightarrow [Face/Eye Prior. in AF] \rightarrow desired setting.

Menu item details

On:

Focuses on the faces or eyes with priority if there are faces or eyes inside or around the designated focus area.

Off:

Does not prioritize faces or eyes when performing auto-focusing.

Hint

- By combining the [☐ Face/Eye Prior. in AF] function with [☐ Focus Area] → [Tracking], you can maintain focus on a moving eye or face.
- When [Face/Eye Priority Select] is assigned to the desired key using [Custom Key Setting] or [Custom Key Setting] or [Custom Key Setting], you can switch the [Face/Eye Prior. in AF] function on or off by pressing the key.
- By assigning [Face/Eye Prio. Off Hold] or [Face/Eye Prio. Off Tggle.] to the desired key with [Custom Key Setting], you can switch [Face/Eye Prior. in AF] to [Off] temporarily using the key.

Note

- If the camera does not detect any faces or eyes inside or around the designated focus area, it will focus on another detectable subject.
- When the shooting mode is set to [Intelligent Auto], [Face/Eye Prior. in AF] is locked to [On].

Related Topic

- Focusing on human eyes
- Face/Eye Subject (still image/movie)
- Subject Sel. Setting (still image/movie)
- Right/Left Eye Select (still image/movie)
- Assigning frequently used functions to buttons (Custom Key Setting)

Help Guide

Interchangeable Lens Digital Camera

ILCE-1 α1

Face/Eye Subject (still image/movie)



Selects the target to be detected with the Face/Eye AF function.



Menu item details

Human:

Detects human faces/eyes.

Animal:

Detects animal eyes.

Bird:

Detects the eyes of birds.

Hint

To detect animal or bird eyes, compose the shot so that the entire head is within the angle of view. Once you focus on the animal's or bird's head, the eyes will be detected more easily.

Note

- When [☐ Face/Eye Subject] is set to [Animal] or [Bird], the following functions cannot be used.
 - Face Priority in Multi Metering
 - Regist. Faces Priority
 - Eye detection function during movie recording
- Even when [Face/Eye Subject] is set to [Animal], the eyes of some types of animals cannot be detected.
- Even when [Face/Eye Subject] is set to [Bird], the eyes of some types of birds cannot be detected.

Related Topic

- Focusing on human eyes
- Face/Eye Prior. in AF (still image/movie)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Subject Sel. Setting (still image/movie)



Sets the types of detection targets that are available when using the custom key to which [Swt Face/Eye Sbjc Dtc] is assigned.



MENU \to AF_{MF} (Focus) \to [Face/Eye AF] \to [Figure Subject Sel. Setting] \to Add check marks to the detection targets that you want to select, and then select [OK].

The types of targets marked with \checkmark (check mark) will be available as settings.

Hint

- Assign [Swt Face/Eye Sbjc Dtc] to the desired key using [Custom Key Setting].
- You can select the types of targets to which you did not add a check mark in [☐ Subject Sel. Setting] by selecting MENU → AFMF (Focus) → [Face/Eye AF] → [☐ Face/Eye Subject].

Related Topic

- Face/Eye Subject (still image/movie)
- Assigning frequently used functions to buttons (Custom Key Setting)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 q1

Right/Left Eye Select (still image/movie)



Sets whether to focus on the left eye or right eye when [Face/Eye Subject] is set to [Human] or [Animal].



 $\mathsf{MENU} \to \ ^{\mathsf{AF}}_{\mathsf{MF}} \ (\mathsf{Focus}) \to [\mathsf{Face/Eye} \ \mathsf{AF}] \to [\ ^{\square}_{\mathsf{EH}} \ \mathsf{Right/Left} \ \mathsf{Eye} \ \mathsf{Select}] \to \mathsf{desired} \ \mathsf{setting}.$

Menu item details

Auto:

The camera automatically detects either the left eye or right eye.

Right Eye:

The right eye of the subject (the eye on the left side from the photographer's perspective) is detected.

Left Eye:

The left eye of the subject (the eye on the right side from the photographer's perspective) is detected.

[Switch Right/Left Eye] by custom key

You can also switch the eye to be detected by pressing the custom key.

When [Right/Left Eye Select] is set to [Right Eye] or [Left Eye], you can switch the eye to be detected by pressing the custom key to which you have assigned the [Switch Right/Left Eye] function.

When [Right/Left Eye Select] is set to [Auto], you can temporarily switch the eye to be detected by pressing the custom key to which you have assigned the [Switch Right/Left Eye] function.

The temporary left/right selection is cancelled when you perform the following operations, etc. The camera returns to automatic eye detection.

- Pressing the center of the control wheel
- Pressing the center of the multi-selector
- Stopping pressing the shutter button halfway down (only during still image shooting)
- Stopping pressing the custom key to which [AF On] or [Eye AF] is assigned (only during still image shooting)
- Pressing the MENU button

Hint

When [Face/Eye Frame Disp.] is set to [On], the eye detection frame appears around the eye you selected using [Fight/Left Eye Select] or [Switch Right/Left Eye] with the custom key.

Related Topic

- Focusing on human eyes
- Face/Eye Prior. in AF (still image/movie)
- Face/Eye Subject (still image/movie)
- Face/Eye Frame Disp. (still image/movie)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Face/Eye Frame Disp. (still image/movie)



Sets whether or not to display the face/eye detection frame when a face or eyes are detected.



 $MENU \rightarrow {}^{AF}_{MF}$ (Focus) \rightarrow [Face/Eye AF] \rightarrow [Face/Eye Frame Disp.] \rightarrow desired setting.

Menu item details

On:

Displays a detection frame when a face or eyes are detected.

Off:

Does not display a detection frame when a face or eyes are detected.

Face detection frame

When the camera detects a face, the gray face-detection frame appears. The frame color will be reddish purple if the detected face has been registered using the [Face Memory] function.

The face detection frame turns white when the face is detected inside or around the focus area, and the camera determines that autofocus is enabled.



Eye detection frame

A white eye detection frame appears when an eye is detected and the camera determines that autofocusing is possible.

The eye detection frame is displayed as follows when [Face/Eye Subject] is set to [Animal] or [Bird].



Hint

If you want the face or eye detection frame to disappear within a certain period of time after the camera has focused on the face or eye, set [AF Area Auto Clear] to [On].

Note

- If the subject is moving too much, the detection frame may not be displayed correctly over their eyes.
- The eye detection frame is not displayed when the Eye AF function is unavailable.
- Even if [Face/Eye Frame Disp.] is set to [Off], a green focusing frame will appear over faces or eyes that are in focus when you press the shutter button halfway down, etc.

Related Topic

- Focusing on human eyes
- Face/Eye Prior. in AF (still image/movie)
- Face/Eye Subject (still image/movie)
- Right/Left Eye Select (still image/movie)
- Face Memory

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Face Memory



Sets personal face data. If you register faces in advance, the product can focus on the registered face as a priority. Up to eight faces can be registered.



 $\text{MENU} \to \ ^{\text{AF}}_{\text{MF}} \ (\text{Focus}) \to [\text{Face/Eye AF}] \to [\text{Face Memory}] \to \text{desired setting item}.$

Menu item details

New Registration:

Shoots and registers faces.

Order Exchanging:

When multiple faces are registered, the order of priority for the registered face data can be changed.

Delete:

Deletes registered faces one by one.

Delete All:

Deletes all registered faces at once.

Note

- When performing [New Registration], shoot the face from the front in a brightly lit place. The face may not be registered correctly if it is obscured by a hat, a mask, sunglasses, etc.
- Even if you execute [Delete], the data for registered face will remain in the product. To delete the data for registered faces from the product, select [Delete All].

Related Topic

Regist. Faces Priority (still image/movie)


Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Regist. Faces Priority (still image/movie)



Sets whether to focus with higher priority on faces registered using [Face Memory].



Menu item details

On:

Focuses with higher priority on faces registered using [Face Memory].

Off:

Focuses without giving higher priority to registered faces.

Hint

- To use the [Regist. Faces Priority] function, set as follows.
 - [☐ Face/Eye Prior. in AF] under [Face/Eye AF]: [On]
 - [Face/Eye Subject] under [Face/Eye AF]: [Human]

Related Topic

- Face/Eye Prior. in AF (still image/movie)
- Face Memory

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Focus Standard



If you press the key to which [Focus Standard] is assigned, you can recall useful functions such as automatically focusing on a subject in the center of the screen in accordance with the focus area settings.

- MENU → → (Setup) → [Operation Customize] → [→ Custom Key Setting] or [☐ Custom Key Setting] → desired key, then assign the [Focus Standard] function to the key.
- Press the key to which [Focus Standard] is assigned.
 - What you can do by pressing the key varies depending on the setting for [Focus Area].

Examples of [Focus Standard] key functions

- When [Focus Area] is set to any of the following parameters, pressing the key moves the focusing frame back to the center of the monitor or to the subject you are tracking:
 - [Zone]
 - [Spot: S]/[Spot: M]/[Spot: L]
 - [Expand Spot]
 - [Tracking: Zone]
 - [Tracking: Spot S]/[Tracking: Spot M]/[Tracking: Spot L]
 - [Tracking: Expand Spot]
- When [Fig. Focus Area] is set to [Wide], [Center Fix], [Tracking: Wide], or [Tracking: Center Fix], pressing the key in the autofocus mode makes the camera focus on the center of the screen. If you press the key while recording a movie with manual focus, you can temporarily switch to autofocus and focus on the center of the screen.

Note

You cannot set the [Focus Standard] function to [Left Button], [Right Button] or [Down Button] of the control wheel.

Related Topic

- Assigning frequently used functions to buttons (Custom Key Setting)
- Selecting the focus area (Focus Area)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 q1

Adjusting the focus area settings to the camera's orientation (horizontal/vertical) (Switch V/H AF Area)



You can set whether to switch the [Focus Area] and the position of the focusing frame according to the orientation of the camera (horizontal/vertical). This function is useful when shooting scenes for which you have to change the camera position frequently, such as portraits or sports scenes.



 $\text{MENU} \to \ ^{\text{AF}}_{\text{MF}} \ \ \text{(Focus)} \to \text{[Focus Area]} \to \text{[Switch V/H AF Area]} \to \text{desired setting}.$

Menu item details

Off-

Does not switch the [Focus Area] and the position of the focusing frame according to the orientation of the camera (horizontal/vertical).


AF Point Only:

Switches the position of the focusing frame according to the orientation of the camera (horizontal/vertical). The [Figure 1] Focus Area] is fixed.

AF Point + AF Area:

Switches both the [Focus Area] and the position of the focusing frame according to the orientation of the camera (horizontal/vertical).

An example when [AF Point + AF Area] is selected



- (A) Vertical: [Spot] (Upper left corner)
- (B) Horizontal: [Spot] (Upper right corner)
- (C) Vertical: [Zone] (Lower left corner)
 - Three camera orientations are detected: horizontal, vertical with the side of the shutter button facing up, and vertical with the side of the shutter button facing down.

Note

- If the setting for [Switch V/H AF Area] is changed, the focus settings for each camera orientation will not be retained.
- The [Focus Area] and the position of the focusing frame will not change even when [Switch V/H AF Area] is set to [AF Point + AF Area] or [AF Point Only] in the following situations:
 - When the shooting mode is set to [Intelligent Auto]
 - While the shutter button is pressed halfway down
 - During movie shooting
 - While using the digital zoom function
 - While the auto-focusing is activated
 - During continuous shooting

- During the countdown for the self-timer
- When [Focus Magnifier] is activated
- When you shoot images right after the power is turned on and the camera is vertical, the first shot is taken with the horizontal focus setting or with the last focus setting.
- The orientation of the camera cannot be detected when the lens is facing up or down.

Related Topic

Selecting the focus area (Focus Area)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Registering the current focus area (AF Area Registration)



You can move the focusing frame to a preassigned position temporarily using a custom key. This function is useful when shooting scenes in which the subject's movements are predictable; for example, sports scenes. With this function, you can switch the focus area quickly according to the situation.

How to register focus area

- 1. MENU $\rightarrow AF_{MF}$ (Focus) \rightarrow [Focus Area] \rightarrow [AF Area Registration] \rightarrow [On].
- 2. Set the focus area to the desired position and then hold down the Fn (Function) button.

How to call up the registered focus area

- Set the camera to the shooting mode, hold down the key to which [Regist. AF Area hold] has been assigned and then press the shutter button to shoot images.

Hint

- When a focusing frame is registered using [AF Area Registration], the registered focusing frame flashes on the monitor.
- If you assign [Regist AF Area tggle] to a custom key, you can use the registered focusing frame without holding down the key.
- If [Reg. AF Area+AF On] is assigned to a custom key, auto focusing using the registered focusing frame is performed when the key is pressed.

Note

- A focus area cannot be registered in the following situations:
 - While [Touch Focus] is being performed
 - While using the digital zoom function
 - While [Touch Tracking] is being performed
 - While focusing
 - While performing focus lock
- You cannot assign [Regist. AF Area hold] to [Left Button], [Right Button], or [Down Button].
- You cannot call up the registered focus area in the following situations:
 - The mode dial is set to either AUTO (Auto Mode), [III] (Movie) or \$&Q (S&Q Motion)
- When [AF Area Registration] is set to [On], the [Lock Operation Parts] setting is locked to [Off].

Related Topic

- Selecting the focus area (Focus Area)
- Deleting a registered AF Area (Del. Regist. AF Area)
- Assigning frequently used functions to buttons (Custom Key Setting)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Deleting a registered AF Area (Del. Regist. AF Area)



Deletes the focusing frame position that was registered using [AF Area Registration].



 $MENU \rightarrow {}^{AF}_{MF}$ (Focus) \rightarrow [Focus Area] \rightarrow [Del. Regist. AF Area].

Related Topic

Registering the current focus area (AF Area Registration)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Focus Area Limit (still image/movie)



By limiting the types of available focus area settings in advance, you can more quickly select settings for [Focus Area].



MENU \to AF_{MF} (Focus) \to [Focus Area] \to [Focus Area Limit] \to Add check marks to the focus areas that you want to use, and then select [OK].

The types of focus areas marked with \checkmark (check mark) will be available as settings.

Hint

• When you assign [Switch Focus Area] to a desired key using [Custom Key Setting] or [Custom Key Setting], the focus area changes every time you press the assigned key. By limiting the types of selectable focus areas with [Focus Area Limit] in advance, you can more quickly select the focus area setting you want.

Note

- Types of focus areas that do not have a check mark cannot be selected using MENU or the Fn (function) menu. To select one, add a check mark using [☐ Focus Area Limit].
- If you remove the check mark for a focus area registered with [Switch V/H AF Area] or [AF Area Registration], the registered settings will change.

Related Topic

- Selecting the focus area (Focus Area)
- Assigning frequently used functions to buttons (Custom Key Setting)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$


Circ. of Focus Point (still image/movie)




Sets whether to allow the focusing frame to jump from one end to the other when you move the focusing frame. This function is useful when you want to move the focusing frame from one end to the other quickly.

The function can be used when the following settings are selected for [Focus Area].

- [Zone]
- [Spot: S]/[Spot: M]/[Spot: L]
- [Expand Spot]
- [Tracking: Zone]
- [Tracking: Spot S]/[Tracking: Spot M]/[Tracking: Spot L]
- [Tracking: Expand Spot]



When [Circulate] is selected:



Menu item details

Does Not Circulate:

The cursor does not move when you try to move the focusing frame past the end.

Circulato

The cursor jumps to the opposite end when you try to move the focusing frame past the end.

Note

Even if you set [Circ. of Focus Point] to [Circulate], the focusing frame will not circulate diagonally.

Related Topic

Selecting the focus area (Focus Area)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 q1

AF Frame Move Amt (still image/movie)



Sets the distance by which the focusing frame is moved when [Fig Focus Area] is set to [Spot], etc. You can quickly move the focusing frame by increasing the distance, such as in situations where the subject is moving a lot.



 $MENU \rightarrow AF_{MF}$ (Focus) \rightarrow [Focus Area] \rightarrow [AF Frame Move Amt] \rightarrow desired setting.

Menu item details

Standard:

The focusing frame moves by the standard distance.

Large

The focusing frame moves over a greater distance at a time than with [Standard].

Hint

- When [Swt. AF Frame Move hold] is assigned to the desired key using [Custom Key Setting] or [Custom Key Setting], the [AF Frame Move Amt] setting temporarily switches while the key is pressed.
- If any of the following functions is assigned to the control wheel using [Custom Key Setting] or [Custom Key Setting], you can move the focusing frame by the distance determined for each function, regardless of the setting for [AF Frame Move Amt].
 - [Move AF Frame ←→ : L]
 - [Move AF Frame ♣ : L]
 - [Move AF Frame ←→ : Std]
 - [Move AF Frame ↑: Std]
- If any of the following functions is assigned to the front/rear dials or control wheel using [My Dial Settings], you can move the focusing frame by the distance determined for each function, regardless of the setting for [AF Frame Move Amt].
 - [Move AF Frame ←→: L]
 - [Move AF Frame ‡ : L]
 - [Move AF Frame ←→ : Std]
 - [Move AF Frame : Std]

Related Topic

- Selecting the focus area (Focus Area)
- Assigning frequently used functions to buttons (Custom Key Setting)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Focus Area Color (still image/movie)



You can specify the color of the frame indicating the focusing area. If the frame is difficult to see because of the subject, make it more visible by changing its color.



 $\text{MENU} \to \ ^{\text{AF}}_{\text{MF}} \ \ (\text{Focus}) \to [\text{Focus Area}] \to [\ ^{\text{Cols}}_{\text{Ell}} \ \text{Focus Area Color}] \to \text{desired color}.$

Menu item details

White:

Displays the frame indicating the focusing area in white.

Red:

Displays the frame indicating the focusing area in red.

Related Topic

Selecting the focus area (Focus Area)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

AF Area Auto Clear



Sets whether the focus area should be displayed all the time or should disappear automatically shortly after focus is achieved.



 $\text{MENU} \to \ ^{\text{AF}}_{\text{MF}} \ \ \text{(Focus)} \to \text{[Focus Area]} \to \text{[AF Area Auto Clear]} \to \text{desired setting}.$

Menu item details

On:

The focus area disappears automatically shortly after focus is achieved.

Off:

The focus area is displayed all the time.

Related Topic

Selecting the focus area (Focus Area)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Area Disp. dur Tracking



Sets whether or not to display the frame for the focusing area when [Figure Focus Area] is set to [Tracking].



 $\text{MENU} \rightarrow \text{ }^{\text{AF}}_{\text{MF}} \text{ (Focus)} \rightarrow \text{[Focus Area]} \rightarrow \text{[Area Disp. dur Tracking]} \rightarrow \text{desired setting.}$

Menu item details

On:

Displays the frame for the focusing area during tracking. Since the tracking start area is displayed while tracking the subject, it is helpful when starting the next session of shooting.

Off:

Does not display the frame for the focusing area during tracking.

Related Topic

Selecting the focus area (Focus Area)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

AF-C Area Display



You can set whether or not to display the area that is in focus when [Focus Area] is set to [Wide] or [Zone], in [Continuous AF] mode.



 $\text{MENU} \to \text{ AF}_{\text{MF}} \text{ (Focus)} \to \text{[Focus Area]} \to \text{[AF-C Area Display]} \to \text{desired setting}.$

Menu item details

On:

Displays the focus area that is in focus.

Off:

Does not display the focus area that is in focus.

Note

- When [☐ Focus Area] is set to one of the following, the focusing frames in the area that is in focus turn green:
 - [Center Fix]
 - [Spot]
 - [Expand Spot]

Related Topic

Selecting the focus area (Focus Area)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Phase Detect. Area



Sets whether or not to display the Phase Detection AF area.



 $\text{MENU} \to \ ^{\text{AF}}_{\text{MF}} \ (\text{Focus}) \to [\text{Focus Area}] \to [\text{Phase Detect. Area}] \to \text{desired setting}.$

Menu item details

On:

Displays the Phase Detection AF area.

Off:

Does not display the Phase Detection AF area.

Note

- Phase Detection AF is available only with compatible lenses. If an incompatible lens is attached, you will be unable to use Phase Detection AF. Phase Detection AF may not operate even with some compatible lens, such as lenses purchased in the past that have not been updated. For details on compatible lenses, visit the Sony web site in your area, or consult your Sony dealer or local authorized Sony service facility.
- When shooting images using a full-frame-size-compatible lens, the Phase Detection AF area will not be displayed even if [Phase Detect. Area] is set to [On].
- When recording movies, the Phase Detection AF area will not be displayed.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

AF Tracking Sensitivity



You can select the AF track sensitivity when the subject goes out of focus in still image mode.



 $MENU \rightarrow {}^{AF}_{MF}$ (Focus) \rightarrow [AF/MF] \rightarrow [AF Tracking Sensitivity] \rightarrow desired setting.

Menu item details

5(Responsive)/4/3(Standard)/2/1(Locked on):

Select [5(Responsive)] to focus responsively on subjects at different distances.

Select [1(Locked on)] to keep the focus on a specific subject when other things are crossing in front of the subject.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

AF Transition Speed



Sets the speed at which the focus position is moved when the target of the auto focus is switched during movie shooting.



 $MENU \rightarrow {}^{AF}_{MF}$ (Focus) \rightarrow [AF/MF] \rightarrow [AF Transition Speed] \rightarrow desired setting.

Menu item details

7 (Fast)/6/5/4/3/2/1 (Slow):

Select a faster value to focus on the subject more quickly.

Select a slower value to focus on the subject more smoothly.

Hint

You can use the touch focus function to intentionally transition the AF.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

AF Subj. Shift Sensitivity



Sets the sensitivity with which the focus switches to another subject when the original subject leaves the focus area during movie shooting.



 $\text{MENU} \to \ ^{\text{AF}}_{\text{MF}} \ \ (\text{Focus}) \to [\text{AF/MF}] \to [\text{AF Subj. Shift Sensitivity}] \to \text{desired setting}.$

Menu item details

5(Responsive)/4/3/2/1(Locked on):

Select a higher value when you want to shoot a quick-moving subject, or when you want to shoot multiple subjects while switching the focus continually.

Select a lower value when you want the focus to remain steady, or when you want to keep the focus on a particular target without being affected by other subjects.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

AF/MF Selector



You can easily switch the focusing mode from auto to manual and vice versa while shooting without changing your holding position.



MENU \rightarrow \leftarrow (Setup) \rightarrow [Operation Customize] \rightarrow [\leftarrow Custom Key Setting] or [\leftarrow Custom Key Setting] \rightarrow desired button \rightarrow [AF/MF Selector Hold] or [AF/MF Selector Toggle].

Menu item details

AF/MF Selector Hold:

Switches the focusing mode while the button is held down.

AF/MF Selector Toggle:

Switches the focusing mode until the button is pressed again.

Note

You cannot set the [AF/MF Selector Hold] function to [Left Button], [Right Button] or [Down Button] of the control wheel.

Related Topic

Assigning frequently used functions to buttons (Custom Key Setting)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

AF w/ Shutter



Selects whether to focus automatically when you press the shutter button halfway down. Select [Off] to adjust the focus and the exposure separately.



 $\text{MENU} \rightarrow \text{ AF}_{\text{MF}} \text{ (Focus)} \rightarrow \text{[AF/MF]} \rightarrow \text{[AF w/ Shutter]} \rightarrow \text{desired setting.}$

Menu item details

On:

The auto focus operates when you press the shutter button halfway down.

Off:

The auto focus does not operate even if you press the shutter button halfway down.

Useful method to micro-adjust the focus

When an A-mount lens is attached, activating the auto focus function with a button other than the shutter button lets you focus more precisely in combination with manual focusing.

- 1. Set [AF w/ Shutter] to [Off].
- 3. Press the AF-ON button to focus.
- **4.** Press the key to which the [Focus Magnifier] function is assigned, and then rotate the focus ring for microadjustments of the focus.
- 5. Press the shutter button fully down to shoot the image.

Related Topic

- AF On
- Focus Magnifier
- Pre-AF

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

AF On

You can focus without pressing the shutter button halfway down. The settings for the focus mode dial will be applied.



Press the AF-ON (AF On) button while shooting.

When shooting a movie, you can perform auto-focusing while holding down the AF-ON button even in the manual focusing mode.

Hint

- Set [AF w/ Shutter] to [Off] when you do not want to perform auto focusing using the shutter button.
- Set [AF w/ Shutter] and [Pre-AF] to [Off] to focus at a specific shooting distance predicting the position of the subject.

Related Topic

- AF w/ Shutter
- Pre-AF

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Focus Hold



Locks the focus while the key to which the Focus Hold function has been assigned is pressed.

- MENU → (Setup) → [Operation Customize] → [Custom Key Setting] or [Custom Key Setting] → assign the [Focus Hold] function to the desired key.
- Focus and press the key to which the [Focus Hold] function has been assigned.
- 3 Press the shutter button while holding down the key.

Related Topic

Assigning frequently used functions to buttons (Custom Key Setting)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Pre-AF



The product automatically adjusts focus before you press the shutter button halfway down.



 $\text{MENU} \to {}^{\text{AF}}_{\text{MF}} \text{ (Focus)} \to [\text{AF/MF}] \to [\text{Pre-AF}] \to \text{desired setting}.$

Menu item details

On:

Adjusts focus before you press the shutter button halfway down.

Off:

Does not adjust focus before you press the shutter button halfway down.

Note

- [Pre-AF] is available only when an E-mount lens is mounted.
- During focusing operations, the screen may shake.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Priority Set in AF-S



Sets whether or not to release the shutter even if the subject is not in focus when the focus mode dial is set to AF-S (Single-shot AF) or DMF (direct manual focus) and the subject is remaining still.



 $\text{MENU} \to \ ^{\text{AF}}_{\text{MF}} \ (\text{Focus}) \to [\text{AF/MF}] \to [\text{Priority Set in AF-S}] \to \text{desired setting}.$

Menu item details

AF:

Prioritizes focusing. The shutter will not be released until the subject is in focus.

Release:

Prioritizes the shutter's release. The shutter will be released even if the subject is out of focus.

Balanced Emphasis:

Shoots with a balanced emphasis on both focusing and shutter release.

Related Topic

- Selecting the focus method (Focus Mode)
- Priority Set in AF-C

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Priority Set in AF-C



Sets whether to release the shutter even if the subject is not in focus when the continuous AF is activated and the subject is in motion.



 $\text{MENU} \to \ ^{\text{AF}}_{\text{MF}} \ \ (\text{Focus}) \to [\text{AF/MF}] \to [\text{Priority Set in AF-C}] \to \text{desired setting}.$

Menu item details

AF:

Prioritizes focusing.

Release:

Prioritizes the shutter's release. The shutter will be released even if the subject is out of focus.

Balanced Emphasis:

Shoots with a balanced emphasis on both focusing and shutter release.

Related Topic

- Selecting the focus method (Focus Mode)
- Priority Set in AF-S

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

AF in Focus Mag.



You can focus on the subject more accurately using auto-focus by magnifying the area where you want to focus. While the magnified image is displayed, you can focus on a smaller area than [Spot] under [Focus Area].

- **2** MENU \rightarrow AF_{MF} (Focus) \rightarrow [Focus Assistant] \rightarrow [Focus Magnifier].
- Magnify the image by pressing the center of the multi-selector, and then adjust the position by pressing the multi-selector up/down/left/right.
 - The magnification scale changes each time you press the center.
- Press the shutter button halfway down to focus.
 - The focus will be achieved at point of + (plus mark) in the center of the screen.
- 5 Press the shutter button all the way down to shoot.
 - The camera exits the magnified display after shooting.

Hint

- Use of a tripod is recommended to accurately identify the location you want to magnify.
- You can check the auto-focusing result by magnifying the displayed image. If you want to readjust the focus position, adjust the focus area on the magnified screen and then press the shutter button halfway down.

Note

- If you enlarge an area at the edge of the screen, the camera may not be able to focus.
- The exposure and white balance cannot be adjusted while the displayed image is being magnified.
- [AF in Focus Mag.] is unavailable in the following situations:
 - During movie shooting
 - When the focus mode is set to [Continuous AF]
 - When using a Mount Adaptor (sold separately).
- While the displayed image is being magnified, the following functions are unavailable:
 - [Eye AF]
 - [Pre-AF]
 - [☐ Face/Eye Prior. in AF]

Related Topic

Focus Magnifier

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

AF Illuminator



The AF illuminator supplies fill light to focus more easily on a subject in dark surroundings. In the time between pressing the shutter button halfway down and locking the focus, the AF illuminator lights up to allow the camera to focus easily. If a flash with an AF illuminator function is attached to the Multi Interface Shoe, when the flash is turned on, the AF illuminator of the flash will turn on as well.



 $\text{MENU} \rightarrow \text{ AF}_{\text{MF}} \text{ (Focus)} \rightarrow \text{[AF/MF]} \rightarrow \text{[AF Illuminator]} \rightarrow \text{desired setting}.$

Menu item details

Auto:

The AF illuminator lights up automatically in dark surroundings.

Off:

Does not use the AF illuminator.

Note

- You cannot use [AF Illuminator] in the following situations:
 - When the shooting mode is [Movie] or [S&Q Motion].
 - When the focus mode is set to [Continuous AF].
 - When [Focus Magnifier] is activated.
 - When a Mount Adaptor is attached.
- The AF illuminator emits a very bright light. Although there is no health hazard, do not look directly into the AF illuminator at close range.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Aperture Drive in AF



Changes the aperture drive system to prioritize the auto-focusing tracking performance or to prioritize silence.



 $\text{MENU} \to \ ^{\text{AF}}_{\text{MF}} \ \ (\text{Focus}) \to [\text{AF/MF}] \to [\text{Aperture Drive in AF}] \to \text{desired setting}.$

Menu item details

Focus Priority:

Changes the aperture drive system to prioritize auto-focusing performance.

Standard:

Uses the standard aperture drive system.

Silent Priority:

Changes the aperture drive system to prioritize silence so that the sound from the aperture drive is quieter than in [Standard].

Note

- When [Focus Priority] is selected, sound from the aperture drive may be audible, or the aperture effect may not be visible on the monitor. Also, the continuous shooting speed may become slower or the screen may flicker. To avoid these phenomena, change the setting to [Standard].
- When [Silent Priority] is selected, the focusing speed may become slower, and it may be more difficult to focus on a subject.
- Focus during continuous shooting is locked to the setting of the first shot when the parameter for [Aperture Drive in AF] is set to [Standard] or [Silent Priority], and the F-value is greater than F22.
- The effect may differ depending on the lens you use and the shooting conditions.

Related Topic

Silent Mode Settings (still image/movie)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Manual Focus



When it is difficult to focus properly in the autofocus mode, you can adjust the focus manually.

- Turn the focus mode dial while pressing the focus mode dial lock release button and select MF.
- When you shoot a still image, you can display the focus distance on the screen by rotating the focusing ring.
 The focus distance is not displayed when the Mount Adaptor (sold separately) is attached.

Note

- When you use the viewfinder, adjust the diopter level to obtain the correct focus on the viewfinder.
- The displayed focus distance is just a reference.

Rotate the focusing ring to achieve sharp focus.

Related Topic

- Using the focus mode dial
- Direct manual focus (DMF)
- Auto Magnifier in MF
- Focus Magnifier
- Peaking Display

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Direct manual focus (DMF)



You can make fine adjustments manually after performing auto focusing, letting you focus on a subject more quickly than when using the manual focus from the beginning. This is convenient in situations such as macro shooting.

- 1 Turn the focus mode dial while pressing the focus mode dial lock release button and select DMF.
- Press the shutter button halfway down to focus automatically.
- 3 Keep the shutter button pressed halfway down, and then rotate the focusing ring to achieve a sharper focus.
 - When you rotate the focusing ring, the focus distance is displayed on the screen.
 The focus distance is not displayed when the Mount Adaptor (sold separately) is attached.
- 4 Press the shutter button fully down to shoot an image.

Related Topic

- Using the focus mode dial
- Manual Focus
- Peaking Display

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Auto Magnifier in MF



Enlarges the image on the screen automatically to make manual focusing easier. This works in Manual Focus or Direct Manual Focus shooting.

- 1
- $\text{MENU} \to \ ^{\text{AF}}_{\text{MF}} \ \ \text{(Focus)} \to \text{[Focus Assistant]} \to \text{[Auto Magnifier in MF]} \to \text{[On]}.$
- 2
 - Turn the focus ring to adjust the focus.
 - The image is enlarged. You can magnify images further by pressing the center of the control wheel.

Hint

• You can set how long the image is to be shown magnified by selecting MENU \rightarrow AF_{MF} (Focus) \rightarrow [Focus Assistant] \rightarrow [Focus Magnif. Time].

Note

- You cannot use [Auto Magnifier in MF] when shooting movies. Use the [Focus Magnifier] function instead.
- [Auto Magnifier in MF] is not available when a Mount Adaptor is attached. Use the [Focus Magnifier] function instead.

Related Topic

- Manual Focus
- Direct manual focus (DMF)
- Focus Magnif. Time (still image/movie)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Focus Magnifier



You can check the focus by enlarging the image before shooting.

Unlike with [Auto Magnifier in MF], you can magnify the image without operating the focus ring.

- Press the center of the multi-selector to enlarge the image and select the area you want to enlarge by pressing the multi-selector up/down/left/right.
 - Each time you press the center, the magnification scale will change.
 - You can set the initial magnification by selecting MENU → AFMF (Focus) → [Focus Assistant] → [Initial Focus Mag.] or [Initial Focus Mag.].
- Confirm the focus.
 - Press the (Delete) button to bring the magnified position into the center of an image.
 - When the focus mode is [Manual Focus], you can adjust the focus while an image is magnified. If [AF in Focus Mag.] is set to [Off], the [Focus Magnifier] function is canceled when the shutter button is pressed halfway down.
 - When the shutter button is pressed halfway down while an image is magnified during the auto-focusing, different functions are performed depending on the [AF in Focus Mag.] setting.
 - When [AF in Focus Mag.] is set to [On]: Auto-focusing is performed again.
 - When [AF in Focus Mag.] is set to [Off]: The [Focus Magnifier] function is canceled.
 - You can set how long the image is to be shown magnified by selecting MENU → ^{AF}_{MF} (Focus) → [Focus Assistant] → [□ Focus Magnif. Time].
- Press the shutter button fully down to shoot the image.

To use the focus magnifier function by touch operation

You can magnify the image and adjust the focus by touching the monitor. Set [Touch Operation] to [On] beforehand. Then, select the appropriate settings under [Touch Panel/Pad]. When the focus mode is [Manual Focus], you can perform [Focus Magnifier] by double-tapping the area to focus on while shooting with the monitor.

While shooting with the viewfinder, a frame is displayed in the center of the monitor by double-tapping and you can move the frame by dragging it. The image is magnified by pressing the center of the multi-selector.

Hint

- While using the focus magnifier function, you can move the magnified area by dragging it on the touch panel.
- To exit the focus magnifier function, double-tap the monitor again. When [AF in Focus Mag.] is set to [Off], the focus magnifier function is ended by pressing the shutter button halfway down.

- Auto Magnifier in MF
- Focus Magnif. Time (still image/movie)
- Initial Focus Mag. (still image)
- Initial Focus Mag. (movie)
- AF in Focus Mag.
- Touch Operation

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Focus Magnif. Time (still image/movie)



Set the duration for which an image is to be magnified using the [Auto Magnifier in MF] or [Focus Magnifier] function.



 $MENU \rightarrow {}^{AF}_{MF}$ (Focus) \rightarrow [Focus Assistant] \rightarrow [Figure 1] Focus Magnif. Time] \rightarrow desired setting.

Menu item details

2 Sec:

Magnifies the images for 2 seconds.

5 Sec:

Magnifies the images for 5 seconds.

No Limit:

Magnifies the images until you press the shutter button.

Related Topic

- Auto Magnifier in MF
- Focus Magnifier

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Initial Focus Mag. (still image)



Sets the initial magnification scale when using [Focus Magnifier]. Select a setting that will help you frame your shot.



 $MENU \rightarrow {}^{AF}_{MF}$ (Focus) \rightarrow [Focus Assistant] \rightarrow [[Initial Focus Mag.] \rightarrow desired setting.

Menu item details

Full-frame shooting

x1.0:

Displays the image with the same magnification as the shooting screen.

x4 2.

Displays a 4.2-times enlarged image.

APS-C/Super 35mm size shooting

x1.0:

Displays the image with the same magnification as the shooting screen.

x2.7:

Displays a 2.7-times enlarged image.

Related Topic

Focus Magnifier

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Initial Focus Mag. (movie)



Sets the initial magnification scale for [Focus Magnifier] in the movie shooting mode.



Menu item details

x1.0:

Displays the image with the same magnification as the shooting screen.

x4.0:

Displays a 4.0-times enlarged image.

Related Topic

Focus Magnifier

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Peaking Display



Sets the peaking function, which enhances the outline of in-focus areas during shooting with Manual Focus or Direct Manual Focus.



 $MENU \rightarrow AF_{MF}$ (Focus) \rightarrow [Peaking Display] \rightarrow Select a menu item and set the desired parameter.

Menu item details

Peaking Display:

Sets whether to display peaking. ([On] / [Off])

Peaking Level:

Sets the level of enhancement of in-focus areas. ([High] / [Mid] / [Low])

Peaking Color:

Sets the color used to enhance in-focus areas. ([Red] / [Yellow] / [Blue] / [White])

Note

- Since the product recognizes sharp areas as in focus, the effect of peaking differs, depending on the subject and lens.
- The outline of in-focus ranges is not enhanced on devices connected via HDMI.

Related Topic

- Manual Focus
- Direct manual focus (DMF)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Exposure Comp. (still image/movie)



Normally, exposure is set automatically (auto exposure). Based on the exposure value set by auto exposure, you can make the entire image brighter or darker if you adjust [Exposure Comp.] to the plus side or minus side, respectively (exposure compensation).

Release the exposure compensation dial lock, and turn the exposure compensation dial.
+ (over) side:


Images become brighter.

- (under) side:


Images become darker.

- Pressing the lock button at the center switches the exposure compensation dial between the locked and unlocked status. The dial is unlocked when the lock button is popped up and the white line is visible.
- You can adjust the exposure compensation value within the range of -3.0 EV to +3.0 EV.
- You can confirm the exposure compensation value that you set on the shooting screen.

Monitor



Viewfinder



To set the exposure compensation value using the MENU

You can adjust the exposure compensation value within a range of -5.0 EV to +5.0 EV when the exposure compensation dial is set to "0."

 $MENU \rightarrow$ [Exposure Comp.] \rightarrow [Exposure Comp.] \rightarrow [Exposure Comp.] \rightarrow desired setting.

Hint

- You can operate the exposure compensation dial any time you want while the exposure compensation dial lock is released. The exposure compensation dial lock prevents unintentional changes to exposure compensation values.
- The settings of the exposure compensation dial will be prioritized over [☐ Exposure Comp.] or [Dial Ev Comp] in MENU.
- Only a value between -3.0 EV and +3.0 EV with the equivalent image brightness appears on the screen when shooting. If you set an exposure compensation value outside this range, the image brightness on the screen will not be affected, but the value will be reflected in the recorded image.
- You can adjust the exposure compensation value within the range of -2.0 EV to +2.0 EV for movies.

Note

- You cannot perform the exposure compensation in the following shooting modes:
 - [Intelligent Auto]
- When using [Manual Exposure], you can perform the exposure compensation only when [☐ ISO] is set to [ISO AUTO].
- If you shoot a subject in extremely bright or dark conditions, or when you use the flash, you may not be able to get a satisfactory effect
- When you set the exposure compensation dial to "0" from a setting other than "0," the exposure value switches to "0" regardless of the [☐ Exposure Comp.] setting.

Related Topic

- Exposure step (still image/movie)
- Dial Ev Comp
- Exp.comp.set
- Bracket Settings: Cont. Bracket
- Bracket Settings: Single Bracket
- Zebra Display

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Histogram display

A histogram shows the luminance distribution, displaying how many pixels there are by luminance. To display the histogram on the shooting screen or playback screen, press the DISP (Display Setting) button repeatedly.

How to read the histogram

The histogram indicates darker values toward the left and brighter values toward the right.

The histogram changes depending on the exposure compensation.

A peak at the right or left end of the histogram indicates that the image has an overexposed or underexposed area, respectively. You cannot correct such defects using a computer after shooting. Perform exposure compensation before shooting as necessary.



(A): Pixel count(B): Brightness

Note

- The information in the histogram display does not indicate the final photograph. It is information about image displayed on the screen. The final result depends on the aperture value, etc.
- The histogram display is extremely different between shooting and playback in the following cases:
 - When the flash is used
 - When shooting a low luminance subject such as a night scene

Related Topic

- Using the DISP (Display Setting) button
- Exposure Comp. (still image/movie)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Reset EV Comp. (still image/movie)



Sets whether to maintain the exposure value set using [Exposure Comp.] when you turn off the power when the exposure compensation dial position is set to "0."



 $\textbf{MENU} \rightarrow \ \ \, \textbf{[Exposure/Color)} \rightarrow \ \ \, \textbf{[Exposure Comp.]} \rightarrow \ \ \, \textbf{[Parker EV Comp.]} \rightarrow \ \ \, \textbf{desired setting.}$

Menu item details

Maintain:

Maintains the settings.

Reset:

Resets the settings.

Related Topic

Exposure Comp. (still image/movie)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Exposure step (still image/movie)



You can adjust the setting increment for the shutter speed, aperture, and exposure compensation values.



Menu item details

0.5EV / 0.3EV

Note

• Even if you set [Exposure step] to [0.5EV], the exposure value adjusted using the exposure compensation dial changes in steps of 0.3EV.

Related Topic

Exposure Comp. (still image/movie)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Exposure Std. Adjust (still image/movie)



Adjusts this camera's standard for the correct exposure value for each metering mode.

- MENU → 【 (Exposure/Color) → [Exposure Comp.] → [☐ Exposure Std. Adjust] → desired metering mode.
- Select the desired value as the metering standard.
 - You can set a value from -1 EV to +1 EV in 1/6 EV increments.

Metering Mode

The set standard value will be applied when you select the corresponding metering mode in MENU \rightarrow [Exposure/Color) \rightarrow [Metering] \rightarrow [Metering Mode].

Multi/ Center/ Spot/ Entire Screen Average/ Highlight

Note

- The exposure compensation will not be affected when [Exposure Std. Adjust] is changed.
- The exposure value will be locked according to the value set for [Spot] during using spot AEL.
- The standard value for M.M (Metered Manual) will be changed according to the value set in [Exposure Std. Adjust].
- The value set in [Exposure Std. Adjust] is recorded in Exif data separately from the exposure compensation value. The amount of exposure standard value will not be added to the exposure compensation value.
- If you set [Exposure Std. Adjust] during bracketing shooting, the number of shots for the bracketing will be reset.

Related Topic

Metering Mode (still image/movie)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Dial Ev Comp




You can adjust the exposure using the front dial or rear dial when the exposure compensation dial is set to "0." You can adjust the exposure in a range of -5.0 EV to +5.0 EV.

- 1 Set the exposure compensation dial to "0."
- igoplus 2 MENU ightarrow (Setup) ightarrow [Dial Customize] ightarrow [Dial Ev Comp] ightarrow desired setting.

Menu item details

Off:

Does not enable exposure compensation with the front or rear dial.



Enables exposure compensation with the front or rear dial.

Note

- When the exposure compensation function is assigned to the front or rear dial, any function that had been assigned to that dial previously is re-assigned to another dial.
- The settings of the exposure compensation dial will be prioritized over [Exposure Comp.] in MENU or the exposure settings using the front or rear dial.

Related Topic

Exposure Comp. (still image/movie)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

D-Range Optimizer (still image/movie)



By dividing the image into small areas, the product analyzes the contrast of light and shadow between the subject and the background, and creates an image with the optimal brightness and gradation.



Menu item details

Off:

Does not adjust brightness and gradation.

D-Range Optimizer:

If you select [D-Range Optimizer: Auto], the camera will automatically adjust the brightness and gradation. To optimize the gradation of a recorded image by individual areas, select an optimization level from [D-Range Optimizer: Lv1] (weak) to [D-Range Optimizer: Lv5] (strong).

Note

- In the following situations, [D-Range Optimizer] is fixed to [Off]:
 - When [☐ Picture Profile] is set to other than [Off]
- When shooting with [D-Range Optimizer], the image may be noisy. Select the proper level by checking the recorded image, especially when you enhance the effect.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Metering Mode (still image/movie)



Selects the metering mode that sets which part of the screen to measure for determining the exposure.



Menu item details

Multi:

Measures light on each area after dividing the total area into multiple areas and determines the proper exposure of the entire screen (Multi-pattern metering).

(e) Center:

Measures the average brightness of the entire screen, while emphasizing the central area of the screen (Center-weighted metering).

Spot:

Measures only inside the metering circle. This mode is suitable for measuring light on a specified part of the entire screen. The size of the metering circle can be selected from [Spot: Standard] and [Spot: Large]. The position of the metering circle depends the setting for [Spot Metering Point].

Entire Screen Avg.:

Measures the average brightness of the entire screen. The exposure will be stable even if the composition or the position of the subject changes.

To Highlight:

Measures the brightness while emphasizing the highlighted area on the screen. This mode is suitable for shooting the subject while avoiding overexposure.

Hint

- The spot metering point can be coordinated with the focus area by using [Focus Point Link].
- When [Multi] is selected and [Face Priority in Multi Metering] is set to [On], the camera measures brightness based on detected faces.
- When [Metering Mode] is set to [Highlight] and the [D-Range Optimizer] function is activated, the brightness and the contrast will be corrected automatically by dividing the image into small areas and analyzing the contrast of light and shadow. Make settings based on the shooting circumstances.

Note

- Metering Mode] is locked to [Multi] in the following shooting situations:
 - [Intelligent Auto]
 - When using a zoom function other than the optical zoom
- In [Highlight] mode, the subject may be dark if a brighter part exists on the screen.

Related Topic

- AE lock
- Spot Metering Point (still image/movie)

- Face Priority in Multi Metering (still image/movie)
- D-Range Optimizer (still image/movie)


Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Face Priority in Multi Metering (still image/movie)



Sets whether the camera measures brightness based on detected faces when [A Metering Mode] is set to [Multi].



Menu item details

On:

The camera measures brightness based on detected faces.

Off:

The camera measures brightness using the [Multi] setting, without detecting faces.

Note

- When the shooting mode is set to [Intelligent Auto], [Face Priority in Multi Metering] is locked to [On].
- When [☐ Face/Eye Prior. in AF] is set to [On] and [☐ Face/Eye Subject] is set to [Animal] or [Bird] under [Face/Eye AF], [☐ Face Priority in Multi Metering] does not work.

Related Topic

Metering Mode (still image/movie)

Help Guide


Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Spot Metering Point (still image/movie)



Sets whether to coordinate the spot metering position with the focus area when [Focus Area] is set to the following parameters:

- [Spot: S]/[Spot: M]/[Spot: L]
- [Expand Spot]
- [Tracking: Spot S]/[Tracking: Spot M]/[Tracking: Spot L]
- [Tracking: Expand Spot]



Menu item details

Center:

The spot metering position does not coordinate with the focus area, but always meters brightness at the center.

Focus Point Link:

The spot metering position coordinates with the focus area.

Note

- Even if the spot metering position is coordinated with the [Tracking] start position, it will not be coordinated with the tracking of the subject.
- When [☐ Focus Area] is set to the following parameters, the spot metering position is locked to the center.
 - [Wide]
 - [Zone]
 - [Center Fix]
 - [Tracking: Wide]/[Tracking: Zone]/[Tracking: Center Fix]

Related Topic

- Selecting the focus area (Focus Area)
- Metering Mode (still image/movie)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

AE lock

When the contrast between the subject and background is high, such as when shooting a backlit subject or a subject near a window, meter the light at a spot where the subject appears to have the appropriate brightness and lock the exposure before shooting. To reduce the brightness of the subject, meter the light at a spot brighter than the subject and lock the exposure of the entire screen. To make the subject brighter, meter the light at a spot darker than the subject and lock the exposure of the entire screen.

- Adjust the focus on the spot at which the exposure is adjusted.
- Press the AEL button.

 The exposure is locked, and ★ (AE lock) is displayed.
- 3 Keep pressing the AEL button and focus on the subject again, then shoot the picture.
 - Keep holding the AEL button down while taking a shot if you want to continue shooting with the fixed exposure.
 Release the button to reset the exposure.

Hint

If you assign the [AEL toggle] function to the AEL button using [Custom Key Setting] or [Custom Key Setting], you can lock the exposure without holding down the button.

Note

• [• AEL hold] and [• AEL toggle] are not available when using zoom functions other than optical zoom.

Related Topic

- Using the AEL button
- Assigning frequently used functions to buttons (Custom Key Setting)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

AEL w/ Shutter



Sets whether to fix the exposure when you press the shutter button halfway down. Select [Off] to adjust the focus and the exposure separately.



Menu item details

Auto:

Locks the exposure after you adjust the focus automatically by pressing the shutter button halfway down when the focus mode dial is set to AF-S (Single-shot AF).

On:

Fixes the exposure when you press the shutter button halfway down.

Off:

Does not fix the exposure when you press the shutter button halfway down. Use this mode when you want to adjust focus and exposure separately.

The product keeps adjusting the exposure while shooting in [Cont. Shooting] mode.

Note

Operation using the AEL button is prioritized over the [AEL w/ Shutter] settings.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Zebra Display



Sets a zebra pattern, which appears over part of an image if the brightness level of that part meets the IRE level that you have set. Use this zebra pattern as a guide to adjust the brightness.



 $\textbf{MENU} \rightarrow \textbf{ [Zebra Display]} \rightarrow \textbf{Select a menu item and set the desired parameter}.$

Menu item details



Sets whether to display the zebra pattern. ([Off] / [On])



Adjusts the brightness level of the zebra pattern. ([70] / [75] / [80] / [85] / [90]/ [95] / [100] / [100+])

Hint

- You can register values to check the correct exposure or overexposure as well as the brightness level for [Zebra Level]. The settings for correct exposure confirmation and overexposure confirmation are registered to [Custom 1] and [Custom 2] respectively in the default settings.
- To check the correct exposure, set a standard value and the range for the brightness level. The zebra pattern will appear on areas that fall within the range you set.
- To check the overexposure, set a minimum value for the brightness level. The zebra pattern will appear over areas with a brightness level equal to or higher than the value you set.

Note

The zebra pattern is not displayed on devices connected via HDMI.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

ISO (still image/movie)



Sensitivity to light is expressed by the ISO number (recommended exposure index). The larger the number, the higher the sensitivity.



ISO on the control wheel \rightarrow select desired setting.

- You can also select MENU \rightarrow **[** (Exposure/Color) \rightarrow [Exposure] \rightarrow [\rightarrow [ISO].
- You can change the value by 1/3 EV steps by turning the front dial as well as by turning the control wheel. You
 can change the value by 1 EV steps by turning the rear dial.

Menu item details

ISO AUTO:

Sets the ISO sensitivity automatically.

ISO 50 - ISO 102400:

Sets the ISO sensitivity manually. Selecting a larger number increases the ISO sensitivity.

Hint

- You can change the range of ISO sensitivity that is set automatically in [ISO AUTO] mode. Select [ISO AUTO] and press the right side of the control wheel, and set the desired values for [ISO AUTO Maximum] and [ISO AUTO Minimum].
- The higher the ISO value, the more noise will appear on the images.
- The available ISO settings will differ depending on whether you are shooting still images, shooting movies, or shooting slow-motion/quick-motion movies.
- When shooting movies, ISO values between 100 and 32000 are available. If the ISO value is set to a value larger than 32000, the setting is automatically switched to 32000. When you finish recording the movie, the ISO value returns to the original setting.
- When shooting movies, ISO values between 100 and 32000 are available. If the ISO value is set to a value smaller than 100, the setting is automatically switched to 100. When you finish recording the movie, the ISO value returns to the original setting.
- The available range for ISO sensitivity varies depending on the setting for [Gamma] under [Picture Profile].
- The available ISO sensitivity range changes when outputting RAW movies to another device connected via HDMI.

Note

- [ISO] is set to [ISO AUTO] in the following shooting modes:
 - [Intelligent Auto]
- When the ISO sensitivity is set to a value lower than ISO 100, the range for recordable subject brightness (dynamic range) may decrease
- When you select [ISO AUTO] with the shooting mode set to [P], [A], [S] or [M], the ISO sensitivity will be automatically adjusted within the set range.
- If you point the camera at an extremely strong light source while shooting images with a low ISO sensitivity, highlighted areas in the images may be recorded as black areas.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

ISO Range Limit (still image/movie)



You can limit the range of ISO sensitivity when the ISO sensitivity is set manually.



To set the range for [ISO AUTO]

If you want to adjust the range of ISO sensitivity that is automatically set in the [ISO AUTO] mode, select MENU \rightarrow [Exposure/Color) \rightarrow [Exposure] \rightarrow [\rightarrow [ISO AUTO], and then press the right side of the control wheel to select [ISO AUTO Maximum]/[ISO AUTO Minimum].

Note

- ISO sensitivity values beyond the specified range become unavailable. To select ISO sensitivity values beyond the specified range, reset [| ISO Range Limit].
- The available range for ISO sensitivity varies depending on the setting for [Gamma] under [☐ Picture Profile].

Related Topic

ISO (still image/movie)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

ISO AUTO Min. SS



If you select [ISO AUTO] when the shooting mode is P (Program Auto) or A (Aperture Priority), you can set the shutter speed at which the ISO sensitivity starts changing.

This function is effective for shooting moving subjects. You can minimize subject blurring while also preventing camera shake.



Menu item details

SLOWER (Slower)/SLOW (Slow):

The ISO sensitivity will start to change at shutter speeds slower than [Standard], so you can shoot images with less noise.

STD (Standard):

The camera automatically sets the shutter speed based on the focal length of the lens.

FAST (Fast)/FASTER (Faster):

The ISO sensitivity will start to change at shutter speeds faster than [Standard], so you can prevent camera shake and subject blurring.

1/16000 - 30":

The ISO sensitivity starts to change at the shutter speed you have set.

Hint

The difference in shutter speed at which ISO sensitivity starts to change between [Slower], [Slow], [Standard], [Fast], and [Faster] is 1 EV.

Note

- If the exposure is insufficient even when the ISO sensitivity is set to [ISO AUTO Maximum] in [ISO AUTO], in order to shoot with an appropriate exposure, the shutter speed will be slower than the speed set in [ISO AUTO Min. SS].
- In the following situations, the shutter speed may not function as set:
 - When the maximum shutter speed has changed based on the [Shutter Type] setting.
 - When using the flash to shoot bright scenes with [Shutter Type] set to [Electronic Shutter] (The maximum shutter speed is limited to the flash sync speed*.)
 - * The flash sync speed varies according to the setting for [Flash Sync Spd. Prty.].
 - When using the flash to shoot dark scenes with the [Flash Mode] set to [Fill-flash]. (The minimum shutter speed is limited to the speed automatically determined by the camera.)

Related Topic

- Program Auto
- Aperture Priority
- ISO (still image/movie)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

White Balance (still image/movie)



Corrects the tone effect of the ambient light condition to record a neutral white subject in white. Use this function when the color tones of the image did not come out as you expected, or when you want to change the color tones on purpose for photographic expression.



 $MENU \rightarrow$ [White Balance] \rightarrow [White Balance] \rightarrow desired setting.

Menu item details

AWB Auto / AWB Auto: Ambience / AWB Auto: White / 崇 Daylight / 合 Shade / Cloudy / 小 Cloudy / 小 Cloudy / 小 Fluor.: Warm White / 崇 Fluor.: Cool White / 崇 Fluor.: Day White / 崇 Fluor.: Daylight / 肾 Flash / Underwater Auto:

When you select a light source that illuminates the subject, the product adjusts the color tones to suit to the selected light source (preset white balance). When you select [Auto], the product automatically detects the light source and adjusts the color tones.

C.Temp./Filter:

Adjusts the color tones depending on the light source. Achieves the effect of CC (Color Compensation) filters for photography.

Custom 1/Custom 2/Custom 3:

Memorizes the basic white color under the light conditions for the shooting environment.

Hint

- You can display the fine adjustment screen and perform fine adjustments of the color tones as required by pressing the right side of the control wheel. When [C.Temp./Filter] is selected, you can change the color temperature by turning the rear dial instead of pressing the right side of the control wheel.
- If the color tones do not come out as you expected in the selected settings, perform [WB bracket] shooting.
- AWB. (Auto: Ambience), AWB. (Auto: White) is displayed only when [🖳 Priority Set in AWB] is set to [Ambience] or [White].
- If you want to moderate abrupt white balance switching, such as when the recording environment switches during movie recording, you can change the white balance switching speed with the [Shockless WB] function.

Note

- White Balance] is fixed to [Auto] in the following shooting modes:
 - [Intelligent Auto]
- If you use a mercury lamp or a sodium lamp as a light source, the accurate white balance will not be obtained because of the characteristics of the light. It is recommended to shoot images using a flash or select [Custom 1] to [Custom 3].
- Do not cover the visible light and IR sensor when [White Balance] is set to [Auto]. If you do so, the light source may be erroneously classified, and the white balance may be adjusted to an inappropriate color.

Related Topic

Capturing a standard white color to set the white balance (custom white balance)

- Priority Set in AWB (still image/movie)
- Bracket Settings: WB bracket
- Shockless WB

Help Guide

Interchangeable Lens Digital Camera ILCE-1 q1

Capturing a standard white color to set the white balance (custom white balance)



In a scene where the ambient light consists of multiple types of light sources, it is recommended to use the custom white balance in order to accurately reproduce the whiteness. You can register 3 settings.

- MENU → (Exposure/Color) → [White Balance] → [□] White Balance] → Select from among [Custom 1] to [Custom 3], and then press the right side of the control wheel.
- Select SET (custom white balance set), and then press the center of the control wheel.
- Hold the product so that the white area fully covers the white-balance capture frame, and then press the center of the control wheel.

After the shutter sound beeps, the calibrated values (Color Temperature and Color Filter) are displayed.

- You can adjust the position of the white-balance capture frame by pressing the top/bottom/left/right side of the control wheel.
- After capturing a standard white color, you can display the fine adjustment screen by pressing the right side of the control wheel. You can finely adjust the color tones as needed.
- No shutter sound is produced in the following cases.
 - In the movie recording mode
 - When [Silent Mode] is set to [On]
 - When [Shutter Type] is set to [Electronic Shutter]
- 4 Press the center of the control wheel.

The calibrated values will be registered. The monitor returns to the MENU display while retaining the memorized custom white balance setting.

The registered custom white balance setting will remain memorized until overwritten by the another setting.

Note

- The message [Capturing of the custom WB failed.] indicates that the value is in the unexpected range, for example when the subject is too vivid. You can register the setting at this point, but it is recommended that you set the white balance again. When an error value is set, the indicator (custom white balance) turns orange on the recording information display. The indicator will be displayed in white when the set value is in the expected range.
- If you use a flash when capturing a basic white color, the custom white balance will be registered with the lighting from the flash.Be sure to use a flash whenever you shoot with recalled settings that were registered with a flash.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α1

Priority Set in AWB (still image/movie)



Selects which tone to prioritize when shooting under lighting conditions such as incandescent light when [4 White Balance] is set to [Auto].



Menu item details

AWB Standard:

Shoots with standard auto white balance. The camera automatically adjusts the color tones.

Ambience:

Prioritizes the color tone of the light source. This is suitable when you want to produce a warm atmosphere.

White White:

Prioritizes a reproduction of white color when the color temperature of the light source is low.

Related Topic

White Balance (still image/movie)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Shutter AWB Lock



You can set whether or not to lock the white balance while the shutter button is pressed when [White Balance] is set to [Auto] or [Underwater Auto].

This function prevents unintentional changes to the white balance during continuous shooting or when shooting with the shutter button pressed halfway down.



Menu item details

Shutter Half Press:

Locks the white balance while the shutter button is pressed halfway down, even in the auto white balance mode. The white balance is also locked during continuous shooting.

Cont. Shooting:

Locks the white balance to the setting in the first shot during continuous shooting, even in the auto white balance mode.

Off:

Operates with the normal auto white balance.

About [AWB Lock Hold] and [AWB Lock Toggle]

You can also lock the white balance in the auto white balance mode by assigning [AWB Lock Hold] or [AWB Lock Toggle] to the custom key. If you press the assigned key during shooting, the white balance will be locked.

The [AWB Lock Hold] function locks the white balance by stopping the automatic white balance adjustment while the button is pressed.

The [AWB Lock Toggle] function locks the white balance by stopping the automatic white balance adjustment after the button is pressed once. When you press the button again, the AWB lock is released.

• If you want to lock the white balance while recording a movie in the auto white-balance mode, also assign [AWB Lock Hold] or [AWB Lock Toggle] to the custom key.

Hint

• When you shoot with the flash while the automatic white balance is locked, the resulting color tones may be unnatural because the white balance was locked before the flash was emitted. In this case, set [Shutter AWB Lock] to [Off] or [Cont. Shooting], and do not use the [AWB Lock Hold] function or [AWB Lock Toggle] function when shooting. Alternatively, set [Flash].

Related Topic

- White Balance (still image/movie)
- Assigning frequently used functions to buttons (Custom Key Setting)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Shockless WB



Sets the speed at which the white balance switches during movie recording, such as when the setting for [White Balance] or [Priority Set in AWB] is changed.



 $\textbf{MENU} \rightarrow \ \ \textbf{[Shockless WB]} \rightarrow \textbf{desired setting}.$

Menu item details

Off:

The white balance will switch immediately if you change the white balance setting during movie recording.

1 (Fast)/2/3 (Slow):

You can select the speed at which the white balance switches during movie shooting in order to make the white balance of the movie change more smoothly.

The speed settings in the order of fastest to slowest are [1 (Fast)], [2], and [3 (Slow)].

Note

- This function does not affect the speed at which the white balance changes when [White Balance] is set to [Auto].
- Even if a setting other than [Off] is selected, the following will be immediately applied to the movie regardless of the speed setting.
 - Fine adjustments to the color tones
 - Changes to the color temperature using [C.Temp./Filter]

Related Topic

White Balance (still image/movie)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 q1


Creative Look (still image/movie)




"Looks" are presets for image creation preinstalled on the camera.

With this function, you can choose the finish of the image by selecting a "Look." In addition, you can fine-tune the contrast, highlights, shadows, fade, saturation, sharpness, sharpness range, and clarity for each "Look."

- Select the desired "Look" or [Custom Look] using the top/bottom of the control wheel.
- To adjust (Contrast), (Highlights), (Shadows), (Shadows), (Saturation), (Sharpness), (Sharpness Range) and (Clarity), move to the right using the right side of the control wheel. Select the desired item using the right/left sides, and then select the value using the top/bottom sides.



- When selecting [Custom Look], move to the right using the right side of the control wheel, and then select the desired "Look."
 - Using [Custom Look], you can recall the same "Look" presets with slightly different settings.



Menu item details

ST ST

Standard finish for a wide range of subjects and scenes.

PT[†] PT:

For capturing skin in a soft tone, ideally suited for shooting portraits.

INT NT:

The saturation and sharpness are lowered for shooting images in subdued tones. This is also suitable for capturing image material to be modified with a computer.

vv† VV:

The saturation and contrast are heightened for shooting striking images of colorful scenes and subjects such as flowers, spring greenery, blue sky, or ocean views.

₩2[†] VV2:

Creates an image with bright and vivid colors with rich clarity.

底 FL:

Creates an image with moody finish by applying sharp contrast to the calm coloring as well as the impressive sky and colors of the greens.

INT IN:

Creates an image with matte textures by suppressing the contrast and saturation.

SH SH:

Creates an image with bright, transparent, soft, and vivid mood.

BW BW:

For shooting images in black and white monotone.

ISET SE:

For shooting images in sepia monotone.

Registering preferred settings (Custom Look):

Select the six custom look (the boxes with numbers on the left side) to register preferred settings. Then select the desired settings using the right button.

You can recall the same "Look" presets with slightly different settings.

To adjust in greater detail

Based on each "Look," items such as contrast can be adjusted to your liking. You can adjust not only the preset "Looks," but also each [Custom Look], a function that allows you to register your favorite settings.

Select an item to be set by pressing the right/left sides of the control wheel, then set the value using the top/bottom sides of the control wheel.

When a setting value is changed from the default value, \clubsuit (asterisk) is added next to the "Look" icon displayed on the shooting screen.

Contrast:

The higher the value selected, the more the difference of light and shadow is accentuated, and the bigger the effect on the image. (-9 to +9)

Highlights:

Adjusts the brightness of the bright areas. When a higher value is selected, the image becomes brighter. (-9 to +9)

(\$ Shadows:

Adjusts the darkness of the dark areas. When a higher value is selected, the image becomes brighter. (-9 to +9)

(iii) Fade:

Adjusts the degree of fade. A larger value makes the effect greater. (0 to 9)

Saturation:

The higher the value selected, the more vivid the color. When a lower value is selected, the color of the image is restrained and subdued. (-9 to +9)

Sharpness:

Adjusts the sharpness. The higher the value selected, the more the contours are accentuated, and the lower the value selected, the more the contours are softened. (0 to 9)

Sharpness Range:

Adjust the range where the sharpness effect is applied. A larger value makes the sharpness effect apply to finer outlines. (1 to 5)

⚠ Clarity:

Adjusts the degree of clarity. A larger value makes the effect greater. (0 to 9)

To reset adjusted values for each "Look"

Adjusted values such as contrast that you have changed as desired can be collectively reset for each "Look." Press the (delete) button on the adjustment screen for the "Look" that you want to reset. All adjusted values that have been changed will return to their default values.

Hint

For [Sharpness], [Sharpness Range], and [Clarity], take a test shot and either enlarge and play it on the camera monitor, or output it to a playback device to check the effect. Then, readjust the setting if needed.

Note

- Creative Look] is fixed to [ST] in the following situations:
 - [Intelligent Auto]
 - [Picture Profile] is set to other than [Off].
- When this function is set to [BW] or [SE], [Saturation] cannot be adjusted.
- In the movie mode, [Sharpness Range] cannot be adjusted.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Picture Profile (still image/movie)



Allows you to change the settings for the color, gradation, etc. For details on "Picture Profile," refer to https://helpguide.sony.net/di/pp/v1/en/index.html.

Although [Picture Profile] can be used for both still images and movies, the function is designed for movies.

Customizing the picture profile

You can customize the picture quality by adjusting picture profile items such as [Gamma] and [Detail]. When setting these parameters, connect the camera to a TV or monitor, and adjust them while observing the picture on the screen.

- Move to the item index screen by pressing the right side of the control wheel.
- Select the item to change using the top/bottom sides of the control wheel.
- 4 Select the desired value using the top/bottom sides of the control wheel and press in the center.

Using the preset of the picture profile

The default settings [PP1] through [PP11] for movies have been set in advance in the camera based on various shooting conditions.

PP1:

Example setting using [Movie] gamma.

PP2:

Example setting using [Still] gamma.

PP3:

Example setting of natural color tone using the [ITU709] gamma.

PP4:

Example setting of a color tone faithful to the ITU709 standard.

PP5:

Example setting using [Cine1] gamma.

PP6:

Example setting using [Cine2] gamma.

PP7:

Example setting using [S-Log2] gamma.

PP8:

Example setting using the [S-Log3] gamma and the [S-Gamut3.Cine] under [Color Mode].

PP9:

Example setting using the [S-Log3] gamma and the [S-Gamut3] under [Color Mode].

PP10:

Example setting for recording HDR movies using [HLG2] gamma.

PP11:

Example setting using [S-Cinetone] gamma.

HDR movie recording

The camera can record HDR movies when a gamma from [HLG], [HLG1] to [HLG3] is selected in the picture profile. Picture profile preset [PP10] provides an example setting for HDR recording. Movies recorded using [PP10] can be viewed with a wider range of brightness than usual when played back on a TV supporting Hybrid Log-Gamma (HLG). This way, even scenes with a wide range of brightness can be recorded and displayed faithfully, without looking under or over-exposed. HLG is used in HDR TV program production, as defined in the international standard Recommendation ITU-R BT.2100.

Items of the picture profile

Black Level

Sets the black level. (-15 to +15)

Gamma

Selects a gamma curve.

Movie: Standard gamma curve for movies

Still: Standard gamma curve for still images

S-Cinetone: Gamma curve designed to achieve cinematic gradations and color expressions. This setting enables shooting with softer color reproduction ideal for portrait shooting.

Cine1: Softens the contrast in dark parts and emphasizes gradation in bright parts to produce a relaxed color movie. (equivalent to HG4609G33)

Cine2: Similar to [Cine1] but optimized for editing with up to 100% video signal. (equivalent to HG4600G30)

Cine3: Intensifies the contrast in light and shade more than [Cine1] and strengthens gradation in black.

Cine4: Strengthens the contrast in dark parts more than [Cine3].

ITU709: Gamma curve that corresponds to ITU709.

ITU709(800%): Gamma curve for confirming scenes on the assumption of shooting using [S-Log2] or [S-Log3].

S-Log2: Gamma curve for [S-Log2]. This setting is based on the assumption that the picture will be processed after shooting.

S-Log3: Gamma curve for [S-Log3] with more similar features to film. This setting is based on the assumption that the picture will be processed after shooting.

HLG: Gamma curve for HDR recording. Equivalent to the HDR standard Hybrid Log-Gamma, ITU-R BT.2100.

HLG1: Gamma curve for HDR recording. Emphasizes noise reduction. However, shooting is restricted to a narrower dynamic range than with [HLG2] or [HLG3].

HLG2: Gamma curve for HDR recording. Provides a balance of dynamic range and noise reduction.

HLG3: Gamma curve for HDR recording. Wider dynamic range than [HLG2]. However, noise may increase.

• [HLG1], [HLG2], and [HLG3] all apply a gamma curve with the same characteristics, but each offers a different balance between dynamic range and noise reduction. Each has a different maximum video output level, as follows: [HLG1]: approx. 87%, [HLG2]: approx. 95%, [HLG3]: approx. 100%.

Black Gamma

Corrects gamma in low intensity areas.

[Black Gamma] is fixed at "0" and cannot be adjusted when [Gamma] is set to [HLG], [HLG1], [HLG2], or [HLG3].

Range: Selects the correcting range. (Wide / Middle / Narrow)

Level: Sets the correcting level. (-7 (maximum black compression) to +7 (maximum black stretch))

Knee

Sets knee point and slope for video signal compression to prevent over-exposure by limiting signals in high intensity areas of the subject to the dynamic range of your camera.

 $[Knee] \ is \ disabled \ if \ [Mode] \ is \ set \ to \ [Auto] \ when \ [Gamma] \ is \ set \ to \ [Still], \ [Cine1], \ [Cine2], \ [Cine3], \ [Cine4], \ [ITU709(800\%)], \ [S-Log2], \ [S-Log3], \ [HLG1], \ [HLG2], \ or \ [HLG3]. \ To \ enable \ [Knee], \ set \ [Mode] \ to \ [Manual].$

Mode: Selects auto/manual settings.

- Auto: The knee point and slope are set automatically.
- Manual: The knee point and slope are set manually.

Auto Set: Settings when [Auto] is selected for [Mode].

- Max Point: Sets the maximum point of the knee point. (90% to 100%)
- Sensitivity: Sets the sensitivity. (High / Mid / Low)

Manual Set: Settings when [Manual] is selected for [Mode].

- Point: Sets the knee point. (75% to 105%)
- Slope: Sets the knee slope. (-5 (gentle) to +5 (steep))

Color Mode

Sets type and level of colors.

In [Color Mode], only [BT.2020] and [709] are available when [Gamma] is set to [HLG], [HLG1], [HLG2], or [HLG3].

Movie: Suitable colors when [Gamma] is set to [Movie].

Still: Suitable colors when [Gamma] is set to [Still].

S-Cinetone: Suitable colors when [Gamma] is set to [S-Cinetone].

Cinema: Suitable colors when [Gamma] is set to [Cine1] or [Cine2].

Pro: Similar color tones to the standard image quality of Sony professional cameras (when combined with ITU709 gamma)

ITU709 Matrix: Colors corresponding to ITU709 standard (when combined with ITU709 gamma)

Black & White: Sets the saturation to zero for shooting in black and white.

S-Gamut: Setting based on the assumption that the pictures will be processed after shooting. Used when [Gamma] is set to [S-Log2].

S-Gamut3.Cine: Setting based on the assumption that the pictures will be processed after shooting. Used when [Gamma] is set to [S-Log3]. This setting allows you to shoot in a color space that can easily be converted for digital cinema.

S-Gamut3: Setting based on the assumption that the pictures will be processed after shooting. Used when [Gamma] is set to [S-Log3]. This setting allows you to shoot in a wide color space.

BT.2020: Standard color tone when [Gamma] is set to [HLG], [HLG1], [HLG2], or [HLG3].

709: Color tone when [Gamma] is set to [HLG], [HLG1], [HLG2], or [HLG3] and movies are recorded with HDTV color (BT.709).

Saturation

Sets the color saturation. (-32 to +32)

Color Phase

Sets the color phase. (-7 to +7)

Color Depth

Sets the color depth for each color phase. This function is more effective for chromatic colors and less effective for achromatic colors. The color looks deeper as you increase the setting value towards the positive side, and lighter as you decrease the value towards the negative side. This function is effective even if you set [Color Mode] to [Black & White].

[R] -7 (light red) to +7 (deep red)

[G] -7 (light green) to +7 (deep green)

[B] -7 (light blue) to +7 (deep blue)

[C] -7 (light cyan) to +7 (deep cyan)

[M] -7 (light magenta) to +7 (deep magenta)

[Y] -7 (light yellow) to +7 (deep yellow)

Detail

Sets items for [Detail].

Level: Sets the [Detail] level. (-7 to +7)

Adjust: The following parameters can be selected manually.

- Mode: Selects auto/manual setting. (Auto (automatic optimization) / Manual (The details are set manually.))
- V/H Balance: Sets the vertical (V) and horizontal (H) balance of DETAIL. (-2 (off to the vertical (V) side) to +2 (off to the horizontal (H) side))
- B/W Balance: Selects the balance of the lower DETAIL (B) and the upper DETAIL (W). (Type1 (off to the lower DETAIL (B) side) to Type5 (off to the upper DETAIL (W) side))
- Limit: Sets the limit level of [Detail]. (0 (Low limit level: likely to be limited) to 7 (High limit level: unlikely to be limited))
- Crispning: Sets the crispening level. (0 (shallow crispening level) to 7 (deep crispening level))
- Hi-Light Detail: Sets the [Detail] level in the high intensity areas. (0 to 4)

To copy the settings to another picture profile number

You can copy the settings of the picture profile to another picture profile number.

 $\mathsf{MENU} \to \mathbf{Z} \ (\mathsf{Exposure/Color}) \to [\mathsf{Color/Tone}] \to [\mathbf{Z}] \ \mathsf{Picture} \ \mathsf{Profile}] \to [\mathsf{Copy}].$

To reset the picture profile to the default setting

You can reset the picture profile to the default setting. You cannot reset all picture profile settings at once.

 $MENU \rightarrow$ [Color/Tone] \rightarrow [Picture Profile] \rightarrow [Reset].

Note

- If you want to select different settings for movies and still images, add a check mark to [Picture Profile] under [Different Set for Still/Mv].
- If you develop RAW images with shooting settings, the following settings are not reflected:
 - Black Level
 - Black Gamma
 - Knee
 - Color Depth
- If you change [Gamma], the available ISO value range changes.
- There may be more noise in dark parts depending on the gamma settings. It may improve by setting the lens compensation to [Off].
- When using S-Log2 or S-Log3 gamma, the noise becomes more noticeable compared to when using other gammas. If the noise still is significant even after processing pictures, it may be improved by shooting with a brighter setting. However, the dynamic range becomes narrower accordingly when you shoot with a brighter setting. We recommend checking the picture in advance by test shooting when using S-Log2 or S-Log3.
- Setting [ITU709(800%)], [S-Log2] or [S-Log3] may cause an error in the white balance custom setup. In this case, perform custom setup with a gamma other than [ITU709(800%)], [S-Log2], or [S-Log3] first, and then reselect [ITU709(800%)], [S-Log2], or [S-Log3] gamma.
- If you set [Slope] to +5 in [Manual Set] under [Knee], [Knee] will be disabled.
- S-Gamut, S-Gamut3. Cine, and S-Gamut3 are color spaces exclusive to Sony. However, this camera's S-Gamut setting does not support the whole S-Gamut color space; it is a setting to achieve a color reproduction equivalent to S-Gamut.

Related Topic

- Gamma Display Assist
- Different Set for Still/Mv

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Drive Mode

Select the appropriate mode for the subject, such as single shooting, continuous shooting or bracketing shooting.



Select the desired drive mode by turning the drive mode dial.

Turn the drive mode dial while holding down the drive mode dial lock release button.

Setting	item	details
---------	------	---------

Normal shooting mode.

및H[†] 및H 및M 및L Cont. Shooting:

Shoots images continuously while you press and hold down the shutter button.

Self-timer:

Shoots an image using the self-timer after a designated number of seconds have elapsed since the shutter button was pressed.

BRK Bracket:

Shoots images using the bracketing function. The type of bracketing function can be set by MENU \rightarrow [Orive Mode] \rightarrow [Bracket Settings] \rightarrow [Bracket Type].

Related Topic

- Cont. Shooting
- Self-timer Type: Self-timer(Single)
- Self-timer Type: Self-timer(Cont)
- Bracket Settings: Cont. Bracket
- Bracket Settings: Single Bracket
- Bracket Settings: WB bracket
- Bracket Settings: DRO Bracket
- Cont. Shooting Speed

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Cont. Shooting

Shoots images continuously while you press and hold down the shutter button.



Turn the drive mode dial and select the desired mode.

• Turn the drive mode dial while pressing the drive mode dial lock release button.

Setting item details

UH⁺ Continuous Shooting: Hi+ / UH Continuous Shooting: Hi / UM Continuous Shooting: Mid/ UL Continuous Shooting: Lo

The listed continuous shooting speeds reflect the condition of the camera when shipped from the factory.

Continuous shooting setting	Shutter Type: Mechanical Shutter	Shutter Type: Auto/Electronic Shutter *1
Continuous Shooting: Hi+	Maximum 10 images/second*2 *4	Maximum 30 images/second*3 *4 *5
Continuous Shooting: Hi	Maximum 8 images/second*2 *4	Maximum 20 images/second*4 *5
Continuous Shooting: Mid	Maximum 6 images/second*4	Maximum 15 images/second*4
Continuous Shooting: Lo	Maximum 3 images/second	Maximum 5 images/second*4

^{*1} This is the speed when [Aperture Drive in AF] is set to [Standard]. When [Aperture Drive in AF] is set to [Focus Priority], the continuous shooting speed may be slower.

Number of still images recordable with continuous shooting

These numbers are a guide for the number of recordable images when the drive mode dial is set to \square_H^+ (Continuous Shooting: Hi+) or \square_H^+ (Continuous Shooting: Hi). The numbers may vary depending on the shooting conditions and the memory card.

Drive mode: [Continuous Shooting: Hi+]

Image Size: [L:50M]

[Shutter Type]: [Auto] or [Electronic Shutter]

File Format	Number of images when JPEG is selected	Number of images when HEIF is selected
JPEG/HEIF (Fine)	Approx. 165 images	Approx. 153 images
RAW (Compressed RAW)	Approx. 155 images	Approx. 155 images

^{*2} When [Flash Sync Spd. Prty.] is set to [On] or [Auto], the maximum speed may decrease.

^{*3} When shooting in uncompressed RAW or lossless compressed RAW, the maximum speed is 20 images/second.

^{*4} When [Aperture Drive in AF] is set to [Standard] or [Silent Priority] and the aperture value is larger than F22, the focus is locked to the setting in the first shot.

^{*5} When the focus mode is AF-C (Continuous AF), the continuous shooting speed varies depending on the lens attached. For details, refer to the lens compatibility information support page.

File Format	Number of images when JPEG is selected	Number of images when HEIF is selected
RAW & JPEG/RAW & HEIF (Compressed RAW)*1	Approx. 152 images	Approx. 120 images
RAW (Uncompressed RAW)*2	Approx. 82 images	Approx. 82 images
RAW & JPEG/RAW & HEIF (Uncompressed RAW)*1 *2	Approx. 78 images	Approx. 64 images
RAW (Lossless compression RAW: L)*2	Approx. 96 images	Approx. 96 images
RAW & JPEG/RAW & HEIF (Lossless compression RAW: L)*1 *2	Approx. 83 images	Approx. 64 images

^{*1} When [JPEG Quality]/[HEIF Quality] is set to [Fine].

Drive mode: [Continuous Shooting: Hi]

Image Size: [L: 50M]

[Shutter Type]: [Auto] or [Electronic Shutter]

The numbers listed below reflect the condition of the camera when shipped from the factory. (The continuous shooting speed for [Continuous Shooting: Hi] is 20 images per second at maximum.)

File Format	Number of images when JPEG is selected	Number of images when HEIF is selected
JPEG/HEIF (Fine)	Approx. 400 images	Approx. 299 images
RAW (Compressed RAW)	Approx. 238 images	Approx. 238 images
RAW & JPEG/RAW & HEIF (Compressed RAW) [*]	Approx. 192 images	Approx. 164 images
RAW (Uncompressed RAW)	Approx. 82 images	Approx. 82 images
RAW & JPEG/RAW & HEIF (Uncompressed RAW)*	Approx. 78 images	Approx. 64 images
RAW (Lossless compression RAW: L)	Approx. 96 images	Approx. 96 images
RAW & JPEG/RAW & HEIF (Lossless compression RAW: L)*	Approx. 83 images	Approx. 64 images

^{*} When [JPEG Quality]/[HEIF Quality] is set to [Fine].

- Numbers of recordable images are estimates based on shooting under the following conditions:
 - Ambient temperature: 25°C (77°F)
 - Using a Sony CFexpress Type A memory card (sold separately)
 - Number of memory cards inserted: 1

Hint

- To continuously adjust the focus and exposure during continuous shooting, set as follows:
 - Focus mode: [Continuous AF]

^{*2} The continuous shooting speed and the number of images recordable with continuous shooting become lowered to the same level as in the [Continuous Shooting: Hi] mode when shooting in the uncompressed RAW format or the lossless compressed RAW format.

- [AEL w/ Shutter]: [Off] or [Auto]
- When using the electronic shutter, you can select your preferred continuous shooting speed by selecting MENU \rightarrow [O] (Shooting) \rightarrow [Drive Mode] \rightarrow [Cont. Shooting Speed].
- To shoot more images during continuous shooting, set the drive mode to [Continuous Shooting: Mid] (15 images/second at maximum) or slower. You continuously can shoot 1,000 images or more in the JPEG format.

Note

- During continuous shooting, the focus is locked to the setting in the first shot when the F-value is greater than F22. (However, when [Shutter Type] is set to [Mechanical Shutter] and the [Continuous Shooting: Lo] mode is selected, the camera continuously adjusts the focus during continuous shooting.)
- The subject is not displayed in real time on the monitor or viewfinder when [Shutter Type] is set to [Mechanical Shutter] or when shooting in [Continuous Shooting: Hi+] mode.
- The speed of continuous shooting decreases when you shoot with a flash.

Related Topic

- Cont. Shooting Speed
- Remain Shoot Display (still image)
- Selecting the focus method (Focus Mode)
- AEL w/ Shutter

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Cont. Shooting Speed



Sets the continuous shooting speed when using the electronic shutter.

Menu item details

☐ Hi(E-Shutter):

Sets the continuous shooting speed when the drive mode dial is set to $\Box H$ (Continuous Shooting: Hi). ([20 images/sec]/[15 images/sec]/[15 images/sec])

☐ Mid(E-Shutter):

Sets the continuous shooting speed when the drive mode dial is set to \(\subseteq_{\textsum}\mathbb{M}\) (Continuous Shooting: Mid). ([20 images/sec]/[15 images/sec]/[10 images/sec]/[5 images/sec])

□ Lo(E-Shutter):

Sets the continuous shooting speed when the drive mode dial is set to [20] (Continuous Shooting: Lo). ([20] images/sec]/[15] images/sec]/[15] images/sec]/[16] images/sec]/[16] images/sec]/[17] images/sec]/[18] images/sec]/[18]

Hint

■ When using the electronic shutter, the continuous shooting speed with the drive mode dial set to ☐H⁺ (Continuous Shooting: Hi+) is 30 images per second at maximum.

Note

The numbers in the names of the setting values indicate the maximum continuous shooting speed when the setting value is selected

Related Topic

Cont. Shooting

Help Guide

Interchangeable Lens Digital Camera ILCE-1 q1

Self-timer Type: Self-timer(Single)



Shoots an image using the self-timer after a designated number of seconds have elapsed since the shutter button was pressed. Use the 5-second/10-second self-timer when you are going to be in the picture, and use the 2-second self-timer to reduce camera-shake caused by pressing the shutter button.

- Select 💍 (Self-timer) by turning the drive mode dial.
 - Turn the drive mode dial while holding down the drive mode dial lock release button.
- - The setting screen for [Self-timer Type] can be displayed by pressing the Fn button.
- 3 Adjust the focus and shoot the image.

The self-timer lamp flashes, a beep sounds, and a picture is taken after the designated number of seconds have elapsed.

Menu item details

The mode determines the number of seconds until a picture is taken after the shutter button is pressed.

ა 10 Self-timer(Single): 10 sec ა 5 Self-timer(Single): 5 sec ა 2 Self-timer(Single): 2 sec

Hint

- Press the shutter button again to stop the count of the self-timer.
- Select a drive mode other than (Self-timer) by turning the drive mode dial to cancel the self-timer.
- Set [Audio signals] to [Off] to turn off the beeping sound during the self-timer countdown.
- To use the self-timer in bracket mode, select BRK (Bracket) by turning the drive mode dial, then select MENU \rightarrow (Shooting) \rightarrow [Drive Mode] \rightarrow [Bracket Settings] \rightarrow [Selftimer during Bracket].

Related Topic

Audio signals

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Self-timer Type: Self-timer(Cont)



Shoots a designated number of images using the self-timer after a designated number of seconds have elapsed since the shutter button was pressed. You can choose the best from multiple shots.

- 1 Select 💍 (Self-timer) by turning the drive mode dial.
 - Turn the drive mode dial while holding down the drive mode dial lock release button.
- MENU \rightarrow [\bigcirc] (Shooting) \rightarrow [Drive Mode] \rightarrow [Self-timer Type] \rightarrow [Self-timer(Cont)] \rightarrow desired mode.
 - The setting screen for [Self-timer Type] can be displayed by pressing the Fn button.
- 3 Adjust the focus and shoot the image.

The self-timer lamp flashes, a beep sounds, and pictures are taken after the designated number of seconds has elapsed. The designated number of pictures are taken continuously.

Menu item details

For example, three images are shot when 10 seconds have elapsed after the shutter button is pressed when [Self-timer(Cont.): 10 Sec. 3 Img.] is selected.

- ర్జి Self-timer(Cont.): 10 Sec. 3 Img.
- ტენ Self-timer(Cont.): 10 Sec. 5 Img.
- ్రిక్త Self-timer(Cont.): 5 Sec. 3 Img.
- ర్మ్ Self-timer(Cont.): 5 Sec. 5 Img.
- ర్మిక Self-timer(Cont.): 2 Sec. 3 Img.
- ర్మ్ Self-timer(Cont.): 2 Sec. 5 Img.

Hint

- Press the shutter button again to stop the count of the self-timer.
- Select a drive mode other than (Self-timer) by turning the drive mode dial to cancel the self-timer.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Bracket Settings: Cont. Bracket



Shoots multiple images while automatically shifting the exposure from base to darker and then to lighter. You can select an image that suits your purpose after recording.

- Select **BRK** (Bracket) by turning the drive mode dial.
 - Turn the drive mode dial while holding down the drive mode dial lock release button.
- MENU → [O] (Shooting) → [Drive Mode] → [Bracket Settings] → [Bracket Type] → [Cont. Bracket] → desired mode.
 - The setting screen for [Bracket Type] can be displayed by pressing the Fn button.
- 3 Adjust the focus and shoot the image.
 - The base exposure is set at the first shot.
 - Keep pressing and holding the shutter button until bracket shooting is finished.

Menu item details

For example, the camera shoots a total of three images continuously with an exposure value shifted by plus or minus 0.3 EV when [Cont. Bracket: 0.3EV 3 Image] is selected.

Hint

The last shot is shown on the auto review.

Note

- When [ISO AUTO] is selected in [Manual Exposure] mode, the exposure is changed by adjusting the ISO value. If a setting other than [ISO AUTO] is selected, the exposure is changed by adjusting the shutter speed.
- When the exposure is compensated, the exposure is shifted based on the compensated value.
- Bracket shooting is unavailable in the following shooting modes:
 - [Intelligent Auto]
- When the flash is used, the product performs flash bracket shooting, which shifts the amount of flash light even if [Cont. Bracket] is selected. Press the shutter button for each image.

Related Topic

Indicator during bracket shooting

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Bracket Settings: Single Bracket



Shoots multiple images while automatically shifting the exposure from base to darker and then to lighter. You can select the image that suits your purpose after recording.

Since a single picture is taken each time you press the shutter button, you can adjust the focus or the composition for each shot.

- 1 Select BRK (Bracket) by turning the drive mode dial.
 - Turn the drive mode dial while holding down the drive mode dial lock release button.
- **2** MENU → **(Shooting)** → [Drive Mode] → [Bracket Settings] → [Bracket Type] → [Single Bracket] → desired mode.
 - The setting screen for [Bracket Type] can be displayed by pressing the Fn button.
- 3 Adjust the focus and shoot the image.
 - Press the shutter button for each image.

Menu item details

For example, when [Single Bracket: 0.3EV 3 Image] is selected, three images are shot one at a time with the exposure value shifted up and down in increments of 0.3 EV.

Note

- When [ISO AUTO] is selected in [Manual Exposure] mode, the exposure is changed by adjusting the ISO value. If a setting other than [ISO AUTO] is selected, the exposure is changed by adjusting the shutter speed.
- When the exposure is compensated, the exposure is shifted based on the compensated value.
- Bracket shooting is unavailable in the following shooting modes:
 - [Intelligent Auto]

Related Topic

Indicator during bracket shooting

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Indicator during bracket shooting

Viewfinder

Ambient light* bracketing 3 images shifted by 0.3 EV steps Exposure compensation ±0.0 EV



Monitor (Display All Info. or Histogram)

Ambient light* bracketing 3 images shifted by 0.3 EV steps Exposure compensation ±0.0 EV



Flash bracketing 3 images shifted by 0.7 EV steps Flash compensation -1.0 EV

Monitor (For viewfinder)

Ambient light* bracketing (upper indicator) 3 images shifted by 0.3 EV steps Exposure compensation ±0.0 EV

Flash bracketing (lower indicator) 3 images shifted by 0.7 EV steps Flash compensation -1.0 EV

* Ambient light: A generic term for non-flash light including natural light, electric bulb and fluorescent lighting. Whereas the flash light blinks for a moment, ambient light is constant, so this kind of light is called "ambient light."

Hint

- During bracket shooting, guides equal to the number of images to be shot are displayed over/under the bracket indicator.
- When you start single bracket shooting, the guides will disappear one by one as the camera records images.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Bracket Settings: WB bracket



Shoots a total of three images, each with different color tones according to the selected settings for white balance, color temperature and color filter.

- Select **BRK** (Bracket) by turning the drive mode dial.
 - Turn the drive mode dial while holding down the drive mode dial lock release button.
- MENU → [O] (Shooting) → [Drive Mode] → [Bracket Settings] → [Bracket Type] → [WB bracket] → desired mode.
 - The setting screen for [Bracket Type] can be displayed by pressing the Fn button.
- Adjust the focus and shoot the image.

Menu item details

White Balance Bracket: Lo:

Records a series of three images with small changes in the white balance (within the range of 10MK^{-1*}).

White Balance Bracket: Hi:

Records a series of three images with large changes in the white balance (within the range of 20MK^{-1*}).

* MK⁻¹ is the unit that indicates the capability of color temperature conversion filters and indicates the same value as "mired."

Hint

The last shot is shown on the auto review.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Bracket Settings: DRO Bracket



You can record a total of three images, each at a different degree of D-Range Optimizer value.

- Select **BRK** (Bracket) by turning the drive mode dial.
 - Turn the drive mode dial while holding down the drive mode dial lock release button.
- 2 MENU → (Shooting) → [Drive Mode] → [Bracket Settings] → [Bracket Type] → [DRO Bracket] → desired mode.
 - The setting screen for [Bracket Type] can be displayed by pressing the Fn button.
- Adjust the focus and shoot the image.

Menu item details

DRO Bracket: Lo:

Records a series of three images with small changes in the D-Range Optimizer value (Lv 1, Lv 2, and Lv 3).

DRO Bracket: Hi:

Records a series of three images with large changes in the D-Range Optimizer value (Lv 1, Lv 3, and Lv 5).

Hint

The last shot is shown on the auto review.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Bracket Settings: Selftimer during Bracket



Sets whether to use the self-timer during bracket shooting.

- 1 Select BRK (Bracket) by turning the drive mode dial.
 - Turn the drive mode dial while holding down the drive mode dial lock release button.
- 2 MENU → (Shooting) → [Drive Mode] → [Bracket Settings] → [Selftimer during Bracket] → desired setting.

Menu item details

Off:

Does not use the self-timer during bracket shooting.

2 Sec/5 Sec/10 Sec:

Uses the self-timer during bracket shooting. Bracket shooting starts after the designated number of seconds has elapsed.

Related Topic

- Bracket Settings: Cont. Bracket
- Bracket Settings: Single Bracket
- Bracket Settings: WB bracket
- Bracket Settings: DRO Bracket

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Bracket Settings: Bracket order



You can set the shooting order for exposure bracketing or white balance bracketing.

- 1 Select BRK (Bracket) by turning the drive mode dial.
 - Turn the drive mode dial while holding down the drive mode dial lock release button.

Menu item details

0→**-**→**+**:

Shoots images with the exposure shifted in the order of standard, dark, and bright during exposure bracketing. Shoots images with the color temperature shifted in the order of standard, low, and high during white balance bracketing.

-→0→+:

Shoots images with the exposure shifted in the order of dark, standard, and bright during exposure bracketing. Shoots images with the color temperature shifted in the order of low, standard, and high during white balance bracketing.

Related Topic

- Bracket Settings: Cont. Bracket
- Bracket Settings: Single Bracket
- Bracket Settings: WB bracket

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Interval Shoot Func.



You can automatically shoot a series of still images with the shooting interval and number of shots that you set in advance (Interval shooting). On this camera, you cannot create a movie from still images produced by interval shooting.

- MENU → (Shooting) → [Drive Mode] → [Interval Shoot Func.] → Select an item to set, and then select the desired setting.
- 3 Press the shutter button.

When the time set for [Shooting Start Time] has elapsed, shooting will start.

• When the number of shots set for [Number of Shots] is completed, the camera will return to the standby screen for interval shooting.

Menu item details

Interval Shooting:

Sets whether to perform interval shooting. ([Off]/[On])

Shooting Start Time:

Sets the time from when you press the shutter button to when interval shooting starts. (1 second to 99 minutes 59 seconds)

Shooting Interval:

Sets the shooting interval (time from when one exposure starts to when the exposure for the next shot starts). (1 second to 60 seconds)

Number of Shots:

Sets the number of shots for interval shooting. (1 shot to 9999 shots)

AE Tracking Sensitivity:

Sets the tracking sensitivity of the auto exposure against the change in luminance during interval shooting. If you select [Low], exposure changes during interval shooting will be smoother. ([High]/[Mid]/[Low])

Shutter Type in Interval:

Sets the shutter type during interval shooting. ([Mechanical Shutter]/[Electronic Shutter])

Shoot Interval Priority:

Sets whether or not to prioritize the shooting interval when the exposure mode is [Program Auto] or [Aperture Priority] and the shutter speed becomes longer than the time set for [Shooting Interval]. ([Off]/[On])

Hint

- If you press the shutter button during interval shooting, interval shooting will end and the camera will return to the standby screen for interval shooting.
- To return to the normal shooting mode, set [Interval Shooting] to [Off].
- If you press a key to which one of the following functions has been assigned at the moment when shooting starts, the function will remain active during interval shooting even without you holding down the button.

- [AEL hold]
- −[AEL hold]
- [AF/MF Selector Hold]
- [Regist. AF Area hold]
- [AWB Lock Hold]
- [My Dial 1 during Hold] to [My Dial 3 during Hold]
- If you set [Display as Group] to [On], still images shot with the interval shooting function will be displayed in groups.
- Still images shot with interval shooting can be played back continuously on the camera. If you intend to create a movie using the still images, you can preview the result.

Note

- You may not be able to record the set number of images depending on the remaining battery level and the amount of free space on the recording medium. Supply power via USB while shooting, and use a memory card with sufficient space.
- When the shooting interval is short, the camera may get hot easily. Depending on the ambient temperature, you may not be able to record the set number of images because the camera may stop recording to protect the equipment.
- During interval shooting (including the time between pressing the shutter button and the start of shooting), you cannot operate the
 dedicated shooting setting screen or MENU screen. However, you can adjust some settings such as the shutter speed with using
 the customized dial or control wheel.
- During interval shooting, auto review is not displayed.
- [Shutter Type in Interval] is set to [Electronic Shutter] as a default, regardless of the setting for [Shutter Type].
- Interval shooting is unavailable in the following situations:
 - The shooting mode is set to [Intelligent Auto]
 - [Pixel Shift Multi Shoot.] is set to other than [Off]

Related Topic

- Cont. Play for Interval
- Supplying power from a wall outlet (wall socket)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Shooting still images with a higher resolution (Pixel Shift Multi Shoot.)

You can create images with a higher resolution than is possible with regular shooting by recording four or sixteen RAW images and then combining them on a computer. This is helpful when shooting still subjects such as works of art or architecture. To combine multiple RAW images, dedicated software is needed.

Select MENU \rightarrow (Network) \rightarrow [Smartphone Connect] \rightarrow [Smartphone Connection] \rightarrow [Off] beforehand.

- - Configure other [PC Remote Function] settings if needed.
 - PC Remote shooting using a Wi-Fi connection may take a long time to transfer the recorded images. It is recommended that you set [Still Img. Save Dest.] under [PC Remote Function] to [Camera Only], or use a wired connection instead.
- $\textbf{2} \quad \text{MENU} \rightarrow \bigoplus \text{ (Network)} \rightarrow \text{[Transfer/Remote]} \rightarrow \text{[PC Remote Function]} \rightarrow \text{[PC Remote]} \rightarrow \text{[On]}.$
- 3 Connect the camera to the computer according to the setting for [PC Remote Cnct Method], and then launch Imaging Edge Desktop (Remote) on the computer.
- A Secure the camera using a tripod. Perform [Pixel Shift Multi Shoot.] using Imaging Edge Desktop (Remote).

The camera will record the selected number of RAW images at the selected interval. The images will be saved on the computer along with the combined image.

- Try to avoid camera shaking or blurring of the subject.
- The four or sixteen RAW images are recorded with the same settings. You cannot change the settings during the interval between the shots.
- You can cancel the recording by pressing the center of the control wheel during the interval between the recordings.
- If you will not be using a flash (sold separately), select a shortest shooting interval in Imaging Edge Desktop (Remote). If using a flash, set the interval according to the charging time of your flash.
- If you have set [Still Img. Save Dest.] under [PC Remote Function] to [Camera Only], import the recorded four or sixteen RAW images to the computer and then combine them using Imaging Edge Desktop (Remote).
- For techniques for [Pixel Shift Multi Shoot.], refer to the following support site. https://www.sony.net/psms/

Hint

You can also perform [Pixel Shift Multi Shoot.] on the camera itself without using Imaging Edge Desktop (Remote). Select MENU → [6] (Shooting) → [Drive Mode] → [Pixel Shift Multi Shoot.] and set the recording interval and the number of images, and then perform shooting. You can import the recorded RAW images in the computer and combine them using Imaging Edge Desktop (Viewer). If you will not be using Imaging Edge Desktop (Remote) for shooting, use a Wireless Remote Commander (sold separately) or the self-timer function in order to avoid camera shaking and subject blurring.

Note

If camera shaking and subject blurring occurs, the RAW images recorded with [Pixel Shift Multi Shoot.] may not be combined properly. Even when the subject is remaining still, if a nearby person or object moves, the RAW images may not be combined properly because the lighting of the subject can change.

- RAW images recorded with [Pixel Shift Multi Shoot.] cannot be combined using the camera. Use Imaging Edge Desktop (Viewer) to combine the images.
- In [Pixel Shift Multi Shoot.], some settings are locked as follows:
 - [File Format] under [Image Quality Settings]: [RAW]
 - [RAW File Type] under [Image Quality Settings]: [Uncompressed]
- In [Pixel Shift Multi Shoot.], you cannot perform bulb shooting.
- When shooting in the [Pixel Shift Multi Shoot.] mode, you cannot use the optical wireless flash.
- If shooting is set to a mode other than P/A/S/M, you cannot perform [Pixel Shift Multi Shoot.].
- If you use a Mount Adaptor, the shooting interval may be longer.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

JPEG/HEIF Switch



Switches the file format (JPEG / HEIF) of the still image to be recorded.

The JPEG format has general compatibility. You can view and edit JPEG files in various environments. The HEIF format has high compression efficiency. The camera can record with high image quality and small file sizes in the HEIF format. Depending on the computer or software, you may not be able to view or edit HEIF files. In addition, a HEIF-compatible environment is required to play back still images in the HEIF format. You can enjoy high-quality still images by connecting the camera and the TV via HDMI.



 $MENU \rightarrow \lceil \bigcirc \rceil$ (Shooting) \rightarrow [Image Quality] \rightarrow [JPEG/HEIF Switch] \rightarrow desired setting.

Menu item details

JPEG:

Performs digital processing on the RAW file and records it in the JPEG format. This setting gives priority to compatibility.

HEIF(4:2:0):

Performs digital processing on the RAW file and records it in the HEIF (4:2:0) format. This setting gives priority to image quality and compression efficiency.

HEIF(4:2:2):

Performs digital processing on the RAW file and records it in the HEIF (4:2:2) format. This setting gives priority to image quality.

Hint

 Depending on the setting for [JPEG/HEIF Switch], items related to the file format ([File Format], etc.) will switch to JPEG or HEIF.

Note

- HEIF image files recorded with this camera cannot be displayed on other cameras that do not support the HEIF file format. Be
 careful not to accidentally erase HEIF image files by formatting the memory card or deleting the files.
- When recording in the HEIF format with [HLG Still Image] set to [Off], the color space is recorded in sRGB. When [HLG Still Image] is set to [On], it is recorded in the BT.2100 color space (BT.2020 color gamut).

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Image Quality Settings: File Format (still image)



Sets the file format for still images.



 $\textbf{MENU} \to \boxed{\bigcirc} \ (\textbf{Shooting}) \to [\textbf{Image Quality}] \to [\textbf{Image Quality Settings}] \to [\textbf{\colored}] \to \textbf{Grade}$ setting.

Menu item details

RAW:

Digital processing is not performed on this file format. Select this format to process images on a computer for professional purposes.

RAW & JPEG/RAW & HEIF:

A RAW image and a JPEG or HEIF image are created at the same time. This is suitable when you need two image files, a JPEG or HEIF for viewing, and a RAW for editing.

JPEG/HEIF:

The image is recorded in the JPEG or HEIF format.

When [Recording Media] is set to [Sort Recording], you can select the file format for each slot from among RAW and JPEG, or RAW and HEIF.

About RAW images

- To open a RAW image file recorded with this camera, the software Imaging Edge Desktop is needed. With Imaging Edge Desktop, you can open a RAW image file, then convert it into a popular image format such as JPEG or TIFF, or readjust the white balance, saturation or contrast of the image.
- RAW images recorded with this camera have a resolution of 14 bits per pixel.
- You can set the compression method for RAW images using [RAW File Type].

Note

- If you do not intend to edit the images on your computer, we recommend that you record in JPEG or HEIF format.
- An environment supporting the HEIF format is required to play back HEIF images.

Related Topic

- JPEG/HEIF Switch
- Image Quality Settings: JPEG Quality/HEIF Quality
- Image Quality Settings: JPEG Image Size/HEIF Image Size
- Image Quality Settings: RAW File Type
- Rec. Media Settings (still image/movie): Recording Media (still image)
- Introduction to computer software (Imaging Edge Desktop/Catalyst)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Image Quality Settings: RAW File Type



Selects the file type for RAW images.



 $\textbf{MENU} \to \boxed{\bigcirc} \ \, \textbf{(Shooting)} \to \textbf{[Image Quality]} \to \textbf{[Image Quality Settings]} \to \textbf{[RAW File Type]} \to \textbf{desired setting.}$

Menu item details

Uncompressed:

Records images in uncompressed RAW format. When [Uncompressed] is selected for [RAW File Type], the file size of the image will be larger than if it were recorded in lossless compressed RAW format or compressed RAW format.

Lossless Comp (L)/Lossless Comp (M)/Lossless Comp (S) *:

Records images with a lossless compression method that causes no deterioration in image quality and has a high compression rate. The file size is smaller than when [Uncompressed] is selected.

- You can select L/M/S as the image size. The number of pixels after development using a Sony application is the same as the L/M/S size for JPEG/HEIF images.
- The L size can be selected only when shooting in full frame. When shooting in the M or S size, the pixel number does
 not change for full-frame shooting or APS-C-size shooting.
- * When the camera's system software (firmware) version is Ver.1.30 or later
- ** The M size and S size reduce the image size, so the image resolution will be lower than that of the L size.

Compressed:

Records images in compressed RAW format. The file size of the image will be approximately half of that with [Uncompressed].

Hint

- The [RAW File Type] icons are displayed as shown below.
 - Uncompressed: RAW
 - Lossless compression (L/M/S): RAW RAW RAW
 - Compressed: RAW
- The aspect ratio for RAW images is always 3:2. JPEG/HEIF images are recorded with the aspect ratio set in [Aspect Ratio] when RAW images and JPEG/HEIF images are recorded at the same time.

Note

You cannot record RAW images with different formats to Slot 1 and Slot 2. Even when [Recording Media] is set to [Sort Recording], each slot has the same setting for [RAW File Type].

Related Topic

Image Quality Settings: File Format (still image)

- Image Quality Settings: JPEG Image Size/HEIF Image Size
- Rec. Media Settings (still image/movie): Recording Media (still image)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Image Quality Settings: JPEG Quality/HEIF Quality



Selects the image quality when recording JPEG or HEIF images.



 $\textbf{MENU} \rightarrow \boxed{\bigcirc} \ (\textbf{Shooting}) \rightarrow [\textbf{Image Quality}] \rightarrow [\textbf{Image Quality Settings}] \rightarrow [\textbf{JPEG Quality}]/[\textbf{HEIF Quality}] \rightarrow \textbf{desired setting}.$

Menu item details

Extra fine/Fine/Standard/Light:

Since the compression rate increases from [Extra fine] to [Fine] to [Standard] to [Light], the file size decreases in that same order. This allows more files to be recorded on one memory card, but the image quality is lower.

When [Recording Media] is set to [Sort Recording], you can select the image quality for each slot.

Related Topic

- Image Quality Settings: File Format (still image)
- Rec. Media Settings (still image/movie): Recording Media (still image)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Image Quality Settings: JPEG Image Size/HEIF Image Size



The larger the image size, the more detail will be reproduced when the image is printed on large-format paper. The smaller the image size, the more images can be recorded.



Menu item details

When [Aspect Ratio] is set to 3:2

Setting values	Pixel number (horizontal×vertical)	
L: 50M	8640×5760 pixels	
M: 21M	5616×3744 pixels	
S: 12M	4320×2880 pixels	

When [Aspect Ratio] is set to 4:3

Setting values	Pixel number (horizontal×vertical)	
L: 44M	7680×5760 pixels	
M: 19M	4992×3744 pixels	
S: 11M	3840×2880 pixels	

When [Aspect Ratio] is set to 16:9

Setting values	Pixel number (horizontal×vertical)	
L: 42M	8640×4864 pixels	
M: 18M	5616×3160 pixels	
S: 11M	4320×2432 pixels	

When [Aspect Ratio] is set to 1:1

Setting values	Pixel number (horizontal×vertical)
----------------	------------------------------------

Setting values	Pixel number (horizontal×vertical)	
L: 33M	5760×5760 pixels	
M: 14M	3744×3744 pixels	
S: 8.3M	2880×2880 pixels	

Hint

When recording in the M or S size, the pixel number will not change even if you switch the angle of view between the full-frame size and APS-C size.

Note

The L size cannot be selected when shooting in the APS-C size. If you shoot in the APS-C size while the L size is selected, the image size will switch to the M size temporarily.

Related Topic

- Image Quality Settings: File Format (still image)
- Aspect Ratio

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Aspect Ratio





 $\textbf{MENU} \rightarrow \boxed{\bigcirc} \text{ (Shooting)} \rightarrow \textbf{[Image Quality]} \rightarrow \textbf{[Aspect Ratio]} \rightarrow \textbf{desired setting.}$

Menu item details

3:2:

Same aspect ratio as 35 mm film

4:3:

The aspect ratio is 4:3.

16:9:

The aspect ratio is 16:9.

1:1:

The aspect ratio is 1:1.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

HLG Still Image



By using gamma characteristics equivalent to HLG (Hybrid Log-Gamma: standard for HDR images), you can shoot still images with a wide dynamic range and a wide color gamut compatible with BT.2020.

[HLG Still Image] can only be set when shooting in the HEIF format. Set [JPEG/HEIF Switch] to [HEIF(4:2:0)] or [HEIF(4:2:2)], and [File Format] under [Image Quality Settings] to [HEIF] beforehand.



 $\textbf{MENU} \rightarrow \textbf{[O]} \ (\textbf{Shooting}) \rightarrow \textbf{[Image Quality]} \rightarrow \textbf{[HLG Still Image]} \rightarrow \textbf{desired setting}.$

Menu item details

On:

Shoots HLG still images.

Off:

Shoots normal still images.

Hint

- You can reproduce a wider range of brightness by playing back HLG still images on an HLG-compatible TV or monitor.
- We recommend setting MENU → → (Setup) → [External Output] → [♠ HDMI Resolution] to one of the followings when you display HLG still images from the camera on a TV using an HDMI cable (sold separately).
 - Auto
 - 2160p
 - 1080p
 - 1080i
- You can display HLG still images on the camera's monitor in almost the same quality as when they are displayed on an HLG-(BT.2020-) compatible monitor by setting as follows.
 - [Gamma Display Assist]: [On]
 - [Gamma Disp. Assist Typ.]: [Auto] or [HLG(BT.2020)]

Note

- In the following situations, [HLG Still Image] is fixed to [Off]:
 - [JPEG/HEIF Switch] is set to [JPEG]
 - [Mark File Format] under [Image Quality Settings] is set to [RAW] or [RAW & HEIF]
 - When a shooting mode other than P / A / S / M is set during still image shooting
 - When the ISO sensitivity is temporarily activated by the [Reg. Custom Shoot Set] function
 - When the drive mode is temporarily set to [DRO Bracket] by the [Reg. Custom Shoot Set] function
- When [HLG Still Image] is set to [On], the following functions are not available.
 - [D-Range Optimizer]
 - [Creative Look]
 - [DRO Bracket] in the drive mode
 - [Picture Profile]
- When [HLG Still Image] is set to [On], the available ISO range changes.

Related Topic

- JPEG/HEIF Switch
- HDMI Resolution
- Gamma Display Assist

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Color Space



The way colors are represented using combinations of numbers or the range of color reproduction is called "color space." You can change the color space depending on the purpose of the image.



 $\textbf{MENU} \to \lceil \bigcirc \rceil \text{ (Shooting)} \to [\textbf{Image Quality}] \to [\textbf{Color Space}] \to \textbf{desired setting}.$

Menu item details

sRGB:

This is the standard color space of the digital camera. Use [sRGB] in normal shooting, such as when you intend to print out the images without any modification.

AdobeRGB:

This color space has a wide range of color reproduction. When a large part of the subject is vivid green or red, Adobe RGB is effective. The file name of the recorded image starts with "_."

Note

- The [Color Space] setting is invalid when shooting images in the HEIF format. If [HLG Still Image] is set to [Off], images will be recorded with the sRGB color space. When [HLG Still Image] is set to [On], it is recorded in the BT.2100 color space (BT.2020 color gamut).
- [AdobeRGB] is for applications or printers that support color management and DCF2.0 option color space. Images may not be printed or viewed in the correct colors if you use applications or printers that do not support Adobe RGB.
- When displaying images that were recorded with [AdobeRGB] on non-Adobe RGB-compliant devices, the images will be displayed with low saturation.

Related Topic

- JPEG/HEIF Switch
- HLG Still Image

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

File Format (movie)



Selects the movie file format.



 $MENU \to \boxed{\bigcirc} \ (Shooting) \to [Image Quality] \to [\boxed{\blacksquare} \ File \ Format] \to desired \ setting.$

Menu item details

File Format	Characteristics
XAVC HS 8K	Records 8K movies in the XAVC HS format. The XAVC HS format uses the HEVC codec, which has high compression efficiency. The camera can record movies with higher image quality than XAVC S movies but the same data volume. Long GOP compression is used for movies.
XAVC HS 4K	Records 4K movies in the XAVC HS format. The XAVC HS format uses the HEVC codec, which has high compression efficiency. The camera can record movies with higher image quality than XAVC S movies but the same data volume. Long GOP compression is used for movies.
XAVC S 4K	Records movies in 4K resolution (3840×2160). Long GOP compression is used for movies.
XAVC S HD	Records movies in HD resolution (1920×1080). Long GOP compression is used for movies.
XAVC S-I 4K	Records movies in the XAVC S-I format. The XAVC S-I format uses Intra compression for movies. This format is more suitable for editing than Long GOP compression.
XAVC S-I HD	Records movies in the XAVC S-I format. The XAVC S-I format uses Intra compression for movies. This format is more suitable for editing than Long GOP compression.

Intra/Long GOP is a movie compression format. Intra compresses the movie by frame, and Long GOP compresses
multiple frames. Intra compression has better response and flexibility when editing, but Long GOP compression has
better compression efficiency.

Note

- To play back XAVC HS 4K / XAVC HS 8K movies on a computer, you need a device or software with high processing capability that supports the HEVC codec.

- If an APS-C size dedicated lens is attached, the edges of the screen may appear dark. When recording 4K 120p/100p or 8K movies with this camera, we recommend using a lens compatible with the 35 mm full-frame format.
- To properly display 8K movies from the camera on a TV manufactured by Sony using a HDMI cable (sold separately), you need to change the image quality settings for the TV manually. Change the image quality settings (gamma or color mode) for the TV according to the settings applied when shooting.

Related Topic

Memory cards that can be used

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Movie Settings (movie)




Sets the frame rate, bit rate, color information, etc.



MENU → (Shooting) → [Image Quality] → [Image Quality] → [Record Setting] → desired setting.

Example of setting values



(A): Bit rate

(B): Color sampling

(C): Bit depth

- The higher the bit rate, the higher the image quality.
- Color sampling (4:2:2, 4:2:0) is the recording ratio of color information. The more uniform this ratio is, the better the color reproducibility, and it is possible to remove colors neatly even when compositing using a green screen.
- Bit depth represents the gradation of luminance information. When the bit depth is 8 bits, 256 levels of gradation can be obtained. When the bit depth is 10 bits, 1024 levels of gradation can be obtained. A larger value enables smoother expression from dark to bright areas.
- [4:2:2 10 bit] is a setting that assumes that the recorded movie will be edited on a computer. The playback environment for [4:2:2 10 bit] is limited.

Menu item details

When [File Format] is set to [XAVC HS 8K]

Rec Frame Rate	Record Setting	Size	Movie compression format
30p/25p	520M 4:2:2 10bit *1	7680×4320	Long GOP
30p/25p	400M 4:2:0 10bit	7680×4320	Long GOP
30p/25p	260M 4:2:2 10bit *1	7680×4320	Long GOP
30p/25p	200M 4:2:0 10bit	7680×4320	Long GOP
24p *2	520M 4:2:2 10bit *1	7680×4320	Long GOP
24p *2	400M 4:2:0 10bit	7680×4320	Long GOP
24p *2	260M 4:2:2 10bit *1	7680×4320	Long GOP
24p *2	200M 4:2:0 10bit	7680×4320	Long GOP

When [File Format] is set to [XAVC HS 4K]

Rec Frame Rate	Record Setting	Size	Movie compression format
60p/50p	200M 4:2:2 10bit	3840×2160	Long GOP
60p/50p	150M 4:2:0 10bit	3840×2160	Long GOP
60p/50p	100M 4:2:2 10bit	3840×2160	Long GOP
60p/50p	75M 4:2:0 10bit	3840×2160	Long GOP
60p/50p	45M 4:2:0 10bit	3840×2160	Long GOP
24p*	100M 4:2:2 10bit	3840×2160	Long GOP
24p*	100M 4:2:0 10bit	3840×2160	Long GOP
24p*	50M 4:2:2 10bit	3840×2160	Long GOP
24p*	50M 4:2:0 10bit	3840×2160	Long GOP
24p*	30M 4:2:0 10bit	3840×2160	Long GOP
120p/100p	280M 4:2:2 10bit	3840×2160	Long GOP
120p/100p	200M 4:2:0 10bit	3840×2160	Long GOP

^{*} Only when [NTSC/PAL Selector] is set to NTSC.

When [File Format] is set to [XAVC S 4K]

Rec Frame Rate	Record Setting	Size	Movie compression format
60p/50p	200M 4:2:2 10bit	3840×2160	Long GOP
60p/50p	150M 4:2:0 8bit	3840×2160	Long GOP
30p/25p	140M 4:2:2 10bit	3840×2160	Long GOP
30p/25p	100M 4:2:0 8bit	3840×2160	Long GOP
30p/25p	60M 4:2:0 8bit	3840×2160	Long GOP
24p*	100M 4:2:2 10bit	3840×2160	Long GOP
24p*	100M 4:2:0 8bit	3840×2160	Long GOP
24p*	60M 4:2:0 8bit	3840×2160	Long GOP
120p/100p	280M 4:2:2 10bit	3840×2160	Long GOP
120p/100p	200M 4:2:0 8bit	3840×2160	Long GOP

^{*} Only when [NTSC/PAL Selector] is set to NTSC.

When [File Format] is set to [XAVC S HD]

Rec Frame Rate	Record Setting	Size	Movie compression format
60p/50p	50M 4:2:2 10bit	1920×1080	Long GOP
60p/50p	50M 4:2:0 8bit	1920×1080	Long GOP
60p/50p	25M 4:2:0 8bit	1920×1080	Long GOP
30p/25p	50M 4:2:2 10bit	1920×1080	Long GOP
30p/25p	50M 4:2:0 8bit	1920×1080	Long GOP
30p/25p	16M 4:2:0 8bit	1920×1080	Long GOP
24p*	50M 4:2:2 10bit	1920×1080	Long GOP
24p*	50M 4:2:0 8bit	1920×1080	Long GOP
120p/100p	100M 4:2:0 8bit	1920×1080	Long GOP
120p/100p	60M 4:2:0 8bit	1920×1080	Long GOP

^{*} Only when [NTSC/PAL Selector] is set to NTSC.

When [File Format] is set to [XAVC S-I 4K]

Rec Frame Rate	Record Setting	Size	Movie compression format
60p/50p	600M 4:2:2 10bit/500M 4:2:2 10bit	3840×2160	Intra
30p/25p	300M 4:2:2 10bit/250M 4:2:2 10bit	3840×2160	Intra
24p*	240M 4:2:2 10bit	3840×2160	Intra

^{*} Only when [NTSC/PAL Selector] is set to NTSC.

When [File Format] is set to [XAVC S-I HD]

Rec Frame Rate	Record Setting	Size	Movie compression format
60p/50p	222M 4:2:2 10bit/185M 4:2:2 10bit	1920×1080	Intra
30p/25p	111M 4:2:2 10bit/93M 4:2:2 10bit	1920×1080	Intra
24p*	89M 4:2:2 10bit	1920×1080	Intra

^{*} Only when [NTSC/PAL Selector] is set to NTSC.

Note

Recording frame rates are indicated as the closest integer values. The actual corresponding frame rates are as follows: 24p: 23.98 fps, 30p: 29.97 fps, 60p: 59.94 fps, and 120p: 119.88 fps.

Related Topic

File Format (movie)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

S&Q Settings



You can record a moment that cannot be captured by the naked eye (slow-motion recording), or record a long-term phenomenon into a compressed movie (quick-motion recording). For example, you can record an intense sports scene, the moment when a bird starts to fly, a blooming flower, and a changing view of clouds or a starry sky. Sound will not be recorded.

- 1 Set the mode dial to S&Q (S&Q Motion).
- Select MENU → [o] (Shooting) → [Shooting Mode] → [Sk0 Exposure Mode] → and select the desired setting of slow-motion/quick-motion (Program Auto, Aperture Priority, Shutter Priority, or Manual Exposure).
- 3 Select MENU → [o] (Shooting) → [Image Quality] → [S&Q S&Q Settings] → Select an item to set, and then select the desired setting.
- Press the MOVIE (movie) button to start recording.
 - Press the MOVIE button again to stop recording.

Menu item details

S&Q Rec Frame Rate:

Selects the frame rate of the movie.

S&Q Frame Rate:

Selects the shooting frame rate.

S&Q Record Setting:

Selects the bit rate, color sampling, and bit depth of the movie.

- The values that can be set for [S&Q Rec Frame Rate] and [S&Q Record Setting] are the same as the setting values for [☐☐☐ Movie Settings].
- Although the format of the recorded movie will be the same as the [File Format] setting, you cannot select [XAVC HS 8K] for slow-motion/quick-motion shooting. If [XAVC HS 8K] has been selected, it will automatically switch to [XAVC HS 4K].

Playback speed

The playback speed will vary as below depending on the assigned [Sto Rec Frame Rate] and [Sto Frame Rate]. When [NTSC/PAL Selector] is set to NTSC

S&Q Frame	S&Q Rec Frame Rate:			
Rate	24p	30p	60p	120p
240fps	10 times slower	8 times slower	4 times slower	2 times slower

S&Q Frame Rate	S&Q Rec Frame Rate: 24p	S&Q Rec Frame Rate: 30p	S&Q Rec Frame Rate: 60p	S&Q Rec Frame Rate: 120p
120fps	5 times slower	4 times slower	2 times slower	Normal playback speed
60fps	2.5 times slower	2 times slower Normal playback speed		2 times quick
30fps	1.25 times slower	Normal playback speed 2 times quick		4 times quick
15fps	1.6 times quick	2 times quick	4 times quick	8 times quick
8fps	3 times quick	3.75 times quick	7.5 times quick	15 times quick
4fps	6 times quick	7.5 times quick	15 times quick	30 times quick
2fps	12 times quick	15 times quick	30 times quick	60 times quick
1fps	24 times quick	30 times quick	60 times quick	120 times quick

When [NTSC/PAL Selector] is set to PAL

S&Q Frame Rate	S&Q Rec Frame Rate: 25p	S&Q Rec Frame Rate: 50p	S&Q Rec Frame Rate: 100p
200fps	8 times slower	4 times slower	2 times slower
100fps	4 times slower	2 times slower	Normal playback speed
50fps	2 times slower	Normal playback speed	2 times quick
25fps	Normal playback speed	2 times quick	4 times quick
12fps	2.08 times quick	4.16 times quick	8.33 times quick
6fps	4.16 times quick	8.33 times quick	16.66 times quick
3fps	8.33 times quick	16.66 times quick	33.33 times quick
2fps	12.5 times quick	25 times quick	50 times quick
1fps	25 times quick	50 times quick	100 times quick

- [240fps]/[200fps] cannot be selected when [File Format] is set to following items:
 - XAVC HS 4K
 - XAVC S 4K
 - XAVC S-I 4K

Hint

For an estimation of recordable time, refer to "Recordable movie times."

Note

• In slow-motion/quick-motion recording, the actual shooting time differs from the time recorded in the movie. The recordable time displayed toward the top of the monitor shows the remaining recording time for the movie, not the remaining recording time on the memory card.

- In slow-motion recording, the shutter speed becomes faster and you may not be able to obtain the proper exposure. If this happens, decrease the aperture value or set the ISO sensitivity to a higher value.
- During slow-motion/quick-motion recording, the following functions are not available.
 - [Time Code Run]
 - [Time Code Output]

Related Topic

- S&Q Motion: Exposure Mode
- Recordable movie times
- Memory cards that can be used

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Proxy Settings



You can simultaneously record a low-bit-rate proxy movie when recording a movie or slow-motion recording/quick-motion recording.

Since proxy movies are small in file size, they are suitable for transferring to smartphones or uploading to websites.



 $MENU \rightarrow []$ (Shooting) \rightarrow [Image Quality] \rightarrow [Px Proxy Settings] \rightarrow Select an item to set, and then select the desired setting.

Menu item details

Px Proxy Recording:

Selects whether to simultaneously record proxy movies. ([On] / [Off])

Px Proxy File Format:

Selects the recording format of the proxy movie. ([XAVC HS HD] / [XAVC S HD])

Px Proxy Rec. Settings:

Selects the bit rate, color sampling and bit depth of the proxy movie. ([16M 4:2:0 10bit] / [9M 4:2:0 10bit] / [6M 4:2:0 8bit])

Selectable proxy recording settings

Px Proxy File Format	Recording size	Recording frame rate	Px Proxy Rec. Settings	Compression codec
XAVC HS HD	1920×1080	Max. 60p/Max. 50p	16Mbps 4:2:0 10bit 9Mbps 4:2:0 10bit	MPEG-H HEVC/H.265
XAVC S HD	1280×720	Max. 60p/Max. 50p	6Mbps 4:2:0 8bit	MPEG-4 AVC/H.264

Hint

Proxy movies are not displayed on the playback screen (single-image playback screen or image index screen).
Px (proxy) is displayed over movies for which a proxy movie was simultaneously recorded.

Note

- Proxy movies cannot be played back on this camera.
- Proxy recording is not available in the following situations.
 Normal movie recording
 - [Rec Frame Rate] is set to [120p]/[100p] or higher

Slow-motion recording/quick-motion recording

- [S&Q Rec Frame Rate] is set to [120p]/[100p] or higher
- [S&Q Frame Rate] is set to [120fps]/[100fps] or higher

- Deleting/protecting movies that have proxy movies removes/protects both the original and proxy movies. You cannot delete/protect only original movies or proxy movies.
- Movies cannot be edited on this camera.

Related Topic

Memory cards that can be used

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

APS-C S35 (Super 35mm) Shooting (still image/movie)



Sets whether or not to record with the angle of view of APS-C for still images and with an angle of view equivalent to Super 35mm for movies. If you select [On] or [Auto], you can use an APS-C size dedicated lens on this product.



Menu item details

On:

Records in either APS-C-equivalent size or Super 35mm-equivalent size.

When [On] is selected, the angle of view becomes approximately 1.5 times the focal length indicated on the lens.

Auto:

Automatically sets the capture range according to the lens, and camera settings.

Off:

Always captures 35mm full-frame image sensor pictures.

Note

- When you attach an APS-C-compatible lens and set [APS-(535 Shooting] to [Off], you may not achieve optimal shooting results. For example, the edges of the image may become darker.
- When [☐ ANG Shooting] is set to [On], the angle of view is the same as when shooting with an APS-C-size image sensor.
- [Aps. (335 Shooting] is locked to [Off] when shooting movies in 4K 120p/100p or 8K. We recommend using a lens compatible with the 35 mm full-frame format.

Related Topic

Angle of view


Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Angle of view

The angle of view switches to the equivalent of full frame or APS-C/Super 35mm, depending on the setting for [] Shooting] and the attached lens. The angle of view is also different for still image shooting and movie shooting.

Angle of view equivalent to full frame




- (A) When shooting still images
- **(B)** When recording movies (other than 4K 120p/100p), and in slow-motion/quick-motion shooting (other than HD 240fps/200fps)
- (C) When recording movies (4K 120p/100p)
- (D) When shooting slow-motion/quick-motion movies (HD 240fps/200fps)

The camera shoots with an angle of view equivalent to full frame in the following situations.

- When shooting still images
 - [Shooting] is set to [Auto], and a full frame shooting-compatible lens is attached.
 - [Shooting] is set to [Off].
- When shooting movies
 - The movie format is set to 8K, or the frame rate is set to [120p]/[100p].
 - The movie format is set to 4K and [ANG. (5)] Shooting] is set to [Off].
 - The movie format is set to HD, [Shooting] is set to [Auto], and a lens that supports full-frame shooting is attached.
 - The movie format is set to HD and [APS-(SSS Shooting] is set to [Off].

Angle of view equivalent to APS-C size/Super 35mm



- (A) When shooting still images
- (B) When recording movies

The camera shoots with an angle of view equivalent to the APS-C size or Super 35mm in the following situations. The angle of view becomes approx. 1.5 times the focal length indicated on the lens.

- When shooting still images
 - [Shooting] is set to [Auto], and an APS-C-format dedicated lens is attached.
 - [APS-(SSS Shooting] is set to [On].
- When shooting movies
 - The movie format is set to 4K (60p/50p or lower) and [APS-(SS) Shooting] is set to [Auto] or [On].
 - The movie format is set to HD, [Shooting] is set to [Auto], and an APS-C-format dedicated lens is attached.
 - The movie format is set to HD and [ANG Shooting] is set to [On].

Note

- When recording full-frame-size movies and in the 4K 120p/100p mode, the angle of view becomes approximately 1.1 times the focal length indicated on the lens.
- When recording full-frame-size slow- and quick-motion movies and in the HD 240fps/200fps mode, the angle of view becomes approximately 1.2 times the focal length indicated on the lens.

Related Topic

- File Format (movie)
- Movie Settings (movie)
- APS-C S35 (Super 35mm) Shooting (still image/movie)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Touch Operation



Sets whether or not to activate touch operations on the monitor.



Menu item details

On:

Activates touch operations.

On: Playback Only:

Activates touch operations only during playback.

Off:

Deactivates touch operations.

Related Topic

- Touch Func. in Shooting
- Touch Panel/Pad
- Touch Sensitivity
- Touch operations on the monitor

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Touch Sensitivity



Sets the touch operation sensitivity.



 $MENU \rightarrow \longrightarrow (Setup) \rightarrow [Touch Operation] \rightarrow [Touch Sensitivity] \rightarrow desired setting.$

Menu item details

Sensitive:

The touch responsivity is better than with [Standard].

Standard:

Sets the touch sensitivity to normal.

Hint

If you want to deactivate touch operations on the monitor, set [Touch Operation] to [Off].

Note

Even if the touch sensitivity is set to [Sensitive], the touch panel/pad may not react properly depending on the gloves used.

Related Topic

Touch Operation

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Touch Panel/Pad



Touch operations when shooting with the monitor are referred to as "touch panel operations," and touch operations when shooting with the viewfinder are referred to as "touch pad operations." You can select whether to activate touch panel operations or touch pad operations.



 $MENU \rightarrow \overrightarrow{\text{F--}}$ (Setup) \rightarrow [Touch Operation] \rightarrow [Touch Panel/Pad] \rightarrow desired setting.

Menu item details

Both Valid:

Activates both the touch panel operations when shooting with the monitor and touch pad operations when shooting with the viewfinder.

Touch Panel Only:

Activates only the touch panel operations when shooting with the monitor.

Touch Pad Only:

Activates only the touch pad operations when shooting with the viewfinder.

Related Topic

Touch Operation

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Touch Pad Settings



You can adjust settings related to touch pad operations during viewfinder shooting.



 $\textbf{MENU} \rightarrow \overrightarrow{\textbf{F--}} \ (\textbf{Setup}) \rightarrow [\textbf{Touch Operation}] \rightarrow [\textbf{Touch Pad Settings}] \rightarrow \textbf{desired setting}.$

Menu item details

Operation in Vertical Orientation:

Sets whether to enable touch pad operations during vertically oriented viewfinder shooting. You can prevent erroneous operations during vertically oriented shooting caused by your nose, etc. touching the monitor.

Touch Position Mode:


Sets whether to move the focusing frame to the position touched on the screen ([Absolute Position]), or move the focusing frame to the desired position based on the direction of dragging and the amount of movement ([Relative Position]).

Operation Area:

Sets the area to be used for touch pad operations. Restricting the operational area can prevent erroneous operations caused by your nose, etc. touching the monitor.

About Touch Positioning Mode

Selecting [Absolute Position] lets you move the focusing frame to a distant position more quickly because you can directly specify the position of the focusing frame with touch operations.



Selecting [Relative Position] lets you operate the touch pad from wherever is easiest, without having to move your finger over a wide area.



Hint



Related Topic

Touch Panel/Pad

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Touch Func. in Shooting



Sets the operation activated by touching the screen during shooting.



 $MENU \rightarrow \longrightarrow (Setup) \rightarrow [Touch Operation] \rightarrow [Touch Func. in Shooting] \rightarrow desired setting.$

Menu item details

Touch Focus:

The focusing position is set by touching the screen during shooting.

Touch Tracking:

The subject is selected and tracking is started by touching the screen during shooting.

Off:

Disables touch operations during shooting.

Hint

You can change the setting for [Touch Func. in Shooting] by touching ¼/¼/√ hoff (touch function icon) on the shooting screen.

Related Topic

- Focusing using touch operations (Touch Focus)
- Starting tracking with touch operations (Touch Tracking)
- Touch Operation

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$


Focusing using touch operations (Touch Focus)



[Touch Focus] allows you to specify a position where you want to focus using touch operations. Select MENU \rightarrow [Setup) \rightarrow [Touch Operation] \rightarrow [Touch Operation] \rightarrow [On] beforehand.

This function is available when [Focus Area] is set to one of following parameters:


- [Wide]
- [Zone]
- [Center Fix]
- [Tracking: Wide]
- [Tracking: Zone]
- [Tracking: Center Fix]



Specifying the position where you want to focus in the still image mode

When performing auto-focusing, you can specify the position where you want to focus using touch operations. After touching the monitor and specifying a position, press the shutter button halfway down to focus.

- 1. Touch the monitor.
 - When shooting with the monitor, touch the position where you want to focus.
 - When shooting with the viewfinder, you can move the position of the focus by touching and dragging on the monitor while looking through the viewfinder.



- To cancel focusing with touch operations, touch Touch focus release) icon or press the center of the control wheel if shooting with the monitor, and press the center of the control wheel if shooting with the viewfinder.
- 2. Press the shutter button halfway down to focus.
 - Press the shutter button all the way down to shoot images.

Specifying the position where you want to focus in the movie recording mode

The camera will focus on the touched subject.

- 1. Touch the subject on which you want to focus before or during recording.
 - When the focus mode is set to [Continuous AF], the focus mode temporarily switches to manual focus, and the focus can be adjusted using the focus ring (spot focus). Spot focus is not available when shooting with the

viewfinder.

- To cancel spot focus, touch (Touch focus release) icon or press the center of the control wheel.
- When the focus mode is set to [Manual Focus], the focus mode temporarily switches to [Continuous AF]. When the touched area is in focus, the focus mode returns to manual focus.

Hint

- In addition to the touch focus function, touch operations such as the following are also available.
 - The focusing frame for [Spot] and [Expand Spot] can be moved by dragging.
 - When shooting still images in the manual focusing mode, the focus magnifier can be used by double-tapping the monitor.

Note

- The touch focus function is not available in the following situations:
 - When shooting still images in the manual focusing mode
 - When using the digital zoom
 - When using the LA-EA4

Related Topic

- Touch Func. in Shooting
- Touch Operation
- Touch Panel/Pad
- Selecting the focus area (Focus Area)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Starting tracking with touch operations (Touch Tracking)



You can use touch operations to select a subject you want to track in the still image shooting mode and movie recording mode.

Select MENU \rightarrow \longleftrightarrow (Setup) \rightarrow [Touch Operation] \rightarrow [Touch Operation] \rightarrow [On] in advance.

- Touch the subject that you want to track on the monitor.

Tracking will start.

- When shooting with the viewfinder, you can use the touch pad to select a subject you want to track.
- 3 Press the shutter button halfway down to focus.
 - Press the shutter button all the way down to shoot images.

Hint

■ To cancel tracking, touch | (Tracking release) icon or press the center of the control wheel.

Note

- [Touch Tracking] is unavailable in the following situations:
 - When the focus mode is set to [Manual Focus].
 - When using the Smart Zoom, Clear Image Zoom and Digital Zoom

Related Topic

- Touch Func. in Shooting
- Touch Operation

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Silent Mode Settings (still image/movie)



You can configure settings related to the silent mode, which allows you to shoot without shutter sounds or electronic sounds. You can also set whether or not to change the settings for other functions that emit sounds from the camera when the camera is set to the silent mode.



 $\textbf{MENU} \rightarrow \begin{tabular}{l} \hline O \\ \hline \end{tabular} \begin{tabular}{l} \hline \textbf{MENU} \rightarrow \begin{tabular}{l} \hline O \\ \hline \end{tabular} \begin{tabular}{l} \hline \textbf{MENU} \rightarrow \begin{tabular}{l} \hline \textbf{O} \\ \hline \end{tabular} \begin{tabular}{l} \hline \textbf{MENU} \rightarrow \begin{tabular}{l} \hline \textbf{O} \\ \hline \end{tabular} \begin{tabular}{l} \hline \textbf{MENU} \rightarrow \begin{tabular}{l} \hline \textbf{O} \\ \hline \end{tabular} \begin{tabular}{l} \hline \textbf{MENU} \rightarrow \begin{tabular}{l} \hline \textbf{O} \\ \hline \end{tabular} \begin{tabular}{l} \hline \textbf{O} \\ \hline \end{ta$

Menu item details

Silent Mode:

Sets whether or not to shoot without shutter sounds or electronic sounds. ([On]/[Off])

When set to [On], [Shutter Type] and [Shutter Type in Interval] become locked to [Electronic Shutter], and [Audio signals] becomes locked to [Off].

Target Function Settings:

Sets whether or not to simultaneously change the settings for other functions that emit sounds from the camera when the camera is set to the silent mode. ([Aperture Drive in AF]/[Shutter When Pwr OFF]/[Auto Pixel Mapping])

If you select [Not Target], the setting values for each function will be retained even in the silent mode.

Note

- Use the [Silent Mode] function on your own responsibility, while taking sufficient consideration to the privacy and portrait rights of the subject.
- Even if [Silent Mode] is set to [On], it will not be completely silent.
- Even if [Silent Mode] is set to [On], the operating sound of the aperture and focus will sound.
- If [Auto Pixel Mapping] is set to [On], shutter sounds may occasionally be heard when the power is turned off. This is not a malfunction.
- If [Shutter When Pwr OFF] under [Anti-dust Function] is set to [On], a shutter sound will be heard when the camera is turned off.
- Image distortion caused by the movement of the subject or the camera may occur.
- If you shoot images under instantaneous lightning or flickering lights, such as the flash light from other cameras or fluorescent lighting, a striping effect may occur on the image.
- Even if [Silent Mode] is set to [On], you may hear shutter sounds when you register a face using [Face Memory].
- When [Silent Mode] is set to [On], the following functions are not available:
 - Long Exposure NR
 - BULB shooting

Related Topic

- Shutter Type
- Interval Shoot Func.
- Aperture Drive in AF
- Anti-dust Function
- Auto Pixel Mapping

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Shutter Type



You can set whether to shoot with a mechanical shutter or an electronic shutter.



 $\textbf{MENU} \to \lceil \widehat{\bigcirc} \rceil \text{ (Shooting)} \to \textbf{[Shutter/Silent]} \to \textbf{[Shutter Type]} \to \textbf{desired setting.}$

Menu item details

Auto:

The shutter type is automatically switched based on the shooting conditions and shutter speed.

Mechanical Shutter:

Shoot with the mechanical shutter only.

Electronic Shutter:

Shoot with the electronic shutter only.

Hint

- In the following situations, set the [Shutter Type] to [Auto] or [Electronic Shutter].
 - When shooting with a high-speed shutter in a bright environment such as outside in bright sunlight, the beach, or snowy mountains.
 - When you want to increase the speed of continuous shooting.

Note

- In rare cases, the shutter sound may be produced when the power is turned off even if the [Shutter Type] is set to [Electronic Shutter]. However, this is not a malfunction.
- Even if [Shutter Type] is set to [Electronic Shutter], you may hear shutter sounds when you register a face using [Face Memory].
- When [Shutter Type] is set to [Electronic Shutter], the following functions are not available:
 - Long Exposure NR
 - BULB shooting
- When you shoot at high shutter speeds with a large-aperture lens attached and [Mechanical Shutter] mode is selected, out-of-focus circles produced by the bokeh effect may get cut off due to the shutter mechanism.
- When a lens made by another manufacturer (including Minolta/Konica-Minolta lenses) is used and the [Mechanical Shutter] mode is selected, the correct exposure may not be set or the image brightness may become uneven.
- When you shoot at high shutter speeds and the [Mechanical Shutter] mode is selected, the image brightness may become uneven depending on the shooting environment.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Using the electronic shutter

Using the electronic shutter lets you perform various kinds of shooting that are difficult to achieve using the mechanical shutter, such as shooting without sounds or shaking, shooting with a super-fast shutter, and blackout-free shooting*.

* During blackout-free shooting, the screen does not black out or drop frames and you can keep looking at the subject through the viewfinder or monitor while shooting images.

Shutter types and camera performance

The camera's shutter speed range, shutter sound, occurrence of blackout, and availability of the anti-flicker shooting or the flash for each setting are as follows:

Item	Shutter Type: 🗏 Auto	Shutter Type: HECH Mechanical Shutter	Shutter Type: Electronic Shutter
Shutter speed	Single shooting: BULB – 1/32000 Continuous shooting: 0.5" – 1/32000 ^{*1}	Single shooting: BULB – 1/8000 Continuous shooting: 30 – 1/8000	Single shooting: 30 – 1/32000 Continuous shooting: 0.5" – 1/32000
Shutter sound	Single shooting: Mechanical shutter sound Continuous shooting: Electronic shutter sound*2	Mechanical shutter sound	Electronic shutter sound
Blackout	Single shooting: Occurs Continuous shooting: Blackout- free*3 *4	Occurs	Blackout-free*4
Flash	Available*1	Available	Available
Anti-flicker shooting	Available	Available	Available
Shooting with variable shutter	Available		Available

^{*1} When shooting with a flash attached, shooting is performed with the mechanical shutter and the shutter speed range for continuous shooting is 0.5" to 1/8000 second.

Advanced shooting using the electronic shutter: Shooting without shutter sound

You can use the electronic shutter to shoot without shutter sound.

1.
$$MENU \rightarrow \bigcirc$$
 (Shooting) \rightarrow [Shutter/Silent] \rightarrow [\bigcirc Silent Mode Settings] \rightarrow [Silent Mode] \rightarrow [On].

Advanced shooting using the electronic shutter: Blackout-free continuous shooting

You can use the electronic shutter to perform continuous shooting with focus and exposure tracking, without the screen blacking out.

^{*2} When shooting with a flash attached, shooting is performed with the mechanical shutter and the mechanical shutter sound is heard.

^{*3} When shooting with a flash attached, shooting is performed with the mechanical shutter and blackout occurs.

^{*4} When [Shoot. Start Display] is set to [On], blackout occurs only when the first image is shot.

- 1. $MENU \rightarrow [\bigcirc]$ (Shooting) \rightarrow [Shutter/Silent] \rightarrow [Shutter Type] \rightarrow [Auto] or [Electronic Shutter].
- 2. Turn the mode dial and select P (Program Auto), A (Aperture Priority), S (Shutter Priority), or M (Manual Exposure), then set the shutter speed and aperture value. (For example: shutter speed of 1/250 second and aperture value of F2.8)
 - The product will not adjust the exposure in manual exposure mode when [ISO] is set to other than [ISO AUTO].
- 3. Turn the drive mode dial and select ☐H (Continuous Shooting: Hi+), ☐H (Continuous Shooting: Hi), ☐M (Continuous Shooting: Mid) or ☐L (Continuous Shooting: Lo).
- 4. Turn the focus mode dial and select AF-C (Continuous AF), then start shooting images.

Hint

- If you want to display the timing of shooting on the screen during blackout-free shooting, adjust the setting using MENU → (Setup) → [Display Option] → [→ Shoot. Timing Display].
- To take advantage of the performance of the camera, we recommend that you use a UHS-II card or CFexpress card.

Note

- When shooting without the shutter sound, do so on your own responsibility, with sufficient consideration to the privacy and portrait rights of the subject.
- Even if you set the camera to shoot without the shutter sound, it will not be completely silent.
- Even if you set the camera to shoot without the shutter sound, the aperture and focus will make sounds.
- When using a lens compatible with Aperture Drive in AF, sound from the aperture drive may be audible during continuous shooting if [Aperture Drive in AF] is set to [Focus Priority].
- During continuous shooting with the electronic shutter, the refresh rate of the screen display becomes slow when the shutter speed is slow. If you want the screen display to be smooth in order to track the subject, set a shutter speed faster than 1/60 second. Alternatively, set [Frame Rate Low Limit] under [Live View Display Set.] to [On]. If you set [Frame Rate Low Limit] to [On], blackout may occur depending on the shutter speed.
- The electronic shutter operates differently when a Mount Adaptor is attached on the camera.

Related Topic

- Shutter Type
- Silent Mode Settings (still image/movie)
- Shoot. Timing Display (still image)
- Cont. Shooting
- Shoot. Start Display (still image)
- Anti-flicker Set.
- Live View Display Set.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Shoot. Start Display (still image)



Sets whether or not to indicate the shutter release timing with a black screen during blackout-free shooting. The black screen makes it easier to visually confirm when the shutter is released.



 $\textbf{MENU} \rightarrow \begin{tabular}{l} \blacksquare \end{tabular} \textbf{MENU} \rightarrow \begin{tabular}{l} \blacksquare \end{tabular} \textbf{Shoot. Start Display} \end{tabular} \rightarrow \begin{tabular}{l} \blacksquare \end{tabular} \textbf{Shoot. Start Display} \end{tabular} \rightarrow \begin{tabular}{l} \blacksquare \end{tabular} \textbf{MENU} \rightarrow \begin{tabular}{l} \blacksquare \end{tabular} \textbf{Shoot. Start Display} \end{tabular} \rightarrow \begin{tabular}{l} \blacksquare \end{tabular} \textbf{MENU} \rightarrow \begin{ta$

Menu item details

On:

The screen blacks out when shooting the first image during blackout-free shooting.

Off:

The screen does not black out when shooting the first image during blackout-free shooting.

Related Topic

Using the electronic shutter

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Shoot. Timing Display (still image)



Sets whether or not to display marks (such as a frame) on the screen while shooting. This function is useful in situations where it is difficult to determine the timing of shooting just by looking at the screen, such as when the shutter sound is turned off.



 $\textbf{MENU} \rightarrow \begin{tabular}{l} \blacksquare \end{tabular} \textbf{MENU} \rightarrow \begin{tabular}{l} \blacksquare \end{tabular} \textbf{Shoot. Timing Display} \end{tabular} \rightarrow \begin{tabular}{l} \blacksquare \end{tabular} \textbf{Shoot. Timing Display} \end{tabular} \rightarrow \begin{tabular}{l} \blacksquare \end{tabular} \textbf{MENU} \rightarrow \begin{tabular}{l} \blacksquare \end{tabular} \textbf{Shoot. Timing Display} \end{tabular} \rightarrow \begin{tabular}{l} \blacksquare \end{tabular} \textbf{MENU} \rightarrow \begin$

Menu item details

On: Type1:

Displays a frame (dark color) around the focusing frame.

On: Type2:

Displays a frame (light color) around the focusing frame.

On: Type3:


Displays (dark color) in the four corners of the screen.

On: Type4:


Displays (light color) in the four corners of the screen.

Off:

Does not display the shutter release timing during blackout-free shooting.



[On: Type1] / [On: Type2] (Example: [Focus Area] is set to [Center Fix])



[On: Type3] / [On: Type4]

Related Topic

Using the electronic shutter

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Release w/o Lens (still image/movie)



Sets whether or not the shutter can be released when no lens is attached.



Menu item details

Enable:

Releases the shutter when no lens is attached. Select [Enable] when attaching the product to an astronomical telescope, etc.

Disable:

Does not release the shutter when a lens is not attached.

Note

Correct metering cannot be achieved when you use lenses that do not provide a lens contact, such as the lens of an astronomical telescope. In such cases, adjust the exposure manually by checking it on the recorded image.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Release w/o Card



Sets whether the shutter can be released when no memory card has been inserted.



 $\textbf{MENU} \rightarrow \boxed{\bigcirc} \ (\textbf{Shooting}) \rightarrow \textbf{[Shutter/Silent]} \rightarrow \textbf{[Release w/o Card]} \rightarrow \textbf{desired setting}.$

Menu item details

Enable:

Releases the shutter even if no memory card has been inserted.

Disable:

Does not release the shutter when no memory card has been inserted.

Note

- When no memory card has been inserted, the images shot will not be saved.
- The default setting is [Enable]. It is recommended that you select [Disable] prior to actual shooting.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 q1

Anti-flicker Set.



To reduce the impact of flickering from artificial light sources (such as fluorescent or LED light), the camera can time the shooting of images to moments when flickering will have less of an impact, or you can set the shutter speed more finely than usual.

This function reduces differences in exposure and color tone between the upper and lower area of an image during continuous shooting under artificial light sources.



 $\textbf{MENU} \rightarrow \boxed{\bigcirc} \ \, (\textbf{Shooting}) \rightarrow \textbf{[Shutter/Silent]} \rightarrow \textbf{[Anti-flicker Set.]} \rightarrow \textbf{desired setting item}.$

Menu item details

Anti-flicker Shoot.:

Detects flickering and reduces its impact when the frequency of the light source is 100 Hz or 120 Hz while shooting still images. Flicker is detected by pressing the shutter button halfway down. ([On]/[Off])

When [Anti-flicker Shoot.] is set to [On], press the shutter button halfway down and shoot the image after confirming that **Flicker** (flicker icon) is displayed.

Variable Shutter:

Reduces the appearance of band-like light and dark shading on the image by finely adjusting the shutter speed according to the flickering frequency. ([On]/[Off])

[Variable Shutter] can only be selected when the camera is in an exposure mode that allows you to manually adjust the shutter speed (both still images and movies).

Var. Shutter Set.:

Sets the shutter speed when [Variable Shutter] is set to [On].

Select a shutter speed that reduces the impact of flickering while checking the monitor. The faster you set the shutter speed, the more likely there is to be a difference between the monitor display before shooting and the recorded image. Make sure that the impact of flickering is reduced in the recorded image.

Hint

- When [Anti-flicker Shoot.] is set to [On], the color tone of the resulting image may vary if you shoot the same scene using a different shutter speed. In this case, we recommend that you shoot in the [Shutter Priority] or [Manual Exposure] mode with a fixed shutter speed.
- When [Anti-flicker Shoot.] is set to [On], you can perform anti-flicker shooting by pressing the AF-ON (AF On) button.
- When [Anti-flicker Shoot.] is set to [On], you can perform anti-flicker shooting by pressing the shutter button halfway down or pressing the AF-ON (AF On) button, even in the manual focus mode.
- When [♠Anti-flicker Shoot Sel.] or [♠ Var. Shutter Select] is assigned to the desired key using [♠Anti-flicker Shoot.] or [♠ Variable Shutter] function on and off by pressing the key.
- When [Variable Shutter] is set to [On], the shutter-speed denominator is displayed in the decimal format (high-resolution shutter speed).
 - For example, if the normal shutter speed is set to 1/250 second, the value will be displayed as 250.6. (The numbers may differ from the actual ones.)
- On the [Var. Shutter Set.] screen, you can finely adjust the high-resolution shutter speed using the rear dial or control wheel as in the following example.

 $250.6 \rightarrow 253.3 \rightarrow 256.0 \rightarrow 258.8^{\star}$

You can change the high-resolution shutter speed to an integral multiple value using the front dial, as in the following example. $125.3 \ (2 \text{ times}) \leftarrow 250.6 \rightarrow 501.3 \ (1/2 \text{ times})^*$

* The numbers may differ from the actual ones.

- When [Variable Shutter] is set to [On], the high-resolution shutter speed can be finely adjusted on the shooting standby screen. If you want to change the high-resolution shutter speed to an integral multiple value even on the shooting standby screen, assign [Shutter Speed(step)] to a custom key or the "My Dial" setting.
- When you change the [☐ Variable Shutter] setting from [On] to [Off], the high-resolution shutter speed switches to the closest value among normal shutter speeds.

Note

- When you set [Anti-flicker Shoot.] to [On], the image quality of the live view is reduced.
- When you set [Anti-flicker Shoot.] to [On], the shutter release lag may increase slightly. In the continuous shooting mode, the shooting speed may slow down or the interval between shots may become irregular.
- Even when [Anti-flicker Shoot.] is set to [On], the camera may be unable to detect flickering depending on the light source and shooting conditions, such as a dark background. Also, even if the camera detects flickering, its impact may not be reduced sufficiently depending on the light source and the shooting situation. We recommend that you take test shots beforehand.
- [Anti-flicker Shoot.] is not available when shooting in the following situations:
 - While bulb shooting
 - Movie shooting mode
- The color tone of the shot results may differ depending on the setting of [Anti-flicker Shoot.].
- Setting [Anti-flicker Shoot.] to [On] may not decrease flicker on the live-view screen during continuous shooting.
- When [☐ Variable Shutter] is set to [On], the release time lag may be longer.
- Even when [Variable Shutter] is set to [On], depending on the frequency of the light source, you may be unable to set the appropriate shutter speed and eliminate the impact of flickering. In that case, try the following.
 - Setting a slower shutter speed
 - Switching to another shutter type
- When you press the shutter button halfway down, flickering may appear temporarily.
- High-resolution shutter speed setting values cannot be registered to [Reg. Custom Shoot Set]. The default shutter speed value will be applied instead.
- When [Yariable Shutter] is set to [On], the flash sync speed may be limited to the slower side.

Related Topic

- Differences between the [Anti-flicker Shoot.] and [Variable Shutter] functions
- Assigning frequently used functions to buttons (Custom Key Setting)
- Changing the function of the dial temporarily (My Dial Settings)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Differences between the [Anti-flicker Shoot.] and [Variable Shutter] functions

This camera has two different functions to reduce the impact of flickering from artificial light sources (such as fluorescent or LED light).

The features of each function and the corresponding shooting conditions are as follows.

Features and shooting conditions	Anti-flicker Shoot.	입 Variable Shutter
Features	The camera can time the shooting of images to moments when flickering will have less of an impact by detecting the flickering frequency automatically.	You can manually adjust the shutter speed while checking the impact of flickering on the monitor.
Still images/movies	Still images only	Still images/movies
Shutter type	Electronic shutter/mechanical shutter	Electronic shutter/mechanical shutter*1
Exposure mode	P (Program Auto) / A (Aperture Priority) / S (Shutter Priority) / M (Manual Exposure)	S (Shutter Priority) / M (Manual Exposure)/[Flexible Exp. Mode] with the shutter speed adjusted manually
Types of flickering detectable	Flickering with a frequency of 100 Hz or 120 Hz (such as fluorescent light) only *2	Flickering with a frequency of 100 Hz or 120 Hz (such as fluorescent light) and flickering with a frequency higher than 100 Hz or 120 Hz (such as LED light)

^{*1} The faster you set the shutter speed, the more likely there is to be a difference between the monitor display before shooting and the recorded image. Make sure that the impact of flickering is reduced in the recorded image.

Hint

Related Topic

Anti-flicker Set.

^{*2} Even when [Anti-flicker Shoot.] is set to [On], the camera cannot detect flickering frequencies other than 100 Hz or 120 Hz.


Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1


The zoom features available with this product

The zoom feature of the product provides a higher magnification zoom by combining various zoom features. The icon displayed on the screen changes, according to the selected zoom feature.

When a power zoom lens is mounted:



When a lens other than a power zoom lens is mounted:



1. Optical zoom range

Zoom images in the zoom range of a lens.

When a power zoom lens is mounted, the zoom bar of the optical zoom range is displayed.

When a lens other than a power zoom lens is mounted, the zoom slider becomes locked at the left end of the zoom bar while the zoom position is in the optical zoom range. The magnification is displayed as "×1.0." If [Zoom Range] is set to [Optical zoom only], the zoom slider will not be displayed.

2. Smart Zoom range (_S€)

Zoom images without causing the original quality to deteriorate by partially cropping an image (only when [JPEG Image Size]/[HEIF Image Size] is set to [M] or [S]).

3. Clear Image Zoom range (c)

Zoom images using an image process with less deterioration.

When you set [Zoom Range] to [Clear Image Zoom] or [Digital Zoom], you can use this zoom function.

4. Digital Zoom range (p♠)

You can magnify images using an image process.

When you set [Zoom Range] to [Digital Zoom], you can use this zoom function.

Hint

- The default setting for the [Zoom Range] is [Optical zoom only].
- The default setting for the [JPEG Image Size]/[HEIF Image Size] is [L]. To use the smart zoom, change [JPEG Image Size]/[HEIF Image Size] to [M] or [S].
- With a power zoom lens mounted, if you enlarge an image beyond the optical zoom range, the camera will automatically switch to Clear Image Zoom or digital zoom.

Note

- The Smart Zoom, Clear Image Zoom and Digital Zoom functions are not available when shooting in the following situations:
 - [File Format] is set to [RAW] or [RAW & JPEG]/[RAW & HEIF].
 - [File Format] is set to [XAVC HS 8K]
 - [Rec Frame Rate] is set to [120p]/[100p].
 - During slow-motion/quick-motion shooting with the [Sto Frame Rate] set to [240fps]/[200fps] or [120fps]/[100fps]
- You cannot use the Smart Zoom function with movies.
- When you use a zoom function other than the optical zoom, the [Fig Focus Area] setting is disabled and the focusing frame is shown by the dotted line. The AF operates with priority on and around the center area.
- When you use the Smart Zoom, Clear Image Zoom or Digital Zoom function, [☐ Metering Mode] is locked to [Multi].
- When using the Smart Zoom, Clear Image Zoom or Digital Zoom function, the following functions are not available:
 - Face/Eye Prior. in AF
 - Face Priority in Multi Metering
 - Tracking function
- To use another zoom function than the optical zoom for movies, assign [Zoom] to the desired key using [Custom Key Setting].

Related Topic

- Clear Image Zoom/Digital Zoom (Zoom)
- Zoom Range (still image/movie)
- About zoom scale

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Clear Image Zoom/Digital Zoom (Zoom)



When you use a zoom function other than the optical zoom, you can exceed the zoom range of the optical zoom.

- **1** MENU \rightarrow \bigcirc (Shooting) \rightarrow [Zoom] \rightarrow [\bigcirc Zoom Range] \rightarrow Select [Clear Image Zoom] or [Digital Zoom].
- $\begin{tabular}{ll} \begin{tabular}{ll} \be$

Press the center of the control wheel to exit.

- You can also assign the [Zoom] function to the desired key by selecting MENU → (Setup) → [Operation Customize] → [Custom Key Setting] or [Custom Key Setting].
- If you assign [Zoom Operation (T)] or [Zoom Operation (W)] to the desired key in advance by selecting MENU
 → (Setup) → [Operation Customize] → [Custom Key Setting] or [Custom Key Setting], you can zoom in and out simply by pressing that key.

Hint

- When a power zoom lens is attached, you can use the zoom lever or zoom ring to magnify the image. If you exceed the optical zoom magnification, you can switch to a zoom function other than the optical zoom with the same operation.
- Even when you select [Zoom] from MENU to zoom with the power zoom lens attached, the optical zoom is used up to the telephoto end of the lens.

Note

When you select [Zoom] from MENU to zoom with a power zoom lens attached, step zoom operations cannot be performed.

Related Topic

- Zoom Range (still image/movie)
- The zoom features available with this product
- About zoom scale
- Assigning frequently used functions to buttons (Custom Key Setting)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Zoom Range (still image/movie)



You can select the zoom setting of the product.



 $\mathsf{MENU} \to \boxed{\bigcirc} \ (\mathsf{Shooting}) \to [\mathsf{Zoom}] \to [\boxed{\square} \ \mathsf{Zoom} \ \mathsf{Range}] \to \mathsf{desired} \ \mathsf{setting}.$

Menu item details

Optical zoom only:

Limits the zoom range to the optical zoom. You can use the Smart Zoom function if you set [JPEG Image Size]/[HEIF Image Size] to [M] or [S].

Clear Image Zoom:

Select this setting to use Clear Image Zoom. Even if the zoom range exceeds the optical zoom, the product magnifies images using an image process with less deterioration.

Digital Zoom:

When the zoom range of the Clear Image Zoom is exceeded, the product magnifies images to the largest scale. However, the image quality will deteriorate.

Note

Set [Optical zoom only] if you want to magnify images within the range in which image quality does not deteriorate.

Related Topic

- The zoom features available with this product
- About zoom scale

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Zoom Speed (still image/movie)



Sets the zoom speed when using the custom key to which [Zoom Operation (T)] / [Zoom Operation (W)] is assigned. This can be set separately for shooting standby and movie recording.



 $\textbf{MENU} \to \text{$\lceil \bigcirc \rceil$ (Shooting)} \to \text{$[\textbf{Zoom}]$} \to \text{$[\frac{\square}{\square}]$ Zoom Speed]} \to \text{desired setting item}.$

Menu item details

Fixed Speed STBY:

Sets the zoom speed during shooting standby. (1 (Slow) to 8 (Fast))

Fixed Speed REC:

Sets the zoom speed during movie recording. (1 (Slow) to 8 (Fast))

Hint

- If a high speed is set for [Fixed Speed STBY] and a slow speed is set for [Fixed Speed REC], the angle of view can be changed quickly during shooting standby and slowly during movie recording.
- The [\supseteq Zoom Speed] setting is also applied when performing zoom operations from MENU \rightarrow \bigcirc (Shooting) \rightarrow [Zoom] \rightarrow [Zoom].

Note

- The zoom speed does not change when you operate the zoom ring of the lens or the zoom lever of the power zoom lens.
- If you increase the zoom speed, the sound of zoom operations may be recorded.

Related Topic

Clear Image Zoom/Digital Zoom (Zoom)


Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Zoom Speed (Remote commander) (still image/movie)



Sets the zoom speed when performing zoom operations using the remote commander (sold separately) or the remote shooting function via a smartphone. This can be set separately for shooting standby and movie recording.



Menu item details

Speed Type:

Sets whether or not to lock the zoom speed. ([Variable]/[Fix])

Fixed Speed STBY:

Sets the zoom speed during shooting standby when [a Speed Type] is set to [Fix]. (1 (Slow) to 8 (Fast))

Fixed Speed REC:

Sets the zoom speed during movie recording when [a Speed Type] is set to [Fix]. (1 (Slow) to 8 (Fast))

Hint

- When [a Speed Type] is set to [Variable], pressing the zoom lever on the remote commander will increase the zoom speed (some remote commanders do not support variable zoom).
- If [Speed Type] is set to [Fix], a high speed is set for [Fixed Speed STBY], and a slow speed is set for [Fixed Speed REC], the angle of view can be changed quickly during shooting standby and slowly during movie recording.

Note

If you increase the zoom speed, the sound of zoom operations may be recorded.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

About zoom scale

The zoom scale that is used in combination with the zoom of the lens changes according to the selected image size.

When [Aspect Ratio] is [3:2]

Full size

JPEG Image Size/HEIF Image Size	Optical zoom only (smart zoom)	Clear Image Zoom	Digital Zoom
L: 50M	-	Approx. 2.0×	Approx. 4.0×
M: 21M	Approx. 1.5×	Approx. 3.1×	Approx. 6.2×
S: 12M	Approx. 2.0×	Approx. 4.0×	Approx. 8.0×

APS-C size

JPEG Image Size/HEIF Image Size	Optical zoom only (smart zoom)	Clear Image Zoom	Digital Zoom
M: 21M	-	Approx. 2.0×	Approx. 4.0×
S: 12M	Approx. 1.3×	Approx. 2.6×	Approx. 5.2×

Related Topic

- Clear Image Zoom/Digital Zoom (Zoom)
- The zoom features available with this product
- Zoom Range (still image/movie)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Zoom Ring Rotate



Assigns zoom in (T) or zoom out (W) functions to the zoom ring rotation direction. Available only with power zoom lenses that support this function.



 $MENU \rightarrow \overrightarrow{\text{F--}}$ (Setup) \rightarrow [Operation Customize] \rightarrow [Zoom Ring Rotate] \rightarrow desired setting.

Menu item details

Left(W)/Right(T):

Assigns zoom out (W) function to left-handed rotation and zoom-in (T) function to right-handed rotation.

Right(W)/Left(T):

Assigns zoom in (T) function to left-handed rotation and zoom-out (W) function to right-handed rotation.

Help Guide


Interchangeable Lens Digital Camera ILCE-1 q1

Using flash (sold separately)

In dark environments, use the flash to light up the subject while shooting. Also use the flash to prevent camera-shake.

For details on the flash, refer to the instruction manual for the flash.

1 Attach the flash (sold separately) to the product.



- 2 Shoot after you have turned on the flash and it is fully charged.
 - (Charging flash icon) blinking: Charging is in progress
 - (Charging flash icon) lit up: Charging is finished
 - The available flash modes depend on the shooting mode and function.

Note

- The light of the flash may be blocked if the lens hood is attached and the lower part of a recorded image may be shaded. Remove the lens hood.
- You cannot use the flash when recording movies. (You can use an LED light when using a flash (sold separately) with an LED light.)
- Before attaching/removing an accessory such as a flash to/from the Multi Interface Shoe, turn off the product first. When attaching an accessory, make sure that the accessory is fixed securely to the product.
- Do not use the Multi Interface Shoe with a commercially available flash that applies voltage of 250 V or more or has the reverse polarity of the camera. Doing so may cause a malfunction.
- You can use a flash of the reverse polarity with the Sync Terminal. Please use a flash with a sync voltage of 400 V or less.
- When shooting with the flash and the zoom is set to W, the shadow of the lens may appear on the screen, depending on the shooting conditions. If this happens, shoot away from the subject or set the zoom to T and shoot with the flash again.
- The corners of a recorded image may be shaded, depending on the lens.
- When shooting with an external flash, light and dark stripes may appear on the image if the shutter speed is set to faster than 1/4000 seconds. If this occurs, Sony recommends shooting in the manual flash mode and setting the flash level to 1/2 or higher.
- For details on compatible accessories for the Multi Interface Shoe, visit the Sony website, or consult your Sony dealer or local authorized Sony service facility.

Related Topic

- Flash Mode
- Wireless Flash

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Flash Mode



You can set the flash mode.



Menu item details

Flash Off:

The flash does not operate.

Autoflash:

The flash works in dark environments or when shooting towards bright light.

⋠ Fill-flash:

The flash works every time you trigger the shutter.

\$ Slow Sync.:

The flash works every time you trigger the shutter. Slow sync shooting allows you to shoot a clear image of both the subject and the background by slowing the shutter speed.

Rear Sync.:

The flash works right before the exposure is completed every time you trigger the shutter. Rear sync shooting allows you to shoot a natural image of the trail of a moving subject such as a moving car or a walking person.

Note

- The default setting depends on the shooting mode.
- Some [Flash Mode] settings are not available, depending on the shooting mode.

Related Topic

Using flash (sold separately)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Flash Comp.



Adjusts the amount of flash light in a range of –3.0 EV to +3.0 EV. Flash compensation changes the amount of flash light only. Exposure compensation changes the amount of flash light along with the change of the shutter speed and aperture.



 $MENU \rightarrow$ (Exposure/Color) \rightarrow [Flash] \rightarrow [Flash Comp.] \rightarrow desired setting.

 Selecting higher values (+ side) makes the flash level higher, and lower values (- side) makes the flash level lower.

Note

- [Flash Comp.] does not work when the shooting mode is set to the following modes:
 - [Intelligent Auto]
- The higher flash effect (+ side) may not be visible due to the limited amount of flash light available, if the subject is outside the maximum range of the flash. If the subject is very close, the lower flash effect (- side) may not be visible.
- If you attach an ND filter to the lens or attach a diffuser or a color filter to the flash, the appropriate exposure may not be achieved and images may turn out dark. In this case, adjust [Flash Comp.] to the desired value.

Related Topic

Using flash (sold separately)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Exp.comp.set



Sets whether to apply the exposure compensation value to control both flash light and ambient light, or just ambient light.



 $\textbf{MENU} \rightarrow \ \ \, \textbf{Z} \ \, (\textbf{Exposure/Color}) \rightarrow [\textbf{Flash}] \rightarrow [\textbf{Exp.comp.set}] \rightarrow \textbf{desired setting}.$

Menu item details

Ambient&flash:

Applies the exposure compensation value to control both flash light and ambient light.

Ambient only:

Applies the exposure compensation value to control ambient light only.

Related Topic

Flash Comp.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Wireless Flash



There are two methods for wireless flash shooting: light-signal flash shooting that uses the light of the flash attached to the camera as a signal light, and radio-signal flash shooting that uses wireless communication. To perform radio-signal flash shooting, use a compatible flash or the Wireless Radio Commander (sold separately). For details on how to set each method, refer to the instruction manual of the flash or the Wireless Radio Commander.

- Remove the shoe cap from the camera, and then attach the flash or the Wireless Radio Commander.
 When performing light-signal wireless flash shooting, set the attached flash as the controller.
 - When performing light-signal wireless flash shooting, set the attached flash as the controller.
 When performing radio-signal wireless flash shooting with a flash attached to the camera, set the attached flash as the commander.
- Set up an off-camera flash that is set to wireless mode, or that is attached to the Wireless Radio Receiver (sold separately).
 - You can perform a test flashing by assigning the [Wireless Test Flash] function to a custom key using [Custom Key Setting], and then pressing that key.

Menu item details

Off:

Does not use the wireless flash function.

On:

Uses the wireless flash function to make an external flash or flashes emit light at a distance from the camera.

Note

- The off-camera flash may emit light after receiving a light signal from a flash used as the controller of another camera. If this occurs, change the channel of your flash. For details on how to change the channel, refer to the instruction manual for the flash.
- For the flash that is compatible with wireless flash shooting, visit the Sony website, or consult your Sony dealer or local authorized Sony service facility.

Related Topic

External Flash Set.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Flash Sync Spd. Prty.



When the shooting mode is M (Manual Exposure) or S (Shutter Priority) and you are shooting with the mechanical shutter, this function sets whether or not to give priority to the flash sync speed and expand the high end of the speed range.



 $MENU \rightarrow$ [Flash] \rightarrow [Flash Sync Spd. Prty.] \rightarrow desired setting.

Menu item details

Auto:

Expands the flash sync speed range automatically depending on whether an external flash is attached and on the settings of the camera. The flash sync speed is 1/400 second when shooting in the full-frame size, and 1/500 second when shooting in the APS-C size.

On:

Expands the flash sync speed range. The flash sync speed is 1/400 second when shooting in the full-frame size, and 1/500 second when shooting in the APS-C size.

Off:

Does not expand the flash sync speed range. The flash sync speed is 1/320 second when shooting in the full-frame size, and 1/400 second when shooting in the APS-C size.

About the flash sync speed when the shutter type is the electronic shutter

The flash sync speed when shooting with the electronic shutter is 1/200 second with the full-frame size, and 1/250 seconds when shooting in the APS-C size. When shooting with the electronic shutter, the range of the flash sync speed does not expand.

Hint

■ When the shutter speed is set to the extended flash sync speed, the 🕻 (flash) icon will be displayed with the shutter speed.

Note

- When [Flash Sync Spd. Prty.] is set to [Auto], the flash sync speed range will be expanded only when an external flash is attached to the Multi Interface Shoe. Set [Flash Sync Spd. Prty.] to [On] when you shoot images with a flash attached to the (flash sync) terminal.
- While the flash sync speed range is expanded, the continuous shooting speed may become slower or the shutter sound may become louder.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Red Eye Reduction



When using the flash, it is fired two or more times before shooting to reduce the red-eye phenomenon.



Menu item details

On:

The flash is always fired to reduce the red-eye phenomenon.

Off:

Does not use Red Eye Reduction.

Note

Red Eye Reduction may not produce the desired effects. It depends on individual differences and conditions, such as distance to the subject, or whether the subject looks at the pre-strobe or not.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

FEL lock



The flash level is automatically adjusted so that the subject gets the optimum exposure during normal flash shooting. You can also set the flash level in advance.

FEL: Flash Exposure Level

- MENU → → (Setup) → [Operation Customize] → [Custom Key Setting] → desired button, then assign the [FEL Lock toggle] function to the button.
- 2 Center the subject on which FEL is to be locked, and adjust the focus.



- 3 Press the button to which [FEL Lock toggle] is registered, and set the flash amount.
 - A pre-flash flashes.
 - The ¼L (FEL lock) lights up.
- 4 Adjust the composition and shoot the image.



When you want to release the FEL lock, press the button to which the [FEL Lock toggle] is registered again.

Hint

- By setting [FEL Lock hold], you can hold the setting while the button is pressed down. Also, by setting [FEL Lock/AEL hold] and [FEL Lock/AEL tggle.], you can shoot images with the AE locked in the following situations.
 - When [Flash Mode] is set to [Flash Off] or [Autoflash].
 - When the flash cannot go off.
 - When using an external flash that is set to manual flash mode.

Note

- The FEL lock cannot be set when a flash is not attached.
- If a flash that does not support the FEL lock is attached, an error message is displayed.
- $_{\bullet}$ When both AE and FEL lock are fixed, $^{\bigstar}_{\flat L}$ (AE Lock/FEL Lock) icon lights up.

Related Topic

Assigning frequently used functions to buttons (Custom Key Setting)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

External Flash Set.



You can configure the settings of a flash (sold separately) attached to the camera using the monitor and control wheel of the camera.

Update the software of your flash to the latest version before using this function.

For details on flash functions, refer to the instruction manual for the flash.

- Attach the flash (sold separately) to the Multi Interface Shoe of the camera, and then turn on the camera and the flash.
- 3 Configure the setting using the control wheel of the camera.

Menu item details

Ext. Flash Firing Set .:

Allows you to configure settings related to the firing of the flash, such as the flash mode, flash level, etc.

Ext. Flash Cust. Set.:

Allows you to configure other flash settings, wireless settings, and flash unit settings.

Hint

- If you assign [Ext. Flash Firing Set.] to a desired key using [Custom Key Setting], you can open the [Ext. Flash Firing Set.] screen simply by pressing that key.
- You can adjust settings by operating the flash even while you are using [External Flash Set.].
- You can also configure the settings for a Wireless Radio Commander (sold separately) attached to the camera.

Note

- You can only use [External Flash Set.] to configure the settings of a flash (sold separately) or Wireless Radio Commander (sold separately) manufactured by Sony and attached to the Multi Interface Shoe of the camera.
- You can only use [External Flash Set.] when the flash is attached directly to the camera. You cannot use this function when shooting with an off-camera flash that is connected using a cable.
- Only some of the functions of the attached flash are configurable using [External Flash Set.]. You cannot perform pairing with other flashes, reset the flash, initialize the flash, etc. via [External Flash Set.].
- [External Flash Set.] is unavailable under the following conditions:
 - When the flash is not attached to the camera
 - When a flash that does not support [External Flash Set.] is attached
 - When the mode dial is set to [1] (Movie) or **S&Q** (S&Q Motion), or during movie shooting

Also, [External Flash Set.] may be unavailable depending on the state of the flash.

For details on flashes and Wireless Radio Commanders that are compatible with this function, refer to the following support page. https://www.sony.net/dics/1/

Related Topic

Assigning frequently used functions to buttons (Custom Key Setting)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Using a flash with a sync terminal cord

Hint

- If the screen is too dark to check the composition, set [Live View Display] under [Live View Display Set.] to [Setting Effect OFF] to make it easy to check the composition when shooting with a flash.
- Flashes that have a sync terminal with reversed polarity can be used with this product.

Note

- When shooting with the electronic shutter, you cannot shoot images with a flash that uses the \$\frac{1}{2}\$ (flash sync) terminal.
- Set the exposure mode to manual exposure (other than ISO AUTO is recommended for ISO sensitivity), and set the shutter speed to the slower of the following values or slower:
 - Flash sync speed
 - The shutter speed recommended by the flash.

The flash sync speed varies according to the setting for [Flash Sync Spd. Prty.].

- Use flashes with a sync voltage of 400 V or lower.
- Turn off the flash connected to the sync cord when you connect the sync cord to the **\$** (flash sync) terminal. Otherwise, the flash may emit light when the sync cord is connected.
- The flash power is set by the flash. You cannot set the power from the camera.
- Auto white balance function is not recommended. Use the custom white balance function to achieve a more accurate white balance.
- When a flash is connected to the (flash sync) terminal, the flash indicator will not be displayed.

Related Topic

- Sides
- Live View Display Set.
- Flash Sync Spd. Prty.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Video Light Mode



Sets the illumination setting for the HVL-LBPC LED light (sold separately).



 $MENU \rightarrow \longrightarrow (Setup) \rightarrow [Setup Option] \rightarrow [Video Light Mode] \rightarrow desired setting.$

Menu item details

Power Link:

The video light turns on/off in sync with the ON/OFF operation of this camera.

REC Link:

The video light turns on/off in sync with movie recording start/stop.

REC Link&STBY:

The video light turns on when movie recording starts and dims when not recording (STBY).

Auto:

The video light automatically turns on when it is dark.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

SteadyShot (still image)



Sets whether or not to use the SteadyShot function.



 $\textbf{MENU} \rightarrow \boxed{\bigcirc} \ (\textbf{Shooting}) \rightarrow \textbf{[Image Stabilization]} \rightarrow \textbf{[} \boxed{\bigcirc} \textbf{SteadyShot]} \rightarrow \textbf{desired setting}.$

Menu item details

On:

Uses [SteadyShot].

Off:

Does not use [SteadyShot].

Hint

- When using a tripod, etc., make sure to turn off the SteadyShot function because this can cause any malfunction when shooting.
- If you assign [SteadyShot Select] to a desired key using [Custom Key Setting], you can switch the [SteadyShot] function on or off by pressing the key.
- When shooting in a dark place, the (()) (SteadyShot) icon may blink. We recommend that you set a faster shutter speed by decreasing the aperture value or adjusting the ISO sensitivity to a higher value.

Related Topic

- SteadyShot (movie)
- SteadyShot Adjust. (still image/movie)
- Assigning frequently used functions to buttons (Custom Key Setting)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

SteadyShot (movie)



Sets [SteadyShot] effect when shooting movies.

Menu item details

Active:

Provides a more powerful SteadyShot effect.

Standard:

Reduces camera shake under stable movie shooting conditions.

Off:

Does not use [SteadyShot].

Note

- When using a tripod, etc., make sure to turn off the SteadyShot function because this can cause any malfunction when shooting.
- If you change the setting for [SteadyShot], the angle of view will change. When [SteadyShot] is set to [Active], the angle of view becomes narrower. When the focal length is 200 mm or more, we recommend setting [SteadyShot] to [Standard].
- In the following situations, [Active] cannot be selected:
 - When [File Format] is set to [XAVC HS 8K]
 - For normal movies: when [Rec Frame Rate] is set to [120p]/[100p] or higher

 For slow-motion/quick-motion shooting: when [Stop Frame Rate] is set to [120fps]/[100fps] or higher

Related Topic

- SteadyShot (still image)
- SteadyShot Adjust. (still image/movie)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

SteadyShot Adjust. (still image/movie)



You can shoot with an appropriate SteadyShot setting for the attached lens.



 $MENU \rightarrow \boxed{\bigcirc} \ (Shooting) \rightarrow [Image \ Stabilization] \rightarrow [\boxed{\square} \ SteadyShot \ Adjust.] \rightarrow desired \ setting.$

Menu item details

Auto:

Performs the SteadyShot function automatically according to the information obtained from the attached lens.

Manual:

Performs the SteadyShot function according to the focal-length set using [[Carl (Man) Focal Length]. (8mm-1000mm)

Note

- The SteadyShot function may not work optimally when the power has just been turned on, right after you point the camera towards a subject, or when the shutter button has been pressed all the way down without stopping halfway.
- When the camera cannot obtain focal length information from the lens, the SteadyShot function does not work correctly. Set [SteadyShot Adjust.] to [Manual] and set [() Focal Length] to match the lens you are using. The current set value of the SteadyShot focal length will display to the side of () (SteadyShot) icon.
- When using an SEL16F28 lens (sold separately) with a teleconverter, etc., set [SteadyShot Adjust.] to [Manual] and set the focal length.
- If a lens equipped with a SteadyShot switch is attached, the settings can only be changed using that switch on the lens. You cannot switch the settings using the camera.

Related Topic

SteadyShot focal length (still image/movie)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

SteadyShot focal length (still image/movie)



Sets the focal length information to be used for the built-in SteadyShot function when [SteadyShot Adjust.] is set to [Manual].




 $\textbf{MENU} \rightarrow \boxed{\bigcirc} \ (\textbf{Shooting}) \rightarrow [\textbf{Image Stabilization}] \rightarrow [\boxed{\bigcirc} \ \textbf{(All)}) \ \textbf{Focal Length}] \rightarrow \textbf{desired setting}.$

Menu item details

8mm - 1000mm:

The SteadyShot function uses the focal length that you set.

Check the focal-length index on the lens and set the focal-length.



Related Topic

SteadyShot Adjust. (still image/movie)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Lens Compensation (still image/movie)



Compensates for shading in the corners of the screen or distortion of the screen, or reduces color deviation at the corners of the screen caused by certain lens characteristics.



 $\textbf{MENU} \rightarrow \textbf{[} \bigcirc \textbf{]} \ \, (\textbf{Shooting}) \rightarrow \textbf{[Image Quality]} \rightarrow \textbf{[} \bigcirc \textbf{[} \bigcirc \textbf{Lens Compensation]} \rightarrow \textbf{desired setting}.$

Menu item details

Shading Comp.:

Sets whether to automatically compensate for darkness in the corners of the screen. ([Auto]/[Off])

Chromatic Aberration Comp.:

Sets whether to automatically reduce color deviation at the corners of the screen. ([Auto]/[Off])

Distortion Comp.:

Sets whether to automatically compensate for distortion of the screen. ([Auto]/[Off])

Note

- This function is only available when using an automatic compensation compliant lens.
- Darkness in the corners of the screen may not be corrected with [Shading Comp.], depending on the lens type.
- Depending on the attached lens, [Distortion Comp.] is fixed to [Auto], and you cannot select [Off].
- If [SteadyShot] is set to [Active] in the movie recording mode, [Distortion Comp.] will become locked to [Auto].

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Long Exposure NR



When you set the shutter speed to 1 second(s) or longer (long exposure shooting), noise reduction is turned on for the duration that the shutter is open. With the function turned on, the grainy noise typical of long exposures is reduced.



 $\textbf{MENU} \rightarrow \lceil \bigcirc \rceil \text{ (Shooting)} \rightarrow \textbf{[Image Quality]} \rightarrow \textbf{[Long Exposure NR]} \rightarrow \textbf{desired setting}.$

Menu item details

On:

Activates noise reduction for the same duration that the shutter is open. When noise reduction is in progress, a message appears and you cannot take another picture. Select this to prioritize the image quality.

Off:

Does not activate noise reduction. Select this to prioritize the timing of shooting.

Note

- [Long Exposure NR] is not available when [Shutter Type] is set to [Electronic Shutter].
- Noise reduction may not be activated even if [Long Exposure NR] is set to [On] in the following situations:
 - The drive mode is set to [Cont. Shooting] or [Cont. Bracket].
- [Long Exposure NR] cannot be set to [Off] in the following shooting modes:
 - [Intelligent Auto]

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

High ISO NR



When shooting with high ISO sensitivity, the product reduces noise that becomes more noticeable when the product sensitivity is high.



 $MENU \to \bigcap (Shooting) \to [Image Quality] \to [High ISO NR] \to desired setting.$

Menu item details

Normal:

Activates high ISO noise reduction normally.

Low:

Activates high ISO noise reduction moderately.

Off:

Does not activate high ISO noise reduction.

Note

- [High ISO NR] is fixed to [Normal] in the following shooting modes:
 - [Intelligent Auto]
- When [File Format] is set to [RAW], this function is not available.
- [High ISO NR] does not work for RAW images when the [File Format] is [RAW & JPEG]/[RAW & HEIF].

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Auto Review (still image)



You can check the recorded image on the screen right after the shooting. You can also set the display time for Auto Review.



 $\textbf{MENU} \rightarrow \begin{tabular}{l} \hline \label{eq:menu} \hline \end{tabular} \textbf{MENU} \rightarrow \begin{tabular}{l} \hline \end{tabular} \textbf{(Setup)} \rightarrow \begin{tabular}{l} \hline \end{tabular} \textbf{Display Option]} \rightarrow \begin{tabular}{l} \hline \end{tabular} \textbf{Auto Review]} \rightarrow \begin{tabular}{l} \hline \end{tabular} \textbf{desired setting.}$

Menu item details

10 Sec/5 Sec/2 Sec:

Displays the recorded image on the screen right after shooting for the selected duration of time. If you perform a magnifying operation during Auto Review, you can check that image using the magnified scale.

Off:

Does not display the Auto Review.

Note

- When you use a function that performs image processing, the image before processing may be displayed temporarily, followed by the image after processing.
- The DISP (Display Setting) settings are applied for the Auto Review display.

Related Topic

Enlarging an image being played back (Enlarge Image)

Help Guide

Interchangeable Lens Digital Camera


ILCE-1 α1

Remain Shoot Display (still image)



Sets whether or not to display an indicator of the remaining number of still images that can be continuously shot at the same shooting speed.





Menu item details

Always Display:

Always displays the indicator when shooting still images.

Shoot-Only Display:

During shooting, the remaining number of images that can be shot is always displayed. When you press the shutter button halfway down, the remaining number of images is displayed.

Not Displayed:

Does not display the indicator.

Hint

When the internal camera memory for buffering is full, "SLOW" will be displayed and the continuous shooting speed will decrease.

Related Topic

Cont. Shooting

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Grid Line Display (still image/movie)



Sets whether the grid line is displayed or not during shooting. The grid line will help you to adjust the composition of images.



 $\textbf{MENU} \rightarrow \boxed{\bigcirc} \ \, \textbf{(Shooting)} \rightarrow \boxed{\textbf{Shooting Display}} \rightarrow \boxed{\square} \ \, \textbf{Grid Line Display}] \rightarrow \textbf{desired setting}.$

Menu item details

On:

Displays the grid line.

Off:

Does not display the grid line.

Hint

If you assign [Grid Line Display Select] to a desired key using [Custom Key Setting] or [Custom Key Setting], you can show or hide the grid lines by pressing the assigned key.

Related Topic

- Grid Line Type (still image/movie)
- Assigning frequently used functions to buttons (Custom Key Setting)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Grid Line Type (still image/movie)



Sets the displayed type of grid line. The grid line will help you to adjust the composition of images.



 $\mathsf{MENU} \to \boxed{\bigcirc} \ (\mathsf{Shooting}) \to [\mathsf{Shooting Display}] \to [\boxed{\bigcirc} \ \mathsf{Grid Line Type}] \to \mathsf{desired setting}.$

Menu item details

Rule of 3rds Grid:

Place main subjects close to one of the grid lines that divide the image into thirds for a well-balanced composition.

Square Grid:

Square grids make it easier to confirm the horizontal level of your composition. This is useful for assessing the composition when shooting landscapes, closeups, or when performing camera scanning.

Diag. + Square Grid:

Place a subject on the diagonal line to express an uplifting and powerful feeling.

Hint

If you assign [Grid Line Type] to a desired key using [Custom Key Setting] or [Custom Key Setting], you can switch the type of grid line each time you press the assigned key.

Related Topic

- Grid Line Display (still image/movie)
- Assigning frequently used functions to buttons (Custom Key Setting)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Live View Display Set.



Sets whether or not to show images altered with effects of the exposure compensation, white balance, [Creative Look], etc. on the screen.



 $MENU \rightarrow [\cite{O}\cie{O}\cite{O}\cite{O}\cite{O}\cite{O}\cite{O}\cite{O}\cite{O}\cite$

Menu item details

Live View Display:

Sets whether to reflect all the shooting settings on the monitor and display the Live View in conditions close to what your picture will look like once the settings are applied, or to display the Live View without reflecting the settings. ([Setting Effect ON] / [Setting Effect OFF])

If you select [Setting Effect OFF], you can easily check the composition even when shooting with the image composition on the Live View display.

Exposure Effect:

Sets whether or not to display the Live View with automatic correction by reflecting the exposure from the flash when [Live View Display] is set to [Setting Effect ON]. ([Exposure Set. & flash] / [Exposure Setting Only])

When using the flash for shooting a portrait, select [Exposure Setting Only] to manually set the exposure based on the ambient lighting.

Frame Rate Low Limit:

Sets whether or not to keep the frame rate of the Live View from becoming too slow. ([On] / [Off])

If you select [On], the frame rate of the Live View will not become slow even when shooting in a dark place, but noise may appear on the Live View or the display may become dark. Also, blackout may occur during continuous shooting depending on the shutter speed.

Flash Effect dur Sht.:

Sets whether or not to apply the effect of the flash to the live view display when shooting with the flash. ([Flash Effect ON]/[Flash Effect OFF])

Hint

- When you use a third-party flash, such as a studio flash, Live View Display may be dark for some shutter speed settings. When [Live View Display] is set to [Setting Effect OFF], Live View Display will be displayed brightly, so that you can easily check the composition.
- If you select [Setting Effect OFF], Live View is always displayed with the appropriate brightness even in [Manual Exposure] mode.
- When [Setting Effect OFF] is selected, the VIEW (VIEW) icon is displayed on the Live View screen.

Note

- [Exposure Effect] is effective only when using a flash manufactured by Sony.
- [Live View Display] cannot be set to [Setting Effect OFF] in the following shooting modes:
 - [Intelligent Auto]
 - [Movie]
 - [S&Q Motion]
- When [Live View Display] is set to [Setting Effect OFF], the brightness of the shot image will not be the same as that of the displayed Live View.

0	Even if [Live View Display] is set to [Setting Effect OFF], when you use the electrical shutter, images will look as if your setting	ıgs
	were applied.	

• The setting for [Flash Effect dur Sht.] is applied only when [Shutter Type] is set to [Electronic Shutter].


Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Aperture Preview



While you press and hold the key to which you assigned the [Aperture Preview] function, the aperture is stepped down to the set aperture value and you can check the blurriness prior to shooting.



When shooting still images, confirm the images by pressing the key to which [Aperture Preview] is assigned.

Hint

Although you can change the aperture value during the preview, the subject may be defocused if you select a brighter aperture.
We recommend that you adjust the focus again.

Related Topic

- Assigning frequently used functions to buttons (Custom Key Setting)
- Shot. Result Preview


Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Shot. Result Preview



While pressing down the key to which [Shot. Result Preview] is assigned, you can check the image preview with the DRO, shutter speed, aperture and ISO sensitivity settings applied. Check the shooting result preview before shooting.



When shooting still images, confirm the images by pressing the key to which [Shot. Result Preview] is assigned.

Hint

The DRO settings, shutter speed, aperture and ISO sensitivity settings you have set are reflected on the image for [Shot. Result Preview], but some effects cannot be previewed depending on the shooting settings. Even in that case, the settings you have selected will be applied to the images you shoot.

Related Topic

- Assigning frequently used functions to buttons (Custom Key Setting)
- Aperture Preview

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Bright Monitoring



Allows you to adjust the composition when shooting in dark environments. By extending the exposure time, you can check the composition on the viewfinder/monitor even in dark locations such as under the night sky.

- 1 MENU → → (Setup) → [Operation Customize] → [→ Custom Key Setting] → assign the [Bright Monitoring] function to the desired key.
- In a still image shooting mode, press the key to which you assigned the [Bright Monitoring] function, and then shoot an image.
 - The brightness due to [Bright Monitoring] will continue after shooting.
 - To return the monitor brightness to normal, press the key to which you assigned the [Bright Monitoring] function once again.

Note

- During [Bright Monitoring], [Live View Display] will automatically switch to [Setting Effect OFF], and setting values such as exposure compensation will not be reflected in the live view display. It is recommended that you use [Bright Monitoring] only in dark locations.
- [Bright Monitoring] will be automatically cancelled in the following situations.
 - When the camera is turned off.
 - When the shooting mode is changed from P/A/S/M to a mode that is not P/A/S/M.
 - When the focus mode is set to other than manual focus.
 - When [Auto Magnifier in MF] is executed.
 - When [Focus Magnifier] is selected.
- During [Bright Monitoring], the shutter speed may be slower than normal while shooting in dark locations. Also, because the measured brightness range is expanded, the exposure may change.

Related Topic

Live View Display Set.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Emphasized REC Display



Sets whether or not to display a red frame around the edges of the camera's monitor while recording a movie. You can easily check whether the camera is in standby or recording, even when you are looking at the camera monitor from an angle or at a distance.



 $\textbf{MENU} \rightarrow \textbf{[} \textbf{Shooting)} \rightarrow \textbf{[} \textbf{Shooting Display]} \rightarrow \textbf{[} \textbf{Emphasized REC Display]} \rightarrow \textbf{desired setting.}$

Menu item details

On:

Displays a red frame to indicate that recording is in progress.

Off:

Does not display a frame to indicate that recording is in progress.

Hint

The frame displayed by this function can also be output to an external monitor connected via HDMI. Set [HDMI Info. Display] to [On].

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Marker Display



While shooting movies, you can set whether or not to display markers on the monitor or the viewfinder, and select the types of marker.



 $MENU \rightarrow [\bigcirc]$ (Shooting) \rightarrow [Marker Display] \rightarrow Select a menu item and set the desired parameter.

Menu item details

Marker Display:

Sets whether or not to display markers. ([On] / [Off])

Center Marker:

Sets whether or not to display the center marker in the middle of the shooting screen. ([Off] / [On])

Aspect Marker:

Sets the aspect marker display. ([Off] / [4:3] / [13:9] / [14:9] / [15:9] / [1.66:1] / [1.85:1] / [2.35:1])

Safety Zone:

Sets the safety zone display. This becomes the standard range that can be received by a general household TV. ([Off] / [80%] / [90%])

Guideframe:

Sets whether or not to display the guide frame. You can verify whether the subject is level or perpendicular to the ground. ([Off] / [On])

Hint

- You can display several markers at the same time.
- Position the subject at the cross point of [Guideframe] to ensure a balanced composition.

Note

- The markers are displayed when the mode dial is set to ☐ (Movie) or \$&Q (S&Q Motion), or when shooting movies.
- You cannot display markers when using [Focus Magnifier].
- The markers are displayed on the monitor or viewfinder. (You cannot output the markers.)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Gamma Display Assist



Movies with S-Log gamma are assumed to be processed after shooting in order to make use of the wide dynamic range. Images with the HLG gamma are assumed to be displayed on HDR-compatible monitors. They are therefore displayed in low contrast during shooting, and may be difficult to monitor. However, you can use the [Gamma Display Assist] function to reproduce contrast equivalent to that of normal gamma. In addition, [Gamma Display Assist] can also be applied when playing back movies on the camera's monitor/viewfinder.



 $\textbf{MENU} \rightarrow \begin{tabular}{l} \hline \textbf{ASSIST} \\ \hline \end{tabular} \rightarrow \begin{tabular}{l} \hline \textbf{Display Option} \\ \hline \end{tabular} \rightarrow \begin{tabular}{l} \hline \textbf{Gamma Display Assist} \\ \hline \end{tabular} \rightarrow \begin{tabular}{l} \hline \textbf{desired setting.} \\ \hline \end{tabular}$

Menu item details

On:

Uses the gamma display assist function.

Off:

Does not use the gamma display assist function.

Hint

If you assign [Gamma Disp. Assist Sel.] to a desired key using [Custom Key Setting], [Custom Key Setting], you can turn the gamma display assist function on or off by pressing the assigned key.

Note

[Gamma Display Assist] is not applied to movies when displayed on a TV or monitor connected to the camera.

Related Topic

- Picture Profile (still image/movie)
- Gamma Disp. Assist Typ.
- HLG Still Image

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Gamma Disp. Assist Typ.



Selects the conversion type for [Gamma Display Assist].



Menu item details

Assist Auto:

- Displays images with effects as follows according to the gamma or color mode set in [Picture Profile].
 - When the gamma is set to [S-Log2]: [S-Log2→709(800%)]
 - When the gamma is set to [S-Log3]: [S-Log3→709(800%)]
 - When the gamma is set to [HLG], [HLG1], [HLG2], or [HLG3], and the color mode is set to [BT.2020]: [HLG(BT.2020)]
 - When the gamma is set to [HLG], [HLG1], [HLG2], or [HLG3], and the color mode is set to [709]: [HLG(709)]
- Displays images with an [HLG(BT.2020)] effect when shooting HLG still images with [HLG Still Image] set to [On].
- Displays images with an [S-Log3→709(800%)] effect when outputting RAW movies to another device connected via HDMI during movie shooting.

Assist S-Log2→709(800%):

Displays images with an S-Log2 gamma reproducing contrast equivalent to ITU709 (800%).

Assist S-Log3→709(800%):

Displays images with an S-Log3 gamma reproducing contrast equivalent to ITU709 (800%).

Assist HLG(BT.2020):

Displays images after adjusting the image quality of the monitor or viewfinder to a quality that is almost the same as when images are displayed on an [HLG(BT.2020)] compatible monitor.

Assist HLG(709):

Displays images after adjusting the image quality of the monitor or viewfinder to a quality that is almost the same as when images are displayed on an [HLG(709)] compatible monitor.

Hint

■ If you assign [Gamma Disp. Assist Typ.] to a desired key using [Custom Key Setting] or [Custom Key Setting], you can switch the [Gamma Disp. Assist Typ.] setting each time you press the assigned key.

Note

- When [Gamma Display Assist] is set to [Auto] during playback, an effect is applied to the image as follows:
 - When playing back a movie recorded with [HLG], [HLG1], [HLG2], or [HLG3]: Displays the image with an [HLG(BT.2020)] or [HLG(709)] effect depending on the color mode.
 - When playing back an HLG still image shot with [HLG Still Image] set to [On]: Displays the image with an [HLG(BT.2020)] effect
 - When playing back a RAW movie output to another device connected via HDMI: Displays the image with an [S-Log3→709(800%)] effect.

In other situations, movies are displayed according to the gamma setting and color mode setting in [Picture Profile].

Related Topic

- Gamma Display Assist
- Picture Profile (still image/movie)
- HDMI Output Settings (movie)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Audio Recording



Sets whether to record sounds when shooting movies. Select [Off] to avoid recording the sounds of the lens and the camera operating.



 $\textbf{MENU} \rightarrow \boxed{\bigcirc} \ \, (\textbf{Shooting}) \rightarrow [\textbf{Audio Recording}] \rightarrow [\textbf{Audio Recording}] \rightarrow \textbf{desired setting}.$

Menu item details

On:

Records sound.

Off:

Does not record sound.

Related Topic

Audio Rec Level

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Audio Rec Level



You can adjust the audio recording level while checking the level meter.



2 Select the desired level using the right/left sides of the control wheel.

Menu item details

+:

Turns up the audio recording level.

-:

Turns down the audio recording level.

Hint

- When you record audio movies with loud volumes, set [Audio Rec Level] to a lower sound level. Doing so enables you to record more realistic audio. When you record audio movies with lower volumes, set [Audio Rec Level] to a greater sound level to make the sound easier to hear.
- To reset the audio recording level to the default setting, press the
 (Delete) button.

Note

- Regardless of the [Audio Rec Level] settings, the limiter always operates.
- [Audio Rec Level] is available only when the shooting mode is set to movie mode.
- [Audio Rec Level] is unavailable during slow-motion/quick-motion shooting.
- The [Audio Rec Level] settings are applied for both the internal microphone and the \(^\bigcup_\) (microphone) terminal input.
- The setting for [Audio Rec Level] does not apply to recordings made using [Voice Memo].

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Audio Out Timing



You can set echo cancellation during audio monitoring and prevent undesirable deviations between video and audio during HDMI output.



 $\textbf{MENU} \rightarrow \textbf{[O]} \ (\textbf{Shooting}) \rightarrow \textbf{[Audio Recording]} \rightarrow \textbf{[Audio Out Timing]} \rightarrow \textbf{desired setting}.$

Menu item details

Livo:

Outputs audio without delay. Select this setting when audio deviation is a problem during audio monitoring.

Lip Sync:

Outputs audio and video in sync. Select this setting to prevent undesirable deviations between video and audio.

Note

Using an external microphone may result in a slight delay. For details, refer to the operating instructions supplied with the microphone.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Wind Noise Reduct.



Sets whether or not to reduce wind noise by cutting the low-range sound of the input audio from the built-in microphone.



 $MENU \rightarrow [\bigcirc]$ (Shooting) \rightarrow [Audio Recording] \rightarrow [Wind Noise Reduct.] \rightarrow desired setting.

Menu item details

On:

Reduces wind noise.

Off:

Does not reduce wind noise.

Note

- Setting this item to [On] where wind is not blowing sufficiently hard may cause normal sound to be recorded with too low volume.
- When an external microphone (sold separately) is used, [Wind Noise Reduct.] does not function.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Shoe Audio Set.



Sets the digital audio transmitted from a microphone (sold separately) attached to the multi-interface shoe of the camera. Use a microphone that supports the digital audio interface. You can set the sampling frequency, the number of quantization bits, and the number of channels.



 $\mathsf{MENU} \to \boxed{\bigcirc} \ (\mathsf{Shooting}) \to [\mathsf{Audio}\ \mathsf{Recording}] \to [\boxed{\phantom{\mathsf{Audio}}} \ \mathsf{Shoe}\ \mathsf{Audio}\ \mathsf{Set.}] \to \mathsf{desired}\ \mathsf{setting}.$

Menu item details

48khz/24bit 4ch

Sets the sampling frequency of audio input to 48 kHz, the number of quantization bits to 24 bits, and the number of channels to 4.

48khz/24bit 2ch

Sets the sampling frequency of audio input to 48 kHz, the number of quantization bits to 24 bits, and the number of channels to 2.

48khz/16bit 2ch

Sets the sampling frequency of audio input to 48 kHz, the number of quantization bits to 16 bits, and the number of channels to 2.

Hint

The audio level display on the monitor is for 4 channels during 4-channel audio recording.

Note

- When an external microphone (sold separately) is connected to the \(\bigcirc\) (microphone) terminal of the camera, the audio is recorded from the external microphone attached to the \(\bigcirc\) (microphone) terminal. You cannot set [\(\bigcirc\) Shoe Audio Set.].
- If the attached microphone is set to analog transmission, you cannot set [Shoe Audio Set.].
- When the attached microphone does not support 4-channel audio recording, you cannot select [48khz/24bit 4ch] (48khz/24bit 4ch).
- When the attached microphone does not support 24-bit audio recording, [Shoe Audio Set.] becomes locked to [48khz/16bit 2ch] (48khz/16bit 2ch).
- Audio cannot be recorded correctly in the following situations during movie recording:
 - When you attach or remove the microphone
 - When digital transmission is switched to analog transmission or vice versa on the microphone side

Related Topic

4ch Audio Monitoring (movie)


Help Guide


Interchangeable Lens Digital Camera ILCE-1 α 1

Audio Level Display



Sets whether to display the audio level on the screen.





Menu item details

On:

Displays the audio level.

Off:

Does not display the audio level.

Note

- The audio level is not displayed in the following situations:
 - When [Audio Recording] is set to [Off].
 - When DISP (Display Setting) is set to [No Disp. Info.].
 - During slow-motion/quick-motion shooting
- The audio level is also displayed while shooting stand-by in movie recording mode.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

TC/UB



The time code (TC) and the user bit (UB) information can be recorded as data attached to movies.



 $MENU \rightarrow [\color{o}]$ (Shooting) \rightarrow [TC/UB] \rightarrow Select a menu item and set the desired parameter.

Menu item details

Time Code Preset:

Sets the time code.

User Bit Preset:

Sets the user bit.

Time Code Format:

Sets the recording method for the time code. (Only when [NTSC/PAL Selector] is set to NTSC.)

Time Code Run:

Sets the count up format for the time code.

Time Code Make:

Sets the recording format for the time code on the recording medium.

User Bit Time Rec:

Sets whether or not to record the time as a user bit.

How to set the time code (Time Code Preset)

- 1. MENU \rightarrow [\bigcirc] (Shooting) \rightarrow [TC/UB] \rightarrow [Time Code Preset].
- 2. Turn the control wheel and select the first two digits.
 - The time code can be set between the following range.

When [60p] is selected: 00:00:00.00 to 23:59:59.29

- * When [24p] is selected, you can select the last two digits of the time code in multiples of four from 00 to 23 frames. When [50p] is selected: 00:00:00.00 to 23:59:59.24
- 3. Set the other digits following the same procedure as in step 2, then press in the center of the control wheel.

How to reset the time code

- 1. $MENU \rightarrow \bigcirc$ (Shooting) \rightarrow [TC/UB] \rightarrow [Time Code Preset].
- 2. Press the (Delete) button to reset the time code (00:00:00.00).

How to set the user bit (User Bit Preset)

- 1. MENU \rightarrow [\bigcirc] (Shooting) \rightarrow [TC/UB] \rightarrow [User Bit Preset].
- 2. Turn the control wheel and select the first two digits.
- 3. Set the other digits following the same procedure as in step 2, then press in the center of the control wheel.

How to reset the user bit

- How to select the recording method for the time code (Time Code Format *1)

1. $MENU \rightarrow \bigcirc$ (Shooting) \rightarrow [TC/UB] \rightarrow [Time Code Format].

DF:

Records the time code in Drop Frame*2 format.

NDF:

Records the time code in Non-Drop Frame format.

- *1 Only when [NTSC/PAL Selector] is set to NTSC.
- *2 The time code is based on 30 frames per second. However, a gap between the actual time and the time code will occur during extended periods of recording as the frame frequency of the NTSC image signal is approximately 29.97 frames per second. Drop frame corrects this gap to make the time code and actual time equal. In drop frame, the first 2 frame numbers are removed every minute except for every tenth minute. The time code without this correction is called non-drop frame.
 - The setting is fixed to [-] when recording in 4K/24p or 1080/24p.

How to select the count up format for the time code (Time Code Run)

1. MENU \rightarrow [\bigcirc] (Shooting) \rightarrow [TC/UB] \rightarrow [Time Code Run].

Rec Run:

Sets the stepping mode for the time code to advance only while recording. The time code is recorded sequentially from the last time code of the previous recording.

Free Run:

Sets the stepping mode for the time code to advance anytime, regardless of the camera operation.

- The time code may not be recorded sequentially in the following situations even when the time code advances in [Rec Run] mode.
 - When the recording format is changed.
 - When the recording medium is removed.

How to select how the time code is recorded (Time Code Make)

1. $MENU \rightarrow \bigcirc$ (Shooting) \rightarrow [TC/UB] \rightarrow [Time Code Make].

Preset:

Records the newly set time code on the recording medium.

Regenerate:

Reads the last time code for the previous recording from the recording medium and records the new time code consecutively from the last time code. The time code advances in the [Rec Run] mode regardless of the [Time Code Run] setting.

The time code is read from the memory card in the slot designated by [Recording Media] under [Rec. Media Settings]. When [Recording Media] is set to [Simult. Recording], the time code is read from the memory card in Slot 1.

Related Topic

TC/UB Disp. Setting

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α1

TC/UB Disp. Setting



Sets the display of the recording time counter, time code (TC), and user bit (UB) for movies.



1 MENU → \longrightarrow (Setup) → [Display Option] → [TC/UB Disp. Setting] → desired setting.

Menu item details

Counter:

Displays the time counter of movie recording.

TC:

Displays the time code.

U-Bit:

Displays the user bit.

Related Topic

TC/UB

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Contents of this chapter

The following table of contents lists the features described in this chapter ("Customizing the camera"). From each item name, you can jump to the page describing the respective functions.

Customization features of the camera

Assigning frequently used functions to buttons (Custom Key Setting)

Changing the function of the dial temporarily (My Dial Settings)

Registering and recalling camera settings

- Camera Set. Memory
- Recall Camera Setting
- Memory/Recall Media
- Registering shooting settings to a custom key (Reg. Custom Shoot Set)

Registering frequently used functions to the function menu

Fn Menu Settings

Registering frequently used functions to My Menu

- Add Item
- Sort Item
- Delete Item
- Delete Page
- Delete All
- Display From My Menu

Separately adjusting the camera settings for still images and movies

Different Set for Still/Mv

Customizing the functions of the ring/dial

- Av/Tv Assign in M
- Av/Tv Rotate
- Function Ring(Lens)
- Lock Operation Parts

Recording movies by pressing the shutter button

REC w/ Shutter (movie)

Monitor/viewfinder settings

- Select Finder/Monitor
- DISP (Screen Disp) Set (Monitor/Finder)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1


Customization features of the camera

The camera has various customization features such as registration of functions and shooting settings to custom keys. You can combine your preferred settings to customize the camera for easier operation.

For details on how to configure the settings and use them, refer to the page for each function.


To assign frequently used functions to buttons (Custom Key Setting/ Custom Key Setting/ Custom Key Setting)

You can change the functions of the buttons including the Custom Buttons (C1 to C4) according to your preferences. It is recommended that you assign frequently used functions to easily operable buttons so that you can call up the assigned functions simply by pressing the corresponding button.



To register frequently used functions to the Fn button (Function menu)

If you register functions frequently used in the shooting mode to the Function menu, you can display the registered functions on the screen simply by pressing the Fn (Function) button. On the Function menu screen, you can recall the function you want to use by selecting the icons.




To combine frequently used functions on the menu screen (☆ My Menu)

If you combine the frequently used items from menus such as the shooting and network menu on the "My Menu" screen, you can quickly access the desired menu items.



To assign different functions to the dial and switch the function of the dial (📭 My Dial Settings)

You can assign the desired functions to the front/rear dial and the control wheel, and register up to three combinations of settings to the camera as "My Dial 1 - 3" settings.



Example: [My Dial Settings] screen for models with a front/rear dial

To change the shooting settings quickly according to the scene (MR Camera Set. Memory)

You can register the appropriate shooting settings* for scene to the camera or a memory card, and call up the settings easily by using the mode dial, etc.

You can register the appropriate shooting settings* for scene to the camera or a memory card, and call up the settings easily by using the MODE (Mode) button.

* You cannot register custom key settings.

To save the customized camera settings to a memory card (Save/Load Settings)

You can save camera settings* to a memory card using [Save/Load Settings]. This function is useful when you want to back up the settings, or to import the settings to another camera of the same model, etc.

* Some settings cannot be saved on a memory card.

Related Topic

- Assigning frequently used functions to buttons (Custom Key Setting)
- Using the Fn (Function) button
- Add Item
- Changing the function of the dial temporarily (My Dial Settings)
- Camera Set. Memory
- Save/Load Settings

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α1

Assigning frequently used functions to buttons (Custom Key Setting)




You can use the custom key function to assign the functions you use most frequently to easily operable keys. This lets you skip the process of selecting items from MENU, so you can recall the functions more quickly.

You can separately assign functions to custom keys for the still image shooting mode, movie shooting mode, and playback mode.

Assignable functions vary depending on the keys.


You can assign functions to the following keys.





- 1. AF-ON Button
- 2. Custom Button 3
- 3. MOVIE Button
- 4. Custom Button 2
- 5. Custom Button 1
- 6. Rear dial
- 7. AEL Button
- 8. Center Button
- 9. Control Wheel/Left Button/Right Button/Down Button
- 10. Custom Button 4
- 11. Multi-Slc Center Btn
- 12. Fn/ 🔁 Button
- 13. ## Front dial

The following is the procedure for assigning the [Eye AF] function to the AEL button.



 $MENU \rightarrow \longrightarrow (Setup) \rightarrow [Operation Customize] \rightarrow [\longrightarrow Custom Key Setting].$

• If you want to assign a function to recall while shooting movies, select [Custom Key Setting]. If you want to assign a function to recall while playing back images, select [Custom Key Setting].

- 2
 - Move to the [Rear1] screen using the top/bottom side of the control wheel. Then, select [AEL Button] and press the center of the control wheel.
- 3
- Select [Eye AF] using the top/bottom/left/right side of the control wheel, and then press the center.
 - If you press the AEL button while shooting and eyes are detected, [Eye AF] will activate and the camera will focus on the eyes. Shoot images while holding down the AEL button.

Hint

You can also assign shooting functions to the focus hold button on the lens. However, some lenses do not have a focus hold button.

Related Topic

- Changing the function of the dial temporarily (My Dial Settings)
- Fn Menu Settings

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Changing the function of the dial temporarily (My Dial Settings)



You can assign the desired functions to the front dial, rear dial, and control wheel, and register up to three combinations of settings as "My Dial" settings. You can quickly recall or switch registered "My Dial" settings by pressing the custom key you assigned in advance.

Registering functions to "My Dial"

Register the functions that you want to assign to the front dial, the rear dial, and the control wheel as [My Dial 1] through [My Dial 3].

- 1. $MENU \rightarrow \overrightarrow{\text{f-}}$ (Setup) \rightarrow [Dial Customize] \rightarrow [My Dial Settings].
- Select a dial or wheel for \$\frac{1}{2}\$ (My Dial 1), and press the center of the control wheel.
- Select the desired function to assign using the top/bottom/left/right sides of the control wheel, and then press the center of the control wheel.
 - Select "--" (Not set) for a dial or wheel to which you do not want to assign any function.
- 4. After you select functions for all of the dials and the wheel in \P (My Dial 1) by repeating Steps 2 and 3, select [OK]. The settings for \P (My Dial 1) will be registered.
 - If you want to register ♠ (My Dial 2) and ♠ (My Dial 3) as well, follow the same procedure as described above.

Assigning a key to recall "My Dial"

Assign a custom key to recall the registered "My Dial" settings.

- Select the number of the "My Dial" setting that you want to recall or the pattern for switching "My Dial."

Menu item details

My Dial 1 during Hold /My Dial 2 during Hold/My Dial 3 during Hold:

While you hold down the key, the functions that you registered in [My Dial Settings] are assigned to the dial/wheel.

My Dial $1\rightarrow2\rightarrow3$:

Each time you press the key, the function changes in the following sequence: "Normal function \rightarrow Function of My Dial 1 \rightarrow Function of My Dial 2 \rightarrow Function of My Dial 3 \rightarrow Normal function."

Toggle My Dial 1 /Toggle My Dial 2/Toggle My Dial 3:

The function registered using [My Dial Settings] is maintained even if you do not hold down the key. Press the key again to return to the normal function.

Shooting while switching "My Dial"

During shooting, you can recall "My Dial" using the custom key, and shoot as you change the shooting setting by turning the front dial, the rear dial, and the control wheel.

In the following example, the functions listed below are registered to "My Dial," and [My Dial $1\rightarrow2\rightarrow3$] is assigned to the C1 (Custom 1) button.

Operation part	My Dial 1	My Dial 2	My Dial 3
Control wheel	₽ ISO	White Balance	Not set
Front dial	Aperture	Creative Look	Move AF Frame ←→ : Std
Rear dial	Shutter Speed	Exposure Comp.	Move AF Frame 🛟 : Std

1. Press the C1 (Custom1) button.

The functions registered to [My Dial 1] will be assigned to the control wheel, the front dial, and the rear dial.

• The icons for the functions registered to [My Dial 1] are displayed in the lower part of the screen.



- 2. Turn the control wheel to set the ISO value, turn the front dial to set the aperture value, and turn the rear dial to set the shutter speed.
- 3. Press the C1 button again. The functions registered to [My Dial 2] will be assigned to the control wheel, the front dial, and the rear dial.
- 4. Turn the control wheel to set [White Balance], turn the front dial to set [Creative Look], and turn the rear dial to set [Exposure Comp.].
- 5. Press the C1 button again, and change the setting values for the functions registered to [My Dial 3].
- 6. Press the shutter button to shoot.

Note

- "My Dial" settings in which every dial/wheel is set to [Not set] are not recalled when you press the custom key. They are also skipped in [My Dial 1→2→3].
- Even if a dial/wheel has been locked using the [Lock Operation Parts] function, it will be unlocked temporarily when "My Dial" is recalled.

Related Topic

Assigning frequently used functions to buttons (Custom Key Setting)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Camera Set. Memory



Allows you to register up to 3 often-used modes or product settings to the product and up to 4 (M1 through M4) to the memory card. You can recall the settings using just the mode dial.

- 1 Set the product to the setting you want to register.
- igotimes MENU ightarrow igotimes (Shooting) ightarrow [Shooting Mode] ightarrow [igotimes Camera Set. Memory] ightarrow desired number.
- Press the center of the control wheel to confirm.

Items that can be registered

- You can register various functions for shooting. The items that can actually be registered are displayed on the menu
 of the camera.
- Aperture (F number)
- Shutter speed

To change registered settings

Change the setting to the desired one and re-register the setting to the same mode number.

Note

- M1 through M4 can be selected only when a memory card is inserted into the product.
- When registering the settings on a memory card, only a memory card that has been selected using [MR Memory/Recall Media] can be used.
- Program Shift cannot be registered.
- For some functions, the position of the dial and the setting actually used for shooting may not match. If this happens, shoot images by referring to the information displayed on the monitor.

Related Topic

- Recall Camera Setting
- Memory/Recall Media

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Recall Camera Setting



Allows you to shoot an image after recalling your preferred shooting settings registered with [MR Camera Set. Memory].

Set the mode dial to 1, 2, or 3 (MR Recall Camera Setting).

Press the center of the control wheel to confirm.

You can also recall registered modes or settings by selecting MENU → (Shooting) → [Shooting Mode] → [MR Recall Camera Setting].

Hint

- To recall settings registered to the memory card, set the mode dial to 1, 2, 3 (MR Recall Camera Setting), then select the desired number by pressing the left/right side of the control wheel.
- If you recall settings registered to the memory card, the settings are recalled from the memory card in the slot specified in [MR Memory/Recall Media]. You can confirm the memory card slot by selecting MENU → [O] (Shooting) → [Shooting Mode] → [MR Memory/Recall Media].
- Settings registered to a memory card using another camera of the same model name can be recalled with this camera.

Note

- If you set [MR Recall Camera Setting] after completing the shooting settings, the registered settings are given priority and the original settings may become invalid. Check the indicators on the screen before shooting.
- If the slot to which images are recorded is set to change, the shooting settings will not be applied until writing to the memory card is complete even when the mode dial is set to 1/2/3.

Related Topic

- Camera Set. Memory
- Memory/Recall Media

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Memory/Recall Media



Selects the memory card slot from which settings are recalled or to which settings are registered for M1 through M4.



 $MENU \rightarrow [\bigcirc]$ (Shooting) \rightarrow [Shooting Mode] \rightarrow [MR Memory/Recall Media] \rightarrow desired slot.

Menu item details

Slot 1:

Selects the slot 1.

Slot 2:

Selects the slot 2.

Related Topic

- Camera Set. Memory
- Recall Camera Setting

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Registering shooting settings to a custom key (Reg. Custom Shoot Set)



You can register shooting settings (such as exposure, focus setting, drive mode, etc.) to a custom key in advance and temporarily recall them while holding down the key. Simply press the custom key to switch the settings quickly and release the key to go back to the original settings. This function is useful when recording active scenes such as sports.

MENU → [o] (Shooting) → [Shooting Mode] → [Reg. Custom Shoot Set] → Select a registration number from [Recall Custom hold 1] to [Recall Custom hold 3].

The setting screen for the selected number will be displayed.

- Using the top/bottom/left/right side of the control wheel, select the check boxes for the functions that you want to recall with one of the registration numbers and press the center to check each box.
 - A \checkmark (check) mark will be displayed in the boxes for the functions.
 - To cancel a selection, press the center again.
- Select the function that you want to adjust using the top/bottom/left/right side of the control wheel, and press the center to adjust the function to the desired setting.
 - Select [Import Current Setting] to register the current settings of the camera to the registration number that you chose.
- 4 Select [Register].

Items that can be registered

- You can register various functions for shooting. The items that can actually be registered are displayed on the menu
 of the camera.
- Exposure
- Focus setting
- Drive mode (other than self-timer)

To recall registered settings

- 1. MENU → (Setup) → [Operation Customize] → [Custom Key Setting] → Select the desired key and then select one of the registration numbers from [Recall Custom hold 1] to [Recall Custom hold 3].
- 2. On the shooting screen, press the shutter button while holding down the key to which you assigned one of the registration numbers.

The registered settings are activated while you are holding down the custom key.

Hint

You can change the settings for [Reg. Custom Shoot Set] after assigning one of the registration numbers to the custom key using [MCustom Key Setting].

Note

- The registration numbers [Recall Custom hold 1] through [Recall Custom hold 3] are available only when the shooting mode is set to P/A/S/M.
- Depending on the attached lens and the status of the camera when the registered setting recall is executed, the registered settings may not take effect.

Related Topic

Assigning frequently used functions to buttons (Custom Key Setting)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Fn Menu Settings



The Function menu is a menu of 12 functions that is displayed at the bottom of the screen when you press the Fn (Function) button in the shooting mode.

You can register 12 functions to the Function menus for still image shooting and movie shooting, respectively.

The following is the procedure for changing [Drive Mode] in the still image function menu to [Grid Line Display].

- To change the movie function menu, select a movie function menu item in Step 2.
- Select 🐧 🖳 (Drive Mode) from among the 12 still image function menu items using the top/bottom/left/right side of the control wheel, and then press the center.
- Move to the screen showing [Grid Line Display] using the left/right side of the control wheel. Then, select [Grid Line Display] and press the center of the control wheel.
 - Grid Line Display) will be displayed in the former location of 🐧 🖳 (Drive Mode) in the Function menu.

Related Topic

Using the Fn (Function) button

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Add Item



You can register the desired menu items to $\frac{1}{2}$ (My Menu) under MENU.

- **1** MENU $\rightarrow \stackrel{\wedge}{\swarrow}$ (My Menu) \rightarrow [My Menu Setting] \rightarrow [Add Item].
- Select an item that you want to add to can (My Menu) using the top/bottom/left/right sides of the control wheel.
- 3 Select a destination using the top/bottom/left/right sides of the control wheel.

Hint

 $_{\bullet}$ You can add up to 42 items to $\; \frac{\wedge}{\swarrow} \;$ (My Menu).

Note

- You cannot add the following items to ☆ (My Menu).
 - Any item under MENU \rightarrow \blacktriangleright (Playback)

Related Topic

- Sort Item
- Delete Item
- Using the MENU button

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Sort Item



You can rearrange the menu items added to $\mbox{$$

- Select an item that you want to move using the top/bottom/left/right sides of the control wheel.
- 3 Select a destination using the top/bottom/left/right sides of the control wheel.

Related Topic

Add Item

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Delete Item



You can delete menu items added to \swarrow (My Menu) of MENU.

- 2 Select an item that you want to delete using the top/bottom/left/right sides of the control wheel, and then press the center to delete the selected item.

Hint

- To delete all the items on a page, select MENU $\rightarrow \checkmark$ (My Menu) \rightarrow [My Menu Setting] \rightarrow [Delete Page].

Related Topic

- Delete Page
- Delete All
- Add Item

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Delete Page



You can delete all the menu items added to a page under $\[\swarrow \]$ (My Menu) in MENU.

- 2 Select a page that you want to delete using the left/right sides of the control wheel, and then press the center of the control wheel to delete the items.

Related Topic

- Delete All
- Add Item


Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Delete All



You can delete all the menu items added to $\, \swarrow \,$ (My Menu) in MENU.



2 Select [OK].

Related Topic

- Delete Page
- Add Item

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Display From My Menu



You can set My Menu to appear first when you press the MENU button.



 $MENU \rightarrow \checkmark$ (My Menu) \rightarrow [My Menu Setting] \rightarrow [Display From My Menu] \rightarrow desired setting.

Menu item details

On:

My Menu appears first when you press the MENU button.

Off:

The most recently displayed menu appears when you press the MENU button.

Related Topic

- Add Item
- Using the MENU button

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Different Set for Still/Mv



For each item in still image shooting and movie recording, you can select whether to use a common setting or separate settings.



The operation guide screen will appear. Select [OK] to display the setting screen.

- Add check marks to the items that you want to set separately for still image shooting and movie recording, and then select [OK].
 - You can set the following items separately for still image shooting and movie recording.
 - Aperture
 - Shutter Speed
 - ISO
 - Exposure Comp.
 - Metering Mode
 - White Balance
 - Picture Profile

Hint

- When you switch from a common setting to separate settings with [Different Set for Still/Mv], the current settings are applied to both still image shooting and movie recording. However, the custom white balance setting is only applied to still image shooting.
- When you switch from separate settings to a common setting with [Different Set for Still/Mv], the setting values of items return to their initial values. As an exception, the setting values for still image shooting are applied to the aperture value, shutter speed, and custom white balance settings.

Note

Even if you add a check mark to [Exposure Comp.], the exposure compensation value will be simultaneously changed for both still image shooting and movie recording when you change the exposure compensation value with the exposure compensation dial.

Help Guide


Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Av/Tv Assign in M




When the shooting mode is set to "M", you can switch the functions of the front/rear dial.

This function is available when the [Aperture/Shutter Speed] function is assigned to the front/rear dial.



Menu item details



The front dial is used to change the shutter speed and the rear dial to change the aperture value.



The front dial is used to change the aperture value and the rear dial to change the shutter speed.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Av/Tv Rotate



Sets the direction of rotation for the front dial, rear dial, or control wheel when changing the aperture value or shutter speed.



 $\textbf{MENU} \rightarrow \begin{tabular}{l} \hline \textbf{AV/TV Rotate} \\ \hline \end{tabular} \rightarrow \begin{tabular}{l} \hline \textbf{AV/TV Rotate} \\$

Menu item details

Normal:

Does not change the direction of rotation for the front dial, rear dial, or control wheel.

Reverse:

Reverses the direction of rotation for the front dial, rear dial, or control wheel.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Function Ring(Lens)



You can choose which of the following functions to assign to the function ring on the lens: power-assisted focusing (power focus), or switching the angle of view between full frame and APS-C/Super 35 mm (available only with compatible lenses).

For details, refer to the operating instructions supplied with the lens.



 $\textbf{MENU} \rightarrow \overrightarrow{\textbf{foo}} \hspace{0.1cm} (\textbf{Setup}) \rightarrow [\textbf{Dial Customize}] \rightarrow [\textbf{Function Ring(Lens)}] \rightarrow \textbf{desired setting}.$

Menu item details

Power Focus:

The focusing position moves toward infinity when you turn the function ring to the right. The focusing position moves to the closer range when you turn the function ring to the left.

APS.(535/Full Frame:

The angle of view switches between full frame and APS-C/Super 35 mm when the function ring is turned.

The angle of view switches regardless of the direction in which you turn the function ring.

Related Topic

APS-C S35 (Super 35mm) Shooting (still image/movie)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Lock Operation Parts



You can set whether the multi-selector, dials, and wheel can be locked by pressing and holding down the Fn (Function) button.



 $MENU \rightarrow \longrightarrow (Setup) \rightarrow [Dial Customize] \rightarrow [Lock Operation Parts] \rightarrow desired setting.$

To lock the operating parts, hold down the Fn (Function) button until the message "Locked." appears on the monitor.

Menu item details

Off:

Does not lock the multi-selector, front dial, rear dial, or control wheel even if you press and hold down the Fn (Function) button.

Multi-Selector Only:

Locks the multi-selector.

Dial + Wheel:

Locks the front dial, rear dial, and control wheel.

All:

Locks the multi-selector, front dial, rear dial, and control wheel.

Hint

You can release the lock by holding the Fn (Function) button down again.

Note

If you set [AF Area Registration] to [On], [Lock Operation Parts] will be fixed to [Off].

Related Topic

Registering the current focus area (AF Area Registration)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

REC w/ Shutter (movie)



You can start or stop recording movies by pressing the shutter button, which is bigger and easier to press than the MOVIE (Movie) button.



 $\textbf{MENU} \rightarrow \begin{tabular}{l} \hline \label{eq:menu} \hline \textbf{MENU} \rightarrow \begin{tabular}{l} \hline \label{eq:menu} \hline \end{tabular} \begin{tabular}{l} \hline \end{tabular} \textbf{REC w/ Shutter]} \rightarrow \begin{tabular}{l} \hline \end{tabular} \begin{tabular}{l} \hline$

Menu item details

On:

Enables movie recording using the shutter button when the shooting mode is set to [Movie] or [S&Q Motion].

Off:

Disables movie recording using the shutter button.

Hint

• When [REC w/ Shutter] is set to [On], you can use the shutter button to start or stop recording movies on an external recording/playback device using [REC Control].

Note

When [REC w/ Shutter] is set to [On], you cannot focus by pressing the shutter button halfway down during movie recording.

Related Topic

Shooting movies

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Select Finder/Monitor



Sets the method for switching the display between the viewfinder and the monitor.



 $MENU \rightarrow \longrightarrow (Setup) \rightarrow [Finder/Monitor] \rightarrow [Select Finder/Monitor] \rightarrow desired setting.$

Menu item details

Auto:

When you look into the viewfinder, the eye sensor reacts and the display is switched to the viewfinder automatically.

VF(Manual):

The monitor is turned off and the image is displayed only in the viewfinder.

Monitor(Manual):

The viewfinder is turned off and the image is always displayed on the monitor.

Hint

- You can assign the [Select Finder/Monitor] function to your preferred key.
 [Custom Key Setting], [Custom Key Setting] or [Custom Key Setting] → set [Finder/Monitor Sel.] to the preferred key.
- If you want to retain the viewfinder display or the monitor display, set [Select Finder/Monitor] to [VF(Manual)] or [Monitor(Manual)] beforehand.

You can keep the monitor off when you take your eyes off the viewfinder during recording by setting the monitor display to [Monitor Off] using the DISP button. Select [DISP (Screen Disp) Set] \rightarrow [Monitor] and add a check mark to [Monitor Off] beforehand.

Note

- Depending on whether the monitor is open or closed and the angle of the monitor, the eye sensor of the camera may not detect your eye approaching even if [Select Finder/Monitor] is set to [Auto].
- Under strong light sources such as sunlight, the eye sensor may not detect your eye approaching and the display may not switch to the viewfinder even when [Select Finder/Monitor] is set to [Auto]. In such cases, keep the eye sensor from being exposed to the light source.

Related Topic

- Assigning frequently used functions to buttons (Custom Key Setting)
- DISP (Screen Disp) Set (Monitor/Finder)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

DISP (Screen Disp) Set (Monitor/Finder)



Allows you to set the screen display modes that can be selected using DISP (Display Setting) in shooting mode.



The items marked with \checkmark (check) are available.

Menu item details

Display All Info.:

Shows recording information.

No Disp. Info.:


Does not show recording information.

Histogram:

Displays the luminance distribution graphically.

Level:

Indicates whether the product is level in both the front-back (A) and horizontal (B) directions. When the product is level in either direction, the indicator turns to green.



For viewfinder*:

Displays only shooting information on the monitor, not the subject. This setting is a display setting for shooting with the viewfinder.

Monitor Off*:

Always turns the monitor off when shooting images. You can use the monitor when playing back images or operating MENU. This setting is a display setting for shooting with the viewfinder.

* These screen modes are available only in the setting for [Monitor].

Note

- If you tilt the product forward or backward by a large degree, the level error will be great.
- The product may have a margin of error of almost ±1° even when the inclination is corrected by the level.

Related Topic

Using the DISP (Display Setting) button

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Contents of this chapter

The following table of contents lists the features described in this chapter ("Viewing"). From each item name, you can jump to the page describing the respective functions.

Viewing images

- Selecting which memory card to play back (Select Playback Media)
- Playing back still images
- Enlarging an image being played back (Enlarge Image)
- Enlarge Initial Mag
- Enlarge Initial Position
- Rotating recorded images automatically (Display Rotation)
- Playing back movies
- Volume Settings
- 4ch Audio Monitoring (movie)
- Playing back images using slideshow (Slide Show)
- Cont. Play for Interval
- Play Speed for Interval

Changing how images are displayed

- Playing back images on the image index screen (Image Index)
- Switching between still images and movies (View Mode)
- Display as Group
- Focus Frame Display (playback)

Setting how to jump between images

- Select Image Jump Dial
- Image Jump Method

Protecting recorded still images (Protect)

Adding information to images

- Rating
- Rating Set(Custom Key)
- Attaching audio files to images (Voice Memo)
- Voice Memo Play Vol.
- Rotating an image (Rotate)

Crop

Extracting still images from a movie

- Photo Capture
- JPEG/HEIF Switch (Photo Capture)

Copying images from one memory card to another (Copy)

Deleting images

- Deleting multiple selected images (Delete)
- Delete pressing twice
- Delete confirm.

Viewing images on a TV

Viewing images on a TV using an HDMI cable

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Selecting which memory card to play back (Select Playback Media)

Selects a slot that contains a memory card.



 $MENU \rightarrow \blacktriangleright$ (Playback) \rightarrow [Playback Target] \rightarrow [Select Playback Media] \rightarrow desired slot.

Menu item details

Slot 1:

Selects the slot 1.

Slot 2:

Selects the slot 2.

Note

When you select [Date View] in [View Mode], the camera only plays back images from a memory card selected using [Select Playback Media].

Related Topic

Switching between still images and movies (View Mode)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Playing back still images

Plays back the recorded images.

- Select MENU → ► (Playback) → [Playback Target] → [Select Playback Media] to choose which the memory card slot to play back.
- 2 Press the (Playback) button to switch to the playback mode.
- 3 Select the image with the control wheel.
 - Images shot with continuous shooting or interval shooting are displayed as one group. To play back the images
 in the group, press the center of the control wheel.

Hint

- The product creates an image database file on a memory card to record and play back images. An image that is not registered in the image database file may not be played back correctly. To play back images shot using other devices, register those images to the image database file using MENU → [○] (Shooting) → [Media] → [□] Recover Image DB].
- If you play back the images right after continuous shooting, the monitor may display an icon indicating that data is being written/the number of images left to write. During writing, some functions are not available.
- When [Focus Frame Display] is set to [On], the focus frame at the time of shooting is displayed over played-back images.
 The focus frame that the camera used to focus during shooting is displayed in green. Even if multiple focus frames are displayed during shooting, only the one on which the camera actually tried to focus will be displayed during playback.

Related Topic

- Selecting which memory card to play back (Select Playback Media)
- Recover Image DB (still image/movie)
- Display as Group
- Focus Frame Display (playback)
- Enlarging an image being played back (Enlarge Image)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Enlarging an image being played back (Enlarge Image)

Enlarges the image being played back. Use this function to check the focus of the image, etc.

- Display the image you want to enlarge, and then press the
 ⊕ (Enlarge Image) button.
 - Turn the control wheel to adjust the zoom scale. By rotating the front/rear dial, you can switch to the previous or next image while keeping the same zoom scale.
 - The view will zoom in on the part of the image where the camera focused during shooting. If the focus location information cannot be obtained, the camera will zoom in on the center of the image.
- Select the portion you want to enlarge by pressing the top/bottom/right/left sides of the control wheel.
- 3 Press the MENU button or the center of the control wheel to exit the playback zoom.

Hint

- You can also enlarge an image being played back using MENU.
- You can also enlarge the image by touching the monitor. Drag the monitor to move the enlarged position. Set [Touch Operation] to [On] beforehand.

Note

You cannot enlarge movies.

Related Topic

- Enlarge Initial Mag.
- Enlarge Initial Position
- Touch Operation
- Touch operations on the monitor

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Enlarge Initial Mag.

Sets the initial magnification scale when playing back enlarged images.



 $\textbf{MENU} \rightarrow \ \ \, \textbf{[Magnification]} \rightarrow \ \ \, \textbf{[} \oplus \ \ \, \textbf{Enlarge Initial Mag.]} \rightarrow \textbf{desired setting.}$

Menu item details

Standard. Mag.:

Displays an image with the standard magnification.

Previous Mag.:

Displays an image with the previous magnification. The previous magnification is stored even after the enlarged display screen is closed.

Related Topic

- Enlarging an image being played back (Enlarge Image)
- Enlarge Initial Position

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Enlarge Initial Position

Sets the initial position when enlarging an image in playback.



 $\textbf{MENU} \rightarrow \ \ \, \textbf{[Magnification]} \rightarrow \ \ \, \textbf{[} \bigoplus \ \, \textbf{Enlarge Initial Position]} \rightarrow \textbf{desired setting.}$

Menu item details

Focused Position:

Enlarges the image from the point of focus during shooting.

Center

Enlarges the image from the center of the screen.

Related Topic

- Enlarging an image being played back (Enlarge Image)
- Enlarge Initial Mag.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Rotating recorded images automatically (Display Rotation)

Selects the orientation when playing back recorded images.



 $\textbf{MENU} \rightarrow \boxed{\bullet} \ (\textbf{Playback}) \rightarrow \boxed{\textbf{Playback Option}} \rightarrow \boxed{\textbf{Display Rotation}} \rightarrow \texttt{desired setting}.$

Menu item details

Auto:

When you rotate the camera, the camera detects the vertical and horizontal directions, and displays the image being played back according to the orientation.

Manual:

Images shot vertically are displayed vertically. If you have set the image orientation using the [Rotate] function, the image will be displayed accordingly.

Off:

Images are always displayed horizontally.

Note

Movies shot vertically are played back horizontally during movie playback.

Related Topic

Rotating an image (Rotate)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Playing back movies

Plays back the recorded movies.

- Select the slot of the memory card to be played back from MENU → ► (Playback) → [Playback Target] → [Select Playback Media].
- Press the (playback) button to switch to playback mode.
- Select the movie to be played back using the control wheel and press the center of the control wheel to start playback.

Available operations during movie playback

You can perform slow playback and sound volume adjustment, etc. by pressing the down side of the control wheel.

- Playback
- I : Pause
- Fast-forward: Fast-rewind
- Forward slow playback
- ■ : Reverse slow playback
- Next movie file
- Previous movie file
- Displays the next frame
- Displays the previous frame
- Photo Capture
- d): Sound volume adjustment
- S: Closes the operation panel

Hint

- "Forward slow playback," "Reverse slow playback," "Displays the next frame" and "Displays the previous frame" are available during pause.
- Movie files recorded using other products may not be able to be playable on this camera.

Note

• Even if you shoot the movie vertically, the movie will be displayed horizontally on the screen or the finder of the camera.

Related Topic

- Switching between still images and movies (View Mode)
- Selecting which memory card to play back (Select Playback Media)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Volume Settings

Sets the sound volume for movie playback.



 $\textbf{MENU} \rightarrow \begin{tabular}{l} \blacksquare \end{tabular} \textbf{MENU} \rightarrow \begin{tabular}{l} \blacksquare \end{tabular} \textbf{Settings} \end{tabular} \rightarrow \begin{tabular}{l} \blacksquare \end{tabular} \textbf{Settings} \end{tabular} \rightarrow \begin{tabular}{l} \blacksquare \end{tabular} \textbf{Settings} \end{tabular} \rightarrow \begin{tabular}{l} \blacksquare \end{tabular} \textbf{MENU} \rightarrow \begin{tabular}{l} \blacksquare \end{tabular} \textbf{Settings} \end{tabular} \rightarrow \begin{tabular}{l} \blacksquare \end{tabular} \textbf{MENU} \rightarrow \begin{tabular}{l} \blacksquare \end{tabular} \textbf{Settings} \end{tabular} \rightarrow \begin{tabular}{l} \blacksquare \end{tabular} \textbf{Settings} \end{tabular} \rightarrow \begin{tabular}{l} \blacksquare \end{tabular} \textbf{MENU} \rightarrow \begin{tabular}{l} \blacksquare \end{tabular} \textbf{Settings} \end{tabular} \rightarrow \begin{tabular}{l} \blacksquare \end{t$

Adjusting the volume during playback

Press the bottom side of the control wheel while playing back movies to display the operation panel, then adjust the volume. You can adjust the volume while listening to the actual sound.

Note

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

4ch Audio Monitoring (movie)

Sets the audio to be monitored by the device connected to the \bigcap (headphone) terminal of the camera when you record movie audio in 4 channels or when playing back a movie recorded in 4 channels.



 $MENU \rightarrow \longrightarrow (Setup) \rightarrow [Sound Option] \rightarrow [\longrightarrow 4ch Audio Monitoring] \rightarrow desired setting.$

Menu item details

CH1/CH2:

Outputs audio from channel 1 to the L (left) side and from channel 2 to the R (right) side.

CH3/CH4:

Outputs audio from channel 3 to the L (left) side and from channel 4 to the R (right) side.

CH1+3/CH2+4:

Outputs the mixed audio of channel 1 and channel 3 to the L (left) side and the mixed audio of channel 2 and channel 4 to the R (right) side.

CH1/CH1:

Outputs audio from channel 1 to the L (left) side and R (right) side.

CH2/CH2:

Outputs audio from channel 2 to the L (left) side and R (right) side.

Note

- The [4ch Audio Monitoring] settings are enabled when an accessory for 4-channel audio recording is attached to the Multi Interface Shoe of the camera during movie recording.
- The camera cannot output audio in 4 channels to the device connected to the \(\infty\) (headphone) terminal of the camera.
- When outputting audio through the speakers of the camera, the channels will also change depending on the [4ch Audio Monitoring] setting.

Related Topic

Shoe Audio Set.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Playing back images using slideshow (Slide Show)

Automatically plays back images continuously.



Select [Enter].

Menu item details

Repeat:

Select [On], in which images are played back in a continuous loop, or [Off], in which the product exits the slideshow when all the images are played back once.

Interval:

Select the display interval for images from among [1 Sec], [3 Sec], [5 Sec], [10 Sec] or [30 Sec].

To quit the slideshow in the middle of playback

Press the MENU button to quit the slideshow. You cannot pause the slideshow.

Hint

- During playback, you can display the next/previous image by pressing the right/left side of the control wheel.
- You can activate a slideshow only when [View Mode] is set to [Date View] or [Folder View(Still)].

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Cont. Play for Interval

Continuously plays back images shot using interval shooting.

- 2 Select the image group that you want to play back, and then press the center of the control wheel.

Hint

- On the playback screen, you can start continuous playback by pressing the down button while displaying an image in the group.
- You can resume play or pause by pressing the down button during playback.
- You can change the playback speed by turning the front/rear dial or the control wheel during playback. You can also change the playback speed by selecting MENU \rightarrow [Viewing] \rightarrow [Play Speed for 1 Interval].
- You can continuously play back images shot with continuous shooting as well.

Related Topic

- Interval Shoot Func.
- Play Speed for Interval



Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Play Speed for Interval

Sets the playback speed for still images during [Cont. Play for 🐧 Interval].

Hint

You can also change the playback speed by turning the front/rear dial or the control wheel during [Cont. Play for th

Related Topic

Cont. Play for Interval

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Playing back images on the image index screen (Image Index)

You can display multiple images at the same time in playback mode.



Select the image by pressing the top/bottom/right/left sides of the control wheel or turning the control wheel.

To change the number of images to be displayed

 $\mathsf{MENU} \to \boxed{\blacktriangleright} (\mathsf{Playback}) \to [\mathsf{Playback} \ \mathsf{Option}] \to [\mathsf{Image} \ \mathsf{Index}] \to \mathsf{desired} \ \mathsf{setting}.$

Menu item details

9 Images/25 Images

To return to single-image playback

Select the desired image and press the center of the control wheel.

To display a desired image quickly

Select the bar on the left of the image index screen using the control wheel, then press the top/bottom sides of the control wheel. While the bar is being selected, you can display the calendar screen or folder selection screen by pressing the center. In addition, you can switch View Mode by selecting an icon.

Related Topic

Switching between still images and movies (View Mode)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α1

Switching between still images and movies (View Mode)

Sets the View Mode (image display method).



1 MENU → \blacktriangleright (Playback) → [Playback Target] → [View Mode] → desired setting.

Menu item details

Date View:

Displays the images by date.

Folder View(Still):

Displays only still images.

Movie View:

Displays only movies by date.

Help Guide


Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Display as Group

Sets whether or not to display continuously shot images or images shot using interval shooting as a group.



 $MENU \rightarrow \blacktriangleright$ (Playback) \rightarrow [Playback Option] \rightarrow [Display as Group] \rightarrow desired setting.



Menu item details

On:

Displays images as a group.

To play back the images in a group, select the group and press the center of the control wheel.

Off:

Does not display images as a group.

Hint

- The following images are grouped.
 - Images shot with [Drive Mode] set to [Cont. Shooting] (One sequence of images shot continuously by holding down the shutter button during continuous shooting becomes one group.)
 - Images shot with [Interval Shoot Func.] (Images shot during one session of interval shooting become one group.)
- On the image index screen, (Display as Group) icon is displayed over the group.

Note

- Images can be grouped and displayed only when [View Mode] is set to [Date View]. When it is not set to [Date View], images cannot be grouped and displayed, even if [Display as Group] is set to [On].
- If you delete the group, all the images in the group will be deleted. Any voice memos attached to images in the group will also be deleted.

Related Topic

- Cont. Shooting
- Interval Shoot Func.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Focus Frame Display (playback)

Sets whether or not to display a focus frame around the area where the camera focused when you play back a still image.



 $\textbf{MENU} \rightarrow \boxed{\blacktriangleright} \ \ (\textbf{Playback}) \rightarrow \boxed{\textbf{Playback Option}} \rightarrow \boxed{\boxed{\blacktriangleright}} \ \ \textbf{Focus Frame Display} \boxed{\rightarrow} \ \ \textbf{desired setting}.$

Menu item details

Off:

Does not display a focus frame during playback.

On

Displays a focus frame in green during playback.

Hint

- Even if multiple focus frames are displayed at the time of shooting, only the one indicating where the camera actually focused will be displayed during playback.
- Even if a focus frame is displayed around the face of the subject at the time of shooting, the focus frame will be displayed around the eye during playback when an eye is detected.

Note

- A focus frame will not be displayed over the following images.
 - Still images shot with manual focus
 - Movies
 - Still images created with [Photo Capture]
- The focus frame is displayed only on the single-image playback screen. The focus frame is not displayed on the image index screen or over enlarged images.
- The focus frame is not displayed during auto reviewing.
- If you shoot an image with a different composition after performing auto-focusing, the focus frame will appear offset from the subject.
- Even if the focus frame is displayed, it may not be in focus to the subject.
- Even if you turn off the focusing frame display while shooting using the [AF Area Auto Clear] or [AF-C Area Display] function, when [Focus Frame Display] is set to [On], the focusing frame will be displayed during playback.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Select Image Jump Dial

You can jump between images during playback. This function is useful when you want to find one of many recorded images. You can also quickly find protected images or images set with a particular rating. Assign this function to either the front dial or rear dial.

Menu item details

Front dial:

Use the front dial to jump between images.

Rear dial:

Use the rear dial to jump between images.

Related Topic

Image Jump Method

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Image Jump Method

Sets the method for jumping between images during playback by operating a dial.



 $MENU \rightarrow \blacktriangleright$ (Playback) \rightarrow [Playback Option] \rightarrow [Image Jump Method] \rightarrow desired setting item.

Menu item details

One by one:

Plays back images one by one.

By 10 images:

Jumps in units of 10 images.

By 100 images:

Jumps in units of 100 images.

Protect Only:

Plays back only protected images.

Rating Only:

Plays back all rated images.

Rating Only (\bigstar) - Rating Only (\bigstar):

Plays back only images for which a rating (\(\psi \) to \(\forall \)) has been specified.

W/O Rating Only:

Plays back only images that are not rated.

Note

- When [Image Jump Method] is set to [One by one], [By 10 images], or [By 100 images], one group is counted as one image.
- When [Image Jump Method] is set to a parameter other than [One by one], [By 10 images], or [By 100 images], you can jump between images only when [View Mode] is set to [Date View]. When [View Mode] is set to a parameter other than [Date View], images will be played back one by one even if you use the dial assigned using [Select Image Jump Dial].
- When [Image Jump Method] is set to a parameter other than [One by one], [By 10 images], or [By 100 images], movies are always skipped during jumping playback.

Related Topic

- Rating
- Protecting recorded still images (Protect)
- Select Image Jump Dial

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Protecting recorded still images (Protect)

Protects recorded images against accidental erasure. The Om (protect) mark is displayed on protected images.



 $MENU \rightarrow \blacktriangleright$ (Playback) \rightarrow [Selection/Memo] \rightarrow [Protect] \rightarrow desired setting.

Menu item details

Multiple Img.:

Applies the protection of the selected multiple images.

- (1) Select the image to be protected, then press the center of the control wheel. The \checkmark (check) mark is displayed in the check box. To cancel the selection, press the center again to remove the \checkmark (check) mark.
- (2) To protect other images, repeat step (1).
- (3) MENU \rightarrow [OK].

All in this Folder:

Protects all images in the selected folder.

Cancel All in this Folder:

Cancels the protection of all images in the selected folder.

All with this date:

Protects all images taken on the selected date.

Cancel All with this date:

Cancels the protection of all images taken on the selected date.

All Images in This Group:

Protects all the images in the selected group.

Cancel All in This Group:

Cancels the protection of all the images in the selected group.

Hint

- If you assign [Protect] to the key of your choice using MENU → (Setup) → [Operation Customize] → [Custom Key Setting], you can protect images or cancel protection by simply pressing the key. The [Protect] function is assigned to the C3 button in the default settings.
- If you select a group in [Multiple Img.], all the images in the group will be protected. To select and protect particular images within the group, execute [Multiple Img.] while displaying the images within the group.

Note

The menu items that can be selected vary according to the [View Mode] setting and the selected content.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Rating

You can assign ratings to recorded images on a scale of the number of stars (\bigstar - $\star\star\star$) to make it easier to find images.

The image rating selection screen will appear.

- Press the left/right sides of the control wheel to display an image to which you want to assign a rating, and then press the center.
- Select the level of \bigstar (Rating) by pressing the left/right side of the control wheel, and then press the center.
- Press the MENU button to exit the rating setting screen.

Hint

- You can also assign ratings when playing back images by using the custom key. Assign [Rating] to the desired key using [Custom Key Setting] beforehand, and then press the custom key while playing back an image to which you want to assign a rating. The level of ★ (Rating) changes each time you press the custom key.
- By specifying ratings with the [Image Jump Method] function, you can quickly find the desired image.

Related Topic

- Assigning frequently used functions to buttons (Custom Key Setting)
- Rating Set(Custom Key)
- Image Jump Method

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Rating Set(Custom Key)

Sets the available number of \bigstar (rating) when rating (ranking) images with the key to which you have assigned [Rating] using [\blacktriangleright Custom Key Setting].

Related Topic

- Rating
- Assigning frequently used functions to buttons (Custom Key Setting)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Attaching audio files to images (Voice Memo)

You can record shooting conditions or image descriptions with your voice, and attach the audio files to images as voice memos.

Voice memos can be transferred to a computer together with images, and played back on the computer.

The image selection screen will appear.

- 2 Select a still image to which you want to attach a voice memo.
- While holding down the center of the control wheel, record your voice.

 A voice memo file (WAV) with the same file name as the still image will be saved in the folder where to

A voice memo file (.WAV) with the same file name as the still image will be saved in the folder where the corresponding still image is saved.

 Recording continues while the center of the control wheel is pressed. The recording stops when the button is released.

To play back voice memos

- 1. $MENU \rightarrow \blacktriangleright$ (Playback) \rightarrow [Selection/Memo] \rightarrow [Voice Memo].
- 2. Select a still image to which a voice memo you want to play back is attached.
 - (voice memo icon) is displayed on still images having attached voice memos.
- 3. Press the center of the control wheel.

To delete voice memos

- 1. $MENU \rightarrow \blacktriangleright$ (Playback) \rightarrow [Selection/Memo] \rightarrow [Voice Memo].
- 2. Select a still image to which a voice memo you want to delete is attached.
- 3. Press the bottom of the control wheel, and then select [OK].

Hint

- If you assign [Voice Memo hold] to a custom key using [Custom Key Setting], a voice memo will be recorded while the key is pressed. If you assign [Voice Memo toggle] to a custom key, voice memo recording will start when you press the key, and stop when you press the key again. During voice memo playback, playback will start when the key is pressed, and stop when it is pressed again.
- You can still record a voice memo for a protected still image.

Note

- You cannot attach a voice memo to a movie.
- One voice memo file of up to 60 seconds in duration can be attached per still image.
- You cannot add another voice memo to a still image to which a voice memo has already been attached, or overwrite the content of a voice memo that has already been attached. First delete the attached voice memo, and then record a new voice memo.
- You cannot change the microphone input level for recording.

The built-in microphone is used for voice memo recording. You cannot use an external audio input device.

Related Topic

- Voice Memo Play Vol.
- Assigning frequently used functions to buttons (Custom Key Setting)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Voice Memo Play Vol.

Adjusts the playback volume for voice memos.

- 2 Adjust the volume by pressing the left/right side of the control wheel.

Hint

While playing back a voice memo, you can display the volume control screen by pressing the bottom of the control wheel.

Related Topic

Attaching audio files to images (Voice Memo)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Rotating an image (Rotate)

Rotates a recorded image counter-clockwise.



2 Press the center of the control wheel.

The image is rotated counter-clockwise. The image rotates as you press the center. If you rotate the image once, the image remains rotated even after the product is turned off.

Note

- Even if you rotate a movie file, it will be played back horizontally on the monitor or viewfinder of the camera.
- You may not be able to rotate images shot using other products.
- When viewing rotated images on a computer, the images may be displayed in their original orientation depending on the software.



Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Crop

Crops recorded images.

The image selection screen will appear.

- Select the still image that you want to crop, and then press the center of the control wheel.
- 3 Adjust the size and position of the cropping frame.
 - You can change the aspect ratio of the cropping frame using the rear dial. You can also change the orientation.
 - You can change the size of the cropping frame using the front dial or the control wheel.
 - You can move the position of the cropping frame using the top/bottom/left/right side of the control wheel.
 - You can preview the cropped image by pressing the Fn button.
- 4 Press the center of the control wheel.

The cropped image will be saved.

Hint

- The cropped image is saved as a separate image file. The original image remains as is.
- The file format and image quality setting of the cropped image will be the same as those of the original image.
- On the playback screen, the (Crop) icon is displayed with cropped images.

Note

You cannot crop RAW images or movies.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Photo Capture

Captures a chosen scene in a movie to save as a still image. First shoot a movie, then pause the movie during playback to capture decisive moments that tend to be missed when shooting still images, and save them as still images.

- 1 Display the movie that you want to capture as a still image.
- **MENU** \rightarrow [Photo Capture].
- Play back the movie and pause it.
- Find the desired scene using forward slow playback, reverse slow playback, displays the next frame, and displays the previous frame, and then stop the movie.
- 5 Press (Photo Capture) to capture the chosen scene.

The scene is saved as a still image.

Hint

With [] JPEG/HEIF Switch], you can select either JPEG or HEIF as the recording file format for still images.

Related Topic

- Shooting movies
- Playing back movies
- JPEG/HEIF Switch (Photo Capture)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

JPEG/HEIF Switch (Photo Capture)

Switches the file format (JPEG / HEIF) for still images captured with [Photo Capture].

You can view and edit JPEG files in various environments. The HEIF format has high compression efficiency. The camera can record with high image quality and small file sizes in the HEIF format. Depending on the computer or software, you may not be able to view or edit HEIF files. In addition, a HEIF-compatible environment is required to play back still images in the HEIF format. You can enjoy high-quality still images by connecting the camera and the TV via HDMI.



 $\textbf{MENU} \rightarrow \boxed{\blacktriangleright} \ (\textbf{Playback}) \rightarrow [\textbf{Edit}] \rightarrow \boxed{\blacksquare} \ \textbf{JPEG/HEIF Switch} \rightarrow \textbf{desired setting}.$

Menu item details

JPEG:

Performs digital processing on the RAW file and records it in the JPEG format. This setting gives priority to compatibility.

Performs digital processing on the RAW file and records it in the HEIF (4:2:0) format. This setting gives priority to image quality and compression efficiency.

HEIF(4:2:2):

Performs digital processing on the RAW file and records it in the HEIF (4:2:2) format. This setting gives priority to image quality.

Note

HEIF image files recorded with this camera cannot be displayed on other cameras that do not support the HEIF file format. Be
careful not to accidentally erase HEIF image files by formatting the memory card or deleting the files.

Related Topic

Photo Capture

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Copying images from one memory card to another (Copy)

You can copy images from a memory card in a slot that is selected using [Select Playback Media] to a memory card in another slot.



 $\mathsf{MENU} \to \blacktriangleright \mathsf{(Playback)} \to \mathsf{[Edit]} \to \mathsf{[Copy]}.$

All of the contents with a date or in a folder currently being played back will be copied to a memory card in another slot.

Hint

 $\qquad \text{You can select the type of images to be displayed by selecting MENU} \rightarrow \text{[Playback)} \rightarrow \text{[Playback Target]} \rightarrow \text{[View Mode]}.$

Note

- If images in a group are copied, the copied images will not be displayed as a group on the destination memory card.
- If protected images are copied, the protection will be canceled on the destination memory card.
- It may take a long time when many images are to be copied. Use a sufficiently charged battery pack.
- To copy a movie, the destination memory card must support the recording format of the movie. If the movie cannot be copied, a message will be displayed on the monitor of the camera.

Related Topic

- Selecting which memory card to play back (Select Playback Media)
- Switching between still images and movies (View Mode)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 q1

Deleting multiple selected images (Delete)

You can delete multiple selected images. Once you have deleted an image, you cannot restore it. Confirm the image to be deleted beforehand.



 $MENU \rightarrow \blacktriangleright$ (Playback) \rightarrow [Delete] \rightarrow [Delete] \rightarrow desired setting.

Menu item details

All Other Than This Img.:

Deletes all images in the group except the selection.

All Images in This Group:

Deletes all images in the selected group.

Multiple Img.:

Deletes the selected images.

- (1) Select the images to be deleted, then press the center of the control wheel. The \checkmark (check) mark is displayed in the check box. To cancel the selection, press the center again to remove the \checkmark (check) mark.
- (2) To delete other images, repeat step (1).
- (3) MENU \rightarrow [OK].

All in this Folder:

Deletes all images in the selected folder.

All with this date:

Deletes all images taken on the selected date.

Hint

- Perform [Format] to delete all images, including protected images.
- To display the desired folder or date, select the desired folder or date during playback by performing the following procedure:
 (Image Index) button → select the bar on the left using the control wheel → select the desired folder or date using the top/bottom sides of the control wheel.
- If you select a group in [Multiple Img.], all the images in the group will be deleted. To select and delete particular images within the group, execute [Multiple Img.] while displaying the images within the group.

Note

- The protected images cannot be deleted.
- The menu items that can be selected vary according to the [View Mode] setting and the selected content.

Related Topic

- Display as Group
- Using the Delete button
- Format

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Delete pressing twice

Sets whether or not you can delete the image currently being played back by pressing the $\hat{\mathbf{m}}$ (Delete) button twice in sequence.

Menu item details

On:

Enables you to delete the image currently being played back by pressing the 🗂 (Delete) button twice.

Off:

Does not enable you to delete the image currently being played back by pressing the 🗂 (Delete) button twice.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α1

Delete confirm.

You can set whether [Delete] or [Cancel] is selected as a default on the delete confirmation screen.



1 MENU → \blacktriangleright (Playback) → [Delete] → [Delete confirm.] → desired setting.

Menu item details

"Delete" first:

[Delete] is selected as the default setting.

"Cancel" first:

[Cancel] is selected as the default setting.

Help Guide


Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Viewing images on a TV using an HDMI cable

To view images stored on this product using a TV, an HDMI cable (sold separately) and a TV equipped with an HDMI jack are required. For details, refer to the operating instructions supplied with the compatible TV.

- 1 Turn off both this product and the TV.
- Connect the HDMI terminal of this product to the HDMI jack of the TV using an HDMI cable (sold separately).

Use an HDMI cable that is compatible with the HDMI Type-A terminal of the product and the HDMI jack of the TV.



- Turn on the TV and switch the input.
- 4 Turn on this product.

Images shot with the product appear on the TV screen.

- 5 Select an image using the right/left sides of the control wheel.
 - The monitor of this camera is not lit up on the playback screen.

"BRAVIA" Sync

By connecting this product to a TV that supports "BRAVIA" Sync using an HDMI cable (sold separately), you can operate this product's playback functions with the TV remote control.

- 1. After performing the steps above to connect this camera to a TV, select MENU \rightarrow [External Output] \rightarrow [CTRL FOR HDMI] \rightarrow [On].
- 2. Press the SYNC MENU button on the TV remote control, and select the desired mode.
- If you connect this camera to a TV using an HDMI cable, available menu items are limited.

- Only TVs that support "BRAVIA" Sync can provide SYNC MENU operations. For details, refer to the operating
 instructions supplied with the TV.
- If the product performs unwanted operations in response to the TV remote control when the product is connected to another manufacturer's TV using an HDMI connection, select MENU → [External Output] → [CTRL FOR HDMI] → [Off].

Hint

- This product is compatible with the PhotoTV HD standard. When you connect a Sony PhotoTV HD-compatible device using an HDMI cable (sold separately) or the USB cable, the TV becomes set to an image quality suitable for viewing still images, and a whole new world of photos can be enjoyed in breathtakingly high quality.
- The PhotoTV HD allows for a highly-detailed, photo-like expression of subtle textures and colors.

Note

- Do not connect this product and another device using the output terminals of both. Doing so may cause a malfunction.
- Some devices may not work properly when connected to this product. For example, they may not output video or audio.
- Use an HDMI cable with the HDMI logo or a genuine Sony cable.
- When [Time Code Output] is set to [On], the image may not be output properly to the TV or recording device. In such cases, set [Time Code Output] to [Off].
- If images do not appear on the TV screen properly, select MENU → (Setup) → [External Output] → [□ HDMI Resolution] → [4320p/2160p], [2160p], [1080p] or [1080i] according to the TV to be connected.
- To properly display 8K movies from the camera on a TV manufactured by Sony using a HDMI cable (sold separately), you need to change the image quality settings for the TV manually. Change the image quality settings (gamma or color mode) for the TV according to the settings applied when shooting.
- During HDMI output, if you switch the movie format (8K/4K/HD image quality) or change the movie to a different frame rate or color mode, the screen may become dark temporarily. This is not a malfunction.
- When [NTSC/PAL Selector] is set to PAL, the screen may black out for an instant in the following situations. This is not a malfunction.
 - When you start or stop recording movies while the shooting mode is set to a mode other than [1] (Movie) or **S&Q** (S&Q Motion).

 - When you play back a movie for the first time after switching to the playback mode.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Format

When you use a memory card with this camera for the first time, we recommend that you format the card using the camera for stable performance of the memory card. Note that formatting permanently erases all data on the memory card, and is unrecoverable. Save valuable data on a computer, etc.



 $MENU \rightarrow [\bigcirc]$ (Shooting) \rightarrow [Media] \rightarrow [Format] \rightarrow desired memory card slot.



Select [Enter]. (Quick formatting)

• If you press the (Delete) button, a message to perform full formatting will be displayed. You can launch full formatting by selecting [Enter].

The difference between quick formatting and full formatting

Perform full formatting when you feel like the speed of recording to the memory card or read-out from the memory card has become slow, or when you want to erase data completely, etc.

Full formatting takes longer than quick formatting, because all areas of the memory card are initialized.

Hint

- You can also display the screen for formatting the memory card by pressing and holding the MENU button and then the (Delete) button on the shooting screen for approximately two seconds.
- You can cancel full formatting before it is completed. Even if you cancel full formatting in the middle of the process, the data will be erased, so you can use the memory card as is.

Note

- Formatting permanently erases all data including protected images and registered settings (from M1 to M4).
- The access lamp lights up during formatting. Do not remove the memory card while the access lamp is lit up.
- Format the memory card on this camera. If you format the memory card on the computer, the memory card may not be usable depending on the format type.
- It may take a few minutes to complete formatting, depending on the memory card.
- You cannot format the memory card if the remaining battery charge is less than 1%.

Related Topic

- Memory cards that can be used
- Notes on memory card

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Rec. Media Settings (still image/movie): Recording Media (still image)

Selects the memory card slot to record still images. In the default settings, [Slot 1] is selected. If you want to use one memory card without changing the setting, use Slot 1.



Menu item details

Slot 1:

Records still images on the memory card in Slot 1.

Slot 2:

Records still images on the memory card in Slot 2.

Simult. Recording:

Simultaneously records still images on the memory cards in Slot 1 and Slot 2.

Sort Recording:

Records still images with different file formats and image sizes by sorting them to different slots. Set the file format and image size of still images for each slot.

Related Topic

- Rec. Media Settings (still image/movie): Recording Media (movie)
- Rec. Media Settings (still image/movie): Auto Switch Media
- Selecting which memory card to play back (Select Playback Media)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Rec. Media Settings (still image/movie): Recording Media (movie)

Selects the memory card slot to record movies. In the default settings, [Slot 1] is selected. If you want to use one memory card without changing the setting, use Slot 1.



Menu item details

Slot 1:

Records movies on the memory card in Slot 1.

Slot 2:

Records movies on the memory card in Slot 2.

Simult. Recording:

Simultaneously records movies on the memory cards in Slot 1 and Slot 2.

Related Topic

- Rec. Media Settings (still image/movie): Recording Media (still image)
- Rec. Media Settings (still image/movie): Auto Switch Media
- Selecting which memory card to play back (Select Playback Media)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Rec. Media Settings (still image/movie): Auto Switch Media

If a memory card in use becomes full or you have forgotten to insert a memory card into a slot, you can record images to the other memory card.



Menu item details

On:

The camera automatically starts recording on the other memory card when a memory card in use becomes full or if you have forgotten to insert a memory card.

Off:

The camera does not perform [Auto Switch Media].


How the camera switches the memory card slot in use

When recording both still images and movies on a single memory card:

When images cannot be recorded to the memory card in use, the settings for [Recording Media] and [Recording Media] change automatically and images are recorded to the other memory card.

When the other memory card becomes full after switching, the camera starts recording in the former slot again.

Example: When [Recording Media] and [Recording Media] under [Rec. Media Settings] are both set to [Slot 1]



: Recording images

(A): Recording is no longer possible on the memory card (due to lack of capacity, etc.).

(B): The memory card is replaced with a recordable one.


When recording the same image simultaneously to two memory cards:

• [Recording Media] or [Recording Media] under [Rec. Media Settings] is set to [Simult. Recording].

The camera stops simultaneous recording when either of the memory cards becomes full. When you remove the memory card that has become full, the camera starts recording to the other memory card.

When you replace the memory card that has become full with a recordable memory card, the camera starts simultaneous recording with the selected setting again.

Example: [Recording Media] and [Recording Media] are both set to [Simult. Recording]



: Simultaneous recording is available.

: Recording is disabled.

: The same image cannot be recorded simultaneously.

(A): Recording is no longer possible on the memory card (due to lack of capacity, etc.).

(B): The memory card is removed.

(C): A recordable memory card is inserted.


• When the memory card in use becomes full while recording a movie, the movie continues to be recorded to the other memory card until the recording in progress is finished.

When recording images separately to two memory cards in the RAW and JPEG/HEIF formats:

■ When [Recording Media] under [Rec. Media Settings] is set to [Sort Recording]

The camera stops recording when either of the memory cards becomes full. When you remove the memory card that has become full, the camera starts recording both in the RAW and JPEG/HEIF formats to the other memory card. When you replace the memory card that has become full with a recordable memory card, the camera starts recording the two types of images separately with the selected setting again.

Example: When [File Format] for Slot 1 is set to [RAW] and [File Format] for Slot 2 is set to [JPEG]



: Images are sorted by the file format.

: Recording still images is disabled (movies can be recorded).

: Images cannot be sorted.

(A): Recording is no longer possible on the memory card (due to lack of capacity, etc.).

(B): The memory card is removed.

(C): A recordable memory card is inserted.

 When the memory card in use becomes full while recording movies, the camera starts recording to the other memory card.

Hint

- Images are recorded to the memory card in the slot displayed on the monitor with an arrow symbol. After the camera switches the slot using [Auto Switch Media], replace the memory card in the former slot with a recordable memory card.
- When recording both still images and movies on a single memory card, the settings for [Recording Media] and [Recording Media] change automatically as the slot switches. If you want to record on the slot in use before switching, select the desired slot with [Recording Media]/[Recording Media].
- If you want to record with the settings with [Recording Media] and [Recording Media], set [Auto Switch Media] to [Off].

Related Topic


- Memory cards that can be used
- Recordable movie times
- Rec. Media Settings (still image/movie): Recording Media (still image)
- Rec. Media Settings (still image/movie): Recording Media (movie)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Select REC Folder

If [Folder Name] under [File/Folder Settings] is set to [Standard Form] and there are 2 folders or more, you can select the folder on the memory card to which images are to be recorded.



Note

- You cannot select the folder when [Folder Name] under [File/Folder Settings] is set to [Date Form].
- If the camera is set to record images to memory cards in both slots, you may only select a common folder on both memory cards.
 If there is no common folder, you can make one using [Create New Folder].

Related Topic

- File/Folder Settings
- Create New Folder

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Create New Folder

Creates a new folder on the memory card for recording still images. A new folder is created with a folder number one greater than the largest folder number currently used. Images are recorded in the newly created folder. Up to 4,000 images in total can be stored in one folder. When the folder capacity is exceeded, a new folder may be automatically created.



 $MENU \rightarrow [\bigcirc]$ (Shooting) \rightarrow [File] \rightarrow [Create New Folder].

Hint

You can set the last 5 characters of the folder name.

Note

- When you insert a memory card that was used with other equipment into this product and shoot images, a new folder may be automatically created.
- If the camera is set to record images to memory cards in both slots, a new folder will be created on both memory cards. A new folder number will be one greater than the largest existing folder number on the two memory cards.
- If the camera is set to record images to memory cards in both slots and an image is shot, a new folder may be automatically created.
- You cannot change the folder name when [Folder Name] under [File/Folder Settings] is set to [Date Form].

Related Topic

File/Folder Settings

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Recover Image DB (still image/movie)

If image files were processed on a computer, problems may occur in the image database file. In such cases, the images on the memory card will not be played back on this product. If these problems happen, repair the file using [Recover Image DB].

Images recorded on the memory card are not deleted by [Recover Image DB].



Note

• If the battery pack is extremely depleted, image database files cannot be repaired. Use a sufficiently charged battery pack.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Display Media Info. (still image/movie)

Displays the recordable number of still images and the remaining recording time for movies on the memory card.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 q1

File/Folder Settings

Configure settings related to the folder and file name of the still image to be shot.



 $\mathsf{MENU} \to \boxed{\bigcirc} \ (\mathsf{Shooting}) \to [\mathsf{File}] \to [\mathsf{File/Folder Settings}] \to \mathsf{desired setting}.$

Menu item details

File Number:

You can set how to assign file numbers to still images.

[Series]: Does not reset file numbers for each folder.

[Reset]: Resets file numbers for each folder.

Forced File Number Reset:

Resets the still image file number and creates a new folder.

Set File Name:

You can specify the first three characters of the file name.

Folder Name:

You can set how folder names are assigned.

[Standard Form]: Folders are named as "folder number + any 5 characters". Example: 100MSDCF

[Date Form]: Folders are named as "folder number + Y (the last digit of the year)/MM/DD".

Example: 10010405 (Folder number: 100; date: 04/05/2021)

Hint

- The settings for [File Number] and [Set File Name] are applied to both Slot 1 and Slot 2.
- When [File Number] is set to [Series], file numbers will be assigned sequentially across the memory cards in the slots even if you switch the setting for [☐ Rec. Media Settings] → [☐ Recording Media] between Slot 1 and 2.
- When [Folder Name] is set to [Standard Form], the last 5 characters of the folder name can be set using [Create New Folder].
- You can also change the last five characters of the folder name by using [Forced File Number Reset].

Note

- Only capital letters, numbers, and underscores can be used for [Set File Name]. Underscores cannot be used for the first character.
- The three characters specified using [Set File Name] are only applied to files recorded after the setting is made.

Related Topic

- Create New Folder
- File Settings

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

File Settings

Configure settings for the file names of recorded movies.



 $MENU \rightarrow [\cite{O}\cite{O}\cite{O}\cite{O}\cite{O}\cite{O}$ (Shooting) \rightarrow [File] \rightarrow [File Settings] \rightarrow desired setting.

Menu item details

File Number:

You can set how to assign file numbers to movies.

[Series]: Does not reset file numbers even if the memory card is changed.

[Reset]: Resets the file number when the memory card is changed.

Series Counter Reset:

Resets the series counter used when [File Number] is set to [Series].

File Name Format:

You can set the format for movie file names.

[Standard]: The file name of the recorded movie starts with "C." Example: C0001

[Title]: The file name of the recorded movie becomes "Title+File number."

[Date + Title]: The file name of the recorded movie becomes "Date+Title+File number."

[Title + Date]: The file name of the recorded movie becomes "Title+Date+ File number."

Title Name Settings:

You can set the title when [File Name Format] is set to [Title], [Date + Title], or [Title + Date].

Hint

- The settings for [File Number] and [File Name Format] are applied to both Slot 1 and Slot 2.
- When [File Number] is set to [Series], file numbers will be assigned sequentially across the memory cards in the slots even if you switch the setting for [☐ Rec. Media Settings] → [☐ Recording Media] between Slot 1 and 2.

Note

- Only alphanumeric characters and symbols can be input for [Title Name Settings]. Up to 37 characters can be entered.
- Titles specified using [Title Name Settings] are only applied to movies recorded after the setting is made.
- You cannot set how folder names are assigned for movies.
- If you are using an SDHC memory card, [File Name Format] is locked to [Standard].
- If you insert a memory card used with [File Name Format] set to one of the following into another device, the memory card may not function properly.
 - [Title]
 - [Date + Title]
 - [Title + Date]
- If there are unused numbers due to file deletion, etc., these numbers will be reused when the movie file number reaches "9999."

Related Topic

File/Folder Settings

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

IPTC Information

You can write IPTC information* when recording still images. Create and edit IPTC information using the IPTC Metadata Preset (https://www.sony.net/iptc/help/) and write the information to a memory card beforehand.

* IPTC information consists of digital image metadata attributes, as standardized by the International Press Telecommunications Council.



 $\textbf{MENU} \to \lceil \overleftarrow{\bigcirc} \rceil \text{ (Shooting)} \to \lceil \overrightarrow{\text{File}} \rceil \to \lceil \overrightarrow{\text{IPTC Information}} \rceil \to \text{desired setting item}.$

Menu item details

Write IPTC Info:

Sets whether to write IPTC information to still images. ([On]/[Off])

• If you select [On], the IPT((IPTC) icon will appear on the shooting screen.

Register IPTC Info:

Registers IPTC information from a memory card to the camera. Select [Slot 1] or [Slot 2] as the memory card from which to read out IPTC information.

Hint

- When you play back images that have IPTC information, the IPTC (IPTC) icon appears on the screen.
- For details on how to use the IPTC Metadata Preset, refer to the following support page. https://www.sony.net/iptc/help/

Note

- Whenever you register IPTC information, information previously registered to the camera is overwritten.
- You cannot edit or check IPTC information on the camera.
- To delete IPTC information registered to the camera, reset the camera to the initial settings.
- Before lending out or handing over the camera, reset the camera to delete IPTC information.

Related Topic

Setting Reset

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Copyright Info

Writes copyright information onto the still images.



When you select [Set Photographer] or [Set Copyright], a keyboard appears on the screen. Enter your desired name.

You can only enter alphanumeric characters and symbols for [Set Photographer] and [Set Copyright]. You can enter up to 46 letters.

Menu item details

Write Copyright Info:

Sets whether to write copyright information. ([On]/[Off])

• If you select [On], a (C) (Copyright) icon will appear on the shooting screen.

Set Photographer:

Sets the photographer name.

Set Copyright:

Sets the copyright holder name.

Disp. Copyright Info:

Displays the current copyright information.

Note

- A (C) (Copyright) icon appears during the playback of images with copyright information.
- In order to prevent unauthorized use of [Copyright Info], be sure to clear the [Set Photographer] and [Set Copyright] columns before lending out or handing over your camera.
- Sony is not liable for problems or damages resulting from use of [Copyright Info].

Related Topic

Using the keyboard

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α1

Write Serial Number

Writes the camera's serial number to the Exif data when shooting still images.



1 MENU → \bigcirc (Shooting) → [File] → [Write Serial Number] → desired setting.

Menu item details

On:

Writes the camera's serial number to the Exif data for the image.

Off:

Does not write the camera's serial number to the Exif data for the image.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Smartphone Connection

Sets whether to connect the camera and a smartphone.



 $MENU \rightarrow \bigoplus$ (Network) \rightarrow [Smartphone Connect] \rightarrow [Smartphone Connection] \rightarrow desired setting.

Menu item details

On:

Prepares the camera for connection with a smartphone.

Off:

Does not connect the camera and a smartphone.

Related Topic

- One-touch connection with NFC
- Connecting the camera and a smartphone using the QR Code
- Connecting the camera and a smartphone using the SSID and password

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Connection (smartphone connection information)

Displays the QR Code or SSID used to connect the camera to a smartphone.



 $\mathsf{MENU} \to \bigoplus \mathsf{(Network)} \to \mathsf{[Smartphone Connect]} \to \mathsf{[} \square \mathsf{Connection]}.$

QR Code and the SSID are displayed.

• You can switch between displaying the QR Code and password by pressing the 🗂 (Delete) button.

Related Topic

- Smartphone Connection
- Connecting the camera and a smartphone using the QR Code
- Connecting the camera and a smartphone using the SSID and password



Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Always Connected (smartphone)

Sets whether to always connect the camera and a smartphone that has previously been connected.

1

 $MENU \rightarrow \bigoplus (Network) \rightarrow [Smartphone Connect] \rightarrow [\square Always Connected] \rightarrow desired setting.$

Menu item details

On:

Connects the camera and the previously connected smartphone without any operations on the camera.

Off:

Connects the camera and the smartphone manually when you want to connect them.

Note

■ If [Always Connected] is set to [On], the power consumption will be greater than when it is set to [Off].

Related Topic

Smartphone Connection

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Bluetooth Rmt Ctrl

You can operate the camera using a Bluetooth remote commander (sold separately). For details on compatible remote commander, visit the Sony web site in your area, or consult your Sony dealer or local authorized Sony service facility. Select MENU $\rightarrow \bigoplus$ (Network) \rightarrow [Bluetooth] \rightarrow [Bluetooth Function] \rightarrow [On] in advance. Refer to the instruction manual for the Bluetooth remote commander as well.

- $\textbf{0} \quad \text{On the camera, select MENU} \rightarrow \bigoplus \text{ (Network)} \rightarrow \text{[Transfer/Remote]} \rightarrow \text{[Bluetooth Rmt Ctrl]} \rightarrow \text{[On]}.$
 - If there is no Bluetooth device currently paired with the camera, the screen for pairing as described in Step 2 will appear.
- On the camera, select MENU \rightarrow (Network) \rightarrow [Bluetooth] \rightarrow [Pairing] to display the screen for pairing.
- 3 On the Bluetooth remote commander, perform pairing.
 - For details, refer to the instruction manual for the Bluetooth remote commander.
- 4 On the camera, select [OK] on the confirmation screen for the Bluetooth connection.
 - Pairing is complete, and you can now operate the camera from the Bluetooth remote commander. After pairing
 the device once, you can connect the camera and the Bluetooth remote commander again in the future by
 setting [Bluetooth Rmt Ctrl] to [On].

Menu item details

On:

Enables Bluetooth remote commander operation.

Off:

Disables Bluetooth remote commander operation.

Hint

The Bluetooth connection is only active while you are operating the camera using the Bluetooth remote commander.

Note

- When you initialize the camera, the pairing information is also deleted. To use the Bluetooth remote commander, perform pairing again.
- If the Bluetooth connection is unstable, remove any obstacles, such as people or metal objects from between the camera and the paired Bluetooth remote commander.
- The following functions cannot be used when [Bluetooth Rmt Ctrl] is set to [On].
 - Linking location information with a smartphone
 - Infrared remote commander
 - Power-saving mode
- If the function does not work properly, check the following notes and then try pairing again.
 - Confirm that the camera is not connected with other devices using the Bluetooth function.
 - Confirm that [Airplane Mode] for the camera is set to [Off].
 - Execute [Reset Network Set.] of the camera.

Related Topic

- Bluetooth Settings
- Reset Network Set.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

WPS Push

If your access point has a Wi-Fi Protected Setup (WPS) button, you can register the access point to this product easily. For details about the available functions and settings of your access point, see the access point operating instructions or contact the administrator of the access point.



2 Push the Wi-Fi Protected Setup (WPS) button on the access point to connect.

Note

- [WPS Push] works only if the security setting of your access point is set to WPA or WPA2 and your access point supports the Wi-Fi Protected Setup (WPS) button method. If the security setting is set to WEP or your access point does not support the Wi-Fi Protected Setup (WPS) button method, perform [Access Point Set.].
- A connection may not be possible or the communication distance may be shorter depending on the surrounding conditions, such as the type of wall material and the presence of obstructions or radio waves between the product and access point. In this case, change the location of the product or move the product closer to the access point.

Related Topic

Access Point Set.


Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Access Point Set.

You can register your access point manually. Before starting the procedure, check the SSID name of the access point, security system, and password. The password may be preset in some devices. For details, see the access point operating instructions, or consult the access point administrator.


- 2 Select the access point you want to register.



When the desired access point is displayed on the screen: Select the desired access point.

When the desired access point is not displayed on the screen: Select [Manual Setting] and set the access point.

- If you select [Manual Setting], input the SSID name of the access point, then select the security system.
- Input the password, and select [OK].



- Access points without (Key mark) do not require a password.
- 4 Select [OK].

Other setting items

Depending on the status or the setting method of your access point, you may want to set more items.

WPS PIN:

Displays the PIN code you enter into the connected device.

Priority Connection:

Select [On] or [Off].

IP Address Setting:

Select [Auto] or [Manual].

IP Address:

If you are entering the IP address manually, enter the set address.

Subnet Mask/Default Gateway/Primary DNS Server/Second DNS Server:

If you have set [IP Address Setting] to [Manual], enter each address according to your network environment.

Note

• To give the registered access point priority in the future, set [Priority Connection] to [On].

Related Topic

- WPS Push
- Using the keyboard

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Wi-Fi Frequency Band (models supporting 5 GHz)

Sets the frequency band for Wi-Fi communications. [5GHz] has faster communication speeds and more stable data transfers than [2.4GHz]. The [Wi-Fi Frequency Band] setting applies to smartphone transfers, remote shooting, and the PC remote function via a Wi-Fi Direct connection.



Menu item details

2.4GHz/5GHz

Note

• If there are both 2.4 GHz and 5 GHz access points with the same SSID and encryption format, the access point with the stronger radio field will be displayed.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Display Wi-Fi Info.

Displays Wi-Fi information for the camera such as the MAC address, IP address, etc.



 $MENU \rightarrow \bigoplus (Network) \rightarrow [Wi-Fi] \rightarrow [Display Wi-Fi Info.].$

Hint

- Information other than the MAC address is displayed under the following conditions.
 - [FTP Function] under [FTP Transfer Func.] is set to [On], and a Wi-Fi connection has been established.
 - [PC Remote] is set to [On] and [PC Remote Cnct Method] is set to [Wi-Fi Access Point] under [PC Remote Function], and a Wi-Fi connection has been established.

To display the QR Code for the MAC address

- You can import the MAC address of this camera to a smartphone. Use one of the following methods to display the QR Code on the screen, and read the QR Code using the Transfer & Tagging add-on smartphone application.
 - When the camera is turned off, turn the camera on while pressing the ▶ (Playback) button.
 - Press the 🗂 (Delete) button on the [Display Wi-Fi Info.] screen.

For details on how to read the QR Code using the Transfer & Tagging add-on, refer to the following support page. https://support.d-imaging.sony.co.jp/app/transfer/l/macaddress/index.php

The Transfer & Tagging add-on is only available in certain countries and regions.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

SSID/PW Reset

This product shares connection information with devices that have permission to connect when connecting to a smartphone or establishing a Wi-Fi Direct connection with a computer. If you want to change which devices have permission to connect, reset the connection information.



Note

- If you connect this product to a smartphone after resetting the connection information, you must make the settings for the smartphone again.
- If you connect this product to a computer with Wi-Fi Direct after resetting the connection information, you must reconfigure the settings of the computer.

Related Topic

Operating the camera from a computer (PC Remote Function)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Bluetooth Settings

Controls the settings for connecting the camera to a smartphone or Bluetooth remote commander via a Bluetooth connection.

If you want to pair the camera and smartphone in order to use the location information link function, refer to "Location Information ."

If you want to perform pairing in order to use a Bluetooth remote commander, refer to "Bluetooth Rmt Ctrl."



 $MENU \rightarrow \bigoplus$ (Network) \rightarrow [Bluetooth] \rightarrow Select a menu item and set the desired parameter.

Menu item details

Bluetooth Function:

Sets whether to activate or not the Bluetooth function of the camera. (On/Off)

Pairing:

Displays the screen for pairing the camera and smartphone or Bluetooth remote commander.

Disp Device Address:

Displays the BD address of the camera.

Related Topic

- Location Information
- Bluetooth Rmt Ctrl
- Cnct. during Power OFF

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Wired LAN

Configures a wired LAN.



 $MENU \rightarrow \bigoplus (Network) \rightarrow [Wired LAN] \rightarrow desired setting.$

Menu item details

IAN IP Address Setting:

Sets whether to configure the IP address for the wired LAN automatically or manually. ([Auto]/[Manual])

Display Wired LAN Info.:

Displays wired LAN information for this product such as the MAC address or IP address.

IP Address:

If you are entering the IP address manually, enter the fixed address.

Subnet Mask/Default Gateway/Primary DNS Server/Second DNS Server:

If you have set [[AN] IP Address Setting] to [Manual], enter each address according to your network environment.

Hint

To display the QR Code for the MAC address

- You can import the MAC address of this camera to a smartphone. Use one of the following methods to display the QR Code on the screen, and read the QR Code using the Transfer & Tagging add-on smartphone application.

 - Press the 📺 (Delete) button on the [Display Wired LAN Info.] screen.

For details on how to read the QR Code using the Transfer & Tagging add-on, refer to the following support page. https://support.d-imaging.sony.co.jp/app/transfer/l/macaddress/index.php

The Transfer & Tagging add-on is only available in certain countries and regions.

Related Topic

Using the keyboard

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Airplane Mode

When you board an airplane, etc., you can temporarily disable all the wireless-related functions including Wi-Fi.



 $\textbf{MENU} \rightarrow \bigoplus \textbf{(Network)} \rightarrow \textbf{[Network Option]} \rightarrow \textbf{[Airplane Mode]} \rightarrow \textbf{desired setting}.$

If you set [Airplane Mode] to [On], an airplane mark will be displayed on the screen.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Edit Device Name

You can change the device name for Wi-Fi Direct, [PC Remote], or Bluetooth connections.

- 2 Select the input box, then input the device name \rightarrow [OK].

Related Topic

- WPS Push
- Access Point Set.
- Operating the camera from a computer (PC Remote Function)
- Using the keyboard

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Importing root certification to the camera (Import Root Certificate)

Imports a root certificate needed to verify a server from a memory card. Use this function for encrypted communications during FTP transfer.

For details, refer to the "FTP Help Guide." https://rd1.sony.net/help/di/ftp_2040/h_zz/

MENU → ∰ (Network) → [Network Option] → [Import Root Certificate].

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Security(IPsec)

Encrypts data when the camera and a computer communicate via a wired LAN or Wi-Fi connection.



 $MENU \rightarrow \bigoplus (Network) \rightarrow [Network Option] \rightarrow [Security(IPsec)] \rightarrow desired setting.$

Menu item details

IPsec:

Sets whether or not the [Security(IPsec)] function is used. ([On]/[Off])

Dest. IP Address:

Sets the IP address of the device to connect using the [Security(IPsec)] function.

Shared Key:

Sets the shared key used by the [Security(IPsec)] function.

Note

- Use at least eight and no more than 20 alphanumeric characters or symbols for [Shared Key].
- For IPsec communications, the device to connect must be compatible with IPsec.
 Depending on the device, communications may not be possible or the communication speed may be slow.
- On this camera, IPsec operates in transport mode only and uses IKEv2.
 The algorithms are AES with 128-bit keys in CBC mode/Diffie-Hellman 3072-bit modp group/PRF-HMAC-SHA-256/HMAC-SHA-384-192.

The authentication expires after 24 hours.

- Encrypted communications can only be made with devices that are configured correctly. Communications with other devices are not encrypted.
- For details on the IPsec configuration, consult the administrator of the network for your device.

Related Topic

Using the keyboard

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Reset Network Set.

Resets all the network settings to default settings.



Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

FTP Transfer Func.

You can set up image transferring using an FTP server or transfer images to the FTP server. Basic knowledge of FTP servers is required.

For details, refer to the "FTP Help Guide." https://rd1.sony.net/help/di/ftp_2040/h_zz/



Related Topic

Importing root certification to the camera (Import Root Certificate)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Monitor Brightness

Adjust the brightness of the screen.



Menu item details

Manual:

Adjusts the brightness within the range of -2 to +2.

Sunny Weather:

Sets the brightness appropriately for shooting outdoors.

Note

The [Sunny Weather] setting is too bright for shooting indoors. Set [Monitor Brightness] to [Manual] for indoor shooting.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Viewfinder Bright.

When using the viewfinder, this product adjusts the brightness of the viewfinder according to the surrounding environment.



 $\textbf{MENU} \rightarrow \begin{tabular}{l} \hline \bullet \\ \hline \bullet \\ \hline \hline \end{tabular} (Setup) \rightarrow \begin{tabular}{l} \hline \bullet \\ \hline \hline \end{tabular} on itor] \rightarrow \begin{tabular}{l} \hline \bullet \\ \hline \hline \end{tabular} on itor] \rightarrow \begin{tabular}{l} \hline \bullet \\ \hline \hline \end{tabular} on itor] \rightarrow \begin{tabular}{l} \hline \bullet \\ \hline \hline \end{tabular} on itor] \rightarrow \begin{tabular}{l} \hline \bullet \\ \hline \hline \end{tabular} on itor] \rightarrow \begin{tabular}{l} \hline \bullet \\ \hline \hline \end{tabular} on itor] \rightarrow \begin{tabular}{l} \hline \bullet \\ \hline \hline \end{tabular} on itor] \rightarrow \begin{tabular}{l} \hline \bullet \\ \hline \end{tabular} on itor] \rightarrow \begin{tabular}{l} \hline \bullet \\ \hline \end{tabular} on itor] \rightarrow \begin{tabular}{l} \hline \bullet \\ \hline \end{tabular} on itor] \rightarrow \begin{tabular}{l} \hline \bullet \\ \hline \end{tabular} on itor] \rightarrow \begin{tabular}{l} \hline \bullet \\ \hline \end{tabular} on itor] \rightarrow \begin{tabular}{l} \hline \bullet \\ \hline \end{tabular} on itor] \rightarrow \begin{tabular}{l} \hline \bullet \\ \hline \end{tabular} on itor] \rightarrow \begin{tabular}{l} \hline \bullet \\ \hline \end{tabular} on itor] \rightarrow \begin{tabular}{l} \hline \bullet \\ \hline \end{tabular} on itor] \rightarrow \begin{tabular}{l} \hline \bullet \\ \hline \end{tabular} on itor] \rightarrow \begin{tabular}{l} \hline \bullet \\ \hline \end{tabular} on itor] \rightarrow \begin{tabular}{l} \hline \bullet \\ \hline \end{tabular} on itor] \rightarrow \begin{tabular}{l} \hline \bullet \\ \hline \end{tabular} on itor] \rightarrow \begin{tabular}{l} \hline \bullet \\ \hline \end{tabular} on itor] \rightarrow \begin{tabular}{l} \hline \bullet \\ \hline \end{tabular} on itor] \rightarrow \begin{tabular}{l} \hline \bullet \\ \hline \end{tabular} on itor] \rightarrow \begin{tabular}{l} \hline \bullet \\ \hline \end{tabular} on itor] \rightarrow \begin{tabular}{l} \hline \bullet \\ \hline \end{tabular} on itor] \rightarrow \begin{tabular}{l} \hline \bullet \\ \hline \end{tabular} on itor] \rightarrow \begin{tabular}{l} \hline \bullet \\ \hline \end{tabular} on itor] \rightarrow \begin{tabular}{l} \hline \bullet \\ \hline \end{tabular} on itor] \rightarrow \begin{tabular}{l} \hline \bullet \\ \hline \end{tabular} on itor] \rightarrow \begin{tabular}{l} \hline \bullet \\ \hline \end{tabular} on itor] \rightarrow \begin{tabular}{l} \hline \bullet \\ \hline \end{tabular} on itor] \rightarrow \begin{tabular}{l} \hline \bullet \\ \hline \end{tabular} on itor] \rightarrow \begin{tabular}{l} \hline \bullet \\ \hline \end{tabular} on itor] \rightarrow \begin{tabular}{l} \hline \bullet \\ \hline \end{tabular} on itor] \rightarrow \begin{tabular}{l} \hline \bullet \\ \hline \end{tabular} on itor] \rightarrow \begin{tabular}{l} \hline \bullet \\ \hline \end{tabular} on itor] \rightarrow \begin{tabular}{l} \hline \bullet \\ \hline \end{tabular} on itor] \rightarrow \begin{tabular}{l} \hline \bullet \\ \hline \end{tabul$

Menu item details

Auto:

Adjusts the brightness automatically.

Manual:

Selects the brightness of the viewfinder within the range of –2 to +2.

Note

When the temperature of the camera rises, the viewfinder may become dark.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α1

Finder Color Temp.

Adjusts the color temperature of the viewfinder.



1 MENU → \longrightarrow (Setup) → [Finder/Monitor] → [Finder Color Temp.] → desired setting.

Menu item details

-2 to +2:

When you select "-," the viewfinder screen changes to a warmer color, and when you select "+," it changes to a colder color.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Viewfinder Magnifi.

Sets the display magnification of the viewfinder. If you select [Zoom Out], the viewing angle will become narrower. You can easily check the overall composition even when wearing glasses.



Menu item details

Standard

Sets the viewfinder display magnification to standard.

Zoom Out:

Reduces the viewfinder display magnification.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Finder Frame Rate (still image)

Display the subject's movements more smoothly by adjusting the frame rate of the viewfinder during still image shooting. This function is convenient when shooting a fast-moving subject.



 $MENU \rightarrow \ \ \ \ \ \ \$ [Finder/Monitor] \rightarrow [Finder Frame Rate] \rightarrow desired setting.

This function can be assigned to key of your choice using [Custom Key Setting].

Menu item details

Standard:

Displays the subject at a normal frame rate on the viewfinder.

High:

Displays the movements of the subject more smoothly on the viewfinder.

Higher:

Displays the movements of the subject more smoothly on the viewfinder than [High].

Note

- When [Finder Frame Rate] is set to [Higher], the viewfinder resolution becomes lower and the display magnification becomes smaller.
- When [Finder Frame Rate] is set to [High] or [Higher], [Display Quality] becomes locked to [Standard].
- Even if [Finder Frame Rate] is set to [High] or [Higher], the frame rate may be restricted depending on the temperature of the shooting environment and the shooting conditions.
- The frame rate is restricted in the following situations:
 - During playback
 - During HDMI connection
 - When the temperature inside the camera's body is high
 - When [Shutter Type] is set to [Electronic Shutter] or [Auto] and continuous shooting is performed.

Related Topic

Assigning frequently used functions to buttons (Custom Key Setting)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Auto Monitor OFF (still image)

Sets whether or not to turn the monitor off automatically in shooting modes for still images.



 $\textbf{MENU} \rightarrow \begin{tabular}{l} \blacksquare \end{tabular} \textbf{(Setup)} \rightarrow \begin{tabular}{l} \textbf{Power Setting Option]} \rightarrow \begin{tabular}{l} \end{tabular} \begin{tabular}{l} \blacksquare \end{tabular} \textbf{Auto Monitor OFF]} \rightarrow \begin{tabular}{l} \textbf{desired setting.} \end{tabular}$

Menu item details

Does not turn OFF:

Does not turn the monitor off.

2 Sec/5 Sec/10 Sec:

Turns the monitor off after the designated time has been elapsed without any operation performed. You can resume shooting by performing an operation, such as pressing the shutter button halfway down.

Note

If you will not be using the camera for a long period of time, turn the camera off.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Power Save Start Time

Sets time intervals to automatically switch to power save mode when you are not performing operations to prevent wearing down the battery pack. To return to shooting mode, perform an operation such as pressing the shutter button halfway down.



 $MENU \rightarrow \longrightarrow (Setup) \rightarrow [Power Setting Option] \rightarrow [Power Save Start Time] \rightarrow desired setting.$

Menu item details

Off/30 Min/5 Min/2 Min/1 Min/10 Sec

Note

- Turn off the product when you do not use it for a long time.
- The power save function is deactivated in the following situations:
 - While power is being supplied via USB
 - While playing back slideshows
 - During FTP transfer
 - While recording movies
 - While connected to a computer or TV
 - While [IR Remote Ctrl] is set to [On]
 - When [Bluetooth Rmt Ctrl] is set to [On]

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Auto Power OFF Temp.

Sets the temperature of the camera at which the camera turns off automatically during shooting. When it is set to [High], you can continue shooting even when the temperature of the camera gets hotter than normal.



Menu item details

Standard:

Sets the standard temperature for the camera to turn off.

High:

Sets the temperature at which the camera turns off to higher than [Standard].

Notes when [Auto Power OFF Temp.] is set to [High]

- Do not shoot while holding the camera in your hand. Use a tripod.
- Using the camera while holding it in your hand for a long period of time may cause low-temperature burns.

Continuous recording time for movies when [Auto Power OFF Temp.] is set to [High]

The duration of time available for continuous movie recording is as follows when the camera starts recording with the default settings after the power has been turned off for a while. The following values indicate the continuous time from when the camera starts recording until the camera stops recording.

Ambient temperature: 25°C (77°F)

Continuous recording time for movies (HD): Approx. 120 minutes

Continuous recording time for movies (4K): Approx. 30 minutes

Continuous recording time for movies (8K): Approx. 30 minutes

Ambient temperature: 40°C (104°F)

Continuous recording time for movies (HD): Approx. 90 minutes

Continuous recording time for movies (4K): Approx. 10 minutes

Continuous recording time for movies (8K): Approx. 20 minutes

HD: XAVC S HD (60p 50M/50p 50M 4:2:0 8bit; when the camera is not connected via Wi-Fi; when using a CFexpress Type A memory card)

4K: XAVC S 4K (60p 150M/50p 150M 4:2:0 8bit; when the camera is not connected via Wi-Fi; when using a CFexpress Type A memory card)

8K: XAVC HS 8K (30p 200M/25p 200M 4:2:0 10bit; when the camera is not connected via Wi-Fi; when using a CFexpress Type A memory card)

Note

Even if [Auto Power OFF Temp.] is set to [High], depending on the conditions or the temperature of the camera, the recordable time for movies may not change.

Related Topic

Recordable movie times

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Display Quality

You can change the display quality.



 $MENU \rightarrow \longrightarrow (Setup) \rightarrow [Finder/Monitor] \rightarrow [Display Quality] \rightarrow desired setting.$

Menu item details

High:

Displays in high quality.

Standard:

Displays in standard quality.

Note

- When [High] is set, battery consumption will be higher than when [Standard] is set.
- When the temperature of the camera rises, the setting may become locked to [Standard].
- When [Finder Frame Rate] is set to [High] or [Higher], [Display Quality] becomes locked to [Standard].
- When "-" is displayed as the setting value for [Display Quality], you cannot view or change the setting. Set [Finder Frame Rate] to [Standard] to change the setting for [Display Quality].

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

USB Connection

Selects the USB connection method when this product is connected to a computer, etc. Select MENU $\rightarrow \bigoplus$ (Network) \rightarrow [Smartphone Connect] \rightarrow [Smartphone Connection] \rightarrow [Off] beforehand. Also, when you set MENU $\rightarrow \bigoplus$ (Network) \rightarrow [Transfer/Remote] \rightarrow [PC Remote Function] \rightarrow [PC Remote Cnct Method] to [USB], set [PC Remote] under [PC Remote Function] to [Off].



 $MENU \rightarrow \longrightarrow (Setup) \rightarrow [USB] \rightarrow [USB Connection] \rightarrow desired setting.$

Menu item details

Auto:

Establishes a Mass Storage or MTP connection automatically, depending on the computer or other USB devices to be connected.

Mass Storage:

Establishes a Mass Storage connection between this product, a computer, and other USB devices.

MTP:

Establishes an MTP connection between this product, a computer, and other USB devices.

• The memory card in memory card slot 1 is the connection target.

Note

It may take some time to make the connection between this product and a computer when [USB Connection] is set to [Auto].

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

USB LUN Setting

Enhances compatibility by limiting of USB connection functions.



 $\textbf{MENU} \rightarrow \begin{tabular}{l} \blacksquare \end{tabular} \textbf{MENU} \rightarrow \begin{tabular}{l} \blacksquare \end{tabular} \textbf{(Setup)} \rightarrow \begin{tabular}{l} \blacksquare \end{tabular} \textbf{Setting} \end{tabular} \rightarrow \begin{tabular}{l} \blacksquare \end{tabular} \textbf{MENU} \rightarrow \begin{tabular}{l} \blacksquare \end{tabular} \textbf{Setting} \end{tabular} \rightarrow \begin{tabular}{l} \blacksquare \end{tabular} \textbf{MENU} \rightarrow \begin{tabular}{l$

Menu item details

Multi:

Normally, use [Multi].

Single:

Set [USB LUN Setting] to [Single] only if you cannot make a connection.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

USB Power Supply

Sets whether to supply power via the USB cable when the product is connected to a computer or an USB device.



 $\textbf{MENU} \rightarrow \begin{tabular}{l} \hline \bullet \\ \hline \bullet \\ \hline \hline \end{tabular} \begin{tabular}{l} \textbf{MENU} \\ \hline \hline \end{tabular} \rightarrow \begin{tabular}{l} \textbf{USB} \\ \hline \end{tabular} \rightarrow \beg$

Menu item details

On:

Power is supplied to the product via a USB cable when the product is connected to a computer, etc.

Off:

Power is not supplied to the product via a USB cable when the product is connected to a computer, etc.

Operations available while supplying power via a USB cable

The following table shows you which operations are available/unavailable while supplying power via a USB cable.

Operation	Available / Unavailable
Shooting images	Available
Playing back images	Available
Wi-Fi/NFC/Bluetooth connections	Available
Charging a battery pack	Unavailable
Turning the camera on without a battery pack inserted	Unavailable

Note

- Insert the battery pack into the product to supply power via USB cable.
- This product cannot be powered via the Multi/Micro USB terminal. Use the USB Type-C terminal.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

HDMI Resolution

When you connect the camera to a TV or monitor device using an HDMI cable (sold separately), you can select the resolution to be output from the HDMI terminal of the camera during still image shooting or playback.



 $MENU \rightarrow \longrightarrow (Setup) \rightarrow [External Output] \rightarrow [\longrightarrow HDMI Resolution] \rightarrow desired setting.$

Menu item details

Auto:

The camera automatically recognizes the resolution of the connected TV or output device and sets the output resolution accordingly.

4320p/2160p:

Outputs signals in 4320p/2160p.

2160p:

Outputs signals in 2160p.

1080p:

Outputs signals in HD picture quality (1080p).

1080i:

Outputs signals in HD picture quality (1080i).

Note

• If images are not displayed properly using the [Auto] setting, select [1080i], [1080p], [2160p], or [4320p/2160p] based on the connected TV.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

HDMI Output Settings (movie)

Sets the video and audio to be output to an external recorder/player connected via HDMI when shooting a movie. Use a Premium High Speed HDMI Cable (sold separately) to output 4K/8K movies or RAW movies.



 $\textbf{MENU} \rightarrow \ \ \, \textbf{(Setup)} \rightarrow \ \ \, \textbf{[External Output]} \rightarrow \ \ \, \textbf{[III]} \ \, \textbf{HDMI Output Settings]} \rightarrow \ \, \textbf{desired setting item}.$

Menu item details

Rec. Media dur HDMI Output:

Sets whether or not to record movies on the memory card of the camera during HDMI output.

[Off(HDMI Only)]: Does not record movies on the memory card of the camera, and outputs movies only to devices connected via HDMI.

Output Resolution:

Sets the resolution of the image that will be output to another device connected via HDMI when [Rec. Media dur HDMI Output] is set to [On] and [RAW Output] is set to [Off]. ([Auto] / [4320p/2160p] / [2160p] / [1080p] / [1080i])

4K Output Set.(HDMI Only):

Sets the frame rate and color depth of 4K movie output to another device connected via HDMI when [Rec. Media dur HDMI Output] is set to [Off(HDMI Only)] and [RAW Output] is set to [Off]. ([60p 10bit] / [50p 10bit] / [30p 10bit] / [25p 10bit] / [24p 10bit])

RAW Output:

Sets whether or not to output RAW movies to another RAW-compatible device connected via HDMI. ([On] / [Off])

RAW Output Setting:

Sets the frame rate when outputting RAW movies to another RAW-compatible device connected via HDMI. ([60p] / [50p] / [30p] / [25p] / [24p])

Color Gamut for RAW Output:

Sets the color gamut when outputting RAW movies to another RAW-compatible device connected via HDMI. ([S-Gamut3.Cine/S-log3] / [S-Gamut3/S-log3])

Time Code Output:

Sets whether or not to output the time code and user bit to another device connected via HDMI. ([On] / [Off])

Time code information is transmitted as digital data, not as an image displayed on the screen. The connected device can then refer to the digital data in order to recognize the time data.

REC Control:

Sets whether to start or stop recording on the external recorder/player remotely by operating the camera when the camera is connected to an external recorder/player. ([On] / [Off])

4ch Audio Output:

When recording audio in 4 channels, set the combination of audio channels that will be output to other devices connected via HDMI.

[CH1/CH2]: Outputs audio from channel 1 to the L (left) side and from channel 2 to the R (right) side.

[CH3/CH4]: Outputs audio from channel 3 to the L (left) side and from channel 4 to the R (right) side.

Hint

- With [REC Control] set to [On], (STBY) is displayed when a recording command is ready to be sent to the external recorder/player, and (REC) is displayed when a recording command is being sent to the external recorder/player.
- Even when playing back a movie with 4 channels on a device connected to the HDMI terminal of the camera, the audio is output with the [4ch Audio Output] setting.

Note

- RAW movies cannot be recorded on the memory card of the camera.
- When [Output Resolution] is set to [4320p/2160p], 8K output to a TV is enabled but the output format is limited to 4:2:0 8bit.
- During slow-motion/quick-motion shooting, [Rec. Media dur HDMI Output] is locked to [On] and [RAW Output] is locked to [Off]. It is not possible to only output 4K movies to a device connected via HDMI without recording the movies on a memory card. It is also not possible to output RAW movies.
- When [Rec. Media dur HDMI Output] is set to [Off(HDMI Only)] or the camera outputs RAW movies, [HDMI Info. Display] becomes temporarily set to [Off].
- When [Rec. Media dur HDMI Output] is set to [Off(HDMI Only)], the counter does not move forward (the actual recording time is not counted) while the movie is being recorded on an external recorder/player.
- [REC Control] can be used with external recorders/players that support the [REC Control] function.
- When [Time Code Output] is set to [Off], you cannot set [REC Control].
- Even when (REC) is displayed, the external recorder/player may not work properly depending on the settings or status of the recorder/player. Check if the external recorder/player works properly before use.
- When [Time Code Output] is set to [On], images may not be output properly to the TV or recording device. In this case, set [Time Code Output] to [Off].
- It is not possible to output audio in 4 channels to other devices connected via HDMI.
- The gamma is locked to S-Log3 during RAW output. You can reproduce contrast equivalent to that of the normal gamma by setting [Gamma Display Assist] to [On] and [Gamma Disp. Assist Typ.] to [Auto] or [S-Log3→709(800%)].
- While outputting RAW movies, you cannot use [Active] for [SteadyShot].

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

HDMI Info. Display

Selects whether or not to display shooting information on a TV or a monitor device when the camera and TV, etc. are connected via an HDMI cable (sold separately).



 $MENU \rightarrow \longrightarrow (Setup) \rightarrow [External Output] \rightarrow [HDMI Info. Display] \rightarrow desired setting.$

Menu item details

On

Displays the shooting information on the TV.

The recorded image and shooting information are displayed on the TV, while nothing is displayed on the camera's monitor.

Off:

Does not display the shooting information on the TV.

Only the recorded image is displayed on the TV, while the recorded image and shooting information are displayed on the camera's monitor.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

CTRL FOR HDMI

When connecting this product to a "BRAVIA" Sync-compatible TV using an HDMI cable (sold separately), you can operate this product by aiming the TV remote control at the TV.

- Connect this product to a "BRAVIA" Sync-compatible TV.

The input of the TV is switched automatically and images on this product are displayed on the TV screen.

- 3 Press the SYNC MENU button of the TV's remote control.
- 4 Operate this product using the TV's remote control.

Menu item details

On:

You can operate this product with a TV's remote control.

Off:

You cannot operate this product with a TV's remote control.

Note

- If you connect this product to a TV using an HDMI cable, available menu items are limited.
- [CTRL FOR HDMI] is available only with a "BRAVIA" Sync-compatible TV. Also, the SYNC MENU operation differs depending on the TV you are using. For details, refer to the operating instructions supplied with the TV.
- If the product performs unwanted operations in response to the TV remote control when the product is connected to another manufacturer's TV using an HDMI connection, set [CTRL FOR HDMI] to [Off].

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Language

Selects the language to be used in the menu items, warnings and messages.



Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Area/Date/Time Setting

You can set the area (where you are using the camera), daylight savings ([On]/[Off]), the date display format, and the date and time.

The Area/Date/Time Setting screen is displayed automatically when you turn on the product for the first time or when the internal rechargeable backup battery has fully discharged. Select this menu when setting the date and time after the first time.



 $MENU \rightarrow \longrightarrow (Setup) \rightarrow [Area/Date] \rightarrow [Area/Date/Time Setting] \rightarrow desired setting.$

Menu item details

Area Setting:

Sets the area where you are using the camera.

Daylight Savings:

Selects Daylight Savings [On] / [Off].

Date/Time:

Sets the date and time.

Date Format:

Selects the date display format.

Hint

- To charge the internal rechargeable backup battery, insert a charged battery pack, and leave the product for 24 hours or more with the power off.
- If the clock resets every time the battery is charged, the internal rechargeable backup battery may be worn out. Consult your service facility.

Related Topic

Setting language, date and time

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

NTSC/PAL Selector

Plays back movies recorded with the product on a NTSC/PAL system TV.



Note

When you perform [NTSC/PAL Selector], and the setting is changed from the default one, a message "Running on NTSC." or "Running on PAL." will appear on the start-up screen.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Audio signals

Selects whether the product produces a sound or not.



 $MENU \rightarrow \longrightarrow (Setup) \rightarrow [Sound Option] \rightarrow [Audio signals] \rightarrow desired setting.$

Menu item details

On:all:

Sounds are produced for example when the focus is achieved by pressing the shutter button halfway down.

On:w/o shutter

Sounds are produced when focusing by pressing the shutter button halfway down, etc. The electronic shutter does not produce any sounds.

On:shutter only:

Only the electronic shutter produces sounds. Sounds are not produced when focusing by pressing the shutter button halfway down, etc.

Off:

Sounds are not produced.

Hint

When [Silent Mode] is set to [On], [Audio signals] becomes locked to [Off].

Note

If [Focus Mode] is set to [Continuous AF], the camera will not beep when it focuses on a subject.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

IR Remote Ctrl

You can operate the camera using a Infrared Remote Commander (sold separately). For details on compatible remote commander, visit the Sony web site in your area, or consult your Sony dealer or local authorized Sony service facility. Refer also to the operating instructions for the Infrared Remote Commander.



 $\textbf{MENU} \rightarrow \begin{tabular}{l} \hline \bullet \\ \hline \bullet \\ \hline \hline \end{tabular} \begin{tabular}{l} \textbf{MENU} \\ \hline \hline \end{tabular} \rightarrow \begin{tabular}{l} \textbf{Setup} \\ \hline \end{tabular} \rightarrow \begin{tabular}{l} \textbf{IR} \\ \hline \end{tabular} \begin{tabular}{l} \textbf{Remote Ctrl} \\ \hline \end{tabular} \rightarrow \begin{tabular}{l} \textbf{desired setting.} \\ \hline \end{tabular}$

Menu item details

On:

Allows infrared remote commander operation.

Off:

Does not allow infrared remote commander operation.

Note

- The lens or lens hood may block the infrared remote sensor that receive the signals. Use the infrared remote commander in the position from which the signal can reach the product.
- When [IR Remote Ctrl] is set to [On], the product does not switch to power save mode. Set [Off] after using an infrared remote commander.
- An infrared remote commander cannot be used while [Bluetooth Rmt Ctrl] is set to [On].

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Anti-dust Function

If dust or debris gets inside the camera and adheres to the surface of the image sensor, clean the image sensor using [Sensor Cleaning]. You can also set whether or not to close the shutter when you turn off the camera so that dust or debris is prevented from adhering to the image sensor.



 $MENU \rightarrow \ \ \ \ \ \ \$ (Setup) \rightarrow [Setup Option] \rightarrow [Anti-dust Function] \rightarrow desired setting item.

Menu item details

Sensor Cleaning:

The image sensor vibrates a little to shake off the dust. Use a commercially available blower to clean the image sensor surface if necessary.

Shutter When Pwr OFF:

Sets whether to close the shutter when you turn off the camera. ([On]/[Off])

• If you select [On], the shutter will close when you set the ON/OFF (power) switch to OFF while the camera is turned on. Note that it may take some time for the shutter to close after you set the ON/OFF (power) switch to OFF.
The shutter also makes a sound when the ON/OFF (power) switch is set to ON or OFF.

Hint

To clean the image sensor by yourself, execute [Sensor Cleaning] or set [Shutter When Pwr OFF] to [Off].

Note

- When [Shutter When Pwr OFF] is set to [On], attach the lens cap before storing the camera. Otherwise, a strong light source (such as sunlight) may become focused inside the camera, causing smoke or fire. Even if the light source is slightly away from the angle of view, it may still cause smoke or fire when the lens cap is not attached.
- Do not touch the closed shutter with your fingers or clean it with a blower. The shutter may become damaged.
- If there is a risk of water droplets adhering to the shutter, set [Shutter When Pwr OFF] to [Off]. If [Shutter When Pwr OFF] is set to [On], water droplets may adhere to the shutter and cause a malfunction.
- Make sure that the remaining battery level is 1 (3 remaining battery icons) or more before performing [Sensor Cleaning].
- Even if [Shutter When Pwr OFF] is set to [On], the shutter will not close when the power turns off due to activation of the power-saving mode or battery exhaustion. In this case, you can close the shutter by turning the camera on and off again.

Related Topic

Cleaning the image sensor (Sensor Cleaning)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Auto Pixel Mapping

Sets whether or not to automatically optimize the image sensor (pixel mapping). Normally, set this function to [On].



 $MENU \rightarrow \longrightarrow (Setup) \rightarrow [Setup Option] \rightarrow [Auto Pixel Mapping] \rightarrow desired setting.$

Menu item details

On:

Performs pixel mapping automatically at regular intervals when you turn off the camera.

During this time, shutter sounds will be produced.

Off:

Does not perform pixel mapping automatically.

Hint

• If [Auto Pixel Mapping] is set to [Off], perform [Pixel Mapping] regularly. We recommend that you perform the operation once every three days.

Note

If [Pixel Mapping] is not performed regularly, bright spots may appear in recorded images.

Related Topic

- Pixel Mapping
- Silent Mode Settings (still image/movie)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Pixel Mapping

You can manually optimize the image sensor (pixel mapping). If [Auto Pixel Mapping] is set to [Off], perform [Pixel Mapping] regularly according to the following procedure. We recommend that you perform the operation once every three days.



2 Select [OK] on the confirmation screen.

Pixel mapping will be performed.

- The camera cannot be operated during pixel mapping.
- The camera will restart when pixel mapping is complete.

Hint

If you see bright spots in a recorded image on the camera monitor, immediately perform [Pixel Mapping].

Note

Pixel mapping cannot be performed when the battery is low.

Related Topic

Auto Pixel Mapping

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Version

Displays the version of this product's software. Check the version when updates for this product's software are released, etc.

Also displays the version of the lens if a lens compatible with firmware updates is attached.

The version of the Mount Adaptor is displayed in the lens area if a Mount Adaptor compatible with firmware updates is attached.



 $\mathsf{MENU} \to \ \, \overline{\longleftarrow} \ \, (\mathsf{Setup}) \to [\mathsf{Setup Option}] \to [\mathsf{Version}].$

Note

Updating can be performed only when the battery level is battery pack.
 (3 remaining battery bars) or more. Use a sufficiently charged battery pack.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Save/Load Settings

You can save/load camera settings to/from a memory card. You can also load settings from another camera of the same model.



 $MENU \rightarrow \longrightarrow (Setup) \rightarrow [Reset/Save Settings] \rightarrow [Save/Load Settings] \rightarrow desired item.$

Menu item details

Load:

Loads the settings from a memory card to this camera.

Save

Saves the current settings of this camera to a memory card.

Delete:

Deletes the settings saved on a memory card.

Settings that cannot be saved

The following setting parameters cannot be saved using the [Save/Load Settings] function. (Menu items without setting parameters, such as, [Focus Magnifier], are not listed.)

(Shooting)

IPTC Information

Copyright Info

(Exposure/Color)

External Flash Set.

White Balance: Custom 1/Custom 2/Custom 3

AF_{MF} (Focus)

Face Memory

(Network)

FTP Transfer Func.*

WPS Push

Access Point Set.

Wi-Fi Frequency Band

LAN IP Address Setting

Edit Device Name

Import Root Certificate

Security(IPsec)

* You can save or load settings under [FTP Transfer Func.] by selecting MENU → (Network) → [Transfer/Remote] → [FTP Transfer Func.] → [Save/Load FTP Settings]. For details, refer to the "FTP Help Guide." https://rd1.sony.net/help/di/ftp_2040/h_zz/

(Setup)

Area/Date/Time Setting

Note

- You can save up to 10 settings per memory card. When 10 settings have been already saved, you cannot perform [Save New].
 Delete the existing settings using [Delete], or overwrite them.
- Only Slot 1 is used for saving or loading data. You cannot change the saving/loading destination slot.
- You cannot load settings from a camera of a different model.
- You can use this function to save settings registered to [MR Camera Set. Memory]. However, [Save/Load Settings] is unavailable when the mode dial is set to 1/2/3 (MR Recall Camera Setting). Set the mode dial to a position other than 1/2/3 before using this function.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Setting Reset

Resets the product to the default settings. Even if you perform [Setting Reset], the recorded images are retained.



 $\textbf{MENU} \rightarrow \begin{tabular}{l} \hline \bullet \\ \hline \bullet \\ \hline \end{tabular} (Setup) \rightarrow [Reset/Save Settings] \rightarrow [Setting Reset] \rightarrow desired setting.$

Menu item details

Camera Settings Reset:

Initializes the main shooting settings to the default settings. The setting values for both still image shooting and movie recording are initialized.

Initialize:

Initializes all the settings to the default settings.

Note

- Be sure not to eject the battery pack while resetting.
- Settings of [Page Profile] will not be reset even when [Camera Settings Reset] or [Initialize] is performed.
- The check mark for [Picture Profile] in [Different Set for Still/Mv] is not reset when you perform either [Camera Settings Reset] or [Initialize].

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Functions available with a smartphone (Imaging Edge Mobile)

Using the smartphone application Imaging Edge Mobile, you can shoot an image while controlling the camera using a smartphone or transfer the images recorded on the camera to the smartphone.

Download and install the application Imaging Edge Mobile from your smartphone's application store. If Imaging Edge Mobile is already installed on your smartphone, be sure to update it to the latest version.

For details on Imaging Edge Mobile, refer to the support page (https://www.sony.net/iem/).

Note

Depending on future version upgrades, the operational procedures or screen displays are subject to change without notice.

Help Guide


Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Connecting the camera and a smartphone using the QR Code

You can connect your smartphone to the camera using the QR Code. You can connect to the camera with the same operation on any Android smartphone, iPhone, or iPad.

To connect the camera and your smartphone, Imaging Edge Mobile is required. Download and install the application Imaging Edge Mobile from your smartphone's application store. If Imaging Edge Mobile is already installed on your smartphone, be sure to update it to the latest version. For details on Imaging Edge Mobile, refer to the support page (https://www.sony.net/iem/).

- On the camera, select MENU \rightarrow \bigoplus (Network) \rightarrow [Smartphone Connect] \rightarrow [Smartphone Connection] \rightarrow [On].
- On the camera, select MENU → ∰ (Network) → [Smartphone Connect] → [☐ Connection] to display the QR code screen.



- 3 Launch Imaging Edge Mobile on your smartphone and select [Connect with a new camera].
- Scan the QR Code displayed on the camera while the [Connect using the camera QR Code] screen is displayed on the smartphone.

Once the QR Code has been read, a message [Connect with the camera?] will be displayed on the smartphone screen.

5 Select [OK] on the smartphone screen.

The smartphone is connected to the camera.

Hint

Once the QR Code has been read, this camera's SSID (DIRECT-xxxx) and password are registered to the smartphone. This
enables you to easily connect the smartphone to the camera via Wi-Fi at a later date by selecting the camera from the camera list
in Imaging Edge Mobile. (Set [Smartphone Connection] to [On] in advance.)

Note

Radio wave interference may occur as Bluetooth communications and Wi-Fi (2.4 GHz) communications use the same frequency band. If your Wi-Fi connection is unstable, it may be improved by turning off the Bluetooth function of the smartphone. If you do this, the location information link function is not available. If you cannot connect your smartphone to the camera using the NFC function or QR Code, use the SSID and password.

Related Topic

- Functions available with a smartphone (Imaging Edge Mobile)
- Using a smartphone as a remote commander
- Select on Cam & Send (transferring to a smartphone)
- Smartphone Connection
- Connection (smartphone connection information)
- Connecting the camera and a smartphone using the SSID and password

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Connecting the camera and a smartphone using the SSID and password

Connect your smartphone to the camera using the SSID and password if you cannot connect using NFC or the QR code. You can connect to the camera with the same operation on any Android smartphone, iPhone, or iPad.

To connect the camera and your smartphone, Imaging Edge Mobile is required. Download and install the application Imaging Edge Mobile from your smartphone's application store. If Imaging Edge Mobile is already installed on your smartphone, be sure to update it to the latest version. For details on Imaging Edge Mobile, refer to the support page (https://www.sonv.net/iem/).

	ps://www.sony.net/iem/).
1	On the camera, select MENU \rightarrow \bigoplus (Network) \rightarrow [Smartphone Connect] \rightarrow [Smartphone Connection] \rightarrow [On].
2	On the camera, select MENU $\rightarrow \bigoplus$ (Network) \rightarrow [Smartphone Connect] \rightarrow [\square Connection] to display the QR code screen.
3	Press the iii (Delete) button on the camera to switch to the SSID and password screen. SSID DIRECT-XXXX:MODEL-NAME Password XXXX

- Launch Imaging Edge Mobile on your smartphone, and select [Connect with a new camera] → [Connect using the camera SSID/password].
- Input the password that is displayed on the camera.

The smartphone is connected to the camera.

Note

Radio wave interference may occur as Bluetooth communications and Wi-Fi (2.4 GHz) communications use the same frequency band. If your Wi-Fi connection is unstable, it may be improved by turning off the Bluetooth function of the smartphone. If you do this, the location information link function is not available.

Related Topic

- Functions available with a smartphone (Imaging Edge Mobile)
- Using a smartphone as a remote commander
- Select on Cam & Send (transferring to a smartphone)

- Smartphone Connection
- Connection (smartphone connection information)

Help Guide


Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

One-touch connection with NFC

You can connect the camera to an NFC-enabled smartphone by touching them together.

To connect the camera and your smartphone, Imaging Edge Mobile is required. Download and install the application Imaging Edge Mobile from your smartphone's application store. If Imaging Edge Mobile is already installed on your smartphone, be sure to update it to the latest version. For details on Imaging Edge Mobile, refer to the support page (https://www.sony.net/iem/).

- 1 Activate the NFC function of the smartphone.
 - On an iPhone, launch Imaging Edge Mobile, and then select [Connect with a new camera] → [Connect with the camera through One-touch (NFC)] to activate the NFC function.
- On the camera, select MENU → ⊕ (Network) → [Smartphone Connect] → [Smartphone Connection] → [On].
- Keep touching the smartphone to the camera for 1 to 2 seconds.



The smartphone and the camera are connected.

About "NFC"

NFC is a technology that enables short-range wireless communication between various devices, such as mobile phones or IC tags, etc. NFC makes data communication simpler with just a touch on the designated touch-point.

NFC (Near Field Communication) is an international standard of short-range wireless communication technology.

Note

- If you cannot make a connection, do as the following:
 - Launch Imaging Edge Mobile on your smartphone, and then move the smartphone slowly toward the N (N-Mark) of this camera.
 - If the camera or smartphone is in a case, remove it.
 - Check whether the NFC function is activated on your smartphone.
- Radio wave interference may occur as Bluetooth communications and Wi-Fi (2.4 GHz) communications use the same frequency band. If your Wi-Fi connection is unstable, it may be improved by turning off the Bluetooth function of the smartphone. If you do this, the location information link function is not available.
- When [Airplane Mode] is set to [On], you cannot connect this product and the smartphone. Set [Airplane Mode] to [Off].

Related Topic

- Functions available with a smartphone (Imaging Edge Mobile)
- Using a smartphone as a remote commander
- Select on Cam & Send (transferring to a smartphone)
- Smartphone Connection
- Connecting the camera and a smartphone using the QR Code
- Connecting the camera and a smartphone using the SSID and password
- Airplane Mode

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Using a smartphone as a remote commander

With Imaging Edge Mobile, you can shoot images while checking the shooting range of the camera on the screen of the smartphone. Connect the camera and smartphone by referring to "Related Topic" at the bottom of this page. For details on functions that can be operated from a smartphone, see the Imaging Edge Mobile support page: https://www.sony.net/iem/

Related Topic

- Connecting the camera and a smartphone using the QR Code
- Connecting the camera and a smartphone using the SSID and password
- One-touch connection with NFC
- Remote Shoot Setting (smartphone)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α1

Remote Shoot Setting (smartphone)
Configures settings for images saved when performing remote shooting using a smartphone.
Menu item details
Still Img. Save Dest.:
Sets whether or not to save still images to both the camera and the smartphone during remote shooting. ([Smartphone Only]/[Smartphone+Cam.]/[Camera Only])
☐ Save Image Size:
Selects the file size for images to be transferred to the smartphone when [Still Img. Save Dest.] is set to [Smartphone+Cam.]. The original-sized JPEG/HEIF file or a 2M-equivalent JPEG/HEIF file can be transferred. ([Original]/[2M])
RAW+J Save Image:
Selects the file type for images to be transferred to the smartphone when [Still Img. Save Dest.] is set to [Smartphone+Cam.]. ([RAW & JPEG]/[JPEG Only]/[RAW Only])
RAW+H Save Image:
Selects the file type for images to be transferred to the smartphone when [Still Img. Save Dest.] is set to [Smartphone+Cam.]. ([RAW & HEIF]/[HEIF Only]/[RAW Only])
☐ Save JPEG Size/ ☐ Save HEIF Size:
Selects the image size to be saved on the smartphone when [Still Img. Save Dest.] is set to [Smartphone+Cam.]. ([Larg Size]/[Small Size])
Note
• When an unrecordable memory card is inserted into the camera, you cannot record still images even if [Still Img. Save Dest.] is set to [Camera Only] or [Smartphone+Cam.].
When [Camera Only] or [Smartphone+Cam.] is selected for [Still Img. Save Dest.] and no memory card is inserted into the camera, the shutter will not be released even if [Release w/o Card] is set to [Enable].
While a still image is being played back on the camera, you cannot perform remote shooting using a smartphone.
■ [☐ RAW+J Save Image] and [☐ RAW+H Save Image] can be set only when [፫፫ File Format] under [Image Quality Settings] is set to [RAW & JPEG] or [RAW & HEIF].
D.L.()

Related Topic

Using a smartphone as a remote commander

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1


Select on Cam & Send (transferring to a smartphone)

You can transfer images to a smartphone by selecting images on the camera.

The following is the procedure for transferring the image currently displayed on the camera.

- MENU → ∰ (Network) → [Smartphone Connect] → [★ Select on Cam & Send] → [Size of Sending Image], [RAW+J/H Send Target], and [Px Sending Target] → desired setting.
- Display the image to be transferred on the playback screen.
- 3 MENU → ∰ (Network) → [Smartphone Connect] → [♠ Select on Cam & Send] → [♠ Send] → [This Image].

The QR code is displayed on the monitor of the camera.



- You can also display the [★] Send] screen by pressing the ★☐ (Send to Smartphone) button.
- Launch Imaging Edge Mobile on your smartphone, and select [Connect with a new camera].
- Scan the camera's QR code with your smartphone while displaying the [Connect using the camera QR Code] screen on the smartphone.

Once the QR code is read, [Connect with the camera?] will appear on the smartphone.

6 Select [OK] on the smartphone.

The camera and your smartphone will be connected, and the image will be transferred.

You can transfer multiple images at once by selecting a setting other than [This Image] in [* Send].

Menu item details

★ Send:

Selects images and transfers them to a smartphone. ([This Image]/[All Images in This Group]/[All with this date]/[All with this date]/[

- The options displayed may differ depending on the View Mode selected on the camera.
- If you select [Multiple Images], select the desired images using the center of the control wheel, then press MENU → [Enter].

Size of Sending Image:

Selects the file size for images to be transferred to the smartphone. The original-sized JPEG/HEIF file or a 2M-equivalent JPEG/HEIF file can be transferred. ([Original]/[2M])

RAW+J/H Send Target:

Selects the file type for images to be transferred to a smartphone when the images are shot with [File Format] under [Image Quality Settings] set to [RAW & JPEG] or [RAW & HEIF]. ([JPEG & HEIF]/[RAW]/[RAW+J & RAW+H])

Px Sending Target:

Sets whether to transfer the low-bit-rate proxy movie or the high-bit-rate original movie when transferring a movie to a smartphone. ([Proxy Only]/[Original Only]/[Proxy & Original])

Hint

For connection methods other than using the QR code, refer to "Related Topic" at the bottom of this page.

Note

- Depending on the smartphone, the transferred movie may not be played back correctly. For example, the movie may not play smoothly, or there may be no sound.
- Depending on the format of the still image, movie, slow-motion movie, or quick-motion movie, it may not be possible to play it back on a smartphone.
- This product shares connection information for transferring images with devices that have permission to connect. If you want to change the devices that are permitted to connect to the product, reset the connection information by following these steps. MENU → (Network) → [Wi-Fi] → [SSID/PW Reset]. After resetting the connection information, you must register the smartphone again.
- When [Airplane Mode] is set to [On], you cannot connect this product and the smartphone. Set [Airplane Mode] to [Off].

Related Topic

- Connecting the camera and a smartphone using the QR Code
- Connecting the camera and a smartphone using the SSID and password
- One-touch connection with NFC
- Airplane Mode

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Cnct. during Power OFF

Sets whether or not to accept Bluetooth connections from a smartphone while the camera is turned off. When [Cnct. during Power OFF] is set to [On], you can browse images on the camera's memory card and transfer images from the camera to a smartphone by operating the smartphone.



 $MENU \rightarrow \bigoplus$ (Network) \rightarrow [Smartphone Connect] \rightarrow [Cnct. during Power OFF] \rightarrow desired setting.

Menu Item Details

On:

Accepts Bluetooth connections from a smartphone while the camera is turned off.

The battery level is depleted gradually while the camera is turned off. If you do not want to use [Cnct. during Power OFF], turn it off.

Off:

Does not accept Bluetooth connections from a smartphone while the camera is turned off.

How to browse/transfer images on the smartphone

Advance Preparation

- Select MENU → ∰ (Network) → [Bluetooth] → [Bluetooth Function] → [On] on the camera.
- 2. MENU → ∰ (Network) → [Smartphone Connect] → [Cnct. during Power OFF] → [On].
- Select MENU → ∰ (Network) → [Bluetooth] → [Pairing] on the camera to display the screen for pairing.
- **4.** Launch Imaging Edge Mobile on the smartphone, and then select the camera to be paired on the [Camera Remote Power ON/OFF] screen.

Operations

- 1. Turn off the camera.
- 2. Select [Camera Remote Power ON/OFF] in Imaging Edge Mobile.
- 3. Select the camera on the [Remote Power ON/OFF] screen to turn on the camera.
 - When the power turns on, the power mark turns green.
- 4. Select the [Import In-camera Images] button on the screen to select the function.
 - The images saved on the memory card of the camera can be viewed and are ready to be transferred.

Note

- If the smartphone is not operated for a certain period of time, the Bluetooth connection will become deactivated. Select [Camera Remote Power ON/OFF] again on the smartphone.
- When the camera is turned on, the camera will switch to the shooting screen, and the connection with the smartphone will be terminated.

Related Topic

• Functions available with a smartphone (Imaging Edge Mobile)

- Select on Cam & Send (transferring to a smartphone)
- Bluetooth Settings

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Location Information

You can use the application Imaging Edge Mobile to obtain location information from a smartphone that is connected with your camera using Bluetooth communication. You can record the obtained location information when shooting images.

Preparation in advance

To use the location information linking function of the camera, the application Imaging Edge Mobile is required. <u>If "Location Information Linkage" is not displayed on the top page of Imaging Edge Mobile, you need to perform the following steps beforehand.</u>

- 1. Install Imaging Edge Mobile on your smartphone.
 - You can install Imaging Edge Mobile from the application store of your smartphone. If you have already installed the application, update it to the latest version.
- 2. Use the [Connection] function of the camera to connect the camera and the smartphone beforehand.
 - After the camera and the smartphone are connected, "Location Information Linkage" will appear on the top page of the application.

Operating procedure

- : Operations performed on the smartphone : Operations performed on the camera
- 1. \square : Confirm that the Bluetooth function of your smartphone is activated.
 - Do not perform the Bluetooth pairing operation on the smartphone setting screen. In steps 2 to 7, the pairing operation is performed using the camera and the application Imaging Edge Mobile.
 - If you accidentally perform the pairing operation on the smartphone setting screen in step 1, cancel the pairing and then perform the pairing operation by following Steps 2 through 7 using the camera and the application Imaging Edge Mobile.
- 2. \bigcirc : On the camera, select MENU \rightarrow \bigoplus (Network) \rightarrow [Bluetooth] \rightarrow [Bluetooth Function] \rightarrow [On].
- 4.

 : Launch Imaging Edge Mobile on your smartphone and tap "Location Information Linkage."
 - If "Location Information Linkage" is not displayed, follow the steps in "Preparation in advance" above.
- 5. : Activate [Location Information Linkage] on the [Location Information Linkage] setting screen of Imaging Edge Mobile.
- **6.** \square : Follow the instructions on the [Location Information Linkage] setting screen of Imaging Edge Mobile, and then select your camera from the list.
- 7. Select [OK] when a message is displayed on the monitor of the camera.

- Pairing of the camera and Imaging Edge Mobile is complete.
- 8. \bigcirc : On the camera, select MENU \rightarrow \bigoplus (Network) \rightarrow [Location Information] \rightarrow [Location Info Link] \rightarrow [On].
 - <u>A</u> (obtaining location information icon) will be displayed on the monitor of the camera. Location information obtained by your smartphone using GPS, etc., will be recorded when shooting images.

Menu item details

Location Info Link:

Sets whether to obtain the location information by linking with a smartphone.

Auto Time Correction:

Sets whether to automatically correct the date and time setting of the camera using information from a linked smartphone.

Auto Area Adjustment:

Sets whether to automatically correct the area setting of the camera using information from a linked smartphone.

Icons displayed when obtaining the location information

♠ (Obtaining location information): The camera is obtaining the location information.

(Location information cannot be obtained): The camera cannot obtain the location information.

[3] (Bluetooth connection available): Bluetooth connection with the smartphone is established.

[8] (Bluetooth connection unavailable): Bluetooth connection with the smartphone is not established.

Hint

- Location information can be linked when Imaging Edge Mobile is running on your smartphone even if the smartphone monitor is off. However, if the camera has been turned off for a while, location information may not be linked immediately when you turn the camera back on. In this case, location information will be linked immediately if you open the Imaging Edge Mobile screen on the smartphone.
- When Imaging Edge Mobile is not operating, such as when the smartphone is restarted, launch Imaging Edge Mobile to resume location information linking.
- If the location information linking function does not work properly, see the following notes and perform pairing again.
 - Confirm that the Bluetooth function of your smartphone is activated.
 - Confirm that the camera is not connected with other devices using the Bluetooth function.
 - Confirm that [Airplane Mode] for the camera is set to [Off].
 - Delete the pairing information for the camera registered in Imaging Edge Mobile.
 - Delete the pairing information for the camera registered in the Bluetooth settings of the smartphone.
 - Execute [Reset Network Set.] of the camera.
- For more detailed instructions, refer to the following support page. https://www.sony.net/iem/btg/

Note

- When you initialize the camera, the pairing information is also deleted. Before performing pairing again, first delete the pairing information for the camera registered in the smartphone's Bluetooth settings and Imaging Edge Mobile.
- The location information will not be recorded when it cannot be obtained, such as when the Bluetooth connection is disconnected.
- The camera can be paired with up to 15 Bluetooth devices, but can link the location information with that of only one smartphone.
 If you want to link the location information with that of another smartphone, turn off the [Location Information Linkage] function of the smartphone that is already linked.
- If the Bluetooth connection is unstable, remove any obstacles, such as people or metal objects from between the camera and the paired smartphone.
- When pairing the camera and your smartphone, be sure to use the [Location Information Linkage] menu on Imaging Edge Mobile.
- To use the location information linkage function, set [Bluetooth Rmt Ctrl] to [Off].

• The communication distance for Bluetooth or Wi-Fi may vary depending on the conditions of use.

Supported smartphones

Refer to the support page for the latest information.

https://www.sony.net/iem/

• For details on Bluetooth versions compatible with your smartphone, check the product website for your smartphone.

Related Topic

- Functions available with a smartphone (Imaging Edge Mobile)
- Bluetooth Settings
- Bluetooth Rmt Ctrl

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Recommended computer environment

You can confirm the operating computer environment of the software from the following URL: https://www.sony.net/pcenv/

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Connecting the camera to a computer

- 1 Insert a sufficiently charged battery pack into the camera.
- 2 Turn on the camera and the computer.
- \bullet (Setup) \rightarrow [USB] \rightarrow Set [USB Connection] to [Mass Storage].
- 4 Connect the USB Type-C terminal on the camera to the computer with a USB cable.
 - When you connect the camera to the computer for the first time, the procedure for recognizing the camera may start automatically on the computer. Wait until the procedure is finished.
 - If you connect the camera to your computer using the USB cable when [USB Power Supply] is set to [On], power is supplied from your computer. (Default setting: [On])
 - Use the USB cable (supplied) or a USB-standard cable.
 - Use a SuperSpeed USB 10Gbps (USB 3.2)-compatible computer and the USB cable (supplied) for higherspeed communications.

Note

Do not turn on/off or restart the computer, or wake the computer from sleep mode when a USB connection has been established between the computer and the camera. Doing so may cause a malfunction. Before turning on/off or restarting the computer, or waking the computer from sleep mode, disconnect the camera from the computer.

Related Topic

- Sides
- USB Connection
- USB LUN Setting

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Disconnecting the camera from the computer

Perform the following operations on the computer before disconnecting the camera from the computer.

1 Click 👆 (Safely Remove Hardware and Eject Media) in the taskbar.

Click the displayed message.

The following operations are available after you have completed the steps above.

- Disconnecting the USB cable.
- Removing a memory card.
- Turning off the camera.

Note

- On Mac computers, drag and drop the memory card icon or the drive icon into the "Trash" icon. The camera will be disconnected from the computer.
- On some computers, the disconnection icon may not appear. In this case, you can skip the steps above.
- Do not remove the USB cable from the camera while the access lamp is lit. The data may be damaged.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Introduction to computer software (Imaging Edge Desktop/Catalyst)

Imaging Edge Desktop

Imaging Edge Desktop is a software suite that includes functions such as remote shooting from a computer, and adjusting or developing RAW images recorded with the camera.

For details on how to use Imaging Edge Desktop, refer to the support page. https://www.sony.net/disoft/help/

Installing Imaging Edge Desktop on your computer

Download and install the software by accessing the following URL: https://www.sony.net/disoft/d/

Catalyst Browse (free software)/Catalyst Prepare (paid software)

Catalyst Browse is software for previewing clips. You can preview recorded XAVC S/XAVC HS clips, view and edit media metadata, apply image stabilization* using metadata, apply color calibration, copy to the local hard drive, or transcode to a variety of formats and so on with Catalyst Browse.

Catalyst Prepare adds to the functions of Catalyst Browse allowing you to organize clips using bins, perform basic timeline editing with storyboards, and so on.

* For the conditions of use of the image stabilization function, refer to the support page.

Installing Catalyst Browse/Catalyst Prepare on your computer

Download and install the software by accessing the following URL: https://www.sony.net/disoft/

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$


Importing images to the computer

You can import images from the camera to a computer by connecting the camera to the computer with a USB cable, or by inserting the memory card of the camera into the computer.


Open the folder in which the images you want to import are stored on the computer, and then copy the images to the computer.

Example: Folder tree during USB Mass Storage connection

SD card



CFexpress Type A memory card



DCIM: still images CLIP: movies SUB: proxy movies

Note

- Do not edit or otherwise process movie files/folders from the connected computer. Movie files may be damaged or become unplayable. Do not delete movies on the memory card from the computer. Sony is not held liable for consequences resulting from such operations via the computer.
- If you delete images or perform other operations from the connected computer, the image database file may become inconsistent. In this case, repair the image database file.
- The folder tree is different during MTP connection.


Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Operating the camera from a computer (PC Remote Function)

Uses a Wi-Fi or USB connection, etc. to control the camera from a computer, including such functions as shooting and storing images on the computer.

Select MENU \rightarrow (Network) \rightarrow [Smartphone Connect] \rightarrow [Smartphone Connection] \rightarrow [Off] beforehand.



Connect the camera to the computer, and then launch Imaging Edge Desktop (Remote) on the computer.

You can now operate the camera using Imaging Edge Desktop (Remote).

 The connection method between the camera and the computer depends on the setting for [PC Remote Cnct Method].

Menu item details

PC Remote:

Sets whether or not to use the [PC Remote] function. ([On] / [Off])

PC Remote Cnct Method:

Selects the connection method when the camera is connected to a computer using [PC Remote]. ([USB]/[Wired LAN]/[Wi-Fi Direct]/[Wi-Fi Access Point])

Connect without Pairing:

Selects whether to connect the camera to a computer without pairing when [PC Remote Cnct Method] is set to [Wired LAN] or [Wi-Fi Access Point]. ([Enable]/[Disable])

Pairing:

When [PC Remote Cnct Method] is set to [Wired LAN] or [Wi-Fi Access Point], pair the camera with the computer.

Wi-Fi Direct Info.:

Displays the information needed to connect to the camera from the computer when [PC Remote Cnct Method] is set to [Wi-Fi Direct].

Still Img. Save Dest.:

Sets whether or not to save still images to both the camera and the computer during PC Remote shooting. ([PC Only]/[PC+Camera]/[Camera Only])

PC Save Image Size:

Selects the file size for images to be transferred to the computer when [Still Img. Save Dest.] is set to [PC+Camera]. The original-sized JPEG/HEIF file or a 2M-equivalent JPEG/HEIF file can be transferred. ([Original]/[2M])

RAW+J PC Save Img:

Selects the file type for images to be transferred to the computer when [Still Img. Save Dest.] is set to [PC+Camera]. ([RAW & JPEG]/[JPEG Only]/[RAW Only])

RAW+H PC Save Image:

Selects the file type for images to be transferred to the computer when [Still Img. Save Dest.] is set to [PC+Camera]. ([RAW & HEIF]/[HEIF Only]/[RAW Only])

PC Save JPEG Size/PC Save HEIF Size:

Sets the image size to be saved to the computer when [Still Img. Save Dest.] is set to [PC+Camera]. ([Large Size]/[Small Size])

How to connect the camera and the computer

When [PC Remote Cnct Method] is set to [USB]

Connect the USB Type-C terminal on the camera to the computer with a USB cable.

When [PC Remote Cnct Method] is set to [Wired LAN]

Connect the camera to the computer or a switching hub using a commercially available LAN cable. The camera and the computer need to be paired in advance if [Connect without Pairing] is set to [Disable].

Connect the camera and the computer or switching hub using the LAN cable, and select MENU \rightarrow (Network) \rightarrow [PC Remote Function] \rightarrow [Pairing] on the camera, then use Imaging Edge Desktop (Remote) to pair the camera and the computer. Select [OK] on the pairing confirmation screen displayed on the camera to finish pairing.

Pairing information is deleted when you initialize the camera.

When [PC Remote Cnct Method] is set to [Wi-Fi Direct]

Use the camera as an access point, and connect the computer to the camera directly via Wi-Fi.

Select MENU \rightarrow \bigoplus (Network) \rightarrow [Transfer/Remote] \rightarrow [PC Remote Function] \rightarrow [Wi-Fi Direct Info.] to display the Wi-Fi connection information (SSID and password) for the camera. Connect the computer and the camera using the Wi-Fi connection information displayed on the camera.

When [PC Remote Cnct Method] is set to [Wi-Fi Access Point]

Connect the camera and the computer via Wi-Fi using a wireless access point. The camera and the computer need to be paired in advance if [Connect without Pairing] is set to [Disable].

Select MENU \rightarrow \bigoplus (Network) \rightarrow [Wi-Fi] \rightarrow [WPS Push] or [Access Point Set.] to connect the camera to the wireless access point. Connect the computer to the same wireless access point.

Select MENU \rightarrow (Network) \rightarrow [Transfer/Remote] \rightarrow [PC Remote Function] \rightarrow [Pairing] on the camera, and then use Imaging Edge Desktop (Remote) to pair the camera and the computer. Select [OK] on the pairing confirmation screen displayed on the camera to finish pairing.

Pairing information is deleted when you initialize the camera.

Note

- When an unrecordable memory card is inserted into the camera, you cannot record still images even if [Still Img. Save Dest.] is set to [Camera Only] or [PC+Camera].
- When [Camera Only] or [PC+Camera] is selected and no memory card is inserted into the camera, the shutter will not be released even if [Release w/o Card] is set to [Enable].
- [RAW+J PC Save Img] and [RAW+H PC Save Image] can be set only when [File Format] is set to [RAW & JPEG] or [RAW & HEIF].

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Remote shooting with a wired LAN (Remote Camera Tool)

Remote Camera Tool is software for PC remote shooting using a wired LAN. You can change the camera settings and shoot images from a computer by connecting the camera to a computer or switching hub using a LAN cable.

- 1. $MENU \rightarrow \bigoplus (Network) \rightarrow [Transfer/Remote] \rightarrow [PC Remote Function] \rightarrow [PC Remote] \rightarrow [On].$
- $\textbf{2.} \ \mathsf{MENU} \to \bigoplus (\mathsf{Network}) \to [\mathsf{Transfer/Remote}] \to [\mathsf{PC} \ \mathsf{Remote} \ \mathsf{Function}] \to [\mathsf{PC} \ \mathsf{Remote} \ \mathsf{Cnct} \ \mathsf{Method}] \to [\mathsf{Wired} \ \mathsf{LAN}].$
- 3. Connect the camera and the computer using a LAN cable.
- 4. Configure the required LAN settings.
- 5. Launch Remote Camera Tool on the computer to perform remote shooting.

For details on how to install and use Remote Camera Tool, refer to the following URL: https://support.d-imaging.sony.co.jp/app/remotecameratool/l/index.php

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Audio accessories compatible with the Multi Interface Shoe

If you shoot movies with an audio accessory (sold separately) attached to the Multi Interface Shoe of the camera, analog or digital audio will be recorded via the Multi Interface Shoe.

If you use an audio accessory that supports the digital audio interface, the sound signals will be transmitted in a digital format. This will allow you a wider range of recordable audio quality, such as the following.

- High-quality audio recording with less deterioration
- 4-channel or 24-bit audio recording

The recordable audio quality differs depending on the audio accessory. For details, refer to the instruction manual for the audio accessory.

Hint

■ You can change the audio settings for audio accessories that support the digital audio interface using [Shoe Audio Set.].

Note

Movies recorded with 24-bit audio may not be played back normally on devices or software incompatible with 24-bit audio, resulting in unexpectedly loud volumes or no sound.

Related Topic

- Shoe Audio Set.
- HDMI Output Settings (movie)
- 4ch Audio Monitoring (movie)
- Audio Out Timing
- Audio Level Display
- Audio Recording

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1


Vertical grip

You can attach a vertical grip (sold separately) to this product and record vertically oriented images. When attaching the vertical grip, remove the battery cover in advance.

For details, refer to the operating instructions for the vertical grip.


To remove the battery cover

Pull the battery cover release lever (A) in the direction of the arrow, and then remove the battery cover.



To attach the battery cover

Insert the shaft on one side of the battery cover into the attachment site, and then push in the battery cover by attaching the shaft on the opposite side.



- You can attach the removed battery cover to the vertical grip so that you do not lose it.
- When a vertical grip is attached to this product, the battery remaining is displayed as 1 mm

Note

The LA-EA4 Mount Adaptor (sold separately) and the vertical grip are not designed to be attached at the same time. If you attach them at the same time, the space between the Mount Adaptor and the vertical grip will become narrow, making the camera difficult to hold.


Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Mount Adaptor

Using a Mount Adaptor (sold separately), you can attach an A-mount lens (sold separately) to this product. For details, refer to the operating instructions supplied with the Mount Adaptor.





Note

- You may not be able to use the Mount Adaptor or auto-focus with certain lenses. Consult your Sony dealer or local authorized Sony service facility on compatible lenses.
- You cannot use the AF illuminator when using an A-mount lens.
- The sound of the lens and the product in operation may be recorded during movie recording.
 You can turn the sound off by selecting MENU → [o] (Shooting) → [Audio Recording] → [Audio Recording] → [Off].
- It may take a long time or may be difficult for the product to focus, depending on the lens used or the subject.

Related Topic

- LA-EA3/LA-EA5 Mount Adaptor
- LA-EA4 Mount Adaptor

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

LA-EA3/LA-EA5 Mount Adaptor

If you use the LA-EA3 Mount Adaptor (sold separately) or LA-EA5 Mount Adaptor (sold separately), the following functions are available.

Full frame shooting:

Available with full frame shooting-compatible lenses only

Autofocus:

LA-EA3: Available with SAM/SSM lens only

LA-EA5: Available with A-mount AF lenses* (For lenses other than SAM and SSM, autofocus is driven by the LA-EA5 AF coupler.)

* Autofocus is not available with some Minolta/Konica Minolta lenses and teleconverters.

AF system:

Phase Detection AF

AF/MF select:

Can be changed using the operating switch on the lens.

Focus mode:

Single-shot AF/Continuous AF/Direct manual focus (DMF)/Manual Focus

When using a Mount Adaptor in the movie mode, adjust the aperture value and the focus manually.

Available focus area:

[Wide]/[Zone]/[Center Fix]/[Spot]/[Expand Spot]/[Tracking]

SteadyShot:

In-body

About autofocus during continuous shooting

Although the camera tracks the subject in focus regardless of the settings for continuous shooting and [Shutter Type], the function behaves as follows in some cases.

- The focus is locked to the setting in the first shot when the F-value is greater than F22 under the following conditions.
 - When [Shutter Type] is set to [Mechanical Shutter] and the continuous shooting mode is set to [Continuous Shooting: Hi+], [Continuous Shooting: Hi], or [Continuous Shooting: Mid]
 - When [Shutter Type] is set to [Electronic Shutter] or [Auto]
- When shooting with [Continuous Shooting: Hi+] or [Continuous Shooting: Hi] and [Shutter Type] is set to [Auto] or [Electronic Shutter], the continuous shooting speed varies according to the focus mode setting as follows.
 - [Single-shot AF]/[DMF]/[Manual Focus]: The same speed as when an E-mount lens is attached (The focus is locked to the setting in the first shot.)
 - [Continuous AF]: Maximum of 10 images per second

Related Topic

- Mount Adaptor
- LA-EA4 Mount Adaptor

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

LA-EA4 Mount Adaptor

If you use the LA-EA4 Mount Adaptor (sold separately), the following functions are available.

Full size shooting:

Available with full frame shooting-compatible lenses only

Autofocus:

Not available.

Only the manual focusing mode is supported.

SteadyShot:

In-body

Note

The LA-EA4 Mount Adaptor (sold separately) and the vertical grip (sold separately) are not designed to be attached at the same time. If you attach them at the same time, the space between the Mount Adaptor and the vertical grip will become narrow, making the camera difficult to hold.

Related Topic

- Mount Adaptor
- LA-EA3/LA-EA5 Mount Adaptor

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$


Multi Battery Adaptor Kit

You can use the Multi Battery Adaptor Kit (sold separately) with this camera to shoot for long periods. When using the Multi Battery Adaptor Kit, remove the camera's battery cover.

For details, refer also to the operating instructions supplied with the Multi Battery Adaptor Kit.


To remove the battery cover

Pull the battery cover release lever (A) in the direction of the arrow, and then remove the battery cover.



To attach the battery cover

Insert the shaft on one side of the battery cover into the attachment site, and then push in the battery cover by attaching the shaft on the opposite side.



Note

While the plug-in plate of the Multi Battery Adaptor Kit is inserted in the camera, do not slide the battery lock lever of the camera. The plug-in plate will be ejected from the camera if you do so.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Battery life and number of recordable images

Number of recordable images when shooting still images

Screen mode	Approx. 530 images
Viewfinder mode	Approx. 430 images

Battery life for actual movie shooting

Screen mode	Approx. 95 min.
Viewfinder mode	Approx. 90 min.

Battery life for continuous movie shooting

Screen mode	Approx. 150 min.
Viewfinder mode	Approx. 145 min.

- The above estimates for battery life and number of recordable images apply when the battery pack has been fully charged. The battery life and number of images may decrease depending on the conditions of use.
- The battery life and number of recordable images are estimates based on shooting with the default settings under the following conditions:
 - Using the battery pack at an ambient temperature of 25°C (77°F).
 - Using a Sony CFexpress Type A memory card (sold separately)
 - Using a FE 28-70mm F3.5-5.6 OSS lens (sold separately)
- The numbers of recordable still images are based on the CIPA standard and shooting under the following conditions:
 (CIPA: Camera & Imaging Products Association)
 - One picture is taken every 30 seconds.
 - The power is turned on and off once every ten times.
- The number of minutes for movie shooting is based on the CIPA standard and shooting under the following conditions:
 - The image quality is set to XAVC S HD 60p 50M /50p 50M 4:2:0 8bit.
 - Actual shooting (movies): Battery life based on repeated shooting, zooming, shooting stand-by, turning on/off, etc.
 - Continuous shooting (movies): No operations other than starting and ending shooting are performed.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Number of recordable images

When you insert a memory card into the camera and turn the camera on, the number of images that can be recorded (should you continue to shoot using the current settings) is displayed on the screen.

Note

- When "0" (the number of recordable images) flashes in orange, the memory card is full. Replace the memory card with another one, or delete images from the current memory card.
- When "NO CARD" flashes in orange, it means no memory card has been inserted. Insert a memory card.
- If the (Warning) icon or the (Malfunction) icon is displayed, there is something wrong with the memory card. Replace the memory card with another one.

The number of images that can be recorded on a memory card

The table below shows the approximate number of images that can be recorded on a memory card formatted with this camera.

The numbers shown reflect the following conditions:

- Using a Sony memory card
- [Aspect Ratio] is set to [3:2], and [JPEG Image Size]/[HEIF Image Size] is set to [L: 50M]. *1

The values may vary depending on the shooting conditions and the type of memory card used.

(Unit: images)

JPEG Quality/HEIF Quality/ To File Format		nory card	CFexpress Type A memory card	
The Guanty/Tien Quanty/ Profile to that	64GB	128GB	80GB	160GB
JPEG Light	6800	13600	7900	15600
JPEG Standard	4700	9400	5400	10800
JPEG Fine	3200	6400	3700	7400
JPEG Extra fine	1700	3400	1900	4000
HEIF Light	9100	18200	10600	21200
HEIF Standard	6800	13600	7900	15600
HEIF Fine	5100	10200	5900	11800
HEIF Extra fine	3400	6900	4000	8000
RAW & JPEG (Compressed RAW)*2	700	1400	800	1700
RAW & HEIF (Compressed RAW)*2	800	1600	900	1800
RAW (Compressed RAW)	900	1900	1100	2200
RAW & JPEG (Lossless Compressed: L)*2	600	1300	700	1500

JPEG Quality/HEIF Quality/ File Format	SD memory card		CFexpress Type A memory card	
	64GB	128GB	80GB	160GB
RAW & HEIF (Lossless Compressed: L)*2	700	1400	800	1600
RAW (Lossless Compressed: L)	800	1600	900	1900
RAW & JPEG (Uncompressed RAW)*2	400	800	500	1000
RAW & HEIF (Uncompressed RAW)*2	400	900	500	1000
RAW (Uncompressed RAW)	500	1000	600	1200

When [Aspect Ratio] is set to other than [3:2], you can record more images than the numbers shown in the table above. (except when [RAW] is selected)

Note

• Even if the number of recordable images is higher than 9999 images, "9999" will appear.

Related Topic

Memory cards that can be used

^{*2} JPEG image quality when [RAW & JPEG] is selected: [Fine] HEIF image quality when [RAW & HEIF] is selected: [Fine]

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Recordable movie times

The table below shows the approximate total recording times using a memory card formatted with this camera. The values may vary depending on the shooting conditions and the type of memory card used.

(h (hour), min (minute))

File Format	Rec Frame Rate	Record Setting	SD mem	ory card	CFexpress Type A memory card		
1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1		Record Setting	64 GB	128 GB	80 GB	160 GB	
		520M *	10 min	25 min	15 min	30 min	
XAVC HS 8K	30p/25p/24p	400M	15 min	35 min	20 min	40 min	
AAVC HS OK	30p/23p/24p	260M *	25 min	55 min	30 min	1 h	
		200M	35 min	70 min	40 min	1 h 25 min	
		200M	35 min	70 min	40 min	1 h 25 min	
		150M	45 min	1 h 35 min	55 min	1 h 50 min	
XAVC HS 4K	60p/50p	100M	1 h 10 min	2 h 20 min	1 h 20 min	2 h 50 min	
		75M	1 h 30 min	3 h	1 h 40 min	3 h 40 min	
		45M	2 h 20 min	4 h 50 min	2 h 40 min	5 h 40 min	
XAVC S 4K	60p/50p	200M	35 min	1 h 10 min	40 min	1 h 25 min	
XAVO 3 4K	оор/зор	150M	45 min	1 h 35 min	55 min	1 h 50 min	
XAVC S HD	60p/50p	50M	2 h 10 min	4 h 30 min	2 h 30 min	5 h 10 min	
AAVO 3 IID	7AVC 3 11D 00p/30p	25M	3 h 50 min	7 h 50 min	4 h 30 min	9 h 10 min	
XAVC S-I 4K	60p/50p	600M/500M	10 min	25 min	10 min	25 min	
XAVC S-I HD	60p/50p	222M/185M	30 min	1 h 5 min	35 min	1 h 15 min	

^{*} When the camera's system software (firmware) version is Ver.1.30 or later

The recording times when [Px Proxy Recording] is set to [Off].

- The times shown are recordable times using a Sony memory card.
- The duration of time available for movie recording varies depending on the file format/recording settings for movies, memory card, ambient temperature, Wi-Fi network environment, condition of the camera before you start recording, and condition of the charging of the battery.
 - The maximum continuous recording time for a single movie shooting session is approximately 13 hours (a product specification limit).

Note

The recordable time of movies varies because the camera is equipped with VBR (Variable Bit-Rate), which automatically adjusts image quality depending on the shooting scene. When you record a fast-moving subject, the image is clearer but the recordable time is shorter because more memory is required for recording. The recordable time also varies depending on the shooting conditions, the subject or the image quality/size settings.

Notes on continuous movie recording

- High-quality movie recording and high-speed continuous shooting require large amounts of power. Therefore, if you continue to shoot, the temperature inside the camera will rise, especially that of the image sensor. In such cases, the camera will turn off automatically because the surface of the camera is heated to a high temperature or the high temperature affects the quality of the images or the internal mechanism of the camera.
- The duration of time available for continuous movie recording when the camera records with the default settings after the power has been turned off for a while is as follows. The values indicate the continuous time from when the camera starts recording until the camera stops recording.

When [Auto Power OFF Temp.] is set to [High]

File Format	XAVC S HD	XAVC S 4K	XAVC HS 8K
Ambient temperature: 25°C (77°F)	Approx. 120 minutes	Approx. 30 minutes	Approx. 30 minutes
Ambient temperature: 40°C (104°F)	Approx. 90 minutes	Approx. 10 minutes	Approx. 20 minutes

When [Auto Power OFF Temp.] is set to [Standard]

File Format	XAVC S HD	XAVC S 4K	XAVC HS 8K
Ambient temperature: 25°C (77°F)	Approx. 30 minutes	Approx. 10 minutes	Approx. 10 minutes
Ambient temperature: 40°C (104°F)	Approx. 20 minutes	Approx. 10 minutes	Approx. 10 minutes

XAVC S HD: 60p 50M/50p 50M 4:2:0 8bit, when the camera is not connected via Wi-Fi, when using a CFexpress Type A memory card

XAVC S 4K: 60p 150M/50p 150M 4:2:0 8bit, when the camera is not connected via Wi-Fi, when using a CFexpress Type A memory card

XAVC HS 8K: 30p 200M/25p 200M 4:2:0 10bit, when the camera is not connected via Wi-Fi, when using a CFexpress Type A memory card

- The duration of time available for movie recording varies with the temperature, file format/record setting for movies, Wi-Fi network environment, or condition of the camera before you start recording. If you frequently recompose or shoot images after the power is turned on, the temperature inside the camera will rise and the recording time available will be shorter.
- If the II (Overheating warning) icon appears, the temperature of the camera has risen.
- If the camera stops movie recording due to a high temperature, leave it for some time with the power turned off. Start
 recording after the temperature inside the camera drops fully.
- If you observe the following points, you will be able to record movies for longer periods of time.
 - Keep the camera out of direct sunlight.
 - Turn the camera off when it is not being used.

- Memory cards that can be used
- Battery life and number of recordable images

Help Guide


Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

List of icons on the monitor


The displayed contents and their positions in the illustrations are just guidelines, and may differ from the actual displays. Descriptions are given below the indications of the icons.

Icons on the shooting screen


Monitor mode



Viewfinder mode



1. Shooting mode/Scene recognition



1 2 3 M M M M M M M M

Register number



Scene Recognition icons

2. Camera settings



Memory card status

100/1h30m

Remaining number of recordable images/Recordable time of movies

11113

Writing data / Number of images left to write

50M / 44M / 42M / 33M / 21M / 19M / 18M / 14M / 12M / 11M / 8.3M

Image size of still images

RAW RAW RAW RAW RAW

RAW recording (compressed/lossless compression (L/M/S)/uncompressed)

J-X.FINE J-FINE J-STD J-LIGHT H-X.FINE H-FINE H-STD H-LIGHT

JPEG Quality / HEIF Quality

4:2:2

HEIF color sampling

XAVC HS 8K XAVC HS 4K XAVC S 4K XAVC S HD XAVC S-I 4K XAVC S-I HD

File format of movies

120p 100p 60p 50p 30p 25p 24p

Frame rate of movies

600 | 520 | 500 | 400 | 300 | 280 | 260 | 250 | 240 | 222 | 200 | 185 | 150 | 140 | 111 | 100 | 93 | 89 | 75 | 60 | 50 | 45 | 30 | 25 | 16 |

Record setting of movies

100 E 60 E 50 E 25 E 16 Ex

Proxy Recording

4:2:2 10bit/4:2:0 10bit/4:2:0 8bit

Color sampling and bit depth of movies

240fps 200fps 120fps 100fps 60fps 50fps 30fps 25fps 15fps 12fps 8fps 6fps 4fps 3fps 2fps 1fps

Frame rate for slow/quick motion shooting

4.

Flash charge in progress

VIEW

Setting Effect OFF

VIFW &

Exposure Effect (Exposure Setting Only)

D:ON

AF Illuminator

Flicker

Flickering detected

Ø

NFC active

SteadyShot off/on, Camera shake warning

((♣))□□□ ((♣)) 8mm

SteadyShot focal length / Camera shake warning

s**⊕** c**⊕** d

Optical zoom only /Clear Image Zoom/Digital Zoom

-PC-

PC remote

+:..

Bright Monitoring

ď

Silent mode

Î

Remote control

FTP FTP[↑]

FTP function / FTP transfer status


Wi-Fi Wi-Fi

Connected to Wi-Fi/Disconnected from Wi-Fi

LAN (LAN)

Connected to LAN/Disconnected from LAN

No audio recording of movies



ST PT NT VV VV2 FL IN SH BW SE Creative Look AF AF Face/Eye Prior. in AF PP1 - PP11 PP OFF Picture Profile AUTO MECH ELEC Shutter Type **₹1 ₹2** Recording media CFPS CFPS Finder Frame Rate 3:2 4:3 16:9 1:1 Aspect ratio of still images 5. Focus indicator/exposure settings Focus indicator 1/250 Shutter speed 1/400 [4] Flash Sync Spd. Prty. F3.5 Aperture value **†∠** M.M. Exposure compensation/Metered Manual **ISO400 ISO AUTO** A ISO 400 ISO sensitivity ¥ \$L AWB AE lock/FEL lock/AWB lock Shooting APS-(535 Shooting 6. Guides/other Tracking Cancel Guide display for tracking Focus Cancel Guide display for canceling focusing Control wheel function 🚓 🛎 Av 🖚 Tv 🛈 SO Guide display for My Dial ▼▼▼ -6::5::4::3::2::1::0::1::2::3::4+ **Bracket indicator** Spot metering area Histogram ()[) Digital level gauge

STBY REC

Movie recording standby/Movie recording in progress

1:00:12


Actual movie recording time (hours: minutes: seconds)

48khz/16bit 2ch

48khz/24bit 2ch

48khz/24bit 4ch

Audio format



Audio Level Display



REC Control

EXT 4K EXT RAW

4K/RAW external output

00:00:00.00

Time code (hours: minutes: seconds. frames)

00 00 00 00


User Bit

1" 15" 30" 2/4


Pixel Shift Multi Shoot.

Icons on the playback screen

Single-image playback



Histogram display



1. Basic information

1 2

Playback media

IPTC

IPTC Information



	Rating
	От
	Protect
	3/7
	File number/Number of images in the view mode
	NFC active
	Remaining battery
	Display as Group
	Cropped image
	Px
	Proxy movie included
	000000 2/4 Dival Shift Multi Shoot
	Pixel Shift Multi Shoot.
	A Voice Memo is attached.
	FTP transfer status
2.	Camera settings
	Refer to "Icons on the shooting screen."
2	Shooting settings
٥.	Shooting settings 35mm
	Lens focal length
	HLG
	HDR recording (Hybrid Log-Gamma)
	©
	Copyright information exists for image
	Refer to "Icons on the shooting screen" for other icons displayed in this area.
4	
4.	Image information
	Latitude/longitude information
	2021-1-1 10:37:00PM
	Date of recording
	100-0003
	Folder number - file number
	C0003
	Movie file number
	Histogram (Luminance/R/G/B)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

List of default setting values

The default setting values for each menu item at the time of purchase are shown in the following table.

The content of the menu displayed on the screen differs depending on the position of the mode dial. For details, refer to "Finding functions from MENU."

To reset settings to the default values

Select MENU \rightarrow \bigoplus (Setup) \rightarrow [Reset/Save Settings] \rightarrow [Setting Reset] \rightarrow [Camera Settings Reset] or [Initialize] \rightarrow [Enter].

The items that can be reset using [Camera Settings Reset] are limited. See the following tables. If you select [Initialize], all the settings of the camera will be reset to the default values.

(Shooting)

MENU items	Default setting value	Resettable using [Camera Settings Reset]
JPEG/HEIF Switch	JPEG	✓
Image Quality Settings (File Format)	JPEG/HEIF	✓
Image Quality Settings (RAW File Type)	Compressed	✓
Image Quality Settings (JPEG Quality/HEIF Quality)	Fine	✓
Image Quality Settings (JPEG Image Size/HEIF Image Size) (when [Aspect Ratio] is set to [3:2])	L: 50M	✓
Image Quality Settings (JPEG Image Size/HEIF Image Size) (when [Aspect Ratio] is set to [4:3])	L: 44M	✓
Image Quality Settings (JPEG Image Size/HEIF Image Size) (when [Aspect Ratio] is set to [16:9])	L: 42M	✓
Image Quality Settings (JPEG Image Size/HEIF Image Size) (when [Aspect Ratio] is set to [1:1])	L: 33M	✓
Aspect Ratio	3:2	✓
File Format	XAVC S HD	✓
Movie Settings (Rec Frame Rate) (when [File Format] is set to [XAVC HS 8K])	30p/25p	✓
Movie Settings (Rec Frame Rate) (when [File Format] is set to [XAVC HS 4K])	60p/50p	✓
Movie Settings (Rec Frame Rate) (when [File Format] is set to [XAVC S 4K])	60p/50p	✓
Movie Settings (Rec Frame Rate) (when [File Format] is set to [XAVC S HD])	60p/50p	✓

MENU items	Default setting value	Resettable using [Camera Settings Reset]
Movie Settings (Rec Frame Rate) (when [File Format] is set to [XAVC S-I 4K])	60p/50p	✓
Movie Settings (Rec Frame Rate) (when [File Format] is set to [XAVC S-I HD])	60p/50p	✓
Movie Settings (Record Setting) (when [File Format] is set to [XAVC HS 8K], and [Rec Frame Rate] is set to [30p]/[25p])	200M 4:2:0 10bit	✓
Movie Settings (Record Setting) (when [File Format] is set to [XAVC HS 8K], and [Rec Frame Rate] is set to [24p])	200M 4:2:0 10bit	✓
Movie Settings (Record Setting) (when [File Format] is set to [XAVC HS 4K], and [Rec Frame Rate] is set to [60p]/[50p])	45M 4:2:0 10bit	✓
Movie Settings (Record Setting) (when [File Format] is set to [XAVC HS 4K], and [Rec Frame Rate] is set to [24p])	50M 4:2:0 10bit	✓
Movie Settings (Record Setting) (when [File Format] is set to [XAVC HS 4K], and [Rec Frame Rate] is set to [120p]/[100p])	200M 4:2:0 10bit	✓
Movie Settings (Record Setting) (when [File Format] is set to [XAVC S 4K], and [Rec Frame Rate] is set to [60p]/[50p])	150M 4:2:0 8bit	✓
Movie Settings (Record Setting) (when [File Format] is set to [XAVC S 4K], and [Rec Frame Rate] is set to [30p]/[25p])	60M 4:2:0 8bit	✓
Movie Settings (Record Setting) (when [File Format] is set to [XAVC S 4K], and [Rec Frame Rate] is set to [24p])	60M 4:2:0 8bit	✓
Movie Settings (Record Setting) (when [File Format] is set to [XAVC S 4K], and [Rec Frame Rate] is set to [120p]/[100p])	200M 4:2:0 8bit	✓
Movie Settings (Record Setting) ([File Format] is set to [XAVC S HD], and [Rec Frame Rate] is set to [60p]/[50p])	50M 4:2:0 8bit	✓
Movie Settings (Record Setting) (when [File Format] is set to [XAVC S HD], and [Rec Frame Rate] is set to [30p]/[25p])	50M 4:2:0 8bit	✓
Movie Settings (Record Setting) (when [File Format] is set to [XAVC S HD], and [Rec Frame Rate] is set to [24p])	50M 4:2:0 8bit	✓
Movie Settings (Record Setting) (when [File Format] is set to [XAVC S HD], and [Rec Frame Rate] is set to [120p]/[100p])	60M 4:2:0 8bit	✓
Movie Settings (Record Setting) (when [File Format] is set to [XAVC S-I 4K], and [Rec Frame Rate] is set to [60p]/[50p])	600M 4:2:2 10bit/500M 4:2:2 10bit	~
Movie Settings (Record Setting) (when [File Format] is set to [XAVC S-I 4K], and [Rec Frame Rate] is set to [30p]/[25p])	300M 4:2:2 10bit/250M 4:2:2 10bit	~
Movie Settings (Record Setting) (when [File Format] is set to [XAVC S-I 4K], and [Rec Frame Rate] is set to [24p])	240M 4:2:2 10bit	✓

MENU items	Default setting value	Resettable using [Camera Settings Reset]
Movie Settings (Record Setting) (when [File Format] is set to [XAVC S-I HD], and [Rec Frame Rate] is set to [60p]/[50p])	222M 4:2:2 10bit/185M 4:2:2 10bit	~
Movie Settings (Record Setting) (when [File Format] is set to [XAVC S-I HD], and [Rec Frame Rate] is set to [30p]/[25p])	111M 4:2:2 10bit/93M 4:2:2 10bit	~
Movie Settings (Record Setting) (when [File Format] is set to [XAVC S-I HD], and [Rec Frame Rate] is set to [24p])	89M 4:2:2 10bit	✓
S&Q Settings (S&Q Rec Frame Rate)	60p/50p	✓
S&Q Settings (S&Q Frame Rate)	120fps/100fps	✓
S&Q Settings (S&Q Record Setting) (when [File Format] is set to [XAVC HS 4K], and [Rec Frame Rate] is set to [60p]/[50p])	45M 4:2:0 10bit	✓
S&Q Settings (S&Q Record Setting) (when [File Format] is set to [XAVC HS 4K], and [Rec Frame Rate] is set to [24p])	50M 4:2:0 10bit	✓
S&Q Settings (S&Q Record Setting) (when [File Format] is set to [XAVC HS 4K], and [Rec Frame Rate] is set to [120p]/[100p])	200M 4:2:0 10bit	✓
S&Q Settings (S&Q Record Setting) (when [File Format] is set to [XAVC S 4K], and [Rec Frame Rate] is set to [60p]/[50p])	150M 4:2:0 8bit	✓
S&Q Settings (S&Q Record Setting) (when [File Format] is set to [XAVC S 4K], and [Rec Frame Rate] is set to [30p]/[25p])	60M 4:2:0 8bit	✓
S&Q Settings (S&Q Record Setting) (when [File Format] is set to [XAVC S 4K], and [Rec Frame Rate] is set to [24p])	60M 4:2:0 8bit	✓
S&Q Settings (S&Q Record Setting) (when [File Format] is set to [XAVC S 4K], and [Rec Frame Rate] is set to [120p]/[100p])	200M 4:2:0 8bit	✓
S&Q Settings (S&Q Record Setting) (when [File Format] is set to [XAVC S HD], and [Rec Frame Rate] is set to [60p]/[50p])	50M 4:2:0 8bit	✓
S&Q Settings (S&Q Record Setting) (when [File Format] is set to [XAVC S HD], and [Rec Frame Rate] is set to [30p]/[25p])	50M 4:2:0 8bit	✓
S&Q Settings (S&Q Record Setting) (when [File Format] is set to [XAVC S HD], and [Rec Frame Rate] is set to [24p])	50M 4:2:0 8bit	✓
S&Q Settings (S&Q Record Setting) (when [File Format] is set to [XAVC S HD], and [Rec Frame Rate] is set to [120p]/[100p])	60M 4:2:0 8bit	✓
S&Q Settings (S&Q Record Setting) (when [File Format] is set to [XAVC S-I 4K], and [Rec Frame Rate] is set to [60p]/[50p])	600M 4:2:2 10bit/500M 4:2:2 10bit	~
S&Q Settings (S&Q Record Setting) (when [File Format] is set to [XAVC S-I 4K], and [Rec Frame Rate] is set to [30p]/[25p])	300M 4:2:2 10bit/250M 4:2:2 10bit	✓
S&Q Settings (S&Q Record Setting) (when [File Format] is set to [XAVC S-I 4K], and [Rec Frame Rate] is set to [24p])	240M 4:2:2 10bit	✓

MENU items	Default setting value	Resettable using [Camera Settings Reset]
S&Q Settings (S&Q Record Setting) (when [File Format] is set to [XAVC S-I HD], and [Rec Frame Rate] is set to [60p]/[50p])	222M 4:2:2 10bit/185M 4:2:2 10bit	✓
S&Q Settings (S&Q Record Setting) (when [File Format] is set to [XAVC S-I HD], and [Rec Frame Rate] is set to [30p]/[25p])	111M 4:2:2 10bit/93M 4:2:2 10bit	~
S&Q Settings (S&Q Record Setting) (when [File Format] is set to [XAVC S-I HD], and [Rec Frame Rate] is set to [24p])	89M 4:2:2 10bit	✓
Px Proxy Settings (Px Proxy Recording)	Off	✓
Px Proxy Settings (Px Proxy File Format)	XAVC S HD	✓
Px Proxy Settings (Px Proxy Rec. Settings) (when [Px Proxy File Format] is set to [XAVC HS HD])	9M 4:2:0 10bit	✓
Px Proxy Settings (Px Proxy Rec. Settings) (when [Px Proxy File Format] is set to [XAVC S HD])	6M 4:2:0 8bit	✓
APS-(S35 Shooting	Auto	_
Long Exposure NR	On	✓
High ISO NR	Normal	✓
HLG Still Image	Off	✓
Color Space	sRGB	✓
Lens Compensation (Shading Comp.)	Auto	_
Lens Compensation (Chromatic Aberration Comp.)	Auto	_
Lens Compensation (Distortion Comp.)	Off	_
Format	_	_
Rec. Media Settings (Recording Media)	Slot 1	_
Rec. Media Settings (Recording Media)	Slot 1	_
Rec. Media Settings (Auto Switch Media)	Off	_
Recover Image DB* * This item is not reset even if you select [Camera Settings Reset] or [Initialize].	_	_
Display Media Info.	_	_
File/Folder Settings (File Number)	Series	_
File/Folder Settings (Forced File Number Reset)	_	_
File/Folder Settings (Set File Name)	DSC	_
File/Folder Settings (Folder Name)	Standard Form	_
Select REC Folder	_	_

MENU items	Default setting value	Resettable using [Camera Settings Reset]
Create New Folder	_	_
IPTC Information (Write IPTC Info)	Off	_
IPTC Information (Register IPTC Info)	_	_
Copyright Info (Write Copyright Info)	Off	_
Copyright Info (Set Photographer)	_	_
Copyright Info (Set Copyright)	_	_
Copyright Info (Disp. Copyright Info)	_	_
Write Serial Number	Off	_
File Settings (File Number)	Series	_
File Settings (Series Counter Reset)	_	_
File Settings (File Name Format)	Standard	_
File Settings (Title Name Settings)	_	_
Exposure Mode	Program Auto	✓
S&Q Exposure Mode	Program Auto	✓
Exposure Ctrl Type	P/A/S/M Mode	_
MR Recall Camera Setting	_	_
MR Camera Set. Memory	_	_
MR Memory/Recall Media	Slot 1	✓
Reg. Custom Shoot Set	Recall Custom hold 1	_
Cont. Shooting Speed (🍱 Hi(E-Shutter))	20 images/sec	✓
Cont. Shooting Speed (Mid(E-Shutter))	15 images/sec	✓
Cont. Shooting Speed (Lo(E-Shutter))	5 images/sec	✓
Self-timer Type	Self-timer(Single)	✓
Bracket Settings (Bracket Type)	Cont. Bracket	✓
Bracket Settings (Selftimer during Bracket)	Off	✓
Bracket Settings (Bracket order)	0→-→+	✓
Interval Shoot Func. (Interval Shooting)	Off	✓
Interval Shoot Func. (Shooting Start Time)	1 Sec	✓
Interval Shoot Func. (Shooting Interval)	3 Sec	✓
Interval Shoot Func. (Number of Shots)	30	✓

MENU items	Default setting value	Resettable using [Camera Settings Reset]
Interval Shoot Func. (AE Tracking Sensitivity)	Mid	✓
Interval Shoot Func. (Shutter Type in Interval)	Electronic Shutter	~
Interval Shoot Func. (Shoot Interval Priority)	Off	✓
Pixel Shift Multi Shoot.	Off	✓
Silent Mode Settings (Silent Mode)	Off	✓
Silent Mode Settings ([Aperture Drive in AF] under [Target Function Settings])	Standard	~
Silent Mode Settings ([Shutter When Pwr OFF] under [Target Function Settings])	Off	~
Silent Mode Settings ([Auto Pixel Mapping] under [Target Function Settings])	Off	~
Shutter Type	Auto	_
Release w/o Lens	Enable	_
Release w/o Card	Enable	_
Anti-flicker Set. (Anti-flicker Shoot.)	Off	✓
Anti-flicker Set. (Variable Shutter)	Off	✓
Anti-flicker Set. (Var. Shutter Set.)	_	_
Audio Recording	On	✓
Audio Rec Level	26	✓
Audio Out Timing	Live	✓
Wind Noise Reduct.	Off	✓
ni Shoe Audio Set.	48khz/16bit 2ch	✓
Audio Level Display	On	_
Time Code Preset	00:00:00.00	_
User Bit Preset	00 00 00 00	_
Time Code Format	DF	_
Time Code Run	Rec Run	_
Time Code Make	Preset	_
User Bit Time Rec	Off	_
SteadyShot	On	✓
□ SteadyShot	Standard	✓
SteadyShot Adjust.	Auto	✓

MENU items	Default setting value	Resettable using [Camera Settings Reset]
Focal Length (when [SteadyShot Adjust.] is set to [Manual])	8mm	✓
Zoom	_	_
Zoom Range	Optical zoom only	_
Zoom Speed (Fixed Speed \$TBY)	3	✓
Zoom Speed (Fixed Speed REC)	3	✓
Zoom Speed (Speed Type)	Variable	✓
Zoom Speed (Fixed Speed STBY)	3	✓
☐ Zoom Speed (☐ Fixed Speed REC)	3	✓
Grid Line Display	Off	_
Grid Line Type	Rule of 3rds Grid	_
Live View Display Set. (Live View Display)	Setting Effect ON	_
Live View Display Set. (Exposure Effect)	Exposure Set. & flash	_
Live View Display Set. (Frame Rate Low Limit)	Off	✓
Live View Display Set. (Flash Effect dur Sht.)	Flash Effect ON	_
Emphasized REC Display	Off	✓
Marker Display	Off	_
Center Marker	Off	_
Aspect Marker	Off	_
Safety Zone	Off	_
Guideframe	Off	_

(Exposure/Color)

MENU items	Default setting value	Resettable using [Camera Settings Reset]
Auto Slow Shutter	On	✓
₽ ISO	ISO AUTO	✓
ISO Range Limit	_	_
ISO AUTO Min. SS	Standard	✓
Auto/Manual Swt. Set. (Av Auto/Manual Switch)	Manual	✓
Auto/Manual Swt. Set. (Tv Auto/Manual Switch)	Manual	✓

MENU items	Default setting value	Resettable using [Camera Settings Reset]
Auto/Manual Swt. Set. (ISO Auto/Manual Set)	Manual	✓
Exposure Comp.	±0.0	✓
Reset EV Comp.	Reset	_
Exposure step	0.3EV	_
Exposure Std. Adjust (Multi)	±0	_
Exposure Std. Adjust (±0	_
Exposure Std. Adjust (Spot)	±0	_
Exposure Std. Adjust (Entire Screen Average)	±0	_
Exposure Std. Adjust (Tighlight)	±0	_
Metering Mode	Multi	✓
Face Priority in Multi Metering	On	✓
Spot Metering Point	Center	✓
AEL w/ Shutter	Auto	_
Flash Mode	Autoflash	✓
Flash Comp.	±0.0	✓
Exp.comp.set	Ambient&flash	_
Wireless Flash	Off	✓
Flash Sync Spd. Prty.	Auto	✓
Red Eye Reduction	Off	✓
External Flash Set. (Ext. Flash Firing Set.)	_	✓
External Flash Set. (Ext. Flash Cust. Set.)	_	✓
White Balance	Auto	✓
Priority Set in AWB	Standard	✓
Shutter AWB Lock	Off	_
Shockless WB	1 (Fast)	✓
D-Range Optimizer	D-Range Optimizer: Auto	✓
Creative Look	ST	✓
Picture Profile	Off	✓
Zebra Display	Off	_
Zebra Level	70	_

AF_{MF} (Focus)

MENU items	Default setting value	Resettable using [Camera Settings Reset]
Priority Set in AF-S	Balanced Emphasis	_
Priority Set in AF-C	Balanced Emphasis	_
AF Tracking Sensitivity	3(Standard)	✓
AF Illuminator	Auto	✓
Aperture Drive in AF	Standard	_
AF w/ Shutter	On	_
Pre-AF	Off	_
AF Transition Speed	5	✓
AF Subj. Shift Sensitivity	5(Responsive)	✓
Focus Area	Wide	✓
Focus Area Limit	_	✓
Switch V/H AF Area	Off	✓
Focus Area Color	White	_
AF Area Registration	Off	_
Del. Regist. AF Area	_	_
AF Area Auto Clear	Off	_
Area Disp. dur Tracking	Off	_
AF-C Area Display	On	_
Phase Detect. Area	Off	_
Circ. of Focus Point	Does Not Circulate	_
AF Frame Move Amt	Standard	✓
Face/Eye Prior. in AF	On	✓
Face/Eye Subject	Human	✓
Subject Sel. Setting	_	_
Right/Left Eye Select	Auto	✓
Face/Eye Frame Disp.	Off	✓
Face Memory	_	_
Regist. Faces Priority	On	✓
Auto Magnifier in MF	On	_
Focus Magnifier	_	✓
Focus Magnif. Time	No Limit	_

MENU items	Default setting value	Resettable using [Camera Settings Reset]
Initial Focus Mag.	x1.0	_
AF in Focus Mag.	On	_
Initial Focus Mag.	x1.0	_
Peaking Display	Off	_
Peaking Level	Mid	_
Peaking Color	White	_

► (Playback)

To reset the items for [Playback] to the default values, select [Initialize]. These items are not reset to the default values even if you select [Camera Settings Reset].

MENU items	Default setting value
Select Playback Media	_
View Mode	Date View
⊕ Enlarge Image	_
⊕ Enlarge Initial Mag.	Standard. Mag.
⊕ Enlarge Initial Position	Focused Position
Protect	_
Rating	_
Rating Set(Custom Key)	_
Voice Memo	_
Voice Memo Play Vol.	7
Delete	_
Delete pressing twice	Off
Delete confirm.	"Cancel" first
Crop	_
Rotate	_
Сору	_
Photo Capture	_
JPEG/HEIF Switch	JPEG
Cont. Play for 🙌 Interval	_
Play Speed for 🚯 Interval	5
Slide Show (Repeat)	Off
Slide Show (Interval)	3 Sec

MENU items	Default setting value
Image Index	9 Images
Display as Group	Off
Display Rotation	Auto
Focus Frame Display	Off
Select Image Jump Dial	Front dial
Image Jump Method	One by one

(Network)

To reset the items for [Network] to the default values, select [Initialize] or [Reset Network Set.]. These items are not reset to the default values even if you select [Camera Settings Reset].

MENU items	Default setting value
Smartphone Connection	On
Connection	_
Select on Cam & Send (Send)	_
Select on Cam & Send (Size of Sending Image)	2M
Select on Cam & Send (RAW+J/H Send Target)	JPEG & HEIF
Select on Cam & Send (Px Sending Target)	Proxy Only
Cnct. while Power OFF	Off
Remote Shoot Setting (Still Img. Save Dest.)	Smartphone+Cam.
Remote Shoot Setting (Save Image Size)	2M
Remote Shoot Setting (RAW+J Save Image)	JPEG Only
Remote Shoot Setting (RAW+H Save Image)	HEIF Only
Remote Shoot Setting (Save JPEG Size)	Large Size
Remote Shoot Setting (Save HEIF Size)	Large Size
Always Connected	Off
FTP Transfer Func. (FTP Function)	Off
FTP Transfer Func. (FTP Connect Method)	Wired LAN
FTP Transfer Func. (Tethering Connection)	_
FTP Transfer Func. (Tethering Disconnection)	_
FTP Transfer Func. (Server Setting)	Server 1
FTP Transfer Func. (Save/Load FTP Settings)	_
FTP Transfer Func. (when [FTP Transfer] is set to [Target Group])	This Date
FTP Transfer Func. (when [FTP Transfer] is set to [Still Images/Movies])	All

MENU items	Default setting value
FTP Transfer Func. (when [FTP Transfer] is set to [Target Img (Protect)])	All
FTP Transfer Func. (when [FTP Transfer] is set to [Transfer Status])	All
FTP Transfer Func. (Display FTP Result)	_
FTP Transfer Func. (Auto FTP Transfer)	Off
FTP Transfer Func. (RAW+J/H Transfer Target)	JPEG & HEIF
FTP Transfer Func. (Transfer JPEG Size)	Large Size
FTP Transfer Func. (Transfer HEIF Size)	Large Size
FTP Transfer Func. (Px Transfer Target)	Proxy Only
FTP Transfer Func. (FTP Power Save)	Off
PC Remote Function (PC Remote)	Off
PC Remote Function (PC Remote Cnct Method)	USB
PC Remote Function (Connect without Pairing)	Disable
PC Remote Function (Pairing)	_
PC Remote Function (Wi-Fi Direct Info.)	_
PC Remote Function (Still Img. Save Dest.)	PC Only
PC Remote Function (PC Save Image Size)	Original
PC Remote Function (RAW+J PC Save Img)	RAW & JPEG
PC Remote Function (RAW+H PC Save Image)	RAW & HEIF
PC Remote Function (PC Save JPEG Size)	Large Size
PC Remote Function (PC Save HEIF Size)	Large Size
Bluetooth Rmt Ctrl	Off
Location Info Link	Off
Auto Time Correction (when [Location Info Link] is set to [On])	On
Auto Area Adjustment (when [Location Info Link] is set to [On])	On
WPS Push	_
Access Point Set.	_
Wi-Fi Frequency Band	2.4GHz
Display Wi-Fi Info.	_
SSID/PW Reset	_
Bluetooth Function	Off
Pairing	_

MENU items	Default setting value
Disp Device Address	_
LAN IP Address Setting	Auto
Display Wired LAN Info.	_
Airplane Mode	Off
Edit Device Name	_
Import Root Certificate	_
Security(IPsec) (IPsec)	Off
Security(IPsec) (Dest. IP Address)	_
Security(IPsec) (Shared Key)	_
Reset Network Set.	_

(Setup)

To reset the items for [Setup] to the default values, select [Initialize]. These items are not reset to the default values even if you select [Camera Settings Reset].

MENU items	Default setting value
[A] Language	_
Area/Date/Time Setting (Area Setting)	_
Area/Date/Time Setting (Daylight Savings)	Off
Area/Date/Time Setting (Date/Time)	_
Area/Date/Time Setting (Date Format)	_
Setting Reset	_
Save/Load Settings	_
Custom Key Setting (Front dial)	Aperture/Shutter Speed
Custom Key Setting (Rear dial)	Aperture/Shutter Speed
Custom Key Setting (Control Wheel)	Not set
Custom Key Setting (Custom Button 1)	White Balance
Custom Key Setting (Custom Button 2)	Autofocus Area
Custom Key Setting (Custom Button 3)	Shutter Type
Custom Key Setting (Custom Button 4)	Touch Operation Select
Custom Key Setting (Multi-Slc Center Btn)	Focus Standard
Custom Key Setting (Center Button)	Not set
Custom Key Setting (Left Button)	Not set
Custom Key Setting (Right Button)	₽ ISO

MENU items	Default setting value
Custom Key Setting (Down Button)	Not set
Custom Key Setting (AEL Button)	AEL hold
Custom Key Setting (AF-ON Button)	AF On
Custom Key Setting (MOVIE Button)	Movie Shooting
Custom Key Setting (Focus Hold Button)	Focus Hold
Custom Key Setting (Front dial)	Follow Custom ()
Custom Key Setting (Rear dial)	Follow Custom ()
Custom Key Setting (Control Wheel)	Follow Custom ()
Custom Key Setting (Custom Button 1)	Follow Custom ()
Custom Key Setting (Custom Button 2)	Follow Custom ()
Custom Key Setting (Custom Button 3)	Follow Custom ()
Custom Key Setting (Custom Button 4)	Follow Custom ()
Custom Key Setting (Multi-Slc Center Btn)	Follow Custom ()
Custom Key Setting (Center Button)	Follow Custom ()
Custom Key Setting (Left Button)	Follow Custom ()
Custom Key Setting (Right Button)	Follow Custom ()
Custom Key Setting (Down Button)	Follow Custom ()
Custom Key Setting (AEL Button)	Follow Custom ()
Custom Key Setting (AF-ON Button)	Follow Custom ()
Custom Key Setting (MOVIE Button)	Movie Shooting
Custom Key Setting (Focus Hold Button)	Follow Custom ()
Custom Key Setting (Custom Button 1)	Follow Custom (/ 11)
Custom Key Setting (Custom Button 2)	Follow Custom (/ 11)
Custom Key Setting (Custom Button 3)	Protect
Custom Key Setting (MOVIE Button)	Follow Custom ([]/ []
► Custom Key Setting (Fn/ ► Button)	★] Send
Fn Menu Settings	_
Different Set for Still/Mv	_
DISP (Screen Disp) Set (Monitor)	Display All Info.
DISP (Screen Disp) Set (Finder)	Level
REC w/ Shutter	Off
Zoom Ring Rotate	Left(W)/Right(T)

MENU items	Default setting value
My Dial Settings	_
Av/Tv Assign in M	▲ Av ▼ Tv
Av/Tv Rotate	Normal
Dial Ev Comp	Off
Function Ring(Lens)	Power Focus
Lock Operation Parts	Off
Touch Operation	On
Touch Sensitivity	Standard
Touch Panel/Pad	Touch Panel Only
Touch Pad Settings (Operation in Vertical Orientation)	On
Touch Pad Settings (Touch Position Mode)	Absolute Position
Touch Pad Settings (Operation Area)	Right 1/2
Touch Func. in Shooting	Touch Tracking
Select Finder/Monitor	Auto
Monitor Brightness	±0
Viewfinder Bright.	Auto
Finder Color Temp.	±0
Viewfinder Magnifi.	Standard
Display Quality	Standard
Finder Frame Rate	High
TC/UB Disp. Setting	Counter
Gamma Display Assist	Off
Gamma Disp. Assist Typ.	Auto
Shoot. Start Display	Off
Shoot. Timing Display	On: Type1
Remain Shoot Display	Not Displayed
Auto Review	Off
Auto Monitor OFF	Does not turn OFF
Power Save Start Time	1 Min
Auto Power OFF Temp.	Standard
Volume Settings	7
4ch Audio Monitoring	CH1/CH2

MENU items	Default setting value
Audio signals	On:all
USB Connection	Auto
USB LUN Setting	Multi
USB Power Supply	On
HDMI Resolution	Auto
HDMI Output Settings (Rec. Media dur HDMI Output)	On
HDMI Output Settings (Output Resolution)	Auto
HDMI Output Settings (4K Output Set.(HDMI Only))	60p 10bit/50p 10bit
HDMI Output Settings (RAW Output)	Off
HDMI Output Settings (RAW Output Setting)	60p/50p
HDMI Output Settings (Color Gamut for RAW Output)	S-Gamut3.Cine/S-log3
HDMI Output Settings (Time Code Output)	Off
HDMI Output Settings (REC Control)	Off
HDMI Output Settings (4ch Audio Output)	CH1/CH2
HDMI Info. Display	On
CTRL FOR HDMI	On
Video Light Mode	Power Link
IR Remote Ctrl	Off
Anti-dust Function (Sensor Cleaning)	_
Anti-dust Function (Shutter When Pwr OFF)	Off
Auto Pixel Mapping	On
Pixel Mapping	_
Version	_

☆ (My Menu)

To reset the items for [My Menu] to the default values, select [Initialize] or [Delete All]. These items are not reset to the default values even if you select [Camera Settings Reset].

MENU items	Default setting value
Add Item	_
Sort Item	_
Delete Item	_
Delete Page	_
Delete All	_

MENU items	Default setting value
Display From My Menu	Off

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Specifications

Camera

[System]

Camera Type

Interchangeable Lens Digital Camera

Lens

Sony E-mount lens

[Image sensor]

Image format

35 mm full frame (35.9 mm × 24.0 mm), CMOS image sensor

Effective pixel number of camera

Approx. 50 100 000 pixels

Total pixel number of camera

Approx. 50 500 000 pixels

[SteadyShot]

System

In-camera sensor shift image stabilization system

[Anti-Dust]

System

Anti-dust function based on antistatic coating and ultrasonic vibration

[Auto focus system]

Detection system

Phase-detection system/Contrast detection system

Sensitivity Range

-4 EV to +20 EV (at ISO 100 equivalent, F2.0)

AF illuminator

Approx. 0.3 m to 3.0 m (When using an FE 28-70 mm F3.5-5.6 OSS)

[Electronic Viewfinder]

Type

1.6 cm (0.64 type) Electronic Viewfinder

Total number of dots

9 437 184 dots

Frame coverage

100%

Magnification

Approx. 0.90× with 50 mm lens at infinity, -1 m⁻¹

Eye Point

Approx. 25 mm from the eyepiece and approx. 21 mm from the eyepiece frame at -1 m ⁻¹

Diopter Adjustment

 $-4.0 \text{ m}^{-1} \text{ to } +3.0 \text{ m}^{-1}$

[Monitor]

LCD monitor

7.5 cm (3.0 type) TFT drive, touch panel

Total number of dots

1 440 000 dots

[Exposure control]

Metering method

1 200-zone evaluative metering

Metering Range

-3 EV to +20 EV (at ISO 100 equivalent with F2.0 lens)

ISO sensitivity (Recommended exposure index)

Still images: ISO 100 to ISO 32 000 (Extended ISO: Minimum ISO 50, maximum ISO 102 400), [ISO AUTO] (ISO 100 to ISO 12 800, Maximum/Minimum can be set.)

Movies: ISO 100 to ISO 32 000 equivalent, [ISO AUTO] (ISO 100 to ISO 12 800 equivalent, Maximum/Minimum can be set.)

Exposure compensation

±5.0 EV (switchable between 1/3 EV and 1/2 EV steps)

When using exposure compensation dial: ±3.0 EV (1/3 EV step)

[Shutter]

Type

Electronically-controlled, vertical-traverse, focal-plane type

Speed range

Still images (when shooting with the electronic shutter): 1/32 000 second to 30 seconds (up to 0.5" in continuous shooting)

Still images (when shooting with the mechanical shutter): 1/8 000 second to 30 seconds, BULB

Movies: 1/8 000 second to 1/4 second (1/3 EV step)

60p-compatible devices: up to 1/60 second in AUTO mode (up to 1/30 second in Auto slow shutter mode)

50p-compatible devices: up to 1/50 second in AUTO mode (up to 1/25 second in Auto slow shutter mode)

Flash sync speed (when using a flash manufactured by Sony)

• When [Shutter Type] is set to [Mechanical Shutter]:

When [Flash Sync Spd. Prty.] is set to [On] or [Auto]

1/400 second (Full-frame)

1/500 second (APS-C size)

When [Flash Sync Spd. Prty.] is set to [Off]

1/320 second (Full-frame)

1/400 second (APS-C size)

When [Shutter Type] is set to [Electronic Shutter]:

1/200 second (Full-frame)

1/250 second (APS-C size)

[Continuous shooting]

Continuous shooting speed

(Continuous Shooting: Hi+): Maximum of approx. 30 images per second/ (Continuous Shooting: Hi): Maximum of approx. 20 images per second/ (Continuous Shooting: Mid): Maximum of approx. 15 images per second/ (Continuous Shooting: Lo): Maximum of approx. 5 images per second

- Based on our measurement conditions. The speed of continuous shooting can be slower, depending on the shooting conditions.
- The speed of [Continuous Shooting: Hi], [Continuous Shooting: Mid], and [Continuous Shooting: Lo] changes according to the camera settings.

[Recording format]

File format

JPEG (compliant with DCF Ver. 2.0, Exif Ver. 2.32, and MPF Baseline), HEIF (MPEG-A MIAF compliant), RAW (Sony ARW 4.0 format compliant)

Movie (XAVC HS format)

XAVC Ver2.0: MP4 format compliant

Video: MPEG-H HEVC/H.265

Audio: LPCM 2ch (48 kHz 16 bit), LPCM 4ch (48kHz 24bit)*1, LPCM 2ch (48kHz 24bit)*1, MPEG-4 AAC-LC 2ch*2

Movie (XAVC S format)

XAVC Ver2.0: MP4 format compliant

Video: MPEG-4 AVC/H.264

Audio: LPCM 2ch (48 kHz 16 bit), LPCM 4ch (48kHz 24bit)*1, LPCM 2ch (48kHz 24bit)*1, MPEG-4 AAC-LC 2ch*2

*1 When using accessories that can support 4ch output and 24 bits with the multi-interface shoe

*2 Proxy movies

[Recording media]

CFexpress Type A memory cards, SD cards

[Slot]

SLOT 1/SLOT 2

Slot for CFexpress Type A memory cards, SD cards (UHS-I and UHS-II compatible)

Supports operations between two memory cards.

[Input/output terminals]

USB Type-C terminal

SuperSpeed USB 10Gbps (USB 3.2)

Compatible with USB Power Delivery

Multi/Micro USB Terminal*

Hi-Speed USB (USB 2.0)

* Supports Micro USB compatible devices.

HDMI

HDMI type A jack

(Microphone) terminal

Ø 3.5 mm Stereo mini jack

(Headphones) terminal

Ø 3.5 mm Stereo mini jack

LAN terminal

(Flash sync) terminal

[Power, general]

Rated input

7.2 V ____

Power consumption

Using an FE 28-70 mm F3.5-5.6 OSS

When using the viewfinder: Approx. 4.6 W (while shooting still images)/approx. 6.8 W (while shooting movies) When using the monitor: Approx. 3.7 W (while shooting still images)/approx. 6.6 W (while shooting movies)

Operating temperature

0 to 40°C (32 to 104°F)

Storage temperature

-20 to 55°C (-4 to 131°F)

Dimensions (W/H/D) (Approx.)

128.9 × 96.9 × 80.8 mm

 $128.9 \times 96.9 \times 69.7$ mm (from grip to monitor)

5 1/8 × 3 7/8 × 3 1/4 in.

 $5 \frac{1}{8} \times 3 \frac{7}{8} \times 2 \frac{3}{4}$ in. (from grip to monitor)

Mass (Approx.)

737 g (1 lb 10.0 oz) (including battery pack, SD card)

Microphone

Stereo

Speaker

Monaural

Exif Print

Compatible

PRINT Image Matching III

Compatible

[Wireless LAN]

WW411329 (see name plate on the bottom of camera)

Supported format

IEEE 802.11 a/b/g/n/ac

Frequency band

2.4 GHz / 5 GHz

Security

WEP/WPA-PSK/WPA2-PSK

Connection method

Wi-Fi Protected Setup™ (WPS)/Manual

Access method

Infrastructure mode

WW111327 (see name plate on the bottom of camera)

Supported format

IEEE 802.11 b/g/n

Frequency band

2.4 GHz

Security

WEP/WPA-PSK/WPA2-PSK

Connection method

Wi-Fi Protected Setup™ (WPS)/Manual

Access method

Infrastructure mode

[NFC]

Tag type

NFC Forum Type 3 Tag compliant

[Bluetooth communications]

Bluetooth standard Ver. 5.0

Frequency band

2.4 GHz

Battery charger BC-QZ1

Rated input

100-240 V ${\color{red} \sim}$, 50/60 Hz, 0.38 A

Rated output

8.4 V ___ , 1.6 A

Rechargeable battery pack NP-FZ100

Rated voltage

7.2 V

Design and specifications are subject to change without notice.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

Trademarks

- XAVC S and XAVC S are registered trademarks of Sony Corporation.
- XAVC HS and XAVC HS are registered trademarks of Sony Corporation.
- Mac is a trademark of Apple Inc., registered in the United States and other countries.
- iPhone and iPad are trademarks of Apple Inc., registered in the U.S. and other countries.
- USB Type-C® and USB-C® are registered trademarks of USB Implementers Forum.
- The terms HDMI, HDMI High-Definition Multimedia Interface, and the HDMI Logo are trademarks or registered trademarks of HDMI Licensing Administrator, Inc.
- Microsoft and Windows are registered trademarks or trademarks of Microsoft Corporation in the United States and/or other countries.
- SDXC logo is a trademark of SD-3C, LLC.
- The CFexpress Type A logo is a trademark licensed by the CompactFlash Association.
- Android and Google Play are trademarks or registered trademarks of Google LLC.
- Wi-Fi, the Wi-Fi logo and Wi-Fi Protected Setup are registered trademarks or trademarks of the Wi-Fi Alliance.
- The N-Mark is a trademark or registered trademark of NFC Forum, Inc. in the United States and in other countries.
- The Bluetooth® word mark and logos are registered trademarks owned by the Bluetooth SIG, Inc. and any use of such marks by Sony Corporation is under license.
- QR Code is a trademark of Denso Wave Inc.
- In addition, system and product names used in this manual are, in general, trademarks or registered trademarks of their respective developers or manufacturers. However, the [™] or ® marks may not be used in all cases in this manual.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\,\alpha$ 1

License

Notes on the License

This product comes with software that are used based on licensing agreements with the owners of that software. Based on requests by the owners of copyright of these software applications, we have an obligation to inform you of the following. Licenses (in English) are recorded in the internal memory of your product. Establish a Mass Storage connection between the product and a computer to read licenses in the "PMHOME" - "LICENSE" folder.

THIS PRODUCT IS LICENSED UNDER THE AVC PATENT PORTFOLIO LICENSE FOR THE PERSONAL USE OF A CONSUMER OR OTHER USES IN WHICH IT DOES NOT RECEIVE REMUNERATION TO
(i) ENCODE VIDEO IN COMPLIANCE WITH THE AVC STANDARD ("AVC VIDEO")
AND/OR

(ii) DECODE AVC VIDEO THAT WAS ENCODED BY A CONSUMER ENGAGED IN A PERSONAL ACTIVITY AND/OR WAS OBTAINED FROM A VIDEO PROVIDER LICENSED TO PROVIDE AVC VIDEO.

NO LICENSE IS GRANTED OR SHALL BE IMPLIED FOR ANY OTHER USE. ADDITIONAL INFORMATION INCLUDING THAT RELATING TO PROMOTIONAL, INTERNAL AND COMMERCIAL USES AND LICENSING MAY BE OBTAINED FROM MPEG LA, L.L.C.

SEE HTTPS://WWW.MPEGLA.COM

Covered by one or more claims of the HEVC patents listed at patentlist.accessadvance.com.



On GNU GPL/LGPL applied software

The software that is eligible for the following GNU General Public License (hereinafter referred to as "GPL") or GNU Lesser General Public License (hereinafter referred to as "LGPL") are included in the product.

This informs you that you have a right to have access to, modify, and redistribute source code for these software programs under the conditions of the supplied GPL/LGPL.

Source code is provided on the web.

Use the following URL to download it.

https://oss.sony.net/Products/Linux/

We would prefer you do not contact us about the contents of source code.

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Troubleshooting

If you experience trouble with the product, try the following solutions.

- Remove the battery pack, wait for about one minute, re-insert the battery pack, then turn on the power.
- 2 Initialize the settings.
- 3 Consult your dealer or local authorized service facility. Additional information on this product and answers to frequently asked questions can be found at our Customer Support Website.

 https://www.sony.net/

Related Topic

Setting Reset

Help Guide

Interchangeable Lens Digital Camera ILCE-1 α 1

Warning messages

Set Area/Date/Time.

Set the area, date and time. If you have not used the product for a long time, charge the internal rechargeable backup battery.

Power insufficient.

• The image copying or the image sensor cleaning function will not operate because the remaining battery level is too low. Recharge the battery pack or supply power by connecting the camera with a computer, etc.

Unable to use memory card. Format?

• The memory card was formatted on a computer and the file format was modified. Select [Enter] and then format the memory card. You can use the memory card again, however, all previous data in the memory card is erased. It may take some time to complete the format. If the message still appears, change the memory card.

Memory Card Error

- An incompatible memory card is inserted.
- Formatting has failed. Format the memory card again.

Unable to read memory card. Reinsert memory card.

- An incompatible memory card is inserted.
- The memory card is damaged.
- The terminal section of the memory card is dirty.

Memory card locked.

You are using a memory card with a write-protect switch or a delete-protect switch with the switch set to the LOCK position. Set the switch to the record position.

Cannot open the shutter since the memory card is not inserted.

- No memory card has been inserted into the memory card slot selected in [Recording Media] or [Recording Media].
- To release the shutter without inserting a memory card into the camera, set [Release w/o Card] to [Enable]. In this
 case, images will not be saved.

This memory card may not be capable of recording and playing normally.

An incompatible memory card is inserted.

Processing...

• When performing noise reduction, the reduction process takes place. You cannot do any further shooting during this reduction process.

Unable to display.

• Images recorded with other products or images modified with a computer may not be displayed.

 Processing on the computer such as deletion of the image files may cause inconsistencies in the image database files. Repair the image database files.

Check that a lens is mounted. For an unsupported lens, set "Release w/o Lens" in the menu to "Enable".

- The lens is not attached properly, or the lens is not attached. If the message appears when a lens is attached, reattach the lens. If the message appears frequently, check whether the contacts of the lens and product are clean or not.
- When attaching the product to an astronomical telescope or similar instrument, or using an unsupported lens, set [Release w/o Lens] to [Enable].

Internal temp. high. Allow it to cool.

- The product has become hot because you have been shooting continuously. Turn the power off and cool the product and wait until the product is ready to shoot again.
- (Overheating warning)
- You have been recording images for a long time, the product temperature has risen.
- (Database file error)
- The number of images exceeds that for which date management in a database file by the product is possible.
- (Database file error)
- Unable to register to the database file. Import all the images to a computer and recover the memory card.

Image DataBase File error

There is something wrong in the Image Database File. Select MENU → (Shooting) → [Media] → [Recover Image DB].

System Error

Camera Error. Turn power off then on.

 Remove the battery pack, and then re-insert it. If the message appears frequently, consult local authorized Sony service facility.

Image Database File error. Recover?

 You cannot record and play back a movie because the Image Database File is damaged. Recover the Image Database File following the on-screen instructions.

Unable to magnify.

Unable to rotate image.

Images recorded with other products may not be enlarged or rotated.

Cannot create more folders.

A folder in the memory card has the first three digits "999." You cannot create any more folders on this camera.

Related Topic

- Notes on memory card
- Area/Date/Time Setting
- Format

- Release w/o Card
- Release w/o Lens (still image/movie)
- Recover Image DB (still image/movie)

Help Guide

Interchangeable Lens Digital Camera ILCE-1 $\alpha1$

Recommended pages

Using the electronic shutter

Using the electronic shutter lets you perform shooting without sounds, blackout-free shooting, etc.

Mean Continuous shooting

Refer to this topic for the continuous shooting speed and the number of images recordable with continuous shooting.

Custom key setting

You can assign frequently used functions to the desired buttons and dials.

■ Recordable movie times

Refer to this topic for the shooting duration of movies recordable on the memory card.

ILCE-1 support information

This website provides basic information about the camera and information regarding compatible lenses and accessories. (Another window will open.)